Comcast Confidential - Any unauthorized disclosure or use is strictly prohibited

Test Case for Tr69Hostif

1. tr69hostif initialization:
    a. Start the binary and verify the below threads have been started successfully:
        - jsonIfHandlerThread
        - HTTPServerStartThread
        - shutdown_thread
        - libpd_client_mgr
        - Verify the below initializations are success:
            - init_rbus_dml_provider()
            - hostIf_initalize_ConfigManger()
            - loadDataModel()
            - updateHandler::Init()
2. Data Model validation
    - Verify that the data model initialization is successful.
3. RFC namespace get/set handlers
    - Verify the get and set handlers using rbuscli for a few RFC namespace parameters.
4. Non-RFC namespace get/set handlers
    - Verify the get and set handlers using rbuscli for a few non-RFC namespace parameters.
5. DeviceInfo get/set handlers
    - Device.DeviceInfo

    Read-Only Parameters (77)

#	Parameter	Data Type
1	`Device.DeviceInfo.AdditionalSoftwareVersion`	string
2	`Device.DeviceInfo.Description`	string
3	`Device.DeviceInfo.FirstUseDate`	dateTime
4	`Device.DeviceInfo.HardwareVersion`	string
5	`Device.DeviceInfo.Manufacturer`	string
6	`Device.DeviceInfo.ManufacturerOUI`	string
7	`Device.DeviceInfo.MemoryStatus.Free`	unsignedInt
8	`Device.DeviceInfo.MemoryStatus.Total`	unsignedInt
9	`Device.DeviceInfo.Migration.MigrationStatus`	string
10	`Device.DeviceInfo.MigrationPreparer.MigrationReady`	string
11	`Device.DeviceInfo.ModelName`	string
12	`Device.DeviceInfo.ProcessStatus.CPUUsage`	unsignedInt
13	`Device.DeviceInfo.ProcessStatus.Process.{i}.CPUTime`	unsignedInt
14	`Device.DeviceInfo.ProcessStatus.Process.{i}.Command`	string
15	`Device.DeviceInfo.ProcessStatus.Process.{i}.PID`	unsignedInt
16	`Device.DeviceInfo.ProcessStatus.Process.{i}.Priority`	unsignedInt
17	`Device.DeviceInfo.ProcessStatus.Process.{i}.Size`	unsignedInt
18	`Device.DeviceInfo.ProcessStatus.Process.{i}.State`	string
19	`Device.DeviceInfo.ProcessStatus.ProcessNumberOfEntries`	unsignedInt
20	`Device.DeviceInfo.Processor.{i}.Architecture`	string
21	`Device.DeviceInfo.ProcessorNumberOfEntries`	unsignedInt
22	`Device.DeviceInfo.ProductClass`	string
23	`Device.DeviceInfo.SerialNumber`	string
24	`Device.DeviceInfo.SoftwareVersion`	string
25	`Device.DeviceInfo.SupportedDataModel.1.Features`	string

Comcast Confidential - Any unauthorized disclosure or use is strictly prohibited

26	Device.DeviceInfo.SupportedDataModel.1.URL	string
27	Device.DeviceInfo.SupportedDataModel.1.URN	string
28	Device.DeviceInfo.SupportedDataModelNumberOfEntries	unsignedInt
29	Device.DeviceInfo.UpTime	unsignedInt
30	Device.DeviceInfo.VendorLogFileNumberOfEntries	unsignedInt
31	Device.DeviceInfo.X_COMCAST-COM_FirmwareDownloadStatus	string
32	Device.DeviceInfo.X_COMCAST-COM_FirmwareFilename	string
33	Device.DeviceInfo.X_COMCAST-COM_FirmwareToDownload	string
34	Device.DeviceInfo.X_COMCAST-COM_PowerStatus	string
35	Device.DeviceInfo.X_COMCAST-COM_STB_IP	string
36	Device.DeviceInfo.X_COMCAST-COM_STB_MAC	string
37	Device.DeviceInfo.X_RDKCENTRAL-COM.BootStatus	string
38	Device.DeviceInfo.X_RDKCENTRAL-COM_BootTime	unsignedInt
39	Device.DeviceInfo.X_RDKCENTRAL-COM_Experience	string
40	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadPercent	int
41	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadStatus	string
42	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareFilename	string
43	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareUpdateState	string
44	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.IPAddr	string
45	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.MACAddr	string
46	Device.DeviceInfo.X_RDKCENTRAL-COM_RDKVersion	string
47	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.getProfileData	string
48	Device.DeviceInfo.X_RDKCENTRAL-COM_xAccount.HotelCheckout.LastResetTime	unsignedLong
49	Device.DeviceInfo.X_RDKCENTRAL-COM_xAccount.HotelCheckout.Status	string
50	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.Active	int
51	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.DeviceID	string
52	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.DeviceType	string
53	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.Name	string
54	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDeviceCnt	unsignedInt
55	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.DeviceID	string
56	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.MAC	string
57	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.Manufacturer	int
58	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.Profile	string
59	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.RSSI	int
60	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.SignalStrength	string
61	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.DeviceID	string
62	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.DeviceType	string
63	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.Name	string
64	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.Paired	boolean
65	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDeviceCnt	unsignedInt
66	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveryEnabled	boolean

67	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.Enabled	string
68	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.GetDeviceInfo	string
69	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.Connected	boolean
70	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.DeviceID	string
71	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.DeviceType	string
72	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.Name	string
73	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDeviceCnt	unsignedInt
74	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.Logging.xOpsDMLogsUploadStatus	string
75	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshStatus	string
76	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.hwHealthTest.Results	string
77	Device.DeviceInfo.X_RDK_FirmwareName	string

Read-Write Parameters (352)

#	Parameter	Data Type
1	Device.DeviceInfo.ProvisioningCode	string
2	Device.DeviceInfo.SupportedDataModel.2.Features	string
3	Device.DeviceInfo.SupportedDataModel.2.URL	string
4	Device.DeviceInfo.SupportedDataModel.2.URN	string
5	Device.DeviceInfo.X_COMCAST-COM_Reset	string
6	Device.DeviceInfo.X_RDKCENTRAL-COM.CPUTemp	int
7	Device.DeviceInfo.X_RDKCENTRAL-COM.IUI.AppsVersion	string
8	Device.DeviceInfo.X_RDKCENTRAL-COM.IUI.Version	string
9	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadDeferReboot	boolean
10	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadNow	boolean
11	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadProtocol	string
12	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadURL	string
13	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadUseCodebig	boolean
14	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareToDownload	string
15	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.Enable	boolean
16	Device.DeviceInfo.X_RDKCENTRAL-COM_LastRebootReason	string
17	Device.DeviceInfo.X_RDKCENTRAL-COM_Manufacturing.UIbranding	string
18	Device.DeviceInfo.X_RDKCENTRAL-COM_PreferredGatewayType	string
19	Device.DeviceInfo.X_RDKCENTRAL-COM_RDKDownloadManager.DownloadStatus	boolean
20	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.AuthService.Host	string
21	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDB	boolean
22	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDBEnd	boolean
23	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.NetflixESNprefix	string
24	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.OsClass	string
25	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerName	string
26	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerProductName	string

27	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.SsrUrl	string
28	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfRecoveryUrl	string
29	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfUrl	string
30	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.ClearParam	string
31	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CloudStore.Uri	string
32	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ClearDB	boolean
33	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ClearDBEnd	boolean
34	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigChangeTime	unsignedInt
35	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigSetHash	string
36	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigSetTime	unsignedInt
37	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.RetrieveNow	unsignedInt
38	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.XconfSelector	string
39	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.XconfUrl	string
40	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.S3BucketUrl	string
41	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.S3SigningUrl	string
42	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalDEVUrl	string
43	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalPRODUrl	string
44	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalSTBUrl	string
45	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalVBNUrl	string
46	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.ConfigURL	string
47	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.dacBundleFirmwareCompatibilityKey	string
48	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.dacBundlePlatformName	string
49	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DynamicIUIUpdate.IUISelector	string
50	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DynamicIUIUpdate.Pathway.Uri	string
51	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.1080pGraphics.Enable	boolean
52	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.DashPlaybackExclusions	string
53	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.DashPlaybackInclusions	string
54	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.b64Config	string
55	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID	string
56	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Airplay.Enable	boolean
57	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AmazonPrimeVideo.SyePlayer.Enable	boolean
58	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppName	string
59	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppSize	string
60	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppUrl	string
61	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.AppCnt	unsignedInt
62	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.Enable	boolean
63	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.DelayInSecLaunchedToSuspended	unsignedInt
64	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.DelayInSecResumedToSuspended	unsignedInt
65	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.Enable	boolean
66	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AutoReboot.Enable	boolean

67	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AutoReboot.fwDelayReboot	int
68	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.AudioIn.Enable	boolean
69	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.DebugMode.Enable	boolean
70	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.GamePad.Enable	boolean
71	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTSplitAudio.Enable	boolean
72	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTSplitAudio.Language	string
73	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BootstrapConfig.Enable	boolean
74	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CDLDM.CDLModuleUrl	string
75	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CPC1960.Enable	boolean
76	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CRL.DirectOCSP	boolean
77	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CRL.Enable	boolean
78	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Canary.wakeUpEnd	int
79	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Canary.wakeUpStart	int
80	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CrashportalEndpoint.Enable	string
81	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CrashportalEndpoint.URL	string
82	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CredDwnld.Enable	string
83	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CredDwnld.Use	string
84	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DAB.Enable	boolean
85	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DHCPv6Client.Enable	boolean
86	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DNSStrictOrder.Enable	boolean
87	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DefaultSupportedLocales	string
88	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.Enable	string
89	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.RecordsToBuffer	string
90	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.ServiceUrl	string
91	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.EnableHttpCDL.Enable	boolean
92	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.EntOsAppPlatform.EnableDistPlatform	boolean
93	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FOG_CFG.b64Config	string
94	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FWUpdate.AutoExcluded.Enable	boolean
95	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FWUpdate.AutoExcluded.XconfUrl	string
96	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.HdmiCecSink.CECVersion	string
97	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IDS.Enable	boolean
98	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IDS.ScanTask	string
99	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPControl.Service.Discovery.Enable	boolean
100	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPControl.Subsystem.RICS.Enable	boolean
101	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPRemotePort.Enable	boolean
102	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.InactiveApplications.Maximum	unsignedInt
103	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IncrementalCDL.Enable	boolean
104	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.JSPPCache.Enable	boolean
105	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.AdCacheEnable	string
106	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Advt_Opt_Out_Key	string
107	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.AltconReceiver	string

108	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.ByteRangeDownload	string
109	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Enable	string
110	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.PSNUrl	string
111	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.PlacementReqUrl	string
112	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.ProgrammerEnable	string
113	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schema_Location	string
114	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_NGOD	string
115	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_admin	string
116	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_core	string
117	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.XMLNS_Schema	string
118	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.XMLSchema_Instance	string
119	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Xifaid_Xml_Key	string
120	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LaunchDarkly.EnvKeyLabel	string
121	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LnFUseXPKI.Enable	boolean
122	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadBeforeDeepSleep.Enable	boolean
123	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadEndpoint.Enable	string
124	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadEndpoint.URL	string
125	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LoudnessEquivalence.Enable	boolean
126	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MEMSWAP.Enable	string
127	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MOCASSH.Enable	boolean
128	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MS12.DAPv2_Enable	boolean
129	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MS12.DE_Enable	boolean
130	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MTLS.mTlsXcSsr.Enable	boolean
131	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ManageableNotification.Enable	boolean
132	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Miracast.Enable	boolean
133	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NTP.failoverServer	string
134	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonPersistent.WebPACDL.Enable	boolean
135	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.ApparmorBlocklist	string
136	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.Blocklist	string
137	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.Enable	boolean
138	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PeriodicFWCheck.Enable	boolean
139	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PeriodicFwCheck.timeperiod	unsignedInt
140	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.BurstCnt	unsignedInt
141	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.Enable	boolean
142	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.EndTime	unsignedInt
143	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.StartTime	unsignedInt
144	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.Type	string
145	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.DeepSleepNotification.Enable	boolean
146	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.PwrMgr2.Enable	boolean
147	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.UserInactivityNotification.Enable	boolean

148	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.UserInactivityNotification.TimeMinutes	unsignedInt
149	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Preference.URL	string
150	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PressAndRelease.EOSMethod	int
151	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PressAndRelease.EOSTimeout	int
152	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ProtectX1Services.Enable	boolean
153	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.BACKGROUND_MEM_USAGE_HIGH_WATERMARK	unsignedInt
154	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.BACKGROUND_MEM_USAGE_LOW_WATERMARK	unsignedInt
155	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.HTML_APP_RESURRECTION_PERIOD.days	unsignedInt
156	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.Enable	boolean
157	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.IssueType	string
158	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.WebCfgData	string
159	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDMDecoupledVersionManagement.Enable	boolean
160	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.AudioProfileTarget	int
161	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.FF.RspIdle	int
162	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.HostPacketDecryption.Enable	boolean
163	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.OpusEncoderParams	string
164	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XDIU	int
165	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XRC	int
166	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XVP	int
167	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.VoiceEncryption.Enable	boolean
168	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Detection	boolean
169	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Duration	int
170	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Enable	boolean
171	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RedRecovery.Status	string
172	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Resourcemanager.Blacklist.Enable	boolean
173	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Resourcemanager.ReserveTTS.Enable	boolean
174	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RoamTrigger	string
175	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SDCARD_SCRATCHPAD.Enable	string
176	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SHORTS.Enable	boolean
177	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.STAGE.Enable	boolean
178	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLDirect.Enable	boolean
179	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.Enable	boolean
180	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.LowSpeed	int
181	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.TopSpeed	int
182	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ScreenCapture.Enable	boolean
183	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ScreenCapture.URL	string
184	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SecDump.Enable	boolean
185	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SoundPlayer.Enable	boolean

186	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.Enable	boolean
187	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.ForceAutoReboot	int
188	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.StandbyAutoReboot	int
189	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StorageManager.maxAdaptiveBitRate	int
190	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StorageManager.maxTSBDurationMinutes	int
191	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SupportedLanguages	string
192	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.TR069support.Enable	boolean
193	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL	string
194	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version	string
195	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThreadMonitorMinidump.Enable	boolean
196	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThreadPrioConfig.Enable	boolean
197	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThunderSecurity.Enable	boolean
198	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.TvSettings.DynamicAutoLatency	boolean
199	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UNII3.Enable	boolean
200	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UPnP.Refactor.Enable	boolean
201	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UPnPxPKI.Enable	boolean
202	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.USB_AutoMount.Enable	string
203	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.USB_HID.Enable	boolean
204	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UploadLogsOnUnscheduledReboot.Disable	boolean
205	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ViperPPUrl	string
206	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioConfidenceThreshold	string
207	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioDuckingLevel	string
208	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioDuckingType	int
209	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioMode	int
210	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioTiming	int
211	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.KeywordSensitivity	string
212	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.VSDKConfiguration	string
213	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFi.WiFiStatsLogInterval	unsignedInt
214	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.Enable	boolean
215	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.EthernetLoggingInterval	unsignedInt
216	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.PacketLossLoggingInterval	string
217	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.ReassociateTolerance	unsignedInt
218	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.WifiLoggingInterval	unsignedInt
219	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.WifiReassociateInterval	unsignedInt
220	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset. WifiResetIntervalForDriverIssue	unsignedInt
221	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset. WifiResetIntervalForPacketLoss	unsignedInt
222	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WifiOptimizer.Enable	boolean
223	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XDial.AppList	string
224	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRDsp.XR19.Configuration	string
225	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBDerivationMethod	int

226	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBEnable	boolean
227	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBFailThreshold	int
228	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.Default	string
229	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.Enable	boolean
230	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR11v2	string
231	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR15v1	string
232	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR15v2	string
233	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR16v1	string
234	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR19v1	string
235	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XRAv1	string
236	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRmacPolling.Enable	boolean
237	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRmacPolling.macPollingInterval	int
238	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.Enable	boolean
239	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.GraphiteURL	string
240	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.Hostname	string
241	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.PortNumber	unsignedInt
242	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.device_update	string
243	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.global	string
244	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_ble	string
245	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_ip	string
246	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_rf4ce	string
247	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.ble	string
248	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.global	string
249	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.ip	string
250	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.rf4ce	string
251	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.voice	string
252	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.voice	string
253	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.vsdk	string
254	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.eMMCFirmware.Version	string
255	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.eMMCMitigation.Disable	boolean
256	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.fkpskdf.Enable	boolean
257	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.memcapture.Duration	int
258	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.memcapture.Enable	boolean
259	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.systemd-analyze.Enable	boolean
260	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.xMemInsight.Args	string
261	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.xMemInsight.Enable	boolean
262	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.HostIf.ParodusTokenServerUrl	string
263	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Identity.DbgServices.Enable	boolean
264	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Identity.DeviceType	string
265	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcaUploadPRODUrl	string
266	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcaUploadUrl	string

267	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerCQAUrl	string
268	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerDEVUrl	string
269	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerPRODUrl	string
270	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogUrl	string
271	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmScpServerUrl	string
272	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.LogServerUrl	string
273	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.S3SignedBucketUrl	string
274	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.SsrUrl	string
275	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SecManager.dieselUrl	string
276	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.Activation	string
277	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.AuthMessage	string
278	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.NameSpacePrefix	string
279	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.NameSpaceUri	string
280	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.Renewal	string
281	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.URL1	string
282	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.URL2	string
283	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.backoffIntervalMax	unsignedLong
284	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.disableCredentialsPrefetchCaching	boolean
285	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CCRProxyUrl	string
286	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CDNCCPUrl	string
287	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CcpUrl	string
288	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.DAC15CDLUrl	string
289	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.EDGEDNSProxyUrl	string
290	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.FkpsBrokerUrl	string
291	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.FkpsUrl	string
292	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.PRODCDLUrl	string
293	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XcalUrl	string
294	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XconfDEVUrl	string
295	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XconfUrl	string
296	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SystemServices.FriendlyName	string
297	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.TextToSpeech.URL	string
298	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.LRHAcceptValue	string
299	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.LRHContentType	string
300	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SchemeIdUriDaiStream	string
301	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SchemeIdUriVssStream	string
302	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SlowMotion	boolean
303	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.asyncTune	boolean
304	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.cdvrLiveOffset	unsignedLong
305	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.client-dai	boolean

306	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.curlStore	boolean
307	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.defaultBitrate	unsignedLong
308	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.defaultBitrate4K	unsignedLong
309	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableAC3	boolean
310	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableAC4	boolean
311	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableATMOS	boolean
312	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableEC3	boolean
313	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableCMCD	boolean
314	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLiveLatencyCorrection	boolean
315	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLowLatencyCorrection	boolean
316	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLowLatencyDash	boolean
317	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enablePTSReStamp	boolean
318	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableVideoEndEvent	boolean
319	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.info	boolean
320	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.liveOffset	unsignedLong
321	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.liveOffset4K	string
322	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.manifestTimeout	unsignedLong
323	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.maxBitrate	unsignedLong
324	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.maxInitFragCachePerTrack	int
325	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.minBitrate	unsignedLong
326	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.networkTimeout	unsignedLong
327	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.persistBitrateOverSeek	boolean
328	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.playlistTimeout	unsignedLong
329	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.preferredDrm	int
330	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.rateCorrectionDelay	unsignedLong
331	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.sharedSSL	boolean
332	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.stereoOnly	boolean
333	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.supportTLS	unsignedLong
334	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.tsbInterruptHandling	boolean
335	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.useSecManager	boolean
336	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.useWesterosSink	boolean
337	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.apps.watchdogmode	boolean
338	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.fog.ZeroDrmHost	string
339	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.LongpollUrl	string
340	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.Status	string

341	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.UpdateSchedule	string
342	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.vodclient.StunnelConnect	string
343	Device.DeviceInfo.X_RDKCENTRAL-COM_Reset	string
344	Device.DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId	string
345	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.LimitBeaconDetection	boolean
346	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ForwardSSH.Enable	boolean
347	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.DeviceManageableNotification	string
348	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadCompletedNotification	boolean
349	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadStartedNotification	string
350	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.RebootPendingNotification	unsignedInt
351	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshArgs	string
352	Device.DeviceInfo.X_RDK_RDKProfileName	string

Write-Only Parameters (17)

#	Parameter	Data Type
1	Device.DeviceInfo.X_RDKCENTRAL-COM_RDKDownloadManager.InstallPackage	string
2	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DolbyVision.Enable	boolean
3	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.EncryptCloudUpload.Enable	boolean
4	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UhdEnable.Enable	boolean
5	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.Enable	boolean
6	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.EnablePeriodicRun	boolean
7	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.PeriodicRunFrequency	unsignedInt
8	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.ResultFilter.Enable	boolean
9	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.ResultFilter.FilterParams	string
10	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.ResultFilter.QueueDepth	unsignedInt
11	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.ResultFilter.ResultsFiltered	boolean
12	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.cpuThreshold	unsignedInt
13	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.hwHealthTest.dramThreshold	unsignedInt
14	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.Logging.xOpsDMUploadLogsNow	boolean
15	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.RebootNow	boolean
16	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshTrigger	string
17	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.hwHealthTest.ExecuteTest	int

6. Device.Time get/set handlers for NTP servers
   - Device.Time

   Read-Only Parameters (1)

#	Parameter	Data Type
1	Device.Time.X_RDK_CurrentUTCTime	string

   Read-Write Parameters (18)

#	Parameter	Data Type
1	`Device.Time.ChronyEnable`	boolean
2	`Device.Time.CurrentLocalTime`	string
3	`Device.Time.Enable`	boolean
4	`Device.Time.LocalTimeZone`	string
5	`Device.Time.NTPMaxpoll`	unsignedInt
6	`Device.Time.NTPMaxstep`	string
7	`Device.Time.NTPMinpoll`	unsignedInt
8	`Device.Time.NTPServer1`	string
9	`Device.Time.NTPServer1Directive`	string
10	`Device.Time.NTPServer2`	string
11	`Device.Time.NTPServer2Directive`	string
12	`Device.Time.NTPServer3`	string
13	`Device.Time.NTPServer3Directive`	string
14	`Device.Time.NTPServer4`	string
15	`Device.Time.NTPServer4Directive`	string
16	`Device.Time.NTPServer5`	string
17	`Device.Time.NTPServer5Directive`	string
18	`Device.Time.Status`	string

7. Bootstrap get/set handlers
   - Verify the get and set handlers using rbuscli for a few bootstrap parameters that are present in etc/partners_defaults.json.
   -

`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDB`	boolean
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDBEnd`	boolean
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.NetflixESNprefix`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.OsClass`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerName`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerProductName`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.SsrUrl`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfRecoveryUrl`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfUrl`	string

8. WEBPA get/set for tr181 parameters
   - Verify the tr181 parameter get/set handlers by issuing webpa based get and set commands.
   - Device.X_RDK_WebPA

     Read-Only Parameters (2)

#	Parameter	Data Type
1	`Device.X_RDK_WebPA_Server.URL`	string
2	`Device.X_RDK_WebPA_TokenServer.URL`	string

     Read-Write Parameters (1)

#	Parameter	Data Type
1	`Device.X_RDK_WebPA_DNSText.URL`	string

9. REVSSH
   a. RevSSH functionality with following RFC
   b. tr181 -s -v "TEST" Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Identity.DeviceType

10. IP Test
    - Verify the IpAddress is 127.0.0.1 for Interface IpV4Address
    - verify IPV4 address enable status
    - Verify status for IPv4Address is Enabled using TR69 Parameter
    - Verify IPv6AddressNumberOfEntries value is 1 using tr69 parameter.
    - verify address origin for IPV6 address using tr69 params
    - verify the IPAddressStatus for IPv6Address Interface using TR69 Parameter.
    - verify IPV6 Address prefix preferred life time using tr69 Parameter.
    - verify IPV6 Address valid life time using tr69 Parameter.
    - verify static type for IPV6 prefix using tr69 Parameter.
    - verify ValidLifetime for IPV6 prefix using tr69 Parameter.
    - Verify value for IPv6Enable is either true or 1 using TR69 Parameter
    - Verify status for IPv6Address is Enabled using TR69.
    - Device.IP

    Read-Only Parameters (73)

#	Parameter	Data Type
1	`Device.IP.ActivePort.{i}.LocalIPAddress`	string
2	`Device.IP.ActivePort.{i}.LocalPort`	unsignedInt
3	`Device.IP.ActivePort.{i}.RemoteIPAddress`	string
4	`Device.IP.ActivePort.{i}.RemotePort`	unsignedInt
5	`Device.IP.ActivePort.{i}.Status`	string
6	`Device.IP.ActivePortNumberOfEntries`	unsignedInt
7	`Device.IP.Diagnostics.DownloadDiagnostics.BOMTime`	dateTime
8	`Device.IP.Diagnostics.DownloadDiagnostics.DownloadTransports`	string
9	`Device.IP.Diagnostics.DownloadDiagnostics.EOMTime`	dateTime
10	`Device.IP.Diagnostics.DownloadDiagnostics.ROMTime`	dateTime
11	`Device.IP.Diagnostics.DownloadDiagnostics.TCPOpenRequestTime`	dateTime
12	`Device.IP.Diagnostics.DownloadDiagnostics.TCPOpenResponseTime`	dateTime
13	`Device.IP.Diagnostics.DownloadDiagnostics.TestBytesReceived`	unsignedInt
14	`Device.IP.Diagnostics.DownloadDiagnostics.TotalBytesReceived`	unsignedInt
15	`Device.IP.Diagnostics.IPPing.AverageResponseTime`	unsignedInt
16	`Device.IP.Diagnostics.IPPing.FailureCount`	unsignedInt
17	`Device.IP.Diagnostics.IPPing.MaximumResponseTime`	unsignedInt
18	`Device.IP.Diagnostics.IPPing.MinimumResponseTime`	unsignedInt
19	`Device.IP.Diagnostics.IPPing.SuccessCount`	unsignedInt
20	`Device.IP.Diagnostics.TraceRoute.ResponseTime`	unsignedInt
21	`Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.ErrorCode`	unsignedInt
22	`Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.Host`	string
23	`Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.HostAddress`	string
24	`Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.RTTimes`	string
25	`Device.IP.Diagnostics.TraceRoute.RouteHopsNumberOfEntries`	unsignedInt
26	`Device.IP.Diagnostics.UDPEchoConfig.BytesReceived`	unsignedInt
27	`Device.IP.Diagnostics.UDPEchoConfig.BytesResponded`	unsignedInt
28	`Device.IP.Diagnostics.UDPEchoConfig.EchoPlusSupported`	boolean
29	`Device.IP.Diagnostics.UDPEchoConfig.PacketsReceived`	unsignedInt
30	`Device.IP.Diagnostics.UDPEchoConfig.PacketsResponded`	unsignedInt
31	`Device.IP.Diagnostics.UDPEchoConfig.TimeFirstPacketReceived`	dateTime

32	Device.IP.Diagnostics.UDPEchoConfig.TimeLastPacketReceived	dateTime
33	Device.IP.Diagnostics.UploadDiagnostics.BOMTime	dateTime
34	Device.IP.Diagnostics.UploadDiagnostics.EOMTime	dateTime
35	Device.IP.Diagnostics.UploadDiagnostics.ROMTime	dateTime
36	Device.IP.Diagnostics.UploadDiagnostics.TCPOpenRequestTime	dateTime
37	Device.IP.Diagnostics.UploadDiagnostics.TCPOpenResponseTime	dateTime
38	Device.IP.Diagnostics.UploadDiagnostics.TotalBytesSent	unsignedInt
39	Device.IP.Diagnostics.UploadDiagnostics.UploadTransports	string
40	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Status	unsignedInt
41	Device.IP.IPv4Capable	boolean
42	Device.IP.IPv4Status	string
43	Device.IP.Interface.{i}.IPv4Address.{i}.AddressingType	string
44	Device.IP.Interface.{i}.IPv4Address.{i}.Status	string
45	Device.IP.Interface.{i}.IPv4AddressNumberOfEntries	unsignedInt
46	Device.IP.Interface.{i}.IPv6Address.{i}.IPAddressStatus	string
47	Device.IP.Interface.{i}.IPv6Address.{i}.Origin	string
48	Device.IP.Interface.{i}.IPv6Address.{i}.Status	string
49	Device.IP.Interface.{i}.IPv6AddressNumberOfEntries	unsignedInt
50	Device.IP.Interface.{i}.IPv6Prefix.{i}.Origin	string
51	Device.IP.Interface.{i}.IPv6Prefix.{i}.PrefixStatus	string
52	Device.IP.Interface.{i}.IPv6Prefix.{i}.Status	string
53	Device.IP.Interface.{i}.IPv6PrefixNumberOfEntries	unsignedInt
54	Device.IP.Interface.{i}.LastChange	unsignedInt
55	Device.IP.Interface.{i}.Name	string
56	Device.IP.Interface.{i}.Stats.BroadcastPacketsReceived	unsignedLong
57	Device.IP.Interface.{i}.Stats.BroadcastPacketsSent	unsignedLong
58	Device.IP.Interface.{i}.Stats.BytesReceived	unsignedLong
59	Device.IP.Interface.{i}.Stats.BytesSent	unsignedLong
60	Device.IP.Interface.{i}.Stats.DiscardPacketsReceived	unsignedInt
61	Device.IP.Interface.{i}.Stats.DiscardPacketsSent	unsignedInt
62	Device.IP.Interface.{i}.Stats.ErrorsReceived	unsignedInt
63	Device.IP.Interface.{i}.Stats.ErrorsSent	unsignedInt
64	Device.IP.Interface.{i}.Stats.MulticastPacketsReceived	unsignedLong
65	Device.IP.Interface.{i}.Stats.MulticastPacketsSent	unsignedLong
66	Device.IP.Interface.{i}.Stats.PacketsReceived	unsignedLong
67	Device.IP.Interface.{i}.Stats.PacketsSent	unsignedLong
68	Device.IP.Interface.{i}.Stats.UnicastPacketsReceived	unsignedLong
69	Device.IP.Interface.{i}.Stats.UnicastPacketsSent	unsignedLong
70	Device.IP.Interface.{i}.Stats.UnknownProtoPacketsReceived	unsignedInt
71	Device.IP.Interface.{i}.Status	string
72	Device.IP.Interface.{i}.Type	string

73	Device.IP.InterfaceNumberOfEntries	unsignedInt

Read-Write Parameters (71)

#	Parameter	Data Type
1	Device.IP.Diagnostics.DownloadDiagnostics.DSCP	unsignedInt
2	Device.IP.Diagnostics.DownloadDiagnostics.DiagnosticsState	string
3	Device.IP.Diagnostics.DownloadDiagnostics.DownloadURL	string
4	Device.IP.Diagnostics.DownloadDiagnostics.EthernetPriority	unsignedInt
5	Device.IP.Diagnostics.DownloadDiagnostics.Interface	string
6	Device.IP.Diagnostics.IPPing.DSCP	unsignedInt
7	Device.IP.Diagnostics.IPPing.DataBlockSize	unsignedInt
8	Device.IP.Diagnostics.IPPing.DiagnosticsState	string
9	Device.IP.Diagnostics.IPPing.Host	string
10	Device.IP.Diagnostics.IPPing.Interface	string
11	Device.IP.Diagnostics.IPPing.NumberOfRepetitions	unsignedInt
12	Device.IP.Diagnostics.IPPing.Timeout	unsignedInt
13	Device.IP.Diagnostics.TraceRoute.DSCP	unsignedInt
14	Device.IP.Diagnostics.TraceRoute.DataBlockSize	unsignedInt
15	Device.IP.Diagnostics.TraceRoute.DiagnosticsState	string
16	Device.IP.Diagnostics.TraceRoute.Host	string
17	Device.IP.Diagnostics.TraceRoute.Interface	string
18	Device.IP.Diagnostics.TraceRoute.MaxHopCount	unsignedInt
19	Device.IP.Diagnostics.TraceRoute.NumberOfTries	unsignedInt
20	Device.IP.Diagnostics.TraceRoute.Timeout	unsignedInt
21	Device.IP.Diagnostics.UDPEchoConfig.EchoPlusEnabled	boolean
22	Device.IP.Diagnostics.UDPEchoConfig.Enable	boolean
23	Device.IP.Diagnostics.UDPEchoConfig.Interface	string
24	Device.IP.Diagnostics.UDPEchoConfig.SourceIPAddress	string
25	Device.IP.Diagnostics.UDPEchoConfig.UDPPort	unsignedInt
26	Device.IP.Diagnostics.UploadDiagnostics.DSCP	unsignedInt
27	Device.IP.Diagnostics.UploadDiagnostics.DiagnosticsState	string
28	Device.IP.Diagnostics.UploadDiagnostics.EthernetPriority	unsignedInt
29	Device.IP.Diagnostics.UploadDiagnostics.Interface	string
30	Device.IP.Diagnostics.UploadDiagnostics.TestFileLength	unsignedInt
31	Device.IP.Diagnostics.UploadDiagnostics.UploadURL	string
32	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Argument	string
33	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Authentication	string
34	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.ClientType	unsignedInt
35	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Enable	boolean
36	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Enable_Speedtest	boolean
37	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Run	boolean

38	`Device.IP.IPv4Enable`	boolean
39	`Device.IP.Interface.{i}.Alias`	string
40	`Device.IP.Interface.{i}.AutoIPEnable`	boolean
41	`Device.IP.Interface.{i}.Enable`	boolean
42	`Device.IP.Interface.{i}.IPv4Address.{i}.Alias`	string
43	`Device.IP.Interface.{i}.IPv4Address.{i}.Enable`	boolean
44	`Device.IP.Interface.{i}.IPv4Address.{i}.IPAddress`	string
45	`Device.IP.Interface.{i}.IPv4Address.{i}.SubnetMask`	string
46	`Device.IP.Interface.{i}.IPv4Enable`	boolean
47	`Device.IP.Interface.{i}.IPv6Address.{i}.Alias`	string
48	`Device.IP.Interface.{i}.IPv6Address.{i}.Anycast`	boolean
49	`Device.IP.Interface.{i}.IPv6Address.{i}.Enable`	boolean
50	`Device.IP.Interface.{i}.IPv6Address.{i}.IPAddress`	string
51	`Device.IP.Interface.{i}.IPv6Address.{i}.PreferredLifetime`	dateTime
52	`Device.IP.Interface.{i}.IPv6Address.{i}.Prefix`	string
53	`Device.IP.Interface.{i}.IPv6Address.{i}.ValidLifetime`	dateTime
54	`Device.IP.Interface.{i}.IPv6Enable`	boolean
55	`Device.IP.Interface.{i}.IPv6Prefix.{i}.Alias`	string
56	`Device.IP.Interface.{i}.IPv6Prefix.{i}.Autonomous`	boolean
57	`Device.IP.Interface.{i}.IPv6Prefix.{i}.ChildPrefixBits`	string
58	`Device.IP.Interface.{i}.IPv6Prefix.{i}.Enable`	boolean
59	`Device.IP.Interface.{i}.IPv6Prefix.{i}.OnLink`	boolean
60	`Device.IP.Interface.{i}.IPv6Prefix.{i}.ParentPrefix`	string
61	`Device.IP.Interface.{i}.IPv6Prefix.{i}.PreferredLifetime`	dateTime
62	`Device.IP.Interface.{i}.IPv6Prefix.{i}.Prefix`	string
63	`Device.IP.Interface.{i}.IPv6Prefix.{i}.StaticType`	string
64	`Device.IP.Interface.{i}.IPv6Prefix.{i}.ValidLifetime`	dateTime
65	`Device.IP.Interface.{i}.Loopback`	boolean
66	`Device.IP.Interface.{i}.LowerLayers`	string
67	`Device.IP.Interface.{i}.MaxMTUSize`	unsignedInt
68	`Device.IP.Interface.{i}.Reset`	boolean
69	`Device.IP.Interface.{i}.Router`	string
70	`Device.IP.Interface.{i}.ULAEnable`	boolean
71	`Device.IP.ULAPrefix`	string

11. MFR DATAMODEL
    a.

Device.DeviceInfo.AdditionalSoftwareVersion
Device.DeviceInfo.Description
Device.DeviceInfo.FirstUseDate
Device.DeviceInfo.HardwareVersion
Device.DeviceInfo.Manufacturer
Device.DeviceInfo.ManufacturerOUI

Device.DeviceInfo.ModelName
Device.DeviceInfo.ProcessorNumberOfEntries
Device.DeviceInfo.ProductClass
Device.DeviceInfo.ProvisioningCode
Device.DeviceInfo.SerialNumber
Device.DeviceInfo.SoftwareVersion
Device.DeviceInfo.SupportedDataModelNumberOfEntries
Device.DeviceInfo.UpTime
Device.DeviceInfo.VendorLogFileNumberOfEntries
Device.DeviceInfo.X_COMCAST-COM_FirmwareDownloadStatus
Device.DeviceInfo.X_COMCAST-COM_FirmwareFilename
Device.DeviceInfo.X_COMCAST-COM_FirmwareToDownload
Device.DeviceInfo.X_COMCAST-COM_PowerStatus
Device.DeviceInfo.X_COMCAST-COM_Reset
Device.DeviceInfo.X_COMCAST-COM_STB_IP
Device.DeviceInfo.X_COMCAST-COM_STB_MAC
Device.DeviceInfo.X_RDKCENTRAL-COM_BootTime
Device.DeviceInfo.X_RDKCENTRAL-COM_Experience
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadDeferReboot
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadNow
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadPercent
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadProtocol
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadStatus
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadURL
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadUseCodebig
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareFilename
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareToDownload
Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareUpdateState
Device.DeviceInfo.X_RDKCENTRAL-COM_LastRebootReason
Device.DeviceInfo.X_RDKCENTRAL-COM_PreferredGatewayType
Device.DeviceInfo.X_RDKCENTRAL-COM_RDKVersion
Device.DeviceInfo.X_RDKCENTRAL-COM_Reset
Device.DeviceInfo.X_RDK_FirmwareName
Device.DeviceInfo.X_RDK_RDKProfileName

12. Bootstrap initialization sequence
    - Provide a partner ID and verify that the bootstrap.ini and bootstrap.journal files are created with the configuration matching the given Partner ID.
13. Image Upgrade via RDK portal
    a. Ensure the script is triggered.
14. Ensure we have the rfcdefaults.ini created in the device.
15. Verify that parodus connection and reconnection works fine
16. Device.X_COMCAST-COM_Xcalibur.Client.xconfCheckNow
17. Test to verify RFC functionality of Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MEMSWAP.Enable
18. Test case to verify Post reboot status of tr69 and parodus process
19. Test case to verify Post FSR status of tr69 and parodus process
20. Test case to verify parodus crash
21. Test case to verify tr69hostif crash

Comcast Confidential - Any unauthorized disclosure or use is strictly prohibited

22. Test case to verify invalid and non exisiting RFC'S
23. Test case to verify default RFC value in data-model.xml
24. Test case to verify default RFC value in /tmp/rfcdefaults.ini
25. Test case to verify XConf for RFC, Non RFC and bootstrap namespace parameters
26. Test case to verify opt/secure/RFC/ files are created after a warehouse/factory reset
27. Test case to trigger remote debugger using tr181 param
28. Test case to verify tr181 values
29. Test case to modify and verify the telemetry version
30. Verify logs are captured fine in tr69hostif.log
31. Test case to verify crash during standby and maintenance reboot
32. Ethernet DataModel Validation
    a. Device.Ethernet

Read-Only Parameters (25)

#	Parameter	Data Type
1	`Device.Ethernet.Interface.{i}.LastChange`	unsignedInt
2	`Device.Ethernet.Interface.{i}.MACAddress`	string
3	`Device.Ethernet.Interface.{i}.Name`	string
4	`Device.Ethernet.Interface.{i}.Stats.BroadcastPacketsReceived`	unsignedLong
5	`Device.Ethernet.Interface.{i}.Stats.BroadcastPacketsSent`	unsignedLong
6	`Device.Ethernet.Interface.{i}.Stats.BytesReceived`	unsignedLong
7	`Device.Ethernet.Interface.{i}.Stats.BytesSent`	unsignedLong
8	`Device.Ethernet.Interface.{i}.Stats.DiscardPacketsReceived`	unsignedInt
9	`Device.Ethernet.Interface.{i}.Stats.DiscardPacketsSent`	unsignedInt
10	`Device.Ethernet.Interface.{i}.Stats.ErrorsReceived`	unsignedInt
11	`Device.Ethernet.Interface.{i}.Stats.ErrorsSent`	unsignedInt
12	`Device.Ethernet.Interface.{i}.Stats.MulticastPacketsReceived`	unsignedLong
13	`Device.Ethernet.Interface.{i}.Stats.MulticastPacketsSent`	unsignedLong
14	`Device.Ethernet.Interface.{i}.Stats.PacketsReceived`	unsignedLong
15	`Device.Ethernet.Interface.{i}.Stats.PacketsSent`	unsignedLong
16	`Device.Ethernet.Interface.{i}.Stats.UnicastPacketsReceived`	unsignedLong
17	`Device.Ethernet.Interface.{i}.Stats.UnicastPacketsSent`	unsignedLong
18	`Device.Ethernet.Interface.{i}.Stats.UnknownProtoPacketsReceived`	unsignedInt
19	`Device.Ethernet.Interface.{i}.Status`	string
20	`Device.Ethernet.Interface.{i}.Upstream`	boolean
21	`Device.Ethernet.InterfaceNumberOfEntries`	unsignedInt
22	`Device.Ethernet.Link.{i}.MACAddress`	string
23	`Device.Ethernet.Link.{i}.Name`	string
24	`Device.Ethernet.Link.{i}.Status`	string
25	`Device.Ethernet.LinkNumberOfEntries`	unsignedInt

Read-Write Parameters (7)

#	Parameter	Data Type
1	`Device.Ethernet.Interface.{i}.Alias`	string
2	`Device.Ethernet.Interface.{i}.DuplexMode`	string
3	`Device.Ethernet.Interface.{i}.Enable`	boolean
4	`Device.Ethernet.Interface.{i}.LowerLayers`	string

Comcast Confidential - Any unauthorized disclosure or use is strictly prohibited

5	`Device.Ethernet.Interface.{i}.MaxBitRate`	int
6	`Device.Ethernet.Link.{i}.Enable`	boolean
7	`Device.Ethernet.Link.{i}.LowerLayers`	string

33. Telemetry Datamodel Validation
    a. Read-Write Parameters (2)

#	Parameter	Data Type
1	`Device.X_RDKCENTRAL-COM_T2.ReportProfiles`	string
2	`Device.X_RDKCENTRAL-COM_T2.ReportProfilesMsgPack`	string

34. Wifi and Radio Parameter Test
    a. Read-Only Parameters (51)

#	Parameter	Data Type
1	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.Active`	boolean
2	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.AuthenticationState`	boolean
3	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.LastDataDownlinkRate`	unsignedInt
4	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.LastDataUplinkRate`	unsignedInt
5	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.MACAddress`	string
6	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.Retransmissions`	unsignedInt
7	`Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.SignalStrength`	int
8	`Device.WiFi.AccessPoint.{i}.AssociatedDeviceNumberOfEntries`	unsignedInt
9	`Device.WiFi.AccessPoint.{i}.Security.ModesSupported`	string
10	`Device.WiFi.AccessPoint.{i}.Status`	string
11	`Device.WiFi.AccessPoint.{i}.UAPSDCapability`	boolean
12	`Device.WiFi.AccessPoint.{i}.WMMCapability`	boolean
13	`Device.WiFi.AccessPoint.{i}.WPS.ConfigMethodsSupported`	string
14	`Device.WiFi.AccessPointNumberOfEntries`	unsignedInt
15	`Device.WiFi.EndPoint.{i}.Profile.{i}.Status`	string
16	`Device.WiFi.EndPoint.{i}.ProfileNumberOfEntries`	unsignedInt
17	`Device.WiFi.EndPoint.{i}.SSIDReference`	string
18	`Device.WiFi.EndPoint.{i}.Security.ModesEnabled`	string
19	`Device.WiFi.EndPoint.{i}.Security.ModesSupported`	string
20	`Device.WiFi.EndPoint.{i}.Stats.LastDataDownlinkRate`	unsignedInt
21	`Device.WiFi.EndPoint.{i}.Stats.LastDataUplinkRate`	unsignedInt
22	`Device.WiFi.EndPoint.{i}.Stats.Retransmissions`	unsignedInt
23	`Device.WiFi.EndPoint.{i}.Stats.SignalStrength`	int
24	`Device.WiFi.EndPoint.{i}.Status`	string
25	`Device.WiFi.EndPoint.{i}.WPS.ConfigMethodsSupported`	string
26	`Device.WiFi.EndPointNumberOfEntries`	unsignedInt
27	`Device.WiFi.Radio.{i}.OperatingChannelBandwidth`	string
28	`Device.WiFi.Radio.{i}.Stats.Noise`	int
29	`Device.WiFi.Radio.{i}.Stats.PacketsReceived`	unsignedLong
30	`Device.WiFi.RadioNumberOfEntries`	unsignedInt

31	Device.WiFi.SSID.{i}.BSSID	string
32	Device.WiFi.SSID.{i}.LastChange	unsignedInt
33	Device.WiFi.SSID.{i}.MACAddress	string
34	Device.WiFi.SSID.{i}.Name	string
35	Device.WiFi.SSID.{i}.Stats.BroadcastPacketsReceived	unsignedLong
36	Device.WiFi.SSID.{i}.Stats.BroadcastPacketsSent	unsignedLong
37	Device.WiFi.SSID.{i}.Stats.BytesReceived	unsignedLong
38	Device.WiFi.SSID.{i}.Stats.BytesSent	unsignedLong
39	Device.WiFi.SSID.{i}.Stats.DiscardPacketsReceived	unsignedInt
40	Device.WiFi.SSID.{i}.Stats.DiscardPacketsSent	unsignedInt
41	Device.WiFi.SSID.{i}.Stats.ErrorsReceived	unsignedInt
42	Device.WiFi.SSID.{i}.Stats.ErrorsSent	unsignedInt
43	Device.WiFi.SSID.{i}.Stats.MulticastPacketsReceived	unsignedLong
44	Device.WiFi.SSID.{i}.Stats.MulticastPacketsSent	unsignedLong
45	Device.WiFi.SSID.{i}.Stats.PacketsReceived	unsignedLong
46	Device.WiFi.SSID.{i}.Stats.PacketsSent	unsignedLong
47	Device.WiFi.SSID.{i}.Stats.UnicastPacketsReceived	unsignedLong
48	Device.WiFi.SSID.{i}.Stats.UnicastPacketsSent	unsignedLong
49	Device.WiFi.SSID.{i}.Stats.UnknownProtoPacketsReceived	unsignedInt
50	Device.WiFi.SSID.{i}.Status	string
51	Device.WiFi.SSIDNumberOfEntries	unsignedInt

Read-Write Parameters (50)

#	Parameter	Data Type
1	Device.WiFi.AccessPoint.{i}.Alias	string
2	Device.WiFi.AccessPoint.{i}.Enable	boolean
3	Device.WiFi.AccessPoint.{i}.RetryLimit	unsignedInt
4	Device.WiFi.AccessPoint.{i}.SSIDAdvertisementEnabled	boolean
5	Device.WiFi.AccessPoint.{i}.SSIDReference	string
6	Device.WiFi.AccessPoint.{i}.Security.KeyPassphrase	string
7	Device.WiFi.AccessPoint.{i}.Security.ModeEnabled	string
8	Device.WiFi.AccessPoint.{i}.Security.PreSharedKey	hexBinary
9	Device.WiFi.AccessPoint.{i}.Security.RadiusSecret	string
10	Device.WiFi.AccessPoint.{i}.Security.RadiusServerIPAddr	string
11	Device.WiFi.AccessPoint.{i}.Security.RadiusServerPort	unsignedInt
12	Device.WiFi.AccessPoint.{i}.Security.RekeyingInterval	unsignedInt
13	Device.WiFi.AccessPoint.{i}.Security.WEPKey	hexBinary
14	Device.WiFi.AccessPoint.{i}.UAPSDEnable	boolean
15	Device.WiFi.AccessPoint.{i}.WMMEnable	boolean
16	Device.WiFi.AccessPoint.{i}.WPS.ConfigMethodsEnabled	string
17	Device.WiFi.AccessPoint.{i}.WPS.Enable	boolean

18	`Device.WiFi.EndPoint.{i}.Alias`	string
19	`Device.WiFi.EndPoint.{i}.Enable`	boolean
20	`Device.WiFi.EndPoint.{i}.Profile.{i}.Alias`	string
21	`Device.WiFi.EndPoint.{i}.Profile.{i}.Enable`	boolean
22	`Device.WiFi.EndPoint.{i}.Profile.{i}.Location`	string
23	`Device.WiFi.EndPoint.{i}.Profile.{i}.Priority`	unsignedInt
24	`Device.WiFi.EndPoint.{i}.Profile.{i}.SSID`	string
25	`Device.WiFi.EndPoint.{i}.Profile.{i}.Security.KeyPassphrase`	string
26	`Device.WiFi.EndPoint.{i}.Profile.{i}.Security.ModeEnabled`	string
27	`Device.WiFi.EndPoint.{i}.Profile.{i}.Security.PreSharedKey`	hexBinary
28	`Device.WiFi.EndPoint.{i}.Profile.{i}.Security.WEPKey`	hexBinary
29	`Device.WiFi.EndPoint.{i}.ProfileReference`	string
30	`Device.WiFi.EndPoint.{i}.WPS.ConfigMethodsEnabled`	string
31	`Device.WiFi.EndPoint.{i}.WPS.Enable`	boolean
32	`Device.WiFi.SSID.{i}.Alias`	string
33	`Device.WiFi.SSID.{i}.Enable`	boolean
34	`Device.WiFi.SSID.{i}.LowerLayers`	string
35	`Device.WiFi.SSID.{i}.SSID`	string
36	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.80211kvrEnable`	boolean
37	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.Enable`	boolean
38	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolBeaconsMissedTime`	unsignedInt
39	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolThresholdLevel`	int
40	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolTimeframe`	unsignedInt
41	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BackOffTime`	unsignedInt
42	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BestDeltaLevelConnected`	unsignedInt
43	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BestDeltaLevelDisconnected`	unsignedInt
44	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerBeaconsMissedTime`	unsignedInt
45	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerThresholdLevel`	int
46	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerTimeframe`	unsignedInt
47	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PreAssn_BestDeltaLevel`	unsignedInt
48	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PreAssn_BestThresholdLevel`	int
49	`Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.SelfSteer_OverrideEnable`	boolean
50	`Device.WiFi.X_RDKCENTRAL-COM_WiFiEnable`	boolean

35. Force RFC fetch
    a. Run the following command to check the RFC request is triggered again
        - tr181 -s -v 1 Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.RetrieveNow
36. Stability Test
    a. Perform 10 reboots
    b. Check the tr69hostif runs at each time without any issue
    c. Report the crash if found any during reboot from /opt/logs/corelog.txt
37. Datamodel Validation using the Tardis Tools
    a. Run multiple queries on Data Model params from the Tardis tool https://tardis-automatics.comcast.net/bulkquery
38. Device Management Parameter Validation
    a.

`Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.Logging.xOpsDMLogsUploadStatus`	string
`Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshStatus`	string

Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.hwHealthTest.Results	string
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ForwardSSH.Enable	boolean
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.DeviceManageableNotification	string
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadCompletedNotification	boolean
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadStartedNotification	string
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.RebootPendingNotification	unsignedInt
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshArgs	string
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.Logging.xOpsDMUploadLogsNow	boolean
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.RebootNow	boolean
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshTrigger	string
Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.hwHealthTest.ExecuteTest	int

39. Complete DataModel Set/Get Validation
    a.

#	Parameter	Access	Data Type
1	Device.DeviceInfo.AdditionalSoftwareVersion	readOnly	string
2	Device.DeviceInfo.Description	readOnly	string
3	Device.DeviceInfo.FirstUseDate	readOnly	dateTime
4	Device.DeviceInfo.HardwareVersion	readOnly	string
5	Device.DeviceInfo.Manufacturer	readOnly	string
6	Device.DeviceInfo.ManufacturerOUI	readOnly	string
7	Device.DeviceInfo.MemoryStatus.Free	readOnly	unsigned Int
8	Device.DeviceInfo.MemoryStatus.Total	readOnly	unsigned Int
9	Device.DeviceInfo.Migration.MigrationStatus	readOnly	string
10	Device.DeviceInfo.MigrationPreparer.MigrationReady	readOnly	string
11	Device.DeviceInfo.ModelName	readOnly	string
12	Device.DeviceInfo.ProcessStatus.CPUUsage	readOnly	unsigned Int
13	Device.DeviceInfo.ProcessStatus.Process.{i}.CPUTime	readOnly	unsigned Int
14	Device.DeviceInfo.ProcessStatus.Process.{i}.Command	readOnly	string
15	Device.DeviceInfo.ProcessStatus.Process.{i}.PID	readOnly	unsigned Int
16	Device.DeviceInfo.ProcessStatus.Process.{i}.Priority	readOnly	unsigned Int
17	Device.DeviceInfo.ProcessStatus.Process.{i}.Size	readOnly	unsigned Int
18	Device.DeviceInfo.ProcessStatus.Process.{i}.State	readOnly	string
19	Device.DeviceInfo.ProcessStatus.ProcessNumberOfEntries	readOnly	unsigned Int
20	Device.DeviceInfo.Processor.{i}.Architecture	readOnly	string
21	Device.DeviceInfo.ProcessorNumberOfEntries	readOnly	unsigned Int
22	Device.DeviceInfo.ProductClass	readOnly	string
23	Device.DeviceInfo.ProvisioningCode	readWrite	string
24	Device.DeviceInfo.SerialNumber	readOnly	string
25	Device.DeviceInfo.SoftwareVersion	readOnly	string
26	Device.DeviceInfo.SupportedDataModel.1.Features	readOnly	string

27	Device.DeviceInfo.SupportedDataModel.1.URL	readOnly	string
28	Device.DeviceInfo.SupportedDataModel.1.URN	readOnly	string
29	Device.DeviceInfo.SupportedDataModel.2.Features	readWrite	string
30	Device.DeviceInfo.SupportedDataModel.2.URL	readWrite	string
31	Device.DeviceInfo.SupportedDataModel.2.URN	readWrite	string
32	Device.DeviceInfo.SupportedDataModelNumberOfEntries	readOnly	unsigned Int
33	Device.DeviceInfo.UpTime	readOnly	unsigned Int
34	Device.DeviceInfo.VendorLogFileNumberOfEntries	readOnly	unsigned Int
35	Device.DeviceInfo.X_COMCAST-COM_FirmwareDownloadStatus	readOnly	string
36	Device.DeviceInfo.X_COMCAST-COM_FirmwareFilename	readOnly	string
37	Device.DeviceInfo.X_COMCAST-COM_FirmwareToDownload	readOnly	string
38	Device.DeviceInfo.X_COMCAST-COM_PowerStatus	readOnly	string
39	Device.DeviceInfo.X_COMCAST-COM_Reset	readWrite	string
40	Device.DeviceInfo.X_COMCAST-COM_STB_IP	readOnly	string
41	Device.DeviceInfo.X_COMCAST-COM_STB_MAC	readOnly	string
42	Device.DeviceInfo.X_RDKCENTRAL-COM.BootStatus	readOnly	string
43	Device.DeviceInfo.X_RDKCENTRAL-COM.CPUTemp	readWrite	int
44	Device.DeviceInfo.X_RDKCENTRAL-COM.IUI.AppsVersion	readWrite	string
45	Device.DeviceInfo.X_RDKCENTRAL-COM.IUI.Version	readWrite	string
46	Device.DeviceInfo.X_RDKCENTRAL-COM_BootTime	readOnly	unsigned Int
47	Device.DeviceInfo.X_RDKCENTRAL-COM_Experience	readOnly	string
48	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadDeferReboot	readWrite	boolean
49	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadNow	readWrite	boolean
50	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadPercent	readOnly	int
51	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadProtocol	readWrite	string
52	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadStatus	readOnly	string
53	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadURL	readWrite	string
54	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareDownloadUseCodebig	readWrite	boolean
55	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareFilename	readOnly	string
56	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareToDownload	readWrite	string
57	Device.DeviceInfo.X_RDKCENTRAL-COM_FirmwareUpdateState	readOnly	string
58	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.Enable	readWrite	boolean
59	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.IPAddr	readOnly	string
60	Device.DeviceInfo.X_RDKCENTRAL-COM_IPRemoteSupport.MACAddr	readOnly	string
61	Device.DeviceInfo.X_RDKCENTRAL-COM_LastRebootReason	readWrite	string
62	Device.DeviceInfo.X_RDKCENTRAL-COM_Manufacturing.UIbranding	readWrite	string
63	Device.DeviceInfo.X_RDKCENTRAL-COM_PreferredGatewayType	readWrite	string
64	Device.DeviceInfo.X_RDKCENTRAL-COM_RDKDownloadManager.DownloadStatus	readWrite	boolean
65	Device.DeviceInfo.X_RDKCENTRAL-COM_RDKVersion	readOnly	string
66	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.AuthService.Host	readWrite	string
67	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDB	readWrite	boolean
68	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.Control.ClearDBEnd	readWrite	boolean
69	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.NetflixESNprefix	readWrite	string
70	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.OsClass	readWrite	string
71	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerName	readWrite	string

72	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.PartnerProductName	readWrite	string
73	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.SsrUrl	readWrite	string
74	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfRecoveryUrl	readWrite	string
75	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Bootstrap.XconfUrl	readWrite	string
76	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.ClearParam	readWrite	string
77	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CloudStore.Uri	readWrite	string
78	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ClearDB	readWrite	boolean
79	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ClearDBEnd	readWrite	boolean
80	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigChangeTime	readWrite	unsigned Int
81	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigSetHash	readWrite	string
82	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.ConfigSetTime	readWrite	unsigned Int
83	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.RetrieveNow	readWrite	unsigned Int
84	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.XconfSelector	readWrite	string
85	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Control.XconfUrl	readWrite	string
86	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.S3BucketUrl	readWrite	string
87	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.S3SigningUrl	readWrite	string
88	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalDEVUrl	readWrite	string
89	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalPRODUrl	readWrite	string
90	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalSTBUrl	readWrite	string
91	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.CrashUpload.crashPortalVBNUrl	readWrite	string
92	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.ConfigURL	readWrite	string
93	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.dacBundleFirmwareCompatibilityKey	readWrite	string
94	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DAC.dacBundlePlatformName	readWrite	string
95	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DynamicIUIUpdate.IUISelector	readWrite	string
96	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.DynamicIUIUpdate.Pathway.Uri	readWrite	string
97	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.1080pGraphics.Enable	readWrite	boolean
98	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.DashPlaybackExclusions	readWrite	string
99	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.DashPlaybackInclusions	readWrite	string
100	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AAMP_CFG.b64Config	readWrite	string
101	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AccountInfo.AccountID	readWrite	string
102	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Airplay.Enable	readWrite	boolean
103	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AmazonPrimeVideo.SyePlayer.Enable	readWrite	boolean
104	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppName	readWrite	string
105	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppSize	readWrite	string
106	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.App.{i}.AppUrl	readWrite	string
107	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.AppCnt	readWrite	unsigned Int
108	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppConfig.Enable	readWrite	boolean
109	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.DelayInSecLaunchedToSuspended	readWrite	unsigned Int
110	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.DelayInSecResumedToSuspended	readWrite	unsigned Int
111	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AppHibernate.Enable	readWrite	boolean
112	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AutoReboot.Enable	readWrite	boolean
113	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.AutoReboot.fwDelayReboot	readWrite	int
114	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.AudioIn.Enable	readWrite	boolean
115	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.DebugMode.Enable	readWrite	boolean

116	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTR.GamePad.Enable	readWrite	boolean
117	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTSplitAudio.Enable	readWrite	boolean
118	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BTSplitAudio.Language	readWrite	string
119	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.BootstrapConfig.Enable	readWrite	boolean
120	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CDLDM.CDLModuleUrl	readWrite	string
121	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CPC1960.Enable	readWrite	boolean
122	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CRL.DirectOCSP	readWrite	boolean
123	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CRL.Enable	readWrite	boolean
124	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Canary.wakeUpEnd	readWrite	int
125	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Canary.wakeUpStart	readWrite	int
126	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CrashportalEndpoint.Enable	readWrite	string
127	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CrashportalEndpoint.URL	readWrite	string
128	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CredDwnld.Enable	readWrite	string
129	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.CredDwnld.Use	readWrite	string
130	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DAB.Enable	readWrite	boolean
131	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DHCPv6Client.Enable	readWrite	boolean
132	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DNSStrictOrder.Enable	readWrite	boolean
133	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DefaultSupportedLocales	readWrite	string
134	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.Enable	readWrite	string
135	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.RecordsToBuffer	readWrite	string
136	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.DtmAnalytics.ServiceUrl	readWrite	string
137	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.EnableHttpCDL.Enable	readWrite	boolean
138	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.EntOsAppPlatform.EnableDistPlatform	readWrite	boolean
139	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FOG_CFG.b64Config	readWrite	string
140	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FWUpdate.AutoExcluded.Enable	readWrite	boolean
141	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.FWUpdate.AutoExcluded.XconfUrl	readWrite	string
142	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.HdmiCecSink.CECVersion	readWrite	string
143	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IDS.Enable	readWrite	boolean
144	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IDS.ScanTask	readWrite	string
145	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPControl.Service.Discovery.Enable	readWrite	boolean
146	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPControl.Subsystem.RICS.Enable	readWrite	boolean
147	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IPRemotePort.Enable	readWrite	boolean
148	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.InactiveApplications.Maximum	readWrite	unsigne dInt
149	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.IncrementalCDL.Enable	readWrite	boolean
150	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.JSPPCache.Enable	readWrite	boolean
151	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.AdCacheEnable	readWrite	string
152	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Advt_Opt_Out_Key	readWrite	string
153	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.AltconReceiver	readWrite	string
154	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.ByteRangeDownload	readWrite	string
155	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Enable	readWrite	string
156	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.PSNUrl	readWrite	string
157	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.PlacementReqUrl	readWrite	string
158	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.ProgrammerEnable	readWrite	string
159	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schema_Location	readWrite	string
160	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_NGOD	readWrite	string
161	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_admin	readWrite	string

162	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Schemas_core	readWrite	string
163	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.XMLNS_Schema	readWrite	string
164	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.XMLSchema_Instance	readWrite	string
165	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LSA.Xifaid_Xml_Key	readWrite	string
166	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LaunchDarkly.EnvKeyLabel	readWrite	string
167	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LnFUseXPKI.Enable	readWrite	boolean
168	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadBeforeDeepSleep.Enable	readWrite	boolean
169	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadEndpoint.Enable	readWrite	string
170	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LogUploadEndpoint.URL	readWrite	string
171	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.LoudnessEquivalence.Enable	readWrite	boolean
172	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MEMSWAP.Enable	readWrite	string
173	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MOCASSH.Enable	readWrite	boolean
174	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MS12.DAPv2_Enable	readWrite	boolean
175	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MS12.DE_Enable	readWrite	boolean
176	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.MTLS.mTlsXcSsr.Enable	readWrite	boolean
177	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ManageableNotification.Enable	readWrite	boolean
178	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Miracast.Enable	readWrite	boolean
179	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NTP.failoverServer	readWrite	string
180	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonPersistent.WebPACDL.Enable	readWrite	boolean
181	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.ApparmorBlocklist	readWrite	string
182	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.Blocklist	readWrite	string
183	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.NonRootSupport.Enable	readWrite	boolean
184	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PeriodicFWCheck.Enable	readWrite	boolean
185	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PeriodicFwCheck.timeperiod	readWrite	unsigned Int
186	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.BurstCnt	readWrite	unsigned Int
187	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.Enable	readWrite	boolean
188	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.EndTime	readWrite	unsigned Int
189	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.StartTime	readWrite	unsigned Int
190	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PingTelemetry.Type	readWrite	string
191	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.DeepSleepNotification.Enable	readWrite	boolean
192	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.PwrMgr2.Enable	readWrite	boolean
193	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.UserInactivityNotification.Enable	readWrite	boolean
194	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Power.UserInactivityNotification.TimeMinutes	readWrite	unsigned Int
195	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Preference.URL	readWrite	string
196	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PressAndRelease.EOSMethod	readWrite	int
197	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.PressAndRelease.EOSTimeout	readWrite	int
198	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ProtectX1Services.Enable	readWrite	boolean
199	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.BACKGROUND_MEM_USAGE_HIGH_WATERMARK	readWrite	unsigned Int
200	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.BACKGROUND_MEM_USAGE_LOW_WATERMARK	readWrite	unsigned Int
201	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKBROWSER2_CFG.HTML_APP_RESURRECTION_PERIOD.days	readWrite	unsigned Int
202	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.Enable	readWrite	boolean
203	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.IssueType	readWrite	string
204	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.WebCfgData	readWrite	string

205	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDKRemoteDebugger.getProfileData	readOnly	string
206	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RDMDecoupledVersionManagement.Enable	readWrite	boolean
207	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.AudioProfileTarget	readWrite	int
208	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.FF.RspIdle	readWrite	int
209	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.HostPacketDecryption.Enable	readWrite	boolean
210	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.OpusEncoderParams	readWrite	string
211	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XDIU	readWrite	int
212	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XRC	readWrite	int
213	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.RspTime.XVP	readWrite	int
214	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RF4CE.VoiceEncryption.Enable	readWrite	boolean
215	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Detection	readWrite	boolean
216	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Duration	readWrite	int
217	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RebootStop.Enable	readWrite	boolean
218	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RedRecovery.Status	readWrite	string
219	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Resourcemanager.Blacklist.Enable	readWrite	boolean
220	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Resourcemanager.ReserveTTS.Enable	readWrite	boolean
221	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.RoamTrigger	readWrite	string
222	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SDCARD_SCRATCHPAD.Enable	readWrite	string
223	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SHORTS.Enable	readWrite	boolean
224	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.STAGE.Enable	readWrite	boolean
225	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLDirect.Enable	readWrite	boolean
226	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.Enable	readWrite	boolean
227	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.LowSpeed	readWrite	int
228	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SWDLSpLimit.TopSpeed	readWrite	int
229	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ScreenCapture.Enable	readWrite	boolean
230	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ScreenCapture.URL	readWrite	string
231	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SecDump.Enable	readWrite	boolean
232	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SoundPlayer.Enable	readWrite	boolean
233	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.Enable	readWrite	boolean
234	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.ForceAutoReboot	readWrite	int
235	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StandbyReboot.StandbyAutoReboot	readWrite	int
236	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StorageManager.maxAdaptiveBitRate	readWrite	int
237	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.StorageManager.maxTSBDurationMinutes	readWrite	int
238	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.SupportedLanguages	readWrite	string
239	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.TR069support.Enable	readWrite	boolean
240	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.ConfigURL	readWrite	string
241	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Telemetry.Version	readWrite	string
242	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThreadMonitorMinidump.Enable	readWrite	boolean
243	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThreadPrioConfig.Enable	readWrite	boolean
244	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ThunderSecurity.Enable	readWrite	boolean
245	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.TvSettings.DynamicAutoLatency	readWrite	boolean
246	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UNII3.Enable	readWrite	boolean
247	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UPnP.Refactor.Enable	readWrite	boolean
248	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UPnPxPKI.Enable	readWrite	boolean
249	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.USB_AutoMount.Enable	readWrite	string
250	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.USB_HID.Enable	readWrite	boolean
251	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.UploadLogsOnUnscheduledReboot.Disable	readWrite	boolean

252	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ViperPPUrl	readWrite	string
253	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioConfidenceThreshold	readWrite	string
254	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioDuckingLevel	readWrite	string
255	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioDuckingType	readWrite	int
256	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioMode	readWrite	int
257	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.AudioTiming	readWrite	int
258	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.KeywordSensitivity	readWrite	string
259	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.Voice.VSDKConfiguration	readWrite	string
260	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFi.WiFiStatsLogInterval	readWrite	unsigned Int
261	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.Enable	readWrite	boolean
262	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.EthernetLoggingInterval	readWrite	unsigned Int
263	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.PacketLossLoggingInterval	readWrite	string
264	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.ReassociateTolerance	readWrite	unsigned Int
265	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.WifiLoggingInterval	readWrite	unsigned Int
266	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.WifiReassociateInterval	readWrite	unsigned Int
267	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset. WifiResetIntervalForDriverIssue	readWrite	unsigned Int
268	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WiFiReset.WifiResetIntervalForPacketLoss	readWrite	unsigned Int
269	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.WifiOptimizer.Enable	readWrite	boolean
270	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XDial.AppList	readWrite	string
271	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRDsp.XR19.Configuration	readWrite	string
272	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBDerivationMethod	readWrite	int
273	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBEnable	readWrite	boolean
274	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPairing.ASBFailThreshold	readWrite	int
275	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.Default	readWrite	string
276	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.Enable	readWrite	boolean
277	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR11v2	readWrite	string
278	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR15v1	readWrite	string
279	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR15v2	readWrite	string
280	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR16v1	readWrite	string
281	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XR19v1	readWrite	string
282	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRPollingConfiguration.XRAv1	readWrite	string
283	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRmacPolling.Enable	readWrite	boolean
284	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.XRmacPolling.macPollingInterval	readWrite	int
285	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.Enable	readWrite	boolean
286	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.GraphiteURL	readWrite	string
287	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.Hostname	readWrite	string
288	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.collectd.PortNumber	readWrite	unsigned Int
289	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.device_update	readWrite	string
290	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.global	readWrite	string
291	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_ble	readWrite	string
292	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_ip	readWrite	string
293	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.network_rf4ce	readWrite	string
294	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.ble	readWrite	string

295	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.global	readWrite	string
296	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.ip	readWrite	string
297	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.rf4ce	readWrite	string
298	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.telemetry_report.voice	readWrite	string
299	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.voice	readWrite	string
300	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.ctrlm.vsdk	readWrite	string
301	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.eMMCFirmware.Version	readWrite	string
302	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.eMMCMitigation.Disable	readWrite	boolean
303	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.fkpskdf.Enable	readWrite	boolean
304	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.memcapture.Duration	readWrite	int
305	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.memcapture.Enable	readWrite	boolean
306	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.systemd-analyze.Enable	readWrite	boolean
307	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.xMemInsight.Args	readWrite	string
308	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Feature.xMemInsight.Enable	readWrite	boolean
309	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.HostIf.ParodusTokenServerUrl	readWrite	string
310	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Identity.DbgServices.Enable	readWrite	boolean
311	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Identity.DeviceType	readWrite	string
312	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcaUploadPRODUrl	readWrite	string
313	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcaUploadUrl	readWrite	string
314	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerCQAUrl	readWrite	string
315	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerDEVUrl	readWrite	string
316	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogServerPRODUrl	readWrite	string
317	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmLogUrl	readWrite	string
318	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.DcmScpServerUrl	readWrite	string
319	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.LogServerUrl	readWrite	string
320	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.S3SignedBucketUrl	readWrite	string
321	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.LogUpload.SsrUrl	readWrite	string
322	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SecManager.dieselUrl	readWrite	string
323	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.Activation	readWrite	string
324	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.AuthMessage	readWrite	string
325	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.NameSpacePrefix	readWrite	string
326	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.NameSpaceUri	readWrite	string
327	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.Renewal	readWrite	string
328	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.URL1	readWrite	string
329	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.URL2	readWrite	string
330	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning.backoffIntervalMax	readWrite	unsigne dLong
331	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SocProvisioning. disableCredentialsPrefetchCaching	readWrite	boolean
332	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CCRProxyUrl	readWrite	string
333	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CDNCCPUrl	readWrite	string
334	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.CcpUrl	readWrite	string
335	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.DAC15CDLUrl	readWrite	string
336	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.EDGEDNSProxyUrl	readWrite	string
337	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.FkpsBrokerUrl	readWrite	string
338	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.FkpsUrl	readWrite	string
339	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.PRODCDLUrl	readWrite	string
340	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XcalUrl	readWrite	string

341	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XconfDEVUrl	readWrite	string
342	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.Sysint.XconfUrl	readWrite	string
343	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.SystemServices.FriendlyName	readWrite	string
344	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.TextToSpeech.URL	readWrite	string
345	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.LRHAcceptValue	readWrite	string
346	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.LRHContentType	readWrite	string
347	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SchemeIdUriDaiStream	readWrite	string
348	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SchemeIdUriVssStream	readWrite	string
349	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.SlowMotion	readWrite	boolean
350	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.asyncTune	readWrite	boolean
351	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.cdvrLiveOffset	readWrite	unsigned Long
352	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.client-dai	readWrite	boolean
353	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.curlStore	readWrite	boolean
354	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.defaultBitrate	readWrite	unsigned Long
355	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.defaultBitrate4K	readWrite	unsigned Long
356	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableAC3	readWrite	boolean
357	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableAC4	readWrite	boolean
358	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableATMOS	readWrite	boolean
359	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.disableEC3	readWrite	boolean
360	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableCMCD	readWrite	boolean
361	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLiveLatencyCorrection	readWrite	boolean
362	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLowLatencyCorrection	readWrite	boolean
363	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableLowLatencyDash	readWrite	boolean
364	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enablePTSReStamp	readWrite	boolean
365	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.enableVideoEndEvent	readWrite	boolean
366	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.info	readWrite	boolean
367	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.liveOffset	readWrite	unsigned Long
368	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.liveOffset4K	readWrite	string
369	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.manifestTimeout	readWrite	unsigned Long
370	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.maxBitrate	readWrite	unsigned Long
371	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.maxInitFragCachePerTrack	readWrite	int
372	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.minBitrate	readWrite	unsigned Long
373	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.networkTimeout	readWrite	unsigned Long
374	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.persistBitrateOverSeek	readWrite	boolean
375	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.playlistTimeout	readWrite	unsigned Long
376	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.preferredDrm	readWrite	int
377	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.rateCorrectionDelay	readWrite	unsigned Long
378	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.sharedSSL	readWrite	boolean
379	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.stereoOnly	readWrite	boolean
380	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.supportTLS	readWrite	unsigned Long
381	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.tsbInterruptHandling	readWrite	boolean

382	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.useSecManager	readWrite	boolean
383	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.aamp.useWesterosSink	readWrite	boolean
384	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.apps.watchdogmode	readWrite	boolean
385	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.fog.ZeroDrmHost	readWrite	string
386	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.LongpollUrl	readWrite	string
387	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.Status	readWrite	string
388	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.recorder.UpdateSchedule	readWrite	string
389	Device.DeviceInfo.X_RDKCENTRAL-COM_RFC.vodclient.StunnelConnect	readWrite	string
390	Device.DeviceInfo.X_RDKCENTRAL-COM_Reset	readWrite	string
391	Device.DeviceInfo.X_RDKCENTRAL-COM_Syndication.PartnerId	readWrite	string
392	Device.DeviceInfo.X_RDKCENTRAL-COM_xAccount.HotelCheckout.LastResetTime	readOnly	unsigned Long
393	Device.DeviceInfo.X_RDKCENTRAL-COM_xAccount.HotelCheckout.Status	readOnly	string
394	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.Active	readOnly	int
395	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.DeviceID	readOnly	string
396	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.DeviceType	readOnly	string
397	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDevice.{i}.Name	readOnly	string
398	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.ConnectedDeviceCnt	readOnly	unsigned Int
399	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.DeviceID	readOnly	string
400	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.MAC	readOnly	string
401	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.Manufacturer	readOnly	int
402	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.Profile	readOnly	string
403	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.RSSI	readOnly	int
404	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DeviceInfo.SignalStrength	readOnly	string
405	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.DeviceID	readOnly	string
406	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.DeviceType	readOnly	string
407	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.Name	readOnly	string
408	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDevice.{i}.Paired	readOnly	boolean
409	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveredDeviceCnt	readOnly	unsigned Int
410	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.DiscoveryEnabled	readOnly	boolean
411	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.Enabled	readOnly	string
412	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.GetDeviceInfo	readOnly	string
413	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.LimitBeaconDetection	readWrite	boolean
414	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.Connected	readOnly	boolean
415	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.DeviceID	readOnly	string
416	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.DeviceType	readOnly	string
417	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDevice.{i}.Name	readOnly	string
418	Device.DeviceInfo.X_RDKCENTRAL-COM_xBlueTooth.PairedDeviceCnt	readOnly	unsigned Int
419	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ForwardSSH.Enable	readWrite	boolean
420	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.Logging.xOpsDMLogsUploadStatus	readOnly	string
421	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.DeviceManageableNotification	readWrite	string
422	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadCompletedNotification	readWrite	boolean
423	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.FirmwareDownloadStartedNotification	readWrite	string
424	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.RPC.RebootPendingNotification	readWrite	unsigned Int

425	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshArgs	readWrite	string
426	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.ReverseSSH.xOpsReverseSshStatus	readOnly	string
427	Device.DeviceInfo.X_RDKCENTRAL-COM_xOpsDeviceMgmt.hwHealthTest.Results	readOnly	string
428	Device.DeviceInfo.X_RDK_FirmwareName	readOnly	string
429	Device.DeviceInfo.X_RDK_RDKProfileName	readWrite	string
430	Device.Ethernet.Interface.{i}.Alias	readWrite	string
431	Device.Ethernet.Interface.{i}.DuplexMode	readWrite	string
432	Device.Ethernet.Interface.{i}.Enable	readWrite	boolean
433	Device.Ethernet.Interface.{i}.LastChange	readOnly	unsigned Int
434	Device.Ethernet.Interface.{i}.LowerLayers	readWrite	string
435	Device.Ethernet.Interface.{i}.MACAddress	readOnly	string
436	Device.Ethernet.Interface.{i}.MaxBitRate	readWrite	int
437	Device.Ethernet.Interface.{i}.Name	readOnly	string
438	Device.Ethernet.Interface.{i}.Stats.BroadcastPacketsReceived	readOnly	unsigned Long
439	Device.Ethernet.Interface.{i}.Stats.BroadcastPacketsSent	readOnly	unsigned Long
440	Device.Ethernet.Interface.{i}.Stats.BytesReceived	readOnly	unsigned Long
441	Device.Ethernet.Interface.{i}.Stats.BytesSent	readOnly	unsigned Long
442	Device.Ethernet.Interface.{i}.Stats.DiscardPacketsReceived	readOnly	unsigned Int
443	Device.Ethernet.Interface.{i}.Stats.DiscardPacketsSent	readOnly	unsigned Int
444	Device.Ethernet.Interface.{i}.Stats.ErrorsReceived	readOnly	unsigned Int
445	Device.Ethernet.Interface.{i}.Stats.ErrorsSent	readOnly	unsigned Int
446	Device.Ethernet.Interface.{i}.Stats.MulticastPacketsReceived	readOnly	unsigned Long
447	Device.Ethernet.Interface.{i}.Stats.MulticastPacketsSent	readOnly	unsigned Long
448	Device.Ethernet.Interface.{i}.Stats.PacketsReceived	readOnly	unsigned Long
449	Device.Ethernet.Interface.{i}.Stats.PacketsSent	readOnly	unsigned Long
450	Device.Ethernet.Interface.{i}.Stats.UnicastPacketsReceived	readOnly	unsigned Long
451	Device.Ethernet.Interface.{i}.Stats.UnicastPacketsSent	readOnly	unsigned Long
452	Device.Ethernet.Interface.{i}.Stats.UnknownProtoPacketsReceived	readOnly	unsigned Int
453	Device.Ethernet.Interface.{i}.Status	readOnly	string
454	Device.Ethernet.Interface.{i}.Upstream	readOnly	boolean
455	Device.Ethernet.InterfaceNumberOfEntries	readOnly	unsigned Int
456	Device.Ethernet.Link.{i}.Enable	readWrite	boolean
457	Device.Ethernet.Link.{i}.LowerLayers	readWrite	string
458	Device.Ethernet.Link.{i}.MACAddress	readOnly	string
459	Device.Ethernet.Link.{i}.Name	readOnly	string
460	Device.Ethernet.Link.{i}.Status	readOnly	string
461	Device.Ethernet.LinkNumberOfEntries	readOnly	unsigned Int

462	Device.IP.ActivePort.{i}.LocalIPAddress	readOnly	string
463	Device.IP.ActivePort.{i}.LocalPort	readOnly	unsigned Int
464	Device.IP.ActivePort.{i}.RemoteIPAddress	readOnly	string
465	Device.IP.ActivePort.{i}.RemotePort	readOnly	unsigned Int
466	Device.IP.ActivePort.{i}.Status	readOnly	string
467	Device.IP.ActivePortNumberOfEntries	readOnly	unsigned Int
468	Device.IP.Diagnostics.DownloadDiagnostics.BOMTime	readOnly	dateTime
469	Device.IP.Diagnostics.DownloadDiagnostics.DSCP	readWrite	unsigned Int
470	Device.IP.Diagnostics.DownloadDiagnostics.DiagnosticsState	readWrite	string
471	Device.IP.Diagnostics.DownloadDiagnostics.DownloadTransports	readOnly	string
472	Device.IP.Diagnostics.DownloadDiagnostics.DownloadURL	readWrite	string
473	Device.IP.Diagnostics.DownloadDiagnostics.EOMTime	readOnly	dateTime
474	Device.IP.Diagnostics.DownloadDiagnostics.EthernetPriority	readWrite	unsigned Int
475	Device.IP.Diagnostics.DownloadDiagnostics.Interface	readWrite	string
476	Device.IP.Diagnostics.DownloadDiagnostics.ROMTime	readOnly	dateTime
477	Device.IP.Diagnostics.DownloadDiagnostics.TCPOpenRequestTime	readOnly	dateTime
478	Device.IP.Diagnostics.DownloadDiagnostics.TCPOpenResponseTime	readOnly	dateTime
479	Device.IP.Diagnostics.DownloadDiagnostics.TestBytesReceived	readOnly	unsigned Int
480	Device.IP.Diagnostics.DownloadDiagnostics.TotalBytesReceived	readOnly	unsigned Int
481	Device.IP.Diagnostics.IPPing.AverageResponseTime	readOnly	unsigned Int
482	Device.IP.Diagnostics.IPPing.DSCP	readWrite	unsigned Int
483	Device.IP.Diagnostics.IPPing.DataBlockSize	readWrite	unsigned Int
484	Device.IP.Diagnostics.IPPing.DiagnosticsState	readWrite	string
485	Device.IP.Diagnostics.IPPing.FailureCount	readOnly	unsigned Int
486	Device.IP.Diagnostics.IPPing.Host	readWrite	string
487	Device.IP.Diagnostics.IPPing.Interface	readWrite	string
488	Device.IP.Diagnostics.IPPing.MaximumResponseTime	readOnly	unsigned Int
489	Device.IP.Diagnostics.IPPing.MinimumResponseTime	readOnly	unsigned Int
490	Device.IP.Diagnostics.IPPing.NumberOfRepetitions	readWrite	unsigned Int
491	Device.IP.Diagnostics.IPPing.SuccessCount	readOnly	unsigned Int
492	Device.IP.Diagnostics.IPPing.Timeout	readWrite	unsigned Int
493	Device.IP.Diagnostics.TraceRoute.DSCP	readWrite	unsigned Int
494	Device.IP.Diagnostics.TraceRoute.DataBlockSize	readWrite	unsigned Int
495	Device.IP.Diagnostics.TraceRoute.DiagnosticsState	readWrite	string
496	Device.IP.Diagnostics.TraceRoute.Host	readWrite	string
497	Device.IP.Diagnostics.TraceRoute.Interface	readWrite	string
498	Device.IP.Diagnostics.TraceRoute.MaxHopCount	readWrite	unsigned Int

499	Device.IP.Diagnostics.TraceRoute.NumberOfTries	readWrite	unsigned Int
500	Device.IP.Diagnostics.TraceRoute.ResponseTime	readOnly	unsigned Int
501	Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.ErrorCode	readOnly	unsigned Int
502	Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.Host	readOnly	string
503	Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.HostAddress	readOnly	string
504	Device.IP.Diagnostics.TraceRoute.RouteHops.{i}.RTTimes	readOnly	string
505	Device.IP.Diagnostics.TraceRoute.RouteHopsNumberOfEntries	readOnly	unsigned Int
506	Device.IP.Diagnostics.TraceRoute.Timeout	readWrite	unsigned Int
507	Device.IP.Diagnostics.UDPEchoConfig.BytesReceived	readOnly	unsigned Int
508	Device.IP.Diagnostics.UDPEchoConfig.BytesResponded	readOnly	unsigned Int
509	Device.IP.Diagnostics.UDPEchoConfig.EchoPlusEnabled	readWrite	boolean
510	Device.IP.Diagnostics.UDPEchoConfig.EchoPlusSupported	readOnly	boolean
511	Device.IP.Diagnostics.UDPEchoConfig.Enable	readWrite	boolean
512	Device.IP.Diagnostics.UDPEchoConfig.Interface	readWrite	string
513	Device.IP.Diagnostics.UDPEchoConfig.PacketsReceived	readOnly	unsigned Int
514	Device.IP.Diagnostics.UDPEchoConfig.PacketsResponded	readOnly	unsigned Int
515	Device.IP.Diagnostics.UDPEchoConfig.SourceIPAddress	readWrite	string
516	Device.IP.Diagnostics.UDPEchoConfig.TimeFirstPacketReceived	readOnly	dateTime
517	Device.IP.Diagnostics.UDPEchoConfig.TimeLastPacketReceived	readOnly	dateTime
518	Device.IP.Diagnostics.UDPEchoConfig.UDPPort	readWrite	unsigned Int
519	Device.IP.Diagnostics.UploadDiagnostics.BOMTime	readOnly	dateTime
520	Device.IP.Diagnostics.UploadDiagnostics.DSCP	readWrite	unsigned Int
521	Device.IP.Diagnostics.UploadDiagnostics.DiagnosticsState	readWrite	string
522	Device.IP.Diagnostics.UploadDiagnostics.EOMTime	readOnly	dateTime
523	Device.IP.Diagnostics.UploadDiagnostics.EthernetPriority	readWrite	unsigned Int
524	Device.IP.Diagnostics.UploadDiagnostics.Interface	readWrite	string
525	Device.IP.Diagnostics.UploadDiagnostics.ROMTime	readOnly	dateTime
526	Device.IP.Diagnostics.UploadDiagnostics.TCPOpenRequestTime	readOnly	dateTime
527	Device.IP.Diagnostics.UploadDiagnostics.TCPOpenResponseTime	readOnly	dateTime
528	Device.IP.Diagnostics.UploadDiagnostics.TestFileLength	readWrite	unsigned Int
529	Device.IP.Diagnostics.UploadDiagnostics.TotalBytesSent	readOnly	unsigned Int
530	Device.IP.Diagnostics.UploadDiagnostics.UploadTransports	readOnly	string
531	Device.IP.Diagnostics.UploadDiagnostics.UploadURL	readWrite	string
532	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Argument	readWrite	string
533	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Authentication	readWrite	string
534	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.ClientType	readWrite	unsigned Int
535	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Enable	readWrite	boolean
536	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Enable_Speedtest	readWrite	boolean
537	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Run	readWrite	boolean

538	Device.IP.Diagnostics.X_RDKCENTRAL-COM_SpeedTest.Status	readOnly	unsigned Int
539	Device.IP.IPv4Capable	readOnly	boolean
540	Device.IP.IPv4Enable	readWrite	boolean
541	Device.IP.IPv4Status	readOnly	string
542	Device.IP.Interface.{i}.Alias	readWrite	string
543	Device.IP.Interface.{i}.AutoIPEnable	readWrite	boolean
544	Device.IP.Interface.{i}.Enable	readWrite	boolean
545	Device.IP.Interface.{i}.IPv4Address.{i}.AddressingType	readOnly	string
546	Device.IP.Interface.{i}.IPv4Address.{i}.Alias	readWrite	string
547	Device.IP.Interface.{i}.IPv4Address.{i}.Enable	readWrite	boolean
548	Device.IP.Interface.{i}.IPv4Address.{i}.IPAddress	readWrite	string
549	Device.IP.Interface.{i}.IPv4Address.{i}.Status	readOnly	string
550	Device.IP.Interface.{i}.IPv4Address.{i}.SubnetMask	readWrite	string
551	Device.IP.Interface.{i}.IPv4AddressNumberOfEntries	readOnly	unsigned Int
552	Device.IP.Interface.{i}.IPv4Enable	readWrite	boolean
553	Device.IP.Interface.{i}.IPv6Address.{i}.Alias	readWrite	string
554	Device.IP.Interface.{i}.IPv6Address.{i}.Anycast	readWrite	boolean
555	Device.IP.Interface.{i}.IPv6Address.{i}.Enable	readWrite	boolean
556	Device.IP.Interface.{i}.IPv6Address.{i}.IPAddress	readWrite	string
557	Device.IP.Interface.{i}.IPv6Address.{i}.IPAddressStatus	readOnly	string
558	Device.IP.Interface.{i}.IPv6Address.{i}.Origin	readOnly	string
559	Device.IP.Interface.{i}.IPv6Address.{i}.PreferredLifetime	readWrite	dateTime
560	Device.IP.Interface.{i}.IPv6Address.{i}.Prefix	readWrite	string
561	Device.IP.Interface.{i}.IPv6Address.{i}.Status	readOnly	string
562	Device.IP.Interface.{i}.IPv6Address.{i}.ValidLifetime	readWrite	dateTime
563	Device.IP.Interface.{i}.IPv6AddressNumberOfEntries	readOnly	unsigned Int
564	Device.IP.Interface.{i}.IPv6Enable	readWrite	boolean
565	Device.IP.Interface.{i}.IPv6Prefix.{i}.Alias	readWrite	string
566	Device.IP.Interface.{i}.IPv6Prefix.{i}.Autonomous	readWrite	boolean
567	Device.IP.Interface.{i}.IPv6Prefix.{i}.ChildPrefixBits	readWrite	string
568	Device.IP.Interface.{i}.IPv6Prefix.{i}.Enable	readWrite	boolean
569	Device.IP.Interface.{i}.IPv6Prefix.{i}.OnLink	readWrite	boolean
570	Device.IP.Interface.{i}.IPv6Prefix.{i}.Origin	readOnly	string
571	Device.IP.Interface.{i}.IPv6Prefix.{i}.ParentPrefix	readWrite	string
572	Device.IP.Interface.{i}.IPv6Prefix.{i}.PreferredLifetime	readWrite	dateTime
573	Device.IP.Interface.{i}.IPv6Prefix.{i}.Prefix	readWrite	string
574	Device.IP.Interface.{i}.IPv6Prefix.{i}.PrefixStatus	readOnly	string
575	Device.IP.Interface.{i}.IPv6Prefix.{i}.StaticType	readWrite	string
576	Device.IP.Interface.{i}.IPv6Prefix.{i}.Status	readOnly	string
577	Device.IP.Interface.{i}.IPv6Prefix.{i}.ValidLifetime	readWrite	dateTime
578	Device.IP.Interface.{i}.IPv6PrefixNumberOfEntries	readOnly	unsigned Int
579	Device.IP.Interface.{i}.LastChange	readOnly	unsigned Int
580	Device.IP.Interface.{i}.Loopback	readWrite	boolean
581	Device.IP.Interface.{i}.LowerLayers	readWrite	string

582	Device.IP.Interface.{i}.MaxMTUSize	readWrite	unsigned Int
583	Device.IP.Interface.{i}.Name	readOnly	string
584	Device.IP.Interface.{i}.Reset	readWrite	boolean
585	Device.IP.Interface.{i}.Router	readWrite	string
586	Device.IP.Interface.{i}.Stats.BroadcastPacketsReceived	readOnly	unsigned Long
587	Device.IP.Interface.{i}.Stats.BroadcastPacketsSent	readOnly	unsigned Long
588	Device.IP.Interface.{i}.Stats.BytesReceived	readOnly	unsigned Long
589	Device.IP.Interface.{i}.Stats.BytesSent	readOnly	unsigned Long
590	Device.IP.Interface.{i}.Stats.DiscardPacketsReceived	readOnly	unsigned Int
591	Device.IP.Interface.{i}.Stats.DiscardPacketsSent	readOnly	unsigned Int
592	Device.IP.Interface.{i}.Stats.ErrorsReceived	readOnly	unsigned Int
593	Device.IP.Interface.{i}.Stats.ErrorsSent	readOnly	unsigned Int
594	Device.IP.Interface.{i}.Stats.MulticastPacketsReceived	readOnly	unsigned Long
595	Device.IP.Interface.{i}.Stats.MulticastPacketsSent	readOnly	unsigned Long
596	Device.IP.Interface.{i}.Stats.PacketsReceived	readOnly	unsigned Long
597	Device.IP.Interface.{i}.Stats.PacketsSent	readOnly	unsigned Long
598	Device.IP.Interface.{i}.Stats.UnicastPacketsReceived	readOnly	unsigned Long
599	Device.IP.Interface.{i}.Stats.UnicastPacketsSent	readOnly	unsigned Long
600	Device.IP.Interface.{i}.Stats.UnknownProtoPacketsReceived	readOnly	unsigned Int
601	Device.IP.Interface.{i}.Status	readOnly	string
602	Device.IP.Interface.{i}.Type	readOnly	string
603	Device.IP.Interface.{i}.ULAEnable	readWrite	boolean
604	Device.IP.InterfaceNumberOfEntries	readOnly	unsigned Int
605	Device.IP.ULAPrefix	readWrite	string
606	Device.InterfaceStack.{i}.HigherLayer	readOnly	string
607	Device.InterfaceStack.{i}.LowerLayer	readOnly	string
608	Device.InterfaceStackNumberOfEntries	readOnly	unsigned Int
609	Device.ManagementServer.AliasBasedAddressing	readOnly	boolean
610	Device.ManagementServer.AutoCreateInstances	readWrite	boolean
611	Device.ManagementServer.CWMPRetryIntervalMultiplier	readWrite	unsigned Int
612	Device.ManagementServer.CWMPRetryMinimumWaitInterval	readWrite	unsigned Int
613	Device.ManagementServer.ConnectionRequestURL	readOnly	string
614	Device.ManagementServer.ConnectionRequestUsername	readWrite	string
615	Device.ManagementServer.DefaultActiveNotificationThrottle	readWrite	unsigned Int
616	Device.ManagementServer.DownloadProgressURL	readOnly	string
617	Device.ManagementServer.EnableCWMP	readWrite	boolean

618	Device.ManagementServer.InstanceMode	readWrite	string
619	Device.ManagementServer.KickURL	readOnly	string
620	Device.ManagementServer.NATDetected	readOnly	boolean
621	Device.ManagementServer.ParameterKey	readOnly	string
622	Device.ManagementServer.PeriodicInformEnable	readWrite	boolean
623	Device.ManagementServer.PeriodicInformInterval	readWrite	unsigned Int
624	Device.ManagementServer.PeriodicInformTime	readWrite	dateTime
625	Device.ManagementServer.STUNEnable	readWrite	boolean
626	Device.ManagementServer.STUNMaximumKeepAlivePeriod	readWrite	int
627	Device.ManagementServer.STUNMinimumKeepAlivePeriod	readWrite	unsigned Int
628	Device.ManagementServer.STUNPassword	readWrite	string
629	Device.ManagementServer.STUNServerAddress	readWrite	string
630	Device.ManagementServer.STUNServerPort	readWrite	unsigned Int
631	Device.ManagementServer.STUNUsername	readWrite	string
632	Device.ManagementServer.UDPConnectionRequestAddress	readOnly	string
633	Device.ManagementServer.URL	readWrite	string
634	Device.ManagementServer.UpgradesManaged	readWrite	boolean
635	Device.ManagementServer.Username	readWrite	string
636	Device.Services.STBService.1.Capabilities.HDMI.SupportedResolutions	readOnly	string
637	Device.Services.STBService.1.Capabilities.VideoDecoder.VideoStandards	readOnly	string
638	Device.Services.STBService.1.Capabilities.VideoDecoder.X_RDKCENTRAL-COM_MPEGHPart2.ProfileLevel.1.Alias	readOnly	string
639	Device.Services.STBService.1.Capabilities.VideoDecoder.X_RDKCENTRAL-COM_MPEGHPart2.ProfileLevel.1.Level	readOnly	string
640	Device.Services.STBService.1.Capabilities.VideoDecoder.X_RDKCENTRAL-COM_MPEGHPart2.ProfileLevel.1.MaximumDecodingCapability	readOnly	unsigned Int
641	Device.Services.STBService.1.Capabilities.VideoDecoder.X_RDKCENTRAL-COM_MPEGHPart2.ProfileLevel.1.Profile	readOnly	string
642	Device.Services.STBService.1.Capabilities.VideoDecoder.X_RDKCENTRAL-COM_MPEGHPart2.ProfileLevelNumberOfEntries	readOnly	unsigned Int
643	Device.Services.STBService.1.Components.AudioOutput.1.AudioFormat	readOnly	string
644	Device.Services.STBService.1.Components.AudioOutput.1.AudioLevel	readWrite	unsigned Int
645	Device.Services.STBService.1.Components.AudioOutput.1.CancelMute	readWrite	boolean
646	Device.Services.STBService.1.Components.AudioOutput.1.Enable	readWrite	boolean
647	Device.Services.STBService.1.Components.AudioOutput.1.Name	readOnly	string
648	Device.Services.STBService.1.Components.AudioOutput.1.Status	readOnly	string
649	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioCompression	readWrite	string
650	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioDB	readWrite	string
651	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioEncoding	readWrite	string
652	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioGain	readWrite	string
653	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioLoopThru	readWrite	string
654	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioOptimalLevel	readWrite	string
655	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_AudioStereoMode	readWrite	string
656	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_MaxAudioDB	readOnly	string
657	Device.Services.STBService.1.Components.AudioOutput.1.X_COMCAST-COM_MinAudioDB	readOnly	string
658	Device.Services.STBService.1.Components.AudioOutputNumberOfEntries	readOnly	unsigned Int
659	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.AutoLipSyncSupport	readOnly	boolean

660	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.CECSupport	readOnly	boolean
661	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.EEDID	readOnly	string
662	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.HDMI3DPresent	readOnly	boolean
663	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.PreferredResolution	readOnly	string
664	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.Status	readOnly	string
665	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.SupportedResolutions	readOnly	string
666	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.VideoLatency	readOnly	unsigned Int
667	Device.Services.STBService.1.Components.HDMI.1.DisplayDevice.X_COMCAST-COM_EDID	readOnly	string
668	Device.Services.STBService.1.Components.HDMI.1.Enable	readWrite	boolean
669	Device.Services.STBService.1.Components.HDMI.1.Name	readOnly	string
670	Device.Services.STBService.1.Components.HDMI.1.ResolutionMode	readWrite	string
671	Device.Services.STBService.1.Components.HDMI.1.ResolutionValue	readWrite	string
672	Device.Services.STBService.1.Components.HDMI.1.Status	readOnly	string
673	Device.Services.STBService.1.Components.HDMINumberOfEntries	readOnly	unsigned Int
674	Device.Services.STBService.1.Components.VideoDecoder.1.ContentAspectRatio	readOnly	string
675	Device.Services.STBService.1.Components.VideoDecoder.1.Enable	readWrite	boolean
676	Device.Services.STBService.1.Components.VideoDecoder.1.Name	readOnly	string
677	Device.Services.STBService.1.Components.VideoDecoder.1.Status	readOnly	string
678	Device.Services.STBService.1.Components.VideoDecoder.1.X_COMCAST-COM_Standby	readWrite	boolean
679	Device.Services.STBService.1.Components.VideoDecoder.1.X_RDKCENTRAL-COM_MPEGHPart2	readOnly	string
680	Device.Services.STBService.1.Components.VideoDecoderNumberOfEntries	readOnly	unsigned Int
681	Device.Services.STBService.1.Components.VideoOutput.1.AspectRatioBehaviour	readWrite	string
682	Device.Services.STBService.1.Components.VideoOutput.1.DisplayFormat	readWrite	string
683	Device.Services.STBService.1.Components.VideoOutput.1.Enable	readWrite	boolean
684	Device.Services.STBService.1.Components.VideoOutput.1.HDCP	readWrite	boolean
685	Device.Services.STBService.1.Components.VideoOutput.1.Name	readOnly	string
686	Device.Services.STBService.1.Components.VideoOutput.1.Status	readOnly	string
687	Device.Services.STBService.1.Components.VideoOutput.1.VideoFormat	readWrite	string
688	Device.Services.STBService.1.Components.VideoOutputNumberOfEntries	readOnly	unsigned Int
689	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.BatteryLevelLoaded	readOnly	unsigned Int
690	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.BatteryLevelUnloaded	readOnly	unsigned Int
691	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.BatteryPercentage	readOnly	unsigned Int
692	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.BatteryReplacement	readOnly	boolean
693	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.ImpendingDoom	readOnly	boolean
694	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.LinkQuality	readOnly	unsigned Int
695	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.MACAddress	readOnly	string
696	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.NetworkAddress	readOnly	unsigned Int
697	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.RemoteId	readOnly	unsigned Int
698	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.RemoteType	readOnly	string
699	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.SignalStrength	readOnly	int
700	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.VersionInfoHW	readOnly	string

701	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.Remote.1.VersionInfoSW	readOnly	string
702	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4ceActiveChannel	readOnly	unsigned Int
703	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4ceMACAddress	readOnly	string
704	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4ceNetworkAddress	readOnly	unsigned Int
705	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4cePANID	readOnly	unsigned Int
706	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4cePairedRemotesNumberOfEntries	readOnly	unsigned Int
707	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_RF4CE.rf4ceVersionInfo	readOnly	string
708	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.Capacity	readOnly	unsigned Int
709	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.DeviceReport	readOnly	string
710	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.FirmwareVersion	readOnly	string
711	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.LifeElapsedA	readOnly	int
712	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.LifeElapsedB	readOnly	int
713	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.LotID	readOnly	string
714	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.Manufacturer	readOnly	string
715	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.Model	readOnly	string
716	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.PreEOLStateEUDA	readOnly	string
717	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.PreEOLStateMLC	readOnly	string
718	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.PreEOLStateSystem	readOnly	string
719	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.ReadOnly	readOnly	boolean
720	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.SerialNumber	readOnly	string
721	Device.Services.STBService.1.Components.X_RDKCENTRAL-COM_eMMCFlash.TSBQualified	readOnly	boolean
722	Device.Services.STBService.1.Enable	readWrite	boolean
723	Device.Services.STBServiceNumberOfEntries	readOnly	unsigned Int
724	Device.Time.ChronyEnable	readWrite	boolean
725	Device.Time.CurrentLocalTime	readWrite	string
726	Device.Time.Enable	readWrite	boolean
727	Device.Time.LocalTimeZone	readWrite	string
728	Device.Time.NTPMaxpoll	readWrite	unsigned Int
729	Device.Time.NTPMaxstep	readWrite	string
730	Device.Time.NTPMinpoll	readWrite	unsigned Int
731	Device.Time.NTPServer1	readWrite	string
732	Device.Time.NTPServer1Directive	readWrite	string
733	Device.Time.NTPServer2	readWrite	string
734	Device.Time.NTPServer2Directive	readWrite	string
735	Device.Time.NTPServer3	readWrite	string
736	Device.Time.NTPServer3Directive	readWrite	string
737	Device.Time.NTPServer4	readWrite	string
738	Device.Time.NTPServer4Directive	readWrite	string
739	Device.Time.NTPServer5	readWrite	string
740	Device.Time.NTPServer5Directive	readWrite	string
741	Device.Time.Status	readWrite	string
742	Device.Time.X_RDK_CurrentUTCTime	readOnly	string
743	Device.WiFi.AccessPoint.{i}.Alias	readWrite	string

744	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.Active	readOnly	boolean
745	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.AuthenticationState	readOnly	boolean
746	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.LastDataDownlinkRate	readOnly	unsigned Int
747	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.LastDataUplinkRate	readOnly	unsigned Int
748	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.MACAddress	readOnly	string
749	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.Retransmissions	readOnly	unsigned Int
750	Device.WiFi.AccessPoint.{i}.AssociatedDevice.{i}.SignalStrength	readOnly	int
751	Device.WiFi.AccessPoint.{i}.AssociatedDeviceNumberOfEntries	readOnly	unsigned Int
752	Device.WiFi.AccessPoint.{i}.Enable	readWrite	boolean
753	Device.WiFi.AccessPoint.{i}.RetryLimit	readWrite	unsigned Int
754	Device.WiFi.AccessPoint.{i}.SSIDAdvertisementEnabled	readWrite	boolean
755	Device.WiFi.AccessPoint.{i}.SSIDReference	readWrite	string
756	Device.WiFi.AccessPoint.{i}.Security.KeyPassphrase	readWrite	string
757	Device.WiFi.AccessPoint.{i}.Security.ModeEnabled	readWrite	string
758	Device.WiFi.AccessPoint.{i}.Security.ModesSupported	readOnly	string
759	Device.WiFi.AccessPoint.{i}.Security.PreSharedKey	readWrite	hexBinary
760	Device.WiFi.AccessPoint.{i}.Security.RadiusSecret	readWrite	string
761	Device.WiFi.AccessPoint.{i}.Security.RadiusServerIPAddr	readWrite	string
762	Device.WiFi.AccessPoint.{i}.Security.RadiusServerPort	readWrite	unsigned Int
763	Device.WiFi.AccessPoint.{i}.Security.RekeyingInterval	readWrite	unsigned Int
764	Device.WiFi.AccessPoint.{i}.Security.WEPKey	readWrite	hexBinary
765	Device.WiFi.AccessPoint.{i}.Status	readOnly	string
766	Device.WiFi.AccessPoint.{i}.UAPSDCapability	readOnly	boolean
767	Device.WiFi.AccessPoint.{i}.UAPSDEnable	readWrite	boolean
768	Device.WiFi.AccessPoint.{i}.WMMCapability	readOnly	boolean
769	Device.WiFi.AccessPoint.{i}.WMMEnable	readWrite	boolean
770	Device.WiFi.AccessPoint.{i}.WPS.ConfigMethodsEnabled	readWrite	string
771	Device.WiFi.AccessPoint.{i}.WPS.ConfigMethodsSupported	readOnly	string
772	Device.WiFi.AccessPoint.{i}.WPS.Enable	readWrite	boolean
773	Device.WiFi.AccessPointNumberOfEntries	readOnly	unsigned Int
774	Device.WiFi.EndPoint.{i}.Alias	readWrite	string
775	Device.WiFi.EndPoint.{i}.Enable	readWrite	boolean
776	Device.WiFi.EndPoint.{i}.Profile.{i}.Alias	readWrite	string
777	Device.WiFi.EndPoint.{i}.Profile.{i}.Enable	readWrite	boolean
778	Device.WiFi.EndPoint.{i}.Profile.{i}.Location	readWrite	string
779	Device.WiFi.EndPoint.{i}.Profile.{i}.Priority	readWrite	unsigned Int
780	Device.WiFi.EndPoint.{i}.Profile.{i}.SSID	readWrite	string
781	Device.WiFi.EndPoint.{i}.Profile.{i}.Security.KeyPassphrase	readWrite	string
782	Device.WiFi.EndPoint.{i}.Profile.{i}.Security.ModeEnabled	readWrite	string
783	Device.WiFi.EndPoint.{i}.Profile.{i}.Security.PreSharedKey	readWrite	hexBinary

784	Device.WiFi.EndPoint.{i}.Profile.{i}.Security.WEPKey	readWrite	hexBinary
785	Device.WiFi.EndPoint.{i}.Profile.{i}.Status	readOnly	string
786	Device.WiFi.EndPoint.{i}.ProfileNumberOfEntries	readOnly	unsigneDInt
787	Device.WiFi.EndPoint.{i}.ProfileReference	readWrite	string
788	Device.WiFi.EndPoint.{i}.SSIDReference	readOnly	string
789	Device.WiFi.EndPoint.{i}.Security.ModesEnabled	readOnly	string
790	Device.WiFi.EndPoint.{i}.Security.ModesSupported	readOnly	string
791	Device.WiFi.EndPoint.{i}.Stats.LastDataDownlinkRate	readOnly	unsigneDInt
792	Device.WiFi.EndPoint.{i}.Stats.LastDataUplinkRate	readOnly	unsigneDInt
793	Device.WiFi.EndPoint.{i}.Stats.Retransmissions	readOnly	unsigneDInt
794	Device.WiFi.EndPoint.{i}.Stats.SignalStrength	readOnly	int
795	Device.WiFi.EndPoint.{i}.Status	readOnly	string
796	Device.WiFi.EndPoint.{i}.WPS.ConfigMethodsEnabled	readWrite	string
797	Device.WiFi.EndPoint.{i}.WPS.ConfigMethodsSupported	readOnly	string
798	Device.WiFi.EndPoint.{i}.WPS.Enable	readWrite	boolean
799	Device.WiFi.EndPointNumberOfEntries	readOnly	unsigneDInt
800	Device.WiFi.Radio.{i}.OperatingChannelBandwidth	readOnly	string
801	Device.WiFi.Radio.{i}.Stats.Noise	readOnly	int
802	Device.WiFi.Radio.{i}.Stats.PacketsReceived	readOnly	unsigneDLong
803	Device.WiFi.RadioNumberOfEntries	readOnly	unsigneDInt
804	Device.WiFi.SSID.{i}.Alias	readWrite	string
805	Device.WiFi.SSID.{i}.BSSID	readOnly	string
806	Device.WiFi.SSID.{i}.Enable	readWrite	boolean
807	Device.WiFi.SSID.{i}.LastChange	readOnly	unsigneDInt
808	Device.WiFi.SSID.{i}.LowerLayers	readWrite	string
809	Device.WiFi.SSID.{i}.MACAddress	readOnly	string
810	Device.WiFi.SSID.{i}.Name	readOnly	string
811	Device.WiFi.SSID.{i}.SSID	readWrite	string
812	Device.WiFi.SSID.{i}.Stats.BroadcastPacketsReceived	readOnly	unsigneDLong
813	Device.WiFi.SSID.{i}.Stats.BroadcastPacketsSent	readOnly	unsigneDLong
814	Device.WiFi.SSID.{i}.Stats.BytesReceived	readOnly	unsigneDLong
815	Device.WiFi.SSID.{i}.Stats.BytesSent	readOnly	unsigneDLong
816	Device.WiFi.SSID.{i}.Stats.DiscardPacketsReceived	readOnly	unsigneDInt
817	Device.WiFi.SSID.{i}.Stats.DiscardPacketsSent	readOnly	unsigneDInt
818	Device.WiFi.SSID.{i}.Stats.ErrorsReceived	readOnly	unsigneDInt
819	Device.WiFi.SSID.{i}.Stats.ErrorsSent	readOnly	unsigneDInt
820	Device.WiFi.SSID.{i}.Stats.MulticastPacketsReceived	readOnly	unsigneDLong

821	Device.WiFi.SSID.{i}.Stats.MulticastPacketsSent	readOnly	unsigned Long
822	Device.WiFi.SSID.{i}.Stats.PacketsReceived	readOnly	unsigned Long
823	Device.WiFi.SSID.{i}.Stats.PacketsSent	readOnly	unsigned Long
824	Device.WiFi.SSID.{i}.Stats.UnicastPacketsReceived	readOnly	unsigned Long
825	Device.WiFi.SSID.{i}.Stats.UnicastPacketsSent	readOnly	unsigned Long
826	Device.WiFi.SSID.{i}.Stats.UnknownProtoPacketsReceived	readOnly	unsigned Int
827	Device.WiFi.SSID.{i}.Status	readOnly	string
828	Device.WiFi.SSIDNumberOfEntries	readOnly	unsigned Int
829	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.80211kvrEnable	readWrite	boolean
830	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.Enable	readWrite	boolean
831	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolBeaconsMissedTime	readWrite	unsigned Int
832	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolThresholdLevel	readWrite	int
833	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_APcontrolTimeframe	readWrite	unsigned Int
834	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BackOffTime	readWrite	unsigned Int
835	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BestDeltaLevelConnected	readWrite	unsigned Int
836	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_BestDeltaLevelDisconnected	readWrite	unsigned Int
837	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerBeaconsMissedTime	readWrite	unsigned Int
838	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerThresholdLevel	readWrite	int
839	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PostAssn_SelfSteerTimeframe	readWrite	unsigned Int
840	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PreAssn_BestDeltaLevel	readWrite	unsigned Int
841	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.PreAssn_BestThresholdLevel	readWrite	int
842	Device.WiFi.X_RDKCENTRAL-COM_ClientRoaming.SelfSteer_OverrideEnable	readWrite	boolean
843	Device.WiFi.X_RDKCENTRAL-COM_WiFiEnable	readWrite	boolean
844	Device.X_COMCAST-COM_Xcalibur.Client.SecuritySystem.ssDeviceId	readOnly	string
845	Device.X_COMCAST-COM_Xcalibur.Client.SecuritySystem.ssDeviceReg	readOnly	dateTime
846	Device.X_COMCAST-COM_Xcalibur.Client.SecuritySystem.ssErrorCnt	readOnly	unsigned Int
847	Device.X_COMCAST-COM_Xcalibur.Client.SecuritySystem.ssRegTs	readOnly	boolean
848	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreAppId	readOnly	string
849	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreConnEstTs	readOnly	string
850	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreConnIfName	readOnly	string
851	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreConnRetryAttempts	readOnly	unsigned Int
852	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreConnStatus	readOnly	string
853	Device.X_COMCAST-COM_Xcalibur.Client.XRE.ConnectionTable.xreConnURL	readOnly	string
854	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreAvgCmdProcTime	readOnly	int
855	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreChannelMapId	readOnly	string
856	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreCommandCnt	readOnly	unsigned Int
857	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreControllerId	readOnly	string

858	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreEnable	readWrite	boolean
859	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreErrorCnt	readOnly	unsigned Int
860	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreFlushLocalCache	readWrite	boolean
861	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreGatewaySTBMAC	readOnly	string
862	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreGetTWPDiags	readOnly	string
863	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreLastURLAccessed	readOnly	string
864	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreLastVideoUrl	readOnly	string
865	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreLogLevel	readWrite	string
866	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreMaxCmdProcTime	readOnly	int
867	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreMinCmdProcTime	readOnly	int
868	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xrePlantId	readOnly	string
869	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreReceiverId	readOnly	string
870	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreRefreshXreSession	readWrite	boolean
871	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreRefreshXreSessionWithRR	readWrite	int
872	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreSessionId	readOnly	string
873	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreSessionLastModTs	readOnly	string
874	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreSessionUptime	readOnly	string
875	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreStatus	readOnly	string
876	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotAnimCnt	readOnly	unsigned Int
877	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotAppCnt	readOnly	unsigned Int
878	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotFlashCnt	readOnly	unsigned Int
879	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotFontCnt	readOnly	unsigned Int
880	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotHtmlTxtCnt	readOnly	unsigned Int
881	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotImgCnt	readOnly	unsigned Int
882	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotNineSliceImgCnt	readOnly	unsigned Int
883	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotRectCnt	readOnly	unsigned Int
884	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotSoundCnt	readOnly	unsigned Int
885	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotStyleshtCnt	readOnly	unsigned Int
886	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotTxtCnt	readOnly	unsigned Int
887	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotTxtIpCnt	readOnly	unsigned Int
888	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotVideoCnt	readOnly	unsigned Int
889	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreTotViewCnt	readOnly	unsigned Int
890	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreVersion	readOnly	string
891	Device.X_COMCAST-COM_Xcalibur.Client.XRE.xreVodId	readOnly	string
892	Device.X_COMCAST-COM_Xcalibur.Client.xconfCheckNow	readWrite	string
893	Device.X_COMCAST-COM_Xcalibur.DevApp.devAppNumAps	readOnly	unsigned Int
894	Device.X_COMCAST-COM_Xcalibur.DevApp.devAppTable.{i}.devAppId	readOnly	string
895	Device.X_COMCAST-COM_Xcalibur.DevApp.devAppTable.{i}.devAppRestartCapability	readOnly	string

896	Device.X_COMCAST-COM_Xcalibur.TRM.trmGatewayDeviceFriendlyName	readOnly	string
897	Device.X_COMCAST-COM_Xcalibur.TRM.trmGatewayMoCAIP	readOnly	string
898	Device.X_COMCAST-COM_Xcalibur.TRM.trmGatewayMoCAMAC	readOnly	string
899	Device.X_COMCAST-COM_Xcalibur.TRM.trmGatewaySTBMAC	readOnly	string
900	Device.X_RDKCENTRAL-COM_T2.ReportProfiles	readWrite	string
901	Device.X_RDKCENTRAL-COM_T2.ReportProfilesMsgPack	readWrite	string
902	Device.X_RDK_WebPA_DNSText.URL	readWrite	string
903	Device.X_RDK_WebPA_Server.URL	readOnly	string
904	Device.X_RDK_WebPA_TokenServer.URL	readOnly	string