Linear A

Range: 10600–1077F

This file contains an excerpt from the character code tables and list of character names for
The Unicode Standard, Version 14.0

This file may be changed at any time without notice to reflect errata or other updates to the Unicode Standard.
See https://www.unicode.org/errata/ for an up-to-date list of errata.

See https://www.unicode.org/charts/ for access to a complete list of the latest character code charts.
See https://www.unicode.org/charts/PDF/Unicode-14.0/ for charts showing only the characters added in Unicode 14.0.
See https://www.unicode.org/Public/14.0.0/charts/ for a complete archived file of character code charts for Unicode 14.0.

Disclaimer

These charts are provided as the online reference to the character contents of the Unicode Standard, Version 14.0 but do not provide all the information needed to fully support individual scripts using the Unicode Standard. For a complete understanding of the use of the characters contained in this file, please consult the appropriate sections of The Unicode Standard, Version 14.0, online at https://www.unicode.org/versions/Unicode14.0.0/, as well as Unicode Standard Annexes #9, #11, #14, #15, #24, #29, #31, #34, #38, #41, #42, #44, #45, and #50, the other Unicode Technical Reports and Standards, and the Unicode Character Database, which are available online.

See https://www.unicode.org/ucd/ and https://www.unicode.org/reports/

A thorough understanding of the information contained in these additional sources is required for a successful implementation.

Copying characters from the character code tables or list of character names is not recommended, because for production reasons the PDF files for the code charts cannot guarantee that the correct character codes will always be copied.

Fonts

The shapes of the reference glyphs used in these code charts are not prescriptive. Considerable variation is to be expected in actual fonts. The particular fonts used in these charts were provided to the Unicode Consortium by a number of different font designers, who own the rights to the fonts.

See https://www.unicode.org/charts/fonts.html for a list.

Terms of Use

You may freely use these code charts for personal or internal business uses only. You may not incorporate them either wholly or in part into any product or publication, or otherwise distribute them without express written permission from the Unicode Consortium. However, you may provide links to these charts.

The fonts and font data used in production of these code charts may NOT be extracted, or used in any other way in any product or publication, without permission or license granted by the typeface owner(s).

The Unicode Consortium is not liable for errors or omissions in this file or the standard itself. Information on characters added to the Unicode Standard since the publication of the most recent version of the Unicode Standard, as well as on characters currently being considered for addition to the Unicode Standard can be found on the Unicode web site.

See https://www.unicode.org/pending/pending.html and https://www.unicode.org/alloc/Pipeline.html.

Copyright © 1991-2021 Unicode, Inc. All rights reserved.

	1060	1061	1062	1063	1064	1065	1066	1067	1068	1069	106A	106B
0	10600	10610	10620	10630	10640	10650	10660	10670	10680	10690	106A0	106B0
1	10601	10611	10621	10631	10641	10651	10661	10671	10681	10691	106A1	106B1
2	10602	10612	10622	10632	10642	10652	10662	10672	10682	10692	106A2	106B2
3	10603	10613	10623	10633	10643	10653	10663	10673	10683	10693	106A3	106B3
4	10604	10614	10624	10634	10644	10654	10664	10674	10684	10694	106A4	106B4
5	10605	10615	10625	10635	10645	10655	10665	10675	10685	10695	106A5	106B5
6	10606	10616	10626	10636	10646	10656	10666	10676	10686	10696	106A6	106B6
7	10607	10617	10627	10637	10647	10657	10667	10677	10687	10697	106A7	106B7
8	10608	10618	10628	10638	10648	10658	10668	10678	10688	10698	106A8	106B8
9	10609	10619	10629	10639	10649	10659	10669	10679	10689	10699	106A9	106B9
A	1060A	1061A	1062A	1063A	1064A	1065A	1066A	1067A	1068A	1069A	106AA	106BA
B	1060B	1061B	1062B	1063B	1064B	1065B	1066B	1067B	1068B	1069B	106AB	106BB
C	1060C	1061C	1062C	1063C	1064C	1065C	1066C	1067C	1068C	1069C	106AC	106BC
D	1060D	1061D	1062D	1063D	1064D	1065D	1066D	1067D	1068D	1069D	106AD	106BD
E	1060E	1061E	1062E	1063E	1064E	1065E	1066E	1067E	1068E	1069E	106AE	106BE
F	1060F	1061F	1062F	1063F	1064F	1065F	1066F	1067F	1068F	1069F	106AF	106BF

	106C	106D	106E	106F	1070	1071	1072	1073	1074	1075	1076	1077
0	106C0	106D0	106E0	106F0	10700	10710	10720	10730	10740	10750	10760	
1	106C1	106D1	106E1	106F1	10701	10711	10721	10731	10741	10751	10761	
2	106C2	106D2	106E2	106F2	10702	10712	10722	10732	10742	10752	10762	
3	106C3	106D3	106E3	106F3	10703	10713	10723	10733	10743	10753	10763	
4	106C4	106D4	106E4	106F4	10704	10714	10724	10734	10744	10754	10764	
5	106C5	106D5	106E5	106F5	10705	10715	10725	10735	10745	10755	10765	
6	106C6	106D6	106E6	106F6	10706	10716	10726	10736	10746		10766	
7	106C7	106D7	106E7	106F7	10707	10717	10727		10747		10767	
8	106C8	106D8	106E8	106F8	10708	10718	10728		10748			
9	106C9	106D9	106E9	106F9	10709	10719	10729		10749			
A	106CA	106DA	106EA	106FA	1070A	1071A	1072A		1074A			
B	106CB	106DB	106EB	106FB	1070B	1071B	1072B		1074B			
C	106CC	106DC	106EC	106FC	1070C	1071C	1072C		1074C			
D	106CD	106DD	106ED	106FD	1070D	1071D	1072D		1074D			
E	106CE	106DE	106EE	106FE	1070E	1071E	1072E		1074E			
F	106CF	106DF	106EF	106FF	1070F	1071F	1072F		1074F			

Simple signs

10600	├	LINEAR A SIGN AB001
10601	╀	LINEAR A SIGN AB002
10602	╪	LINEAR A SIGN AB003
10603	₩	LINEAR A SIGN AB004
10604	╤	LINEAR A SIGN AB005
10605	⊤	LINEAR A SIGN AB006
10606	╥	LINEAR A SIGN AB007
10607	⊢	LINEAR A SIGN AB008
10608	╟	LINEAR A SIGN AB009
10609	ⱷ	LINEAR A SIGN AB010
1060A	∫	LINEAR A SIGN AB011
1060B	⸮	LINEAR A SIGN AB013
1060C	ⸯ	LINEAR A SIGN AB016
1060D	⸰	LINEAR A SIGN AB017
1060E	↑	LINEAR A SIGN AB020
1060F	♀	LINEAR A SIGN AB021
		• sheep
		→ 10025 ⸯ linear b syllable b021 qi
10610	⅀	LINEAR A SIGN AB021F
		• ewe
		→ 10086 ⸯ linear b ideogram b106f ewe
10611	⸖	LINEAR A SIGN AB021M
		• ram
		→ 10087 ⸯ linear b ideogram b106m ram
10612	⋀⋏	LINEAR A SIGN AB022
		• goat
		→ 10052 ⸯ linear b symbol b022
10613	⋀⋏	LINEAR A SIGN AB022F
		• she-goat
		→ 10088 ⸯ linear b ideogram b107f she-goat
10614	⋀⋣	LINEAR A SIGN AB022M
		• he-goat
		→ 10089 ⸯ linear b ideogram b107m he-goat
10615	ⸯ	LINEAR A SIGN AB023
		• bovine
		→ 10018 ⸯ linear b syllable b023 mu
10616	⸖	LINEAR A SIGN AB023M
		• bull
		→ 1008D ⸯ linear b ideogram b109m bull
10617	╪	LINEAR A SIGN AB024
10618	ⸯ	LINEAR A SIGN AB026
10619	Ψ	LINEAR A SIGN AB027
1061A	ⸯ	LINEAR A SIGN AB028
1061B	ⸯ	LINEAR A SIGN A028B
1061C	ⸯ	LINEAR A SIGN AB029
1061D	ⸯ	LINEAR A SIGN AB030
		• figs
		→ 1001B ⸯ linear b syllable b030 ni
1061E	Υ	LINEAR A SIGN AB031
1061F	С	LINEAR A SIGN AB034
10620	Λ	LINEAR A SIGN AB037
10621	Ⱥ	LINEAR A SIGN AB038
10622	ⸯ	LINEAR A SIGN AB039
10623	ⸯ	LINEAR A SIGN AB040
10624	ⸯ	LINEAR A SIGN AB041
10625	ⸯ	LINEAR A SIGN AB044
10626	ⸯ	LINEAR A SIGN AB045
10627	Х	LINEAR A SIGN AB046
10628	ⸯ	LINEAR A SIGN AB047
10629	ⸯ	LINEAR A SIGN AB048
		→ 10045 ⸯ linear b syllable b048 nwa

1062A	ⸯ	LINEAR A SIGN AB049
1062B	ⸯ	LINEAR A SIGN AB050
1062C	ⸯ	LINEAR A SIGN AB051
1062D	ⸯ	LINEAR A SIGN AB053
1062E	ⸯ	LINEAR A SIGN AB054
		• cloth
		→ 100A7 ⸯ linear b ideogram b159 cloth
1062F	ⸯ	LINEAR A SIGN AB055
10630	ⸯ	LINEAR A SIGN AB056
10631	ⸯ	LINEAR A SIGN AB057
10632	ⸯ	LINEAR A SIGN AB058
10633	ⸯ	LINEAR A SIGN AB059
10634	ⸯ	LINEAR A SIGN AB060
10635	ⸯ	LINEAR A SIGN AB061
10636	ⸯ	LINEAR A SIGN AB065
10637	ⸯ	LINEAR A SIGN AB066
10638	ⸯ	LINEAR A SIGN AB067
10639	ⸯ	LINEAR A SIGN AB069
1063A	ⸯ	LINEAR A SIGN AB070
1063B	ⸯ	LINEAR A SIGN AB073
1063C	ⸯ	LINEAR A SIGN AB074
1063D	ⸯ	LINEAR A SIGN AB076
1063E	⊕	LINEAR A SIGN AB077
1063F	☺	LINEAR A SIGN AB078
10640	ⸯ	LINEAR A SIGN AB079
10641	ⸯ	LINEAR A SIGN AB080
10642	ⸯ	LINEAR A SIGN AB081
10643	ⸯ	LINEAR A SIGN AB082
10644	ⸯ	LINEAR A SIGN AB085
		• pig
		→ 10042 ⸯ linear b syllable b085 au
10645	ⸯ	LINEAR A SIGN AB086
10646	β	LINEAR A SIGN AB087
10647	ⸯ	LINEAR A SIGN A100-102
		• man or woman
		→ 10080 ⸯ linear b ideogram b100 man
		→ 10081 ⸯ linear b ideogram b102 woman
10648	ⸯ	LINEAR A SIGN AB118
10649	ⸯ	LINEAR A SIGN AB120
		• grain
		→ 1008E ⸯ linear b ideogram b120 wheat
1064A	ⸯ	LINEAR A SIGN A120B
		• grain
1064B	ⸯ	LINEAR A SIGN AB122
		• olives
		→ 10090 ⸯ linear b ideogram b122 olive
1064C	ⸯ	LINEAR A SIGN AB123
1064D	ⸯ	LINEAR A SIGN AB131A
		• wine
		→ 10096 ⸯ linear b ideogram b131 wine
1064E	ⸯ	LINEAR A SIGN AB131B
		• wine
1064F	ⸯ	LINEAR A SIGN A131C
		• wine
10650	ⸯ	LINEAR A SIGN AB164
10651	ⸯ	LINEAR A SIGN AB171
10652	ⸯ	LINEAR A SIGN AB180
10653	ⸯ	LINEAR A SIGN AB188
10654	ⸯ	LINEAR A SIGN AB191
10655	Я	LINEAR A SIGN A301

10656	⩘	LINEAR A SIGN A302

• olive oil
→ 10095 ⩘ linear b ideogram b130 oil

10657	⫯	LINEAR A SIGN A303

• cyperus
→ 10092 ⫯ linear b ideogram b125 cyperus

10658	↑	LINEAR A SIGN A304
10659	⧃	LINEAR A SIGN A305
1065A	⩗	LINEAR A SIGN A306
1065B	⫙	LINEAR A SIGN A307
1065C	◁	LINEAR A SIGN A308
1065D	◯	LINEAR A SIGN A309A
1065E	◯	LINEAR A SIGN A309B
1065F	◎	LINEAR A SIGN A309C
10660	ℂ	LINEAR A SIGN A310
10661	⌒	LINEAR A SIGN A311

• used with 10655 Я linear a sign a301

10662	⌂	LINEAR A SIGN A312
10663	⬎	LINEAR A SIGN A313A

• used with 10647 ⩏ linear a sign a100-102

10664	→	LINEAR A SIGN A313B

• used with 10647 ⩏ linear a sign a100-102

10665	⬊	LINEAR A SIGN A313C

• used with 10647 ⩏ linear a sign a100-102

10666	⧟	LINEAR A SIGN A314
10667	⧓	LINEAR A SIGN A315
10668	⨍	LINEAR A SIGN A316
10669	⧾	LINEAR A SIGN A317
1066A	⧓	LINEAR A SIGN A318
1066B	⊥	LINEAR A SIGN A319
1066C	⅊	LINEAR A SIGN A320
1066D	⊡	LINEAR A SIGN A321
1066E	⅋	LINEAR A SIGN A322
1066F	⩕	LINEAR A SIGN A323
10670	⅄	LINEAR A SIGN A324
10671	♀	LINEAR A SIGN A325
10672	ⵁ	LINEAR A SIGN A326
10673	⊞	LINEAR A SIGN A327
10674	ⵖ	LINEAR A SIGN A328
10675	ⵥ	LINEAR A SIGN A329
10676	⋈⋊	LINEAR A SIGN A330

• used with 10600 ├ linear a sign ab001 and 1061E Y linear a sign ab031

10677	⊞	LINEAR A SIGN A331
10678	⩘	LINEAR A SIGN A332
10679	ⵗ	LINEAR A SIGN A333
1067A	ⵦ	LINEAR A SIGN A334
1067B	ⵘ	LINEAR A SIGN A335
1067C	⵪	LINEAR A SIGN A336
1067D	ⵣ	LINEAR A SIGN A337

• used with 10653 ⊟ linear a sign ab188

1067E	⨅	LINEAR A SIGN A338
1067F	ⵋ	LINEAR A SIGN A339
10680	ⵕ	LINEAR A SIGN A340
10681	ⵛ	LINEAR A SIGN A341

• used with 10622 ⩑ linear a sign ab039

10682	ⵏ	LINEAR A SIGN A342
10683	ⵏ	LINEAR A SIGN A343
10684	ⵎ	LINEAR A SIGN A344
10685	ⵝ	LINEAR A SIGN A345
10686	⊔	LINEAR A SIGN A346
10687	ⵥ	LINEAR A SIGN A347

10688	ⵛ	LINEAR A SIGN A348

• used with 10657 ⫯ linear a sign a303

10689	⧅	LINEAR A SIGN A349
1068A	⋏	LINEAR A SIGN A350
1068B	ⵌ	LINEAR A SIGN A351

• used with 10655 Я linear a sign a301

1068C	ⵟ	LINEAR A SIGN A352
1068D	◿	LINEAR A SIGN A353
1068E	ⵜ	LINEAR A SIGN A354
1068F	Ⲩ	LINEAR A SIGN A355
10690	⧽	LINEAR A SIGN A356
10691	ⵘ	LINEAR A SIGN A357
10692	ⵗ	LINEAR A SIGN A358
10693	ℭ	LINEAR A SIGN A359
10694	⊟	LINEAR A SIGN A360
10695	Ⲩ	LINEAR A SIGN A361
10696	ⵯ	LINEAR A SIGN A362
10697	⵮	LINEAR A SIGN A363
10698	⵬	LINEAR A SIGN A364
10699	ⵀ	LINEAR A SIGN A365
1069A	⵭	LINEAR A SIGN A366
1069B	⵭	LINEAR A SIGN A367
1069C	℗	LINEAR A SIGN A368
1069D	⵲	LINEAR A SIGN A369
1069E	�ₚ	LINEAR A SIGN A370
1069F	⚓	LINEAR A SIGN A371

Vase shapes

106A0	▽	LINEAR A SIGN A400-VAS
106A1	�ⵧ	LINEAR A SIGN A401-VAS
106A2	▽	LINEAR A SIGN A402-VAS
106A3	▽	LINEAR A SIGN A403-VAS
106A4	ⵧ	LINEAR A SIGN A404-VAS
106A5	ⵧ	LINEAR A SIGN A405-VAS
106A6	⵨	LINEAR A SIGN A406-VAS
106A7	ⵡ	LINEAR A SIGN A407-VAS
106A8	ⵥ	LINEAR A SIGN A408-VAS
106A9	ⵤ	LINEAR A SIGN A409-VAS
106AA	ⵥ	LINEAR A SIGN A410-VAS
106AB	ⵥ	LINEAR A SIGN A411-VAS
106AC	ⵛ	LINEAR A SIGN A412-VAS
106AD	ⵯ	LINEAR A SIGN A413-VAS
106AE	ⵆ	LINEAR A SIGN A414-VAS
106AF	ⵁ	LINEAR A SIGN A415-VAS
106B0	ⵁ	LINEAR A SIGN A416-VAS
106B1	ⵤ	LINEAR A SIGN A417-VAS
106B2	⵰	LINEAR A SIGN A418-VAS

Complex signs

106B3	⊩	LINEAR A SIGN A501

• 10600 ├ ab001, 10601 ┼ ab002

106B4	ⵯ	LINEAR A SIGN A502

• 10600 ├ ab001, 10619 Y ab027, 10608 ⊮ ab009

106B5	ⵯ	LINEAR A SIGN A503

• 10600 ├ ab001, 10655 Я a301

106B6	ⵜ	LINEAR A SIGN A504

• 10601 ┼ ab002, 10601 ┼ ab002

106B7	ⵜ	LINEAR A SIGN A505

• 10603 ⵥ ab004, 10601 ┼ ab002

106B8	ⵯ	LINEAR A SIGN A506

• 10606 ⵯ ab007, 1063F ⵙ ab078

106B9 ᛈ LINEAR A SIGN A508
• 1060C ᛉ ab016, 10619 Ψ ab027

106BA ᛈᛜ LINEAR A SIGN A509
• 1060C ᛉ ab016, 10619 Ψ ab027, 1062B ᛗ ab050

106BB ᛈᛜ LINEAR A SIGN A510
• 1060C ᛉ ab016, 1062B ᛗ ab050

106BC ᛈᛜᛥ LINEAR A SIGN A511
• 1060C ᛉ ab016, 1062B ᛗ ab050, 10619 Ψ ab027

106BD ᛇ LINEAR A SIGN A512
• 1060F ᛤ ab021, 10624 ᛨ ab041

106BE ᛊᛜ LINEAR A SIGN A513
• 10614 ᛮ ab022m, 10642 ᛝ ab081

106BF ᛄ LINEAR A SIGN A515
• 10619 Ψ ab027, 10608 ᛈ ab009

106C0 ᛨ LINEAR A SIGN A516
→ 1061A Ψ linear a sign ab028

106C1 ᛨᛝ LINEAR A SIGN A520
• 1061A Ψ ab028, 10655 ᛘ a301

106C2 ᛊᛝ LINEAR A SIGN A521
• 1061E ᛉ ab031, 10615 ᛈ ab023, 10642 ᛝ ab081

106C3 ᛪ LINEAR A SIGN A523
• 10620 ᛘ ab037, 10607 ᛈ ab008

106C4 ᛫ LINEAR A SIGN A524
• 10620 ᛘ ab037, 106AC ᛞ a412-vas

106C5 ᛤ LINEAR A SIGN A525
→ 10621 ᛤ linear a sign ab038

106C6 ᛤ LINEAR A SIGN A526
• 10621 ᛤ ab038, 1063E ⊕ ab077

106C7 ᛤᛜ LINEAR A SIGN A527
• 10623 ᛘ ab040, 1063C ᛝ ab074

106C8 ᛨ LINEAR A SIGN A528
• 10624 ᛨ ab041, 10606 ᛈ ab007

106C9 ᛄ LINEAR A SIGN A529
• 10624 ᛨ ab041, 10608 ᛈ ab009

106CA ᛨᛝ LINEAR A SIGN A530
• 10624 ᛨ ab041, 1060B ᛝ ab013

106CB ᛨᛝ LINEAR A SIGN A531
• 10624 ᛨ ab041, 1060B ᛝ ab013, 10638 ᛘ ab067

106CC ᛨ LINEAR A SIGN A532
• 10624 ᛨ ab041, 10637 ᛘ ab066

106CD ᛪ LINEAR A SIGN A534
→ 1062C ᛪ linear a sign ab051

106CE ᛨ LINEAR A SIGN A535
• 1062E ᛘ ab054, 10642 ᛝ ab081

106CF ᛨ LINEAR A SIGN A536
• 1062E ᛘ ab054, 10662 ᛘ a312

106D0 ᛨ LINEAR A SIGN A537
• 10630 ᛘ ab056, 1063F ☉ ab078

106D1 ᛨ LINEAR A SIGN A538
• 10631 ᛘ ab057, 10618 ᛈ ab026

106D2 ᛨ LINEAR A SIGN A539
• 10631 ᛘ ab057, 1063E ⊕ ab077

106D3 ᛨ LINEAR A SIGN A540
• 10632 ᛘ ab058, 1063B ᛝ ab073

106D4 ᛨ LINEAR A SIGN A541
• 10634 ᛝ ab060, 1063E ⊕ ab077

106D5 ᛨ LINEAR A SIGN A542
• 10636 ᛝ ab065, 10669 ᛨ a317, 1063F ☉ ab078

106D6 ᛨ LINEAR A SIGN A545
• 10638 ᛘ ab067, 10615 ᛈ ab023

106D7 ᛨ LINEAR A SIGN A547
• 10639 ᛨ ab069, 10601 ᛈ ab002

106D8 ᛨ LINEAR A SIGN A548
• 1063B ᛝ ab073, 10631 ᛘ ab057

106D9 ᛨ LINEAR A SIGN A549
→ 106D8 ᛨ linear a sign a548

106DA ᛨ LINEAR A SIGN A550
• 1063B ᛝ ab073, 10631 ᛘ ab057, 10618 ᛈ ab026

106DB ᛨ LINEAR A SIGN A551
• 1063B ᛝ ab073, 10631 ᛘ ab057, 1061A Ψ ab028

106DC ᛨ LINEAR A SIGN A552
• 1063B ᛝ ab073, 10631 ᛘ ab057, 1063E ⊕ ab077

106DD ᛨ LINEAR A SIGN A553
• 1063B ᛝ ab073, 10655 ᛘ a301

106DE ᛨ LINEAR A SIGN A554
• 1063E ⊕ ab077, 10607 ᛈ ab008

106DF ᛨ LINEAR A SIGN A555
• 1063F ☉ ab078, 10649 ᛨ ab120, 10602 ᛈ ab003

106E0 ᛨ LINEAR A SIGN A556
→ 10641 ᛨ linear a sign ab080

106E1 ᛨ LINEAR A SIGN A557
• 10641 ᛨ ab080, 10607 ᛈ ab008

106E2 ᛨ LINEAR A SIGN A559
• 10641 ᛨ ab080, 10618 ᛈ ab026

106E3 ᛨ LINEAR A SIGN A563
• 10641 ᛨ ab080, 10641 ᛨ ab080

106E4 ᛝ LINEAR A SIGN A564
→ 10642 ᛝ linear a sign ab081

106E5 ᛨ LINEAR A SIGN A565
• 10645 ᛨ ab086, 10653 ᛘ ab188

106E6 ᛨ LINEAR A SIGN A566
• 10645 ᛨ ab086, 10653 ᛘ ab188

106E7 ᛨ LINEAR A SIGN A568
• 10647 ᛤ a100-102, 1063E ⊕ ab077

106E8 ᛨ LINEAR A SIGN A569
• 10647 ᛤ a100-102, 1065B ᛤ a307

106E9 ᛨ LINEAR A SIGN A570
• 10647 ᛤ a100-102, 10663 ᛝ a313a

106EA ᛨ LINEAR A SIGN A571
• 10647 ᛤ a100-102, 10664 → a313b

106EB ᛨ LINEAR A SIGN A572
• 10647 ᛤ a100-102, 10665 ᛝ a313c

106EC ᛨ LINEAR A SIGN A573
• 10649 ᛨ ab120, 10600 ᛈ ab001

106ED ᛨ LINEAR A SIGN A574
• 10649 ᛨ ab120, 10602 ᛈ ab003

106EE ᛨ LINEAR A SIGN A575
• 10649 ᛨ ab120, 10610 ᛤ ab021f

106EF ᛨ LINEAR A SIGN A576
• 10649 ᛨ ab120, 10614 ᛮ ab022m

106F0 ᛨ LINEAR A SIGN A577
• 10649 ᛨ ab120, 1062F ᛘ ab056

106F1 ᛨ LINEAR A SIGN A578
• 10649 ᛨ ab120, 1063F ☉ ab078

106F2 ᛨ LINEAR A SIGN A579
• 10649 ᛨ ab120, 10642 ᛝ ab081

106F3	𐛳	LINEAR A SIGN A580	
		• 10649 𐙉 ab120, 10741 ┼ a702 b	
106F4	𐛴	LINEAR A SIGN A581	
		• 10649 𐙉 ab120, 10743 ⟩ a704 e	
106F5	𐛵	LINEAR A SIGN A582	
		• 10649 𐙉 ab120, 10744 ⟩ a705 f	
106F6	𐛶	LINEAR A SIGN A583	
		• 10649 𐙉 ab120, 10745 ⟩ a706 h	
106F7	𐛷	LINEAR A SIGN A584	
		• 10649 𐙉 ab120, 10747 ⊤ a708 k, 10749 ⊑ a709-2 l2	
106F8	𐛸	LINEAR A SIGN A585	
		• 10649 𐙉 ab120, 10749 ⊑ a709-2 l2	
106F9	𐛹	LINEAR A SIGN A586	
		• 10649 𐙉 ab120, 1074A ⊑ a709-3 l3, 1074A ⊑ a709-3 l3	
106FA	𐛺	LINEAR A SIGN A587	
		• 1064B 𐙋 ab122, 10639 ⟱ ab069	
106FB	𐛻	LINEAR A SIGN A588	
		• 1064D 𐙍 ab131a, 10603 ⟱ ab004	
106FC	𐛼	LINEAR A SIGN A589	
		• 1064D 𐙍 ab131a, 1061E Υ ab031	
106FD	𐛽	LINEAR A SIGN A591	
		• 1064D 𐙍 ab131a, 1062E ⊞ ab054	
106FE	𐛾	LINEAR A SIGN A592	
		• 1064D 𐙍 ab131a, 1062E ⊞ ab054	
106FF	𐛿	LINEAR A SIGN A594	
		• 1064D 𐙍 ab131a, 10634 ⟂ ab060	
10700	𐜀	LINEAR A SIGN A595	
		• 1064D 𐙍 ab131a, 10634 ⟂ ab060	
10701	𐜁	LINEAR A SIGN A596	
		• 1064D 𐙍 ab131a, 1063E ⊕ ab077	
10702	𐜂	LINEAR A SIGN A598	
		• 1064D 𐙍 ab131b, 10623 ⊞ ab040	
10703	𐜃	LINEAR A SIGN A600	
		• 10762 ⟩ a802, 10741 ┼ a702 b	
10704	𐜄	LINEAR A SIGN A601	
		• 10762 ⟩ a802, 10748 ⊅ a709 l	
10705	𐜅	LINEAR A SIGN A602	
		• 10652 𐙒 ab180, 10741 ┼ a702 b	
10706	𐜆	LINEAR A SIGN A603	
		• 10652 𐙒 ab180, 10748 ⊅ a709 l	
10707	𐜇	LINEAR A SIGN A604	
		• 10653 ⊞ ab188, 10642 ⟩ ab081	
10708	𐜈	LINEAR A SIGN A606	
		• 10655 Я a301, 10661 ⟨⟩ a311	
10709	𐜉	LINEAR A SIGN A608	
		• 10656 ⟩ a302, 10606 𐙆 ab007	
1070A	𐜊	LINEAR A SIGN A609	
		• 10656 ⟩ a302, 10607 𐙇 ab008	
1070B	𐜋	LINEAR A SIGN A610	
		• 10656 ⟩ a302, 10609 𝑓 ab010	
1070C	𐜌	LINEAR A SIGN A611	
		• 10656 ⟩ a302, 10610 𐙐 ab021f	
1070D	𐜍	LINEAR A SIGN A612	
		• 10656 ⟩ a302, 10617 ╪ ab024	
1070E	𐜎	LINEAR A SIGN A613	
		• 10656 ⟩ a302, 10621 𐙡 ab038	
1070F	𐜏	LINEAR A SIGN A614	
		• 10656 ⟩ a302, 1062D ⟩ ab053	
10710	𐜐	LINEAR A SIGN A615	
		• 10656 ⟩ a302, 10633 ⌊ ab059	

10711	𐜑	LINEAR A SIGN A616	
		• 10656 ⟩ a302, 10634 ⟂ ab060	
10712	𐜒	LINEAR A SIGN A617	
		• 10656 ⟩ a302, 10638 𐙸 ab067	
10713	𐜓	LINEAR A SIGN A618	
		• 10656 ⟩ a302, 10638 𐙸 ab067	
10714	𐜔	LINEAR A SIGN A619	
		• 10656 ⟩ a302, 10638 𐙸 ab067, 10609 𝑓 ab010	
10715	𐜕	LINEAR A SIGN A620	
		• 10656 ⟩ a302, 10638 𐙸 ab067, 1060B 𐙋 ab013	
10716	𐜖	LINEAR A SIGN A621	
		• 10656 ⟩ a302, 10639 ⟱ ab069	
10717	𐜗	LINEAR A SIGN A622	
		• 10656 ⟩ a302, 1063B 𐙻 ab073	
10718	𐜘	LINEAR A SIGN A623	
		• 10656 ⟩ a302, 1063F ☺ ab078, 10606 𐙆 ab007	
10719	𐜙	LINEAR A SIGN A624	
		• 10657 𐙗 a303, 10742 ⟩ a703 d	
1071A	𐜚	LINEAR A SIGN A626	
		• 10657 𐙗 a303, 10743 ⟩ a704 e	
1071B	𐜛	LINEAR A SIGN A627	
		• 10657 𐙗 a303, 10747 ⊤ a708 k	
1071C	𐜜	LINEAR A SIGN A628	
		→ 10658 ↑ linear a sign a304	
1071D	𐜝	LINEAR A SIGN A629	
		• 10658 ↑ a304, 10602 ┼ ab003	
1071E	𐜞	LINEAR A SIGN A634	
		• 1065A 𐙚 a306, 1063B 𐙻 ab073	
1071F	𐜟	LINEAR A SIGN A637	
		• 1065B 𐙛 a307, 10655 Я a301	
10720	𐜠	LINEAR A SIGN A638	
		• 1065B 𐙛 a307, 1065B 𐙛 a307	
10721	𐜡	LINEAR A SIGN A640	
		• 10668 𐙨 a316, 10638 𐙸 ab067	
10722	𐜢	LINEAR A SIGN A642	
		→ 1066A 𐙪 linear a sign a318	
10723	𐜣	LINEAR A SIGN A643	
		• 10676 𐙶 a330, 10600 ⊢ ab001	
10724	𐜤	LINEAR A SIGN A644	
		• 10676 𐙶 a330, 1061E Υ ab031	
10725	𐜥	LINEAR A SIGN A645	
		• 1067D 𐙽 a337, 10653 ⊞ ab188	
10726	𐜦	LINEAR A SIGN A646	
		• 10681 𐚁 a341, 10622 𐙢 ab039	

Complex signs with vase shapes

10727	𐜧	LINEAR A SIGN A648	
		• 106A0 𐚠 a400-vas, 1062D ⟩ ab053	
10728	𐜨	LINEAR A SIGN A649	
		→ 106A1 𐚡 linear a sign a401-vas	
10729	𐜩	LINEAR A SIGN A651	
		• 106A1 𐚡 a401-vas, 10618 𐙘 ab026	
1072A	𐜪	LINEAR A SIGN A652	
		• 106A1 𐚡 a401-vas, 10634 ⟂ ab060	
1072B	𐜫	LINEAR A SIGN A653	
		• 106A1 𐚡 a401-vas, 10658 ↑ a304	
1072C	𐜬	LINEAR A SIGN A654	
		• 106A4 𐚤 a404-vas, 10607 𐙇 ab008	
1072D	𐜭	LINEAR A SIGN A655	
		• 106A5 𐚥 a405-vas, 10750 ⟩ a713 omega	

1072E ⊕ LINEAR A SIGN A656
• 106A6 ⊖ a406-vas, 10625 ✳ ab044
1072F ⊔ LINEAR A SIGN A657
• 106A7 ⊔ a407-vas, 10607 ⊤ ab008
10730 ⊗ LINEAR A SIGN A658
• 106AC ⊗ a412-vas, 10743 ⟩ a704 e
10731 ⊗ LINEAR A SIGN A659
• 106AC ⊗ a412-vas, 10744 ⟩ a705 f
10732 ⊽ LINEAR A SIGN A660
• 106AD ⊽ a413-vas, 10632 ⊏ ab058
10733 ⊽ LINEAR A SIGN A661
→ 106AE ⊽ linear a sign a414-vas
10734 ⊕ LINEAR A SIGN A662
• 106AE ⊽ a414-vas, 10744 ⟩ a705 f
10735 ⊠ LINEAR A SIGN A663
• 106B1 ⊠ a417-vas, 10749 ⊏ a709-2 l2
10736 ⋋ LINEAR A SIGN A664
• 106B2 ⋋ a418-vas, 10749 ⊏ a709-2 l2

Fractions and compound fractions

10740 ‡ LINEAR A SIGN A701 A
• possibly one sixth (value uncertain)
→ 29E7 ‡ thermodynamic
10741 ╪ LINEAR A SIGN A702 B
• one third
10742 ⟩ LINEAR A SIGN A703 D
• one fifth
10743 ⟩ LINEAR A SIGN A704 E
• one quarter
10744 ⟩ LINEAR A SIGN A705 F
• one eighth
10745 ⋋ LINEAR A SIGN A706 H
• possibly one sixth (value uncertain)
10746 ∠ LINEAR A SIGN A707 J
• one half
10747 ⊤ LINEAR A SIGN A708 K
• one sixteenth
→ 1013C ⊤ aegean dry measure first subunit
10748 ⊏ LINEAR A SIGN A709 L
10749 ⊏ LINEAR A SIGN A709-2 L2
1074A ⊏ LINEAR A SIGN A709-3 L3
1074B ⊏ LINEAR A SIGN A709-4 L4
1074C ⊏ LINEAR A SIGN A709-6 L6
• used with 10655 я linear a sign a301
1074D ╫ LINEAR A SIGN A710 W
1074E ╫ LINEAR A SIGN A711 X
→ 10139 # aegean weight second subunit
1074F ⊳ LINEAR A SIGN A712 Y
→ 16B9 ⊳ runic letter wunjo wynn w
10750 ⊳ LINEAR A SIGN A713 OMEGA
• used with 106A5 ⊽ linear a sign a405-vas
10751 ‡ LINEAR A SIGN A714 ABB
10752 ++ LINEAR A SIGN A715 BB
10753 ⟩ LINEAR A SIGN A717 DD
10754 ⟨ΡΡΡ LINEAR A SIGN A726 EYYY
10755 ⟩ LINEAR A SIGN A732 JE
• three quarters

Additional signs

10760 ⊻ LINEAR A SIGN A800
• 10603 ⊻ ab004, 10607 ⊤ ab008
10761 ⊞ LINEAR A SIGN A801
• 1062E ⊞ ab054, 10608 ⊔ ab009

10762 ⊿ LINEAR A SIGN A802
→ 10634 ⊂ linear a sign ab060
10763 ⊞ LINEAR A SIGN A803
• 1064D ⊞ ab131a, 10762 ⊿ a802
10764 ⊱ LINEAR A SIGN A804
• 10652 ⊱ ab180, 1061E Y ab031
10765 я LINEAR A SIGN A805
→ 10655 я linear a sign a301
10766 ⊱ LINEAR A SIGN A806
• 10668 ⊱ a316, 10601 ╪ ab002
10767 ⊱ LINEAR A SIGN A807
• 10668 ⊱ a316, 10742 ⟩ a703 d