Products: InFocus IN102, & IN104

Title: IR Codes & Documentation

Introduction:

IR (infrared) light can be used to send commands to and retrieve status information from many consumer devices. IR communication can be used for two-way data communication (mostly between computers and PDAs), though most display devices, including projectors, are configured to receive commands only. Commonly the IR capability of projectors is used in conjunction with the factory-provided remote control. However, if there are multiple devices that need control, you may wish to use a universal or learning remote.

Many universal remote controls can only control devices that the remote manufacturer has included in their table of pre-programmed codes. These types of universal remote controls aren't usually capable of controlling projectors and other less common equipment. A universal remote with a "Learning" function is suitable for use with projectors and other unique components (game consoles, media PCs & extenders, curtain/lighting controls, etc.). Many other programmable remotes are also able to work with projectors and other equipment.

If you need help setting up your universal "Learning" remote, please refer to the universal remote manufacturer's documentation.

The directions below are intended to help you set up a programmable remote, using the codes for your InFocus projector.

Configuration:

- InFocus projectors use the NEC IR protocol.
- The customer code portion of the IR packet should use the hexadecimal value: 0x83F4
- Please note that the letter O is not used in hexadecimal, only zeros are used.

Supported Commands:

The following table lists all of the currently designated infrared key codes.

Key Name	Description	Hex Code
Menu	Toggles menu state up or down	0Fh
Source Select	Selects next available source	04h
Cursor Left	Moves menu cursor left	0Dh
Cursor Right	Moves menu cursor right	0Eh
Cursor Up	Moves menu cursor up	0Bh
Cursor Down	Moves menu cursor down	0Ch
Power	Toggles power state on or off	02h
Zoom Plus	Increases zoom ratio	18h
Zoom Minus	Decreases zoom ratio	19h
Preset Mode/Enter	Toggles through available presets or used as the "Enter" function key for menu options	10h
Blank	Toggles state of blank screen on or off	07h
Auto	Auto activates automatic image adjust	08h
Freeze/Unfreeze	Toggle State of Screen Image Freeze	03h