

Smart Solar Tracking System Complete Report

Project Report

Submitted By

- Mani
 - Larshitha
 - Rishitha
-

ABSTRACT

Solar energy is one of the most important renewable energy resources available today. However, traditional fixed solar panels are unable to continuously align themselves with the direction of sunlight throughout the day, which reduces energy harvesting efficiency. To overcome this limitation, a Smart Solar Tracking System is developed using Arduino UNO, LDR sensors, and a servo motor.

The system automatically detects the direction of maximum sunlight intensity and rotates the solar panel accordingly. This improves the efficiency of the solar panel compared to fixed-position panels. The project demonstrates the principles of embedded systems, automation, feedback control, sensor interfacing, and actuator control.

The proposed system is cost-effective, simple to implement, and suitable for educational and small-scale renewable energy applications.

TABLE OF CONTENTS

1. Introduction
2. Literature Review
3. Objectives
4. Components Used and Specifications
5. Working Principle
6. System Design
7. Circuit Diagram and Connections
8. Algorithm and Control Logic
9. Testing and Validation
10. Results and Discussion

11. Advantages and Limitations
 12. Applications
 13. Future Scope
 14. Conclusion
 15. References
-

1. INTRODUCTION

Solar energy is one of the most abundant and sustainable energy resources available today. As the demand for renewable energy increases, solar technology continues to play a crucial role in clean-energy solutions.

Traditional fixed solar panels face a major limitation because they remain stationary and cannot follow the movement of the sun across the sky. Due to this, sunlight does not strike the panel perpendicularly throughout the day, especially during morning and evening hours. This results in reduced energy generation.

A solar tracking system solves this problem by automatically adjusting the position of the solar panel according to the direction of sunlight. By continuously aligning the panel toward maximum sunlight intensity, more solar energy can be captured.

This project presents a Smart Solar Tracking System using Arduino UNO, Light Dependent Resistors (LDRs), and a servo motor. The LDR sensors detect the sunlight intensity while the Arduino processes the sensor data and controls the movement of the servo motor.

The project also demonstrates concepts such as:

- Embedded systems
 - Automation
 - Feedback control systems
 - Sensor interfacing
 - PWM motor control
 - Renewable energy optimization
-

2. LITERATURE REVIEW

Solar tracking systems have been widely researched because they can improve solar panel efficiency by approximately 20–40% compared to fixed solar panels.

There are mainly two types of solar tracking systems:

2.1 Single-Axis Solar Tracking System

Single-axis trackers rotate the solar panel along one axis, usually East-West. These systems are simpler, cheaper, and consume less power.

2.2 Dual-Axis Solar Tracking System

Dual-axis trackers rotate the panel in both East-West and North-South directions. These systems provide more accurate alignment but require additional motors and complex control systems.

LDR sensors are commonly used in low-cost solar tracking systems because they are inexpensive and highly sensitive to visible light. By comparing the light intensity detected by multiple LDRs, the direction of maximum sunlight can be determined.

Microcontrollers such as Arduino are widely preferred in educational and prototype-based projects because of their ease of programming, low cost, and availability of open-source libraries.

Several studies also emphasize the importance of control algorithms such as proportional or PID-based control for improving tracking accuracy and reducing unwanted oscillations.

3. OBJECTIVES

The main objectives of the project are:

- To design a low-cost solar tracking prototype.
 - To improve solar energy harvesting efficiency.
 - To study the behavior of LDR sensors under varying light conditions.
 - To implement automatic solar tracking using Arduino.
 - To control the movement of the solar panel using a servo motor.
 - To compare the performance of tracking and fixed solar panels.
 - To understand practical engineering challenges such as sensor noise and actuator response.
-

4. COMPONENTS USED AND SPECIFICATIONS

4.1 Arduino UNO

Arduino UNO is a microcontroller board based on the ATmega328P.

Specifications:

- Operating Voltage: 5V
- Digital I/O Pins: 14
- Analog Input Pins: 6
- Clock Speed: 16 MHz
- USB Interface for Programming

Function:

The Arduino reads the sensor values from the LDRs and controls the servo motor based on the detected light intensity.

4.2 Solar Panel

A small photovoltaic solar panel is used for demonstration purposes.

Function:

The solar panel converts sunlight into electrical energy.

4.3 LDR Sensors

Light Dependent Resistors change their resistance depending on the intensity of light falling on them.

Function:

Two LDR sensors are used to detect the direction of sunlight.

4.4 Servo Motor (SG90)

The SG90 servo motor provides controlled rotational movement.

Specifications:

- Operating Voltage: 4.8V–6V
- Rotation Angle: 0°–180°
- PWM Controlled

Function:

The servo motor rotates the solar panel toward the direction of maximum sunlight.

4.5 Breadboard and Jumper Wires

Used for making temporary electrical connections between components.

4.6 Resistors

Resistors are used with LDRs to create voltage divider circuits.

4.7 Mounting Frame

A lightweight frame supports the solar panel and allows smooth rotation.

5. WORKING PRINCIPLE

The Smart Solar Tracking System works based on the intensity of sunlight detected by two LDR sensors.

Step 1: Sunlight Detection

The two LDR sensors continuously measure sunlight intensity.

Step 2: Signal Processing

The Arduino compares the values from both LDR sensors.

Step 3: Direction Determination

- If the left LDR detects more light, the panel rotates toward the left.
- If the right LDR detects more light, the panel rotates toward the right.
- If both sensors receive equal light, the panel stops moving.

Step 4: Panel Alignment

The servo motor rotates the solar panel toward the direction of maximum sunlight.

Step 5: Continuous Feedback

The process repeats continuously throughout the day.

6. SYSTEM DESIGN

6.1 Conceptual Design

The system follows a closed-loop feedback mechanism.

Closed-Loop Process:

1. Sensors detect sunlight.
 2. Arduino processes sensor readings.
 3. Servo motor receives control signal.
 4. Solar panel rotates.
 5. Feedback continues until proper alignment is achieved.
-

6.2 Mechanical Design

The solar panel is mounted on a lightweight cardboard or wooden frame. The servo motor is fixed at the base of the structure to allow rotational movement.

The two LDR sensors are placed at slightly different angles with a small barrier between them. This creates differential light readings.

6.3 Electrical Design

The LDRs are connected in voltage divider configurations and interfaced with Arduino analog input pins.

The servo motor receives PWM signals from the Arduino digital output pin.

7. CIRCUIT DIAGRAM AND CONNECTIONS

7.1 Pin Connections

Component	Arduino Pin
LDR1 Output	A0
LDR2 Output	A1
Servo GND	GND
Servo Signal Pin	D9
Servo VCC	5V

7.2 Circuit Description

- Two LDR sensors are connected as voltage dividers.
- Analog voltages from the LDRs are given to Arduino analog pins A0 and A1.
- The servo motor signal pin is connected to digital PWM pin D9.
- The Arduino compares the LDR readings and generates servo control signals.

8. ALGORITHM AND CONTROL LOGIC

8.1 Control Logic

The system continuously reads the sensor values and compares them.

Algorithm:

1. Read LDR1 and LDR2 values.
2. Calculate the difference between the readings.
3. If the difference exceeds a threshold:
 - Rotate left or right.
4. Else:
 - Keep the panel stationary.
5. Repeat continuously.

8.2 Threshold Filtering

A small threshold value is used to prevent unnecessary small movements caused by sensor noise.

8.3 PID-Based Concept

PID-inspired feedback concepts are used to improve system stability.

PID Functions:

- **Proportional Control (P)**
Corrects immediate alignment error.
- **Integral Control (I)**
Reduces accumulated steady-state error.
- **Derivative Control (D)**

Reduces overshoot and improves stability.

The PID control equation is:

$$u(t) = K_p e(t) + K_i \int e(t)dt + K_d de(t)/dt$$

9. TESTING AND VALIDATION

The system was tested under different environmental conditions.

9.1 Functional Testing

- Verified LDR response.
 - Tested servo movement.
 - Checked automatic tracking operation.
 - Validated stable panel rotation.
-

9.2 Performance Testing

The system was tested during different times of the day.

Observations:

- Improved sunlight alignment.
 - Better panel orientation.
 - Increased output voltage.
-

9.3 Stress Testing

The system was operated continuously for several hours.

Results:

- Stable servo operation.
- Reliable sensor readings.
- Consistent performance.

9.4 Debugging and Issue Resolution

Problems Faced:

- Sensor noise
- Servo jitter
- Loose wiring connections
- Unstable readings

Solutions Implemented:

- Applied threshold filtering
 - Improved wiring stability
 - Calibrated servo angles
 - Stabilized power supply
-

10. RESULTS AND DISCUSSION

The Smart Solar Tracking System successfully tracked sunlight and aligned the solar panel accordingly.

The tracking panel produced higher voltage output compared to a fixed solar panel, especially during morning and evening hours.

Time	Fixed Panel Voltage	Tracking Panel Voltage
9:00 AM	4.2 V	5.7 V
10:00 AM	5.1 V	6.1 V
12:00 PM	6.1 V	6.4 V
2:00 PM	5.3 V	6.0 V
4:00 PM	3.8 V	5.1 V

The results indicate that the solar tracking system captured more sunlight and generated better output compared to the fixed solar panel configuration.

The system demonstrated:

- Smooth panel movement
- Accurate sunlight detection
- Improved energy efficiency
- Stable operation under natural sunlight conditions

Threshold-based filtering helped reduce sensor noise and unnecessary servo movements, improving overall system stability and tracking accuracy.

Minor vibrations were observed during windy conditions. however, the mechanical structure remained functional and reliable throughout testing.

11. ADVANTAGES AND LIMITATIONS

11.1 Advantages

- Improves solar energy efficiency
 - Low-cost implementation
 - Simple design
 - Easy to program
 - Educational value
-

11.2 Limitations

- Limited tracking range
 - Servo motor load limitations
 - Sensitivity to weather conditions
 - Small-scale prototype only
-

12. APPLICATIONS

The Smart Solar Tracking System can be used in several renewable energy and automation applications.

12.1 Solar Power Plants

Large-scale solar farms can use tracking systems to improve energy generation efficiency.

12.2 Street Lighting Systems

Automatic solar tracking can improve the charging efficiency of solar-powered street lights.

12.3 Rural Electrification

The project can help improve solar energy utilization in rural and remote areas where power availability is limited.

12.4 Educational Projects

The system is highly useful for learning:

- Embedded systems
 - Arduino programming
 - Sensor interfacing
 - Servo motor control
 - Renewable energy systems
-

12.5 Smart Renewable Energy Systems

The project can be integrated with smart energy monitoring systems and IoT platforms.

13. FUTURE SCOPE

The Smart Solar Tracking System can be further enhanced using advanced technologies.

13.1 Dual-Axis Tracking

The current system mainly performs single-axis tracking. By adding another servo motor, the system can be upgraded to dual-axis tracking for improved sunlight alignment.

13.2 IoT-Based Monitoring

The system can be connected to cloud platforms using Wi-Fi modules such as ESP8266 or ESP32.

This enables:

- Remote monitoring
 - Live performance analysis
 - Mobile application control
 - Data storage
-

13.3 Automatic Battery Management

Battery charging and energy storage systems can be integrated for efficient power management.

13.4 Weather Prediction Integration

The system can use weather forecasting data to optimize tracking movement and reduce unnecessary power consumption.

13.5 AI-Based Optimization

Machine learning algorithms can be used to predict sunlight intensity patterns and optimize tracking performance.

13.6 Industrial Applications

The project can be scaled for industrial solar farms with stronger motors and larger panels.

14. ADVANTAGES AND LIMITATIONS

14.1 Advantages

Improved Energy Efficiency

The tracking system captures more sunlight compared to fixed solar panels.

Cost-Effective Design

The system uses low-cost components such as Arduino and LDR sensors.

Automatic Operation

No manual intervention is required during operation.

Educational Value

The project demonstrates embedded systems, automation, and renewable energy concepts.

Easy Maintenance

The system is simple to troubleshoot and maintain.

14.2 Limitations

Limited Tracking Range

The prototype supports limited rotational movement.

Environmental Dependency

Cloudy weather and shadows may affect tracking accuracy.

Servo Motor Constraints

Small servo motors cannot support heavy solar panels.

Prototype Scale

The project is suitable mainly for educational and small-scale applications.

15. CONCLUSION

The Smart Solar Tracking System successfully demonstrates automatic sunlight tracking using Arduino UNO, LDR sensors, and a servo motor.

The system continuously aligns the solar panel toward maximum sunlight intensity, improving solar energy harvesting efficiency compared to fixed-position panels.

The project also demonstrates important engineering concepts such as:

- Embedded systems
- Automation
- Feedback control systems
- Sensor interfacing
- PWM motor control
- Renewable energy optimization

The project provides a low-cost and practical solution for small-scale solar tracking applications.

It also serves as a strong foundation for future developments such as:

- Dual-axis solar tracking

- PID-based advanced control
- IoT integration
- Smart energy management systems

Overall, the project successfully combines electronics, programming, mechanical design, and renewable energy concepts into a functional engineering prototype.

16. REFERENCES

P. S. Paliyal et al.,

“Automatic Solar Tracking System: A Review Pertaining to Its Advancements and Challenges,”

Oxford Academic, 2024.

[Oxford Academic Solar Tracking Review](#)

Reviews modern solar tracking systems and compares efficiency improvements over fixed panels.

H. Shang et al.,

“Design and Implementation of a Dual-Axis Solar Tracking System,”

MDPI Energies, 2023.

[MDPI Dual Axis Solar Tracking Paper](#)

Presents a practical dual-axis tracking system with improved solar energy collection efficiency.

E. K. Mpodi et al.,

“Review of Dual Axis Solar Tracking and Development of Its Functional Model,”

ScienceDirect, 2019.

[Dual Axis Solar Tracking Review Paper](#)

Reviews efficiency improvements and functional models of dual-axis solar trackers.

[pratz222 Dual Axis Solar Tracker using Arduino](#)

Practical dual-axis tracking using LDRs and servo motors.

[abelzk Dual Axis Solar Tracker Arduino](#)

Complete Arduino-based implementation for automatic dual-axis tracking.

[Tinker Twins Dual Axis Solar Tracker](#)

Uses 4 LDR sensors and 2 servo motors for dual-axis solar tracking.

[Arduino Dual Axis Solar Tracker ProjectHub](#)

Complete Arduino project with code and hardware setup.

THANK YOU