

This document provides additional assistance with wiring your Extron IP Link® Pro Series enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link® Pro Series enabled product or the controlled device manufacturer supplied documentation.

Device Specifications

Device Type: Scaler
Manufacturer: Extron
Firmware Version: 1.00
Model(s): DSC 12G-HD A

Tested on the Following Software and Firmware Versions

GC (Plus, Pro) Version	3.33.0.38
IP Link Pro Control Processor Firmware	3.18.0001-b002
IP Link Pro Control Processor Q xi Firmware	1.13.0001-b001
IP Link Pro Control Processor xi Firmware	1.13.0001-b001
MediaLink Plus Controller Firmware	3.04.0000-b001
HC 400 Series Firmware	2.11.0002-b002
TLP Pro x25 and TLC Pro x26 Series Firmware	3.13.0000-b008
TLP Pro 300M Firmware	1.08.0000-b008

Version History

Driver Version	Date	Notes
1_0_0	8/19/2026	Initial Version. Extron certified. Tested on DSC 12G-HD A.

Driver Notes

- User Defined command takes a string parameter and sends the string out of the port.

Driver Timings

- Recommended repeat rate for this driver is .1 seconds.

Control Commands & States

Aspect Ratio			
Value	Fill	Follow	
Audio Format			
Value	None	Analog	LPCM-2Ch
	Multi-Ch		
Audio Mute			
Output	Analog	Digital	
Value	On	Off	
Auto Image			
Value	Execute	Execute and Fill	Execute and Follow
Executive Mode			
Value	On	Off	
Film Mode Detection			
Value	On	Off	
Freeze			
Value	On	Off	
Global Audio Mute			
Value	On	Off	
Input Gain			
Value	-18 to 24 in steps of 1 dB		
Input Preset Recall			
Value	1 – 128		
Input Preset Save			
Value	1 – 128		

Logo			
Value	1 – 16 Off	Screen Saver	HDCP
Logo Assignment			
Logo	1 – 16	Screen Saver	HDCP
Value	String		
Logo Key Setting			
Logo	1 – 16	Screen Saver	HDCP
Value	Disabled Level Key	Transparency Alpha Key	RGB Key

Output Resolution			
Value	720p (25Hz)	720p (29.97Hz)	720p (30Hz)
	720p (50Hz)	720p (59.94Hz)	720p (60Hz)
	1080i (50Hz)	1080i (59.94Hz)	1080i (60Hz)
	1080p (23.98Hz)	1080p (24Hz)	1080p (25Hz)
	1080p (29.97Hz)	1080p (30Hz)	1080p (50Hz)
	1080p (59.94Hz)	1080p (60Hz)	2048x1080 (23.98Hz)
	2048x1080 (24Hz)	2048x1080 (25Hz)	2048x1080 (29.97Hz)
	2048x1080 (30Hz)	2048x1080 (50Hz)	2048x1080 (59.94Hz)
	2048x1080 (60Hz)	3480x2160 (23.98Hz)	3480x2160 (24Hz)
	3480x2160 (25Hz)	3480x2160 (29.97Hz)	3480x2160 (30Hz)
	3480x2160 (50Hz)	3480x2160 (59.94Hz)	3480x2160 (60Hz)
	4096x2160 (23.98Hz)	4096x2160 (24Hz)	4096x2160 (25Hz)
	4096x2160 (29.97Hz)	4096x2160 (30Hz)	4096x2160 (50Hz)
	4096x2160 (59.94Hz)	4096x2160 (60Hz)	Custom Rate 1
	Custom Rate 2	Custom Rate 3	640x480 (60Hz)
	800x600 (60Hz)	1024x768 (60Hz)	1280x768 (60Hz)
	1280x800 (60Hz)	1280x1024 (60Hz)	1360x768 (60Hz)
	1366x768 (60Hz)	1440x900 (60Hz)	1400x1050 (60Hz)
	1600x900 (60Hz)	1680x1050 (60Hz)	1600x1200 (60Hz)
	1920x1200 (60Hz)	480p (59.94Hz)	480p (60Hz)
	576p (50Hz)	2048x1200 (60Hz)	2048x1536 (60Hz)
	2560x1080 (60Hz)	2560x1440 (60Hz)	2560x1600 (60Hz)
	3840x2160 (60Hz)	Custom Rate 4	Custom Rate 5
Power Save Mode			
Value	On	Off	
Test Pattern			
Value	Off	Crop	Alternating Pixels
	Crosshatch	Color Bars	32-level split Grayscale
	Audio Test		
User Defined Command			
Value	None		

User Defined String	
Value	String
Video Mute	
Value	On On with Sync Off
Volume	
Value	-100 to 0 in steps of 1 dB

Status Available

Aspect Ratio			
Value	Fill	Follow	
Audio Format			
Value	None	Analog	LPCM-2Ch
	Multi-Ch		
Audio Mute			
Output	Analog	Digital	
Value	On	Off	
Connection Status ^{RP}			
Value	Connected	Disconnected	
Executive Mode			
Value	On	Off	
Film Mode Detection			
Value	On	Off	
Firmware			
Value	String		
Freeze			
Value	On	Off	
Input Gain			
Value	-18 to 24 in steps of 1 dB		
Input Signal Status			
Value	Active	Not Active	
Logo			
Value	1 – 16	Screen Saver	HDCP
	Off		
Logo Assignment			
Logo	1 – 16	Screen Saver	HDCP
Value	String		

Logo Availability			
Logo	1 – 16	Screen Saver	HDCP
Value	Saved	Empty	
Logo Key Setting			
Logo	1 – 16	Screen Saver	HDCP
Value	Disabled	Transparency	RGB Key
	Level Key	Alpha Key	
MAC Address			
Value	String		
Model Name			
Value	String		

Output Resolution			
Value	720p (25Hz)	720p (29.97Hz)	720p (30Hz)
	720p (50Hz)	720p (59.94Hz)	720p (60Hz)
	1080i (50Hz)	1080i (59.94Hz)	1080i (60Hz)
	1080p (23.98Hz)	1080p (24Hz)	1080p (25Hz)
	1080p (29.97Hz)	1080p (30Hz)	1080p (50Hz)
	1080p (59.94Hz)	1080p (60Hz)	2048x1080 (23.98Hz)
	2048x1080 (24Hz)	2048x1080 (25Hz)	2048x1080 (29.97Hz)
	2048x1080 (30Hz)	2048x1080 (50Hz)	2048x1080 (59.94Hz)
	2048x1080 (60Hz)	3480x2160 (23.98Hz)	3480x2160 (24Hz)
	3480x2160 (25Hz)	3480x2160 (29.97Hz)	3480x2160 (30Hz)
	3480x2160 (50Hz)	3480x2160 (59.94Hz)	3480x2160 (60Hz)
	4096x2160 (23.98Hz)	4096x2160 (24Hz)	4096x2160 (25Hz)
	4096x2160 (29.97Hz)	4096x2160 (30Hz)	4096x2160 (50Hz)
	4096x2160 (59.94Hz)	4096x2160 (60Hz)	Custom Rate 1
	Custom Rate 2	Custom Rate 3	640x480 (60Hz)
	800x600 (60Hz)	1024x768 (60Hz)	1280x768 (60Hz)
	1280x800 (60Hz)	1280x1024 (60Hz)	1360x768 (60Hz)
	1366x768 (60Hz)	1440x900 (60Hz)	1400x1050 (60Hz)
	1600x900 (60Hz)	1680x1050 (60Hz)	1600x1200 (60Hz)
	1920x1200 (60Hz)	480p (59.94Hz)	480p (60Hz)
	576p (50Hz)	2048x1200 (60Hz)	2048x1536 (60Hz)
	2560x1080 (60Hz)	2560x1440 (60Hz)	2560x1600 (60Hz)
	3840x2160 (60Hz)	Custom Rate 4	Custom Rate 5
	Part Number		
Value	String		
Power Save Mode			
Value	On	Off	
Screen Saver Status			
Value	Active Input Detected; Timer not running	No Active Input; Timer expired; Output sync disabled	No Active Input; Timer running; Output sync enabled

Serial Number			
Value	String		
Temperature			
Value	Number		
Test Pattern			
Value	Off	Crop	Alternating Pixels
	Crosshatch	Color Bars	32-level split Grayscale
	Audio Test		
User Defined String			
Value	String		
Video Mute			
Value	On	On with Sync	Off
Volume			
Value	-100 to 0 in steps of 1 dB		

^{RP} Connection Status is based off of the following string: X

Network communication

When configuring the Ethernet driver, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet (SSH)
Default Port:	22023
Logon Credentials Supported:	Yes
Default Username:	admin
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Driver Configuration Description

Please refer to user manual for settings and changes to the network communication.

Notes for the Device