

This document provides additional assistance with wiring your Extron IP Link® Pro Series enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link® Pro Series enabled product or the controlled device manufacturer supplied documentation.

Device Specifications

Device Type: Matrix Switcher
Manufacturer: Extron
Firmware Version: 1.02.0000-b001
Model(s): DTP3 CrossPoint 42, DTP3 CrossPoint 42 USB

Tested on the Following Software and Firmware Versions

GC (Plus, Pro) Version	3.33.0.38
IP Link Pro Control Processor Firmware	3.18.0001-b002
IP Link Pro Control Processor xi Firmware	1.13.0001-b001
IP Link Pro Control Processor Q xi Firmware	1.13.0001-b001
MediaLink Plus Controller Firmware	3.04.0000-b001
HC 400 Series Firmware	2.11.0002-b002
TLP Pro x25 and TLC Pro x26 Series Firmware	3.13.0002-b001
TLP Pro 300M Firmware	1.08.0000-b008

Version History

Driver Version	Date	Notes
1_3_0	7/7/2026	Extron Certified. Added polling to USB Input Signal Status. Removed unsupported Global USB Device Port, USB Device Port, and USB Output Signal Status. Tested on DTP3 CrossPoint 42 USB running firmware version 1.02.0000-b001.
1_2_0	6/22/2026	Extron Certified. Added support for audio-only output 3. Removed unsupported Video tie type. Added Mode 2 to Executive Mode.

		Removed unsupported HDCP Input Status and HDCP Output Status. Tested on DTP3 CrossPoint 42 USB.
1_1_0	6/8/2026	Extron Certified. Added USB Input command. Removed unsupported 6 from USB Device Port. Tested on DTP3 CrossPoint 42 USB.
1_0_1	4/27/2026	Extron Certified. Added model DTP3 CrossPoint 42 USB and Volume command.
1_0_0	4/16/2026	Initial Version. Extron certified. Tested on DTP3 CrossPoint 42.

Driver Notes

- User Defined command takes a string parameter and sends the string out of the port.

Driver Timings

- Recommended repeat rate for this driver is .1 seconds.

Control Commands & States

Audio Mute			
Output	1 – 3		
Value	On	Off	
Auto Image			
Output	1 – 2		
Value	Execute	Execute and Fill	Execute and Follow
Executive Mode			
Value	Off	Mode 1	Mode 2
Freeze			
Output	1 – 2		
Value	On	Off	
Global Video Mute			
Value	Video	Video & Sync	Off
HDCP Input Authorization			
Input	1 – 4		
Value	On	Off	
Logo			
Output	1 – 2		
Value	1 – 16	Off	
Matrix IO Name Command			
Type	Input	Output	
Value	None		
Matrix IO Name String			
Value	String		
Matrix IO Number Select			
Value	1 – 4		

Matrix Tie Command ²			
Input	0 – 4		
Output	1 – 3	All	
Tie Type	Audio ³	Audio/Video ⁴	
Value	None		
Output Resolution			
Output	1 – 2		
Value	640x480 (60Hz)	800x600 (60Hz)	1024x768 (60Hz)
	1280x768 (60Hz)	1280x800 (60Hz)	1280x1024 (60Hz)
	1360x768 (60Hz)	1366x768 (60Hz)	1440x900 (60Hz)
	1400x1050 (60Hz)	1600x900 (60Hz)	1680x1050 (60Hz)
	1600x1200 (60Hz)	1920x1200 (60Hz)	480p (59.94Hz)
	480p (60Hz)	576p (50Hz)	720p (25Hz)
	720p (29.97Hz)	720p (30Hz)	720p (50Hz)
	720p (59.94Hz)	720p (60Hz)	1080i (50Hz)
	1080i (59.94Hz)	1080i (60Hz)	1080p (23.98Hz)
	1080p (24Hz)	1080p (25Hz)	1080p (29.97Hz)
	1080p (30Hz)	1080p (50Hz)	1080p (59.94Hz)
	1080p (60Hz)	2048x1080 (23.98Hz)	2048x1080 (24Hz)
	2048x1080 (25Hz)	2048x1080 (29.97Hz)	2048x1080 (30Hz)
	2048x1080 (50Hz)	2048x1080 (59.94Hz)	2048x1080 (60Hz)
	2048x1200 (60Hz)	2048x1536 (60Hz)	2560x1080 (60Hz)
	2560x1440 (60Hz)	2560x1600 (60Hz)	3840x2160 (23.98Hz)
	3840x2160 (24Hz)	3840x2160 (25Hz)	3840x2160 (29.97Hz)
	3840x2160 (30Hz)	3840x2160 (50Hz)	3840x2160 (59.94Hz)
	3840x2160 (60Hz)	4096x2160 (23.98Hz)	4096x2160 (24Hz)
	4096x2160 (25Hz)	4096x2160 (29.97Hz)	4096x2160 (30Hz)
	4096x2160 (50Hz)	4096x2160 (59.94Hz)	4096x2160 (60Hz)
	Custom 1	Custom 2	Custom 3
	Custom 4		
Power Save Mode			
Value	Off	Mode 1	Mode 2

Preset Recall			
Value	1 – 16		
Refresh Matrix			
Value	None		
Refresh Matrix IO Names			
Value	None		
USB Input ¹			
Value	0 – 3		
User Defined Command			
Value	None		
User Defined String			
Value	String		
Video Mute			
Output	1 – 2		
Value	Video	Video & Sync	Off
Volume			
Value	-100 to 0 in steps of 1 dB		

¹ Only available for DTP3 CrossPoint 42 USB.

² For tie combinations of Input: 0 – 4 and Output: 1 – 3, the configured Tie Type should match the Output. For example, Output: 1 – 2 must be paired with Tie Type: Audio/Video. Output: 3 must be paired with Tie Type: Audio. Mismatches are not supported. Please note, it is not possible for breakaway audio.

³ When using Tie Type: Audio, Output: All is supported, but both ties and breaks only affect Output: 3.

⁴ When using Tie Type: Audio/Video, Output: All is supported, and both ties and breaks affect Output: 1 – 3, where Output: 3 is audio-only.

Status Available

Audio Mute			
Output	1 – 3		
Value	On	Off	
Connection Status ^{RP}			
Value	Connected	Disconnected	
Executive Mode			
Value	Off	Mode 1	Mode 2
Firmware			
Value	String		
Freeze			
Output	1 – 2		
Value	On	Off	
HDCP Input Authorization			
Input	1 – 4		
Value	On	Off	
Input Signal Status			
Input	1 – 4		
Value	Active	Not Active	
Input Tie Status			
Input	1 – 4		
Output	1 – 3		
Value	Audio	Audio/Video	Untied
Logo			
Output	1 – 2		
Value	1 – 16	Off	
MAC Address			
Value	String		

Matrix IO Name Status	
Type	Input Output
Number	1 – 4
Value	String
Matrix IO Name String	
Value	String
Matrix IO Number Select	
Value	1 – 4

Output Resolution			
Output	1 – 2		
Value	640x480 (60Hz)	800x600 (60Hz)	1024x768 (60Hz)
	1280x768 (60Hz)	1280x800 (60Hz)	1280x1024 (60Hz)
	1360x768 (60Hz)	1366x768 (60Hz)	1440x900 (60Hz)
	1400x1050 (60Hz)	1600x900 (60Hz)	1680x1050 (60Hz)
	1600x1200 (60Hz)	1920x1200 (60Hz)	480p (59.94Hz)
	480p (60Hz)	576p (50Hz)	720p (25Hz)
	720p (29.97Hz)	720p (30Hz)	720p (50Hz)
	720p (59.94Hz)	720p (60Hz)	1080i (50Hz)
	1080i (59.94Hz)	1080i (60Hz)	1080p (23.98Hz)
	1080p (24Hz)	1080p (25Hz)	1080p (29.97Hz)
	1080p (30Hz)	1080p (50Hz)	1080p (59.94Hz)
	1080p (60Hz)	2048x1080 (23.98Hz)	2048x1080 (24Hz)
	2048x1080 (25Hz)	2048x1080 (29.97Hz)	2048x1080 (30Hz)
	2048x1080 (50Hz)	2048x1080 (59.94Hz)	2048x1080 (60Hz)
	2048x1200 (60Hz)	2048x1536 (60Hz)	2560x1080 (60Hz)
	2560x1440 (60Hz)	2560x1600 (60Hz)	3840x2160 (23.98Hz)
	3840x2160 (24Hz)	3840x2160 (25Hz)	3840x2160 (29.97Hz)
	3840x2160 (30Hz)	3840x2160 (50Hz)	3840x2160 (59.94Hz)
	3840x2160 (60Hz)	4096x2160 (23.98Hz)	4096x2160 (24Hz)
	4096x2160 (25Hz)	4096x2160 (29.97Hz)	4096x2160 (30Hz)
	4096x2160 (50Hz)	4096x2160 (59.94Hz)	4096x2160 (60Hz)
	Custom 1	Custom 2	Custom 3
	Custom 4		
	Output Tie Status		
Output	1 – 3		
Tie Type	Audio	Audio/Video	
Value	0 – 4		
Output Tie Status Name			
Output	1 – 2		
Tie Type	Audio	Audio/Video	
Value	String		

Power Save Mode	
Value	Off Low Power (Over Temperature) Mode 1 Mode 2
Serial Number	
Value	String
USB Input ¹	
Value	0 – 3
USB Input Signal Status ¹	
Input Value	1 – 3 Active Not Active
User Defined String	
Value	String
Volume	
Value	-100 to 0 in steps of 1 dB

¹ Only available for DTP3 CrossPoint 42 USB.

^{RP} Connection Status is based off of the following string: X

Network communication

When configuring the Ethernet driver, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet (SSH)
Default Port:	22023
Logon Credentials Supported:	Yes
Default Username:	admin
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Driver Configuration Description

Please refer to user manual for settings and changes to the network communication.

Notes for the Device