ADAPTIVE MULTI-ZONE INTRUSION DETECTION USING HYBRID SENSOR FUSION ON ESP32

By:	VK MURALIKRISHNA ROHAN YENIGALLA
Faculty Name:	Dr. VIDHYAPATHI C.M.
Slot:	B1
Semester:	Winter Semester (2025-26)
Subject:	Embedded C Programming (BECE320E)
Affiliation:	Department of Electronics and Communication Vellore Institute of Technology Vellore, India – 632014
Date:	April 16, 2026

Contents

1 FIELD OF THE INVENTION **3**

2 BACKGROUND OF THE INVENTION **3**

2.1 Problems with the Prior Art 3

3 SUMMARY OF THE INVENTION **4**

4 BRIEF DESCRIPTION OF THE DRAWINGS **4**

5 DETAILED DESCRIPTION OF THE INVENTION **5**

5.1 Overview 5
5.2 Multi-Zone Architecture 5
5.3 Hybrid Multi-Sensor Fusion 5
5.4 Sensor Normalization 6
5.5 Cross-Verification Mechanism 6
5.6 Dynamic Threshold Adaptation 6
5.7 Temporal Validation 7
5.8 Sequential Zone Tracking 7
5.9 Sensor Confidence Weighting 7
5.10 Priority-Based Decision Logic 7
5.11 False Trigger Suppression 7
5.12 Redundancy-Based Fault Tolerance 7
5.13 State-Based System Operation 8
5.14 Real-Time Processing Loop 8
5.15 Alert Intensity Mapping 8
5.16 Software Training and Calibration 8
5.17 Permutation-Based Scenario Testing 9
5.18 Conflict Resolution and Edge Case Handling 9
5.19 Hardware Architecture 10
5.20 Sensor Interfacing 10
5.21 Wireless Communication 10
5.22 Scalability and Modularity 10
5.23 Fault Detection and Recovery Mechanism 10
5.24 Self-Diagnostic Capability 10
5.25 Secure Communication Protocol 10
5.26 Edge-Based Intelligent Processing 11
5.27 Multi-Level Alert Prioritization 11
5.28 Real-Time Data Logging and Traceability 11

5.29 Adaptive Learning Mechanism 11
5.30 Configurable Deployment Framework 12
5.31 Energy-Aware Sensor Scheduling 12
5.32 Modular Firmware Architecture 12

6 SYSTEM FLOWCHART 12

7 BLOCK DIAGRAM 13

8 HARDWARE USED 14

9 SOFTWARE USED 15

10 RESULTS AND ANALYSIS 16

11 COMPARATIVE STUDY 17

12 PROJECT TIMELINE 17

13 COST ANALYSIS 18

14 FUTURE SCOPE 19

15 CLAIMS 19

16 ABSTRACT 21

References 22

1. FIELD OF THE INVENTION

The present invention relates to an embedded real-time security system, and more particularly to an adaptive multi-zone intrusion detection system that employs a hybrid multi-sensor fusion framework executed on an ESP32 microcontroller platform. The system integrates ultrasonic sensors, infrared (IR) sensors, force sensing resistors (FSR), an inertial measurement unit (MPU6050), a sound sensor, and a light dependent resistor (LDR) to achieve high-accuracy, low-false-alarm intrusion detection across multiple independently monitored spatial zones.

2. BACKGROUND OF THE INVENTION

In recent years, various intrusion detection and security systems have been developed using different sensing technologies. Traditional systems primarily rely on single sensors such as infrared (IR) sensors or ultrasonic sensors for motion detection. IR-based systems are widely used due to their low cost and simplicity; however, they are prone to false triggering due to environmental changes such as temperature variations and lighting conditions. Similarly, ultrasonic sensors provide distance-based detection but may produce inaccurate readings due to noise, reflections, or improper alignment.

Recent advancements have introduced multi-sensor-based systems where multiple sensing elements are combined to improve detection accuracy. Some systems utilize combinations of PIR sensors, cameras, or microwave sensors to enhance reliability. However, many of these systems either increase system complexity or require high computational resources. Additionally, most existing systems lack proper zone-based detection, which limits their ability to accurately localize intrusion events.

Most existing systems do not effectively integrate multi-modal sensing with zone-based intelligence in a cost-efficient embedded platform.

2.1 Problems with the Prior Art

Existing intrusion detection systems largely depend on single-sensor technologies such as infrared or ultrasonic sensors, which are prone to inaccuracies and false alarms due to environmental variations, noise, and limited sensing capabilities. These systems often fail to provide reliable detection in dynamic conditions and lack the ability to accurately identify the location of intrusion.

Furthermore, most conventional systems do not support multi-zone monitoring, making it difficult to track movement across different regions. This limitation reduces their effectiveness in real-world security applications where precise localization and reliability are critical.

Therefore, there exists a need for a robust, real-time intrusion detection system that integrates multiple sensing technologies, minimizes false triggers, and enables accurate multi-zone detection using an efficient embedded platform.

3. SUMMARY OF THE INVENTION

The present invention provides an adaptive multi-zone intrusion detection system using hybrid sensor fusion implemented on an ESP32 microcontroller. The system overcomes the limitations of prior art by:

(a) Integrating six sensing modalities — ultrasonic, infrared, force sensing resistor, inertial measurement unit, sound, and ambient light — into a unified detection framework;

(b) Dividing the monitored space into multiple independently monitored zones for precise intrusion localization;

(c) Employing a weighted sensor fusion score to combine sensor inputs and suppress false alarms;

(d) Implementing dynamic threshold adaptation, temporal validation, and sequential zone tracking on a low-cost embedded platform;

(e) Providing real-time remote alert notification via the ESP32's built-in Wi-Fi module and integration with messaging platforms such as Telegram.

4. BRIEF DESCRIPTION OF THE DRAWINGS

The accompanying drawings, which form a part of the specification, illustrate preferred embodiments of the invention:

FIG. 1 — Multi-Zone Layout of the Intrusion Detection System.

FIG. 2 — Hybrid Sensor Fusion Model showing input sensors, fusion processing block, and decision algorithm.

FIG. 3 — Finite State Machine (FSM) governing system operation states: Idle, Monitoring, Detection/Alert, and Reset.

FIG. 4 — Sensor State Combination Representation for permutation-based testing (748 unique combinations).

FIG. 5 — Confidence Ranking Decision Flow Chart.

FIG. 6 — System Flowchart depicting the operational sequence from initialization to alert generation.

FIG. 7 — Block Diagram of the Proposed System showing the three-layer architecture (Input Layer, Processing Unit, Output Layer).

FIG. 8 — Photographs of Hardware Components used in the prototype.

FIG. 9 — Physical Working Model of the Security Platform.

FIG. 10 — Telegram Bot Interface showing real-time intrusion alerts transmitted wirelessly.

5. DETAILED DESCRIPTION OF THE INVENTION

5.1 Overview

The proposed system implements an advanced multi-zone intrusion detection framework based on hybrid multi-sensor fusion, referred to herein as the *Omega-Infinity logic*. The system integrates multiple sensing modalities, adaptive decision-making, and real-time processing to achieve high reliability and reduced false detection.

5.2 Multi-Zone Architecture

The monitored space is divided into multiple zones, each equipped with dedicated ultrasonic and infrared sensors. This enables localized detection and precise identification of intrusion regions. FIG. 1 illustrates the multi-zone layout.



Figure 1: Multi-Zone Layout of the Intrusion Detection System

5.3 Hybrid Multi-Sensor Fusion

The system combines inputs from the following sensors: ultrasonic (U), infrared (I), force sensing resistor (F), MPU6050 inertial measurement unit (M), sound sensor (A), and light dependent resistor (L). The combined detection score is computed as:

$$S = w_1U + w_2I + w_3F + w_4M + w_5A + w_6L \tag{1}$$

where w_1 through w_6 are weighting coefficients assigned based on sensor reliability and environmental context. FIG. 2 depicts the hybrid sensor fusion model.



Figure 2: Hybrid Sensor Fusion Model

5.4 Sensor Normalization

Each sensor output is normalized to ensure uniform contribution to the fused score:

$$X_{\text{norm}} = \frac{X - X_{\min}}{X_{\max} - X_{\min}} \tag{2}$$

5.5 Cross-Verification Mechanism

Intrusion is validated only when multiple sensors detect activity simultaneously, thereby reducing false positives. No single sensor can independently trigger an intrusion alert unless corroborated by at least one additional sensor input.

5.6 Dynamic Threshold Adaptation

The detection threshold is dynamically adjusted to account for ambient noise levels:

$$T = T_0 + \alpha \cdot N \tag{3}$$

where T_0 is the base threshold, N represents the measured noise level, and α is a tuning parameter calibrated experimentally.

5.7 Temporal Validation

Sensor readings are averaged over a sliding time window to suppress transient spikes:

$$S_{\text{avg}} = \frac{1}{N} \sum_{t=1}^{N} S(t) \tag{4}$$

An intrusion event is confirmed only if $S_{\text{avg}} \geq T$.

5.8 Sequential Zone Tracking

The system tracks movement across spatial zones using a sequential transition model:

$$Z(t) \rightarrow Z(t+1) \tag{5}$$

This formulation enables motion pattern detection and directional tracking of intruders across zone boundaries.

5.9 Sensor Confidence Weighting

Sensor weights satisfy the normalization constraint:

$$\sum_{i=1}^{6} w_i = 1 \tag{6}$$

Higher weights are assigned to sensors exhibiting greater reliability under the prevailing environmental conditions.

5.10 Priority-Based Decision Logic

Sensors contribute differently based on context, enabling hierarchical decision-making. Context-specific priorities are determined by the operating environment and the detection history within each zone.

5.11 False Trigger Suppression

Noise filtering algorithms eliminate transient spikes and environmental disturbances from the sensor data stream prior to fusion processing.

5.12 Redundancy-Based Fault Tolerance

Multiple sensors provide overlapping spatial coverage within each zone, ensuring that the system continues to function reliably even in the event of partial sensor failure.

5.13 State-Based System Operation

The system operates as a finite state machine (FSM) with the following states: *Idle*, *Monitoring*, *Alert*, and *Reset*. The FSM governs all transitions between operational modes. FIG. 3 illustrates the FSM.



Figure 3: Finite State Machine of System Operation

5.14 Real-Time Processing Loop

The ESP32 microcontroller executes a continuous real-time processing cycle:

$$\textbf{Read} \rightarrow \textbf{Process} \rightarrow \textbf{Evaluate} \rightarrow \textbf{Act}$$

This cycle ensures that all sensor inputs are evaluated and acted upon with minimal latency.

5.15 Alert Intensity Mapping

The intensity of the generated alert is proportional to the detection score:

$$\text{Alert} \propto S \tag{7}$$

This graduated response mechanism enables contextually appropriate notifications.

5.16 Software Training and Calibration

The system uses rule-based training in which thresholds and weighting coefficients are calibrated using experimental data collected under both normal and simulated intrusion conditions.

5.17 Permutation-Based Scenario Testing

To ensure robustness, the system was evaluated under more than 700 distinct sensor input permutations. Each permutation P represents a unique combination of sensor activation states:

$$P = \{U,\, I,\, F,\, M,\, A,\, L\} \tag{8}$$

The total number of meaningful combinations is:

$$N = \prod_i n_i \approx (5.5)^4 \approx 748 \tag{9}$$

where n_i denotes the number of possible states of each sensor. FIG. 4 illustrates representative sensor state combinations.



Figure 4: Sensor State Combination Representation for Permutation-Based Testing

5.18 Conflict Resolution and Edge Case Handling

The system incorporates conflict resolution mechanisms to handle cases where sensor outputs are inconsistent. Sensor fusion logic ensures that no single sensor can independently trigger an intrusion unless supported by additional inputs. Edge cases such as transient noise spikes and partial detections are filtered using temporal validation and thresholding. Additionally, a reset mechanism is implemented after alert generation to stabilize the system before subsequent detection cycles.

5.19 Hardware Architecture

The system consists of an ESP32 microcontroller interfaced with ultrasonic sensors, IR sensors, FSR, MPU6050, LDR, and a sound sensor distributed across the monitored zones.

5.20 Sensor Interfacing

Analog sensors (LDR, FSR) are connected to the ADC pins of the ESP32, while digital sensors (ultrasonic, IR) interface via GPIO pins. The MPU6050 communicates with the microcontroller via the I^2C protocol.

5.21 Wireless Communication

The ESP32 uses its built-in Wi-Fi module to transmit alerts and to enable remote real-time monitoring. Communication platforms such as Telegram can be integrated to deliver instant push notifications to authorized users.

5.22 Scalability and Modularity

The system architecture supports the addition of further zones and sensors without requiring major redesign of the existing hardware or firmware.

5.23 Fault Detection and Recovery Mechanism

The system incorporates a fault detection module that continuously monitors sensor outputs and communication channels for anomalies. In the event of a failure or inconsistent readings, corrective actions such as sensor isolation or fallback logic are triggered. This ensures uninterrupted system functionality and prevents false intrusion alerts due to hardware or communication faults.

5.24 Self-Diagnostic Capability

A built-in self-diagnostic module periodically evaluates the operational status of all sensors and system components. It verifies data consistency, responsiveness, and connectivity during runtime. This feature enhances system reliability by identifying faults early and enabling preventive maintenance.

5.25 Secure Communication Protocol

The system employs secure wireless communication mechanisms to ensure safe transmission of alerts and sensor data. Encryption and authentication techniques are used to prevent unauthorized access and data tampering.

5.26 Edge-Based Intelligent Processing

All sensor data processing and decision-making are performed locally on the ESP32 microcontroller. This edge computing approach reduces latency and ensures real-time response without dependency on cloud infrastructure.

5.27 Multi-Level Alert Prioritization

The system generates alerts based on multiple levels of severity determined by confidence score, sensor agreement, and zone importance. FIG. 5 presents the confidence ranking decision flow chart.



Figure 5: Confidence Ranking Decision Flow Chart

5.28 Real-Time Data Logging and Traceability

A real-time data logging mechanism records sensor values, detection scores, and system decisions during operation. This stored data can be used for post-event analysis, debugging, and performance optimization.

5.29 Adaptive Learning Mechanism

The system incorporates adaptive logic that adjusts thresholds and decision parameters based on environmental conditions and historical data. This allows improved accuracy over time as the system learns typical ambient patterns, reducing false positives in dynamic environments.

5.30 Configurable Deployment Framework

The system is designed to be flexible and configurable for different deployment scenarios such as residential, industrial, or surveillance applications. Parameters including sensor sensitivity, zone configuration, and alert thresholds can be customized to suit the specific use case.

5.31 Energy-Aware Sensor Scheduling

An intelligent scheduling mechanism controls sensor activation based on contextual activity and system requirements. Sensors operate selectively instead of continuously, thereby reducing unnecessary power consumption and improving suitability for long-term deployment.

5.32 Modular Firmware Architecture

The firmware is structured in a modular manner, separating sensing, processing, communication, and control functionalities. Each module can be updated or modified independently without affecting the entire system, supporting scalability, maintainability, and future upgrades.

6. SYSTEM FLOWCHART

The flowchart of the proposed system represents the step-by-step operation of the intrusion detection process. The system begins by initializing the ESP32 microcontroller and all connected sensors. Once initialized, the system continuously reads input data from the ultrasonic sensors, infrared sensors, FSR, and MPU6050. The collected sensor data is then processed using predefined threshold conditions and a sensor fusion approach to determine whether an intrusion has occurred in any of the defined zones. If an intrusion is detected, the system identifies the specific zone and triggers the corresponding output. If no intrusion is detected, the system continues monitoring in a loop.



Figure 6: System Operational Flowchart

7. BLOCK DIAGRAM

The block diagram represents the overall architecture and functional flow of the multi-zone intrusion detection system, divided into three main layers:

1. **Input Layer** — Multiple sensors deployed across different zones: ultrasonic and IR sensors for motion and proximity detection; FSR for pressure-based contact detection; MPU6050 for motion and vibration data; LDR for ambient light monitoring; and a sound sensor for acoustic anomaly detection.
2. **Processing Unit** — The ESP32 microcontroller processes all incoming sensor data using predefined threshold conditions and sensor fusion logic, determining whether an intrusion has occurred and identifying the corresponding zone.
3. **Output Layer** — Visual indicators (LEDs), an audible buzzer, and remote Wi-Fi alert notifications constitute the output mechanisms.



Figure 7: Block Diagram of the Proposed System

8. HARDWARE USED

The key hardware components of the proposed system are described below.

- **ESP32 Microcontroller** — Serves as the central processing unit responsible for collecting data from all sensors, processing inputs in real time, and generating appropriate outputs. Selected for its high processing capability, low power consumption, and built-in Wi-Fi support.
- **Ultrasonic Sensors (HC-SR04)** — Used in each zone to measure object distance by transmitting ultrasonic waves and measuring the time-of-flight of the reflected signal.
- **Infrared (IR) Sensors** — Deployed alongside ultrasonic sensors to detect nearby objects based on reflected infrared light; effective for short-range detection.
- **Force Sensing Resistors (FSR)** — Detect pressure or physical interaction within specific zones by measuring resistance changes upon application of force.
- **MPU6050 (IMU)** — An inertial measurement unit used to detect motion, vibration, and orientation changes, identifying disturbances or tampering events.
- **Light Dependent Resistor (LDR)** — Measures ambient light intensity to allow the system to adapt to varying lighting conditions.
- **Sound Sensor** — Detects abnormal acoustic events within the monitored zones.
- **Buzzer and LEDs** — Provide audible and visual alert indications upon intrusion

detection; LEDs additionally convey system status and intrusion severity level.



Figure 8: Hardware Components Used in the Prototype



Figure 9: Working Model of the Security Platform

9. SOFTWARE USED

The software development of the proposed system is carried out using the Arduino Integrated Development Environment (IDE), which provides a user-friendly platform for writing, compiling, and uploading code to the ESP32 microcontroller.

The system is programmed in Embedded C, enabling efficient real-time processing

of sensor data. The Arduino IDE serial monitor is used for debugging and observing sensor outputs during testing.

The program logic implements the sensor fusion approach described herein, where inputs from ultrasonic sensors, infrared sensors, force sensing resistors, and the MPU6050 are processed together using threshold-based conditions to determine the presence of intrusion in different zones.

The ESP32's built-in Wi-Fi capability enables the system to be extended for remote monitoring and alert notifications. Communication platforms such as Telegram can be integrated to send real-time alerts to the user. The Telegram bot interface is illustrated in FIG. 10.

Figure 10: Telegram Bot Interface Showing Real-Time Intrusion Alerts

10. RESULTS AND ANALYSIS

The proposed multi-zone intrusion detection system was tested under different conditions to evaluate its performance and reliability. Each zone was monitored independently using a combination of ultrasonic and infrared sensors, along with FSR and MPU6050 inputs.

During testing, the ultrasonic sensors were able to detect objects within the defined range of each zone, while the infrared sensors provided reliable short-range detection. The combination of both sensors significantly reduced false detections compared to using a single sensor. The FSR sensors successfully detected pressure-based interactions,

and the MPU6050 was able to identify vibrations and disturbances.

The system was capable of accurately identifying the specific zone in which intrusion occurred. When an intrusion was detected, the corresponding alert mechanisms — LEDs and buzzer — were activated. The system response time was observed to be fast, enabling real-time detection.

Minor variations in sensor readings were observed due to environmental factors such as noise and sensor alignment. These variations were minimized using threshold-based logic and sensor fusion techniques.

Overall, the system demonstrated improved accuracy, reduced false alarms, and effective multi-zone monitoring, making it suitable for real-time security applications.

11. COMPARATIVE STUDY

Traditional intrusion detection systems typically rely on a single sensing technology such as infrared or ultrasonic sensors. While these systems are simple and cost-effective, they often suffer from high false alarm rates and limited detection accuracy due to environmental factors and sensor limitations. Additionally, most conventional systems do not provide multi-zone detection, making it difficult to identify the exact location of intrusion.

Some advanced systems utilize multiple sensors such as PIR sensors, cameras, or microwave sensors to improve detection accuracy. However, these systems tend to increase system complexity, cost, and computational requirements.

The proposed system improves upon existing approaches by implementing a hybrid multi-sensor fusion technique using ultrasonic sensors, infrared sensors, FSR, and an MPU6050. This combination enhances detection reliability by correlating multiple sensor inputs, thereby reducing false alarms. Furthermore, the system introduces a multi-zone architecture that allows precise localization of intrusion events. Compared to existing systems, the proposed design offers a balance between cost, complexity, and performance while maintaining real-time operation on an embedded platform.

12. PROJECT TIMELINE

The project was executed in a structured manner over a period of eight weeks, as summarised in Table 1.

Table 1: Project Timeline

Week	Work Done
1	Problem identification and project planning
2	Literature survey and system design
3	Hardware selection and component procurement
4	Circuit design and initial setup
5	Sensor integration and coding
6	System testing and debugging
7	Performance evaluation and optimization
8	Report preparation and documentation

13. COST ANALYSIS

The total cost of the proposed system is approximately **2720** (Indian Rupees). Table 2 presents a detailed cost breakdown.

Table 2: Cost Analysis of the Proposed System

Component	**Quantity**	**Cost per Unit ()**	**Total Cost ()**
ESP32	1	400	400
Ultrasonic Sensor (HC-SR04)	4	70	280
IR Sensor Module	4	200	800
FSR Module	2	300	600
MPU6050	1	120	120
LDR	1	30	30
Sound Sensor	1	140	140
LEDs, Breadboard, Wires, Buzzer	Miscellaneous	350	350
		TOTAL	**2720**

The system is designed using low-cost and easily available components, making it

suitable for practical and scalable deployment.

14. FUTURE SCOPE

The proposed system can be further enhanced by integrating advanced technologies:

1. **Camera-Based Visual Verification** — Incorporating image processing or computer vision techniques for visual confirmation of detected intrusion events.
2. **Machine Learning Integration** — Implementing adaptive ML algorithms to improve detection accuracy and reduce false alarms through data-driven decision-making.
3. **Cloud Integration** — Introducing cloud connectivity for real-time data storage, remote monitoring, and advanced analytics.
4. **Expanded Zone Coverage** — Increasing the number of zones for larger area surveillance and optimizing sensor placement for improved detection efficiency.
5. **Power Optimization** — Implementing low-power scheduling techniques to make the system suitable for battery-operated deployments.
6. **Mobile Application Interface** — Developing a dedicated mobile application to provide real-time alerts and system control, improving user accessibility.

15. CLAIMS

1. An adaptive multi-zone intrusion detection system comprising:

(a) an ESP32 microcontroller serving as a central processing unit;

(b) a plurality of ultrasonic sensors distributed across multiple independently defined spatial zones;

(c) a plurality of infrared sensors co-located with said ultrasonic sensors in each zone;

(d) at least one force sensing resistor (FSR) configured to detect pressure-based physical interaction;

(e) at least one MPU6050 inertial measurement unit configured to detect motion, vibration, and orientation changes;

(f) at least one light dependent resistor (LDR) configured to monitor ambient light conditions;

(g) at least one sound sensor configured to detect acoustic anomalies;

(h) a sensor fusion processing module executing on said ESP32 microcontroller and

configured to compute a weighted detection score from normalized outputs of all said sensors;

(i) a dynamic threshold adaptation module configured to adjust detection thresholds based on measured ambient noise levels;

(j) a multi-level alert output system comprising at least one LED indicator, an audible buzzer, and a wireless notification module.

2. The system of claim 1, wherein the weighted detection score S is computed as:

$$S = w_1 U + w_2 I + w_3 F + w_4 M + w_5 A + w_6 L$$

where U, I, F, M, A, and L are normalized sensor outputs and w_1 through w_6 are weighting coefficients satisfying $\sum_{i=1}^{6} w_i = 1$.

3. The system of claim 1, wherein the dynamic threshold is computed as:

$$T = T_0 + \alpha \cdot N$$

where T_0 is a base threshold, N is the ambient noise level, and α is a tuning parameter.

4. The system of claim 1, wherein an intrusion event is confirmed only if a temporally averaged detection score S_{avg} satisfies:

$$S_{\text{avg}} = \frac{1}{N} \sum_{t=1}^{N} S(t) \geq T$$

5. The system of claim 1, wherein said system tracks sequential zone transitions according to:

$$Z(t) \rightarrow Z(t+1)$$

to enable motion pattern detection and directional tracking of intrusion.

6. The system of claim 1, wherein said ESP32 microcontroller executes a real-time processing loop comprising read, process, evaluate, and act stages continuously.

7. The system of claim 1, wherein alert intensity is proportional to the detection score S, providing graduated notifications corresponding to intrusion severity.

8. The system of claim 1, further comprising a fault detection module configured to monitor sensor outputs and communication channels for anomalies, and to isolate

failed sensors or invoke fallback logic.

9. The system of claim 1, further comprising a self-diagnostic module configured to periodically verify data consistency, sensor responsiveness, and wireless connectivity.

10. The system of claim 1, wherein said wireless notification module transmits structured alert messages including zone identifier, intrusion type, direction, confidence score, and severity level via a messaging platform.

11. A method of multi-zone intrusion detection using hybrid sensor fusion on an embedded platform, the method comprising:

(a) initializing an ESP32 microcontroller and a plurality of sensors distributed across multiple spatial zones;

(b) continuously reading sensor outputs from ultrasonic, infrared, FSR, MPU6050, LDR, and sound sensors;

(c) normalizing each sensor output to a uniform scale;

(d) computing a weighted detection score by combining normalized sensor outputs with assigned confidence weights;

(e) comparing a temporally averaged detection score against a dynamically adjusted threshold;

(f) confirming an intrusion event when said averaged score meets or exceeds said threshold and multiple sensors concurrently detect activity;

(g) identifying the specific zone of intrusion and activating corresponding visual, audible, and wireless alert mechanisms;

(h) resetting the system to a monitoring state following alert generation.

12. The method of claim 11, wherein sensor weights are calibrated using experimental data collected under normal and simulated intrusion conditions.

13. The method of claim 11, further comprising resolving sensor conflicts by requiring corroboration from at least two sensors before confirming intrusion, and filtering edge cases using temporal validation and adaptive thresholding.

16. ABSTRACT

This invention discloses an adaptive multi-zone intrusion detection system employing hybrid multi-sensor fusion implemented on an ESP32 microcontroller. The system

integrates ultrasonic sensors, infrared sensors, force sensing resistors, an MPU6050 inertial measurement unit, a sound sensor, and a light dependent resistor across multiple independently monitored spatial zones. A weighted sensor fusion algorithm computes a composite detection score from normalized sensor inputs; intrusion is confirmed only when a temporally averaged score exceeds a dynamically adjusted threshold and multiple sensors concurrently detect activity. The system operates as a finite state machine, executes all processing locally on the ESP32, and transmits real-time alerts via built-in Wi-Fi. The proposed approach demonstrably reduces false alarms, enables precise intrusion localization, and was validated across 748 unique sensor input permutations. The total system cost is approximately 2720, making the invention practically deployable for residential, industrial, and surveillance security applications.

Index Terms — Intrusion Detection, Sensor Fusion, ESP32, Multi-Zone System, Embedded Systems, IoT Security, Real-Time Processing.

REFERENCES

[1] A. Kumar and R. Singh, "IoT-Based Smart Intrusion Detection System Using Sensor Fusion," in *Proc. Int. Conf. Smart Computing and Communication*, 2022, pp. 112–118.

[2] S. Patel, J. Park, P. Bonato, L. Chan, and M. Rodgers, "A review of wearable sensors and systems with application in rehabilitation," *J. NeuroEngineering Rehabil.*, vol. 9, no. 21, pp. 1–17, 2012.

[3] M. R. Mahmud, F. Hossain, and M. A. Rahman, "Design of a Low-Cost Security System Using Multiple Sensors," *Int. J. Eng. Res. Technol.*, vol. 8, no. 5, pp. 345–350, 2019.

[4] J. Gutierrez, J. F. Villa-Medina, A. Nieto-Garibay, and M. A. Porta-Gandara, "Automated Irrigation System Using a Wireless Sensor Network and GPRS Module," *IEEE Trans. Instrum. Meas.*, vol. 63, no. 1, pp. 166–176, Jan. 2014.

[5] H. Alemdar and C. Ersoy, "Wireless sensor networks for healthcare: A survey," *Comput. Netw.*, vol. 54, no. 15, pp. 2688–2710, 2010.

[6] K. Ashton, "That 'Internet of Things' Thing," *RFID Journal*, 2009.

[7] L. Atzori, A. Iera, and G. Morabito, "The Internet of Things: A survey," *Comput. Netw.*, vol. 54, no. 15, pp. 2787–2805, 2010.

[8] Y. Zhang, L. Wang, and W. Sun, "Sensor Fusion for Smart Home Security Systems," *IEEE Access*, vol. 8, pp. 123456–123465, 2020.

[9] D. Chen, M. Nixon, and A. Mokhtari, "Wireless Sensor Networks: Concepts and Applications," *IEEE Commun. Mag.*, vol. 52, no. 8, pp. 102–109, 2014.

[10] P. Rawat, K. D. Singh, H. Chaouchi, and J. M. Bonnin, "Wireless sensor networks: A survey on recent developments and potential synergies," *J. Supercomput.*, vol. 68, no. 1, pp. 1–48, 2014.