Chapter 0:
Contents

1 Introduction 3
2 Estimation and Verification Methods 4
2.1 Mutual Convolution Cost Function (MCCF) 4
2.1.1 Preprocessing 4
2.1.2 Setting the Space-Time Doppler Window 5
2.1.3 Mutual Convolution 5
2.1.4 MCLMS Adaptive Filtering 5
2.1.5 Candidate Peak Selection, Cost Function & Moment Estimation 5
2.2 Improved Moments Estimation (IME) 6
2.2.1 Data Preprocessing 6
2.2.2 Adaptive Doppler Window and Prospective Peak Selection 6
2.2.3 Grouping and Cost-Function-Based Profile Tracing 7
2.3 Hybrid 9
2.4 Verification methods 9
2.4.1 Radiosonde 9
2.4.2 Lidar 9
2.4.3 Synthetic data 9
3 Synthetic data creation 10
3.1 Primary UVW syntheis 10
3.2 Spectrum broadening 13
3.3 DC clutter 13
3.4 Bright band 14
References 15

Chapter 1:
Introduction

About the whole project...

Chapter 2:
Estimation and Verification Methods

About what algorithms have been covered... How results are validated

- Radio sonde..
- Lidar (just referencing literature)
- Via Synthetic data (reference next chapter)

Then list methods:

2.1 Mutual Convolution Cost Function (MCCF)

MCCF is a peak estimation algorithm proposed by Tang et al. [1] which uses Mutual convolution to improve SNR and a velocity-frequency-weighted cost function to estimate the most prominent peak in the spectrum. It also uses Space-Time doppler window (ST window) to limit the number of candidate peaks as well as to improve the continuity of velocity profile. Space window is used to improve velocity continuity over height ranges and time window is used for improving velocity continuity in specific height over time.

The algorithm is illustrated in Figure 2.1. Here the cylindrical entries are final data as well as intermediate data acquired. The intermediate data might be useful in future for other algorithms to work on.




Figure 2.1: MCCF Algorithm Flow.

Individual steps are explained in upcoming subsections

2.1.1 Preprocessing

Here the FFT of time series raw data (slow sampled) is computed. Then DC masking is applied in which value of 5 bins near DC bin is replaced with bacground noise with random phase. It is then converted back to time series data.


2.1.2 Setting the Space-Time Doppler Window

This step improves velocity profile continuity by limiting number of candidate peaks. By setting a doppler window in *space axis* peaks outside this window is rejected. This window accounts for maximum wind shear between height bins. Detting a doppler window in *time axis* applies the assumption that during a time interval wind velocity changes at some maximum rate.

The Space-Time window is intersection of both windows.

2.1.3 Mutual Convolution

In this step the noise is heavily suppressed and SNR is improved. It works by slicing a spectrum in a height bin P into n slices of length $N/2$ (where N is length of original spectrum) then convolving adjacent slices together to form $n-1$ results. From these results a optimal solution segment X_r is chosen which contain the highest peak among all results. Also the segment adjacent to X_r is chosen as suboptimal solution X'_r. Both of these are used in MCLMS filter.



2.1.4 MCLMS Adaptive Filtering

MCLMS (Modified Complex Least Mean Square) filter is a adaptive filter. It learns its weight during slicing of spectrums, and after modifying the weight vector final filtered spectra is obrained through the optimal and suboptimal spectras. MCLMS can suppress clutter clutter even more by training a model that tries to match optimal solution with suboptimal solution. In the end the spectrum will have some of the clutter suppressesd.

2.1.5 Candidate Peak Selection, Cost Function & Moment Estimation

Peaks in ST doppler window which has amplitude $\geq 40\%$ of maximum peak are chosen as candidate peaks. The algorithm assigns a "cost" to each of these peaks based on their velocity difference between each frequency bin $V_{r+1,j}$ given by:

$$V_{r+1,j} = 1 - \left| \left(M_{r+1,j} - M_r\right) \frac{d_v}{\alpha V_d} \right|$$

and magnitude of peak itself $M_{r+1,j}$. Here d_v represents the velocity resolution, V_d represents the maximum wind shear, α is the window coefficient. The cost of each peak is given by:

$$F_{r+1,j} = w_1 V_{r+1,j} + w_2 M_{r+1,j}$$

The peaks with higest cost value is taken as the spectral peak. From this moments can be estimated based on Hildreth-Seikh method.

2.2 Improved Moments Estimation (IME)

The Improved Moments Estimation (IME) algorithm proposed by Li **et al.**[2] is designed to extract reliable Doppler velocity profiles from ground-based K-band wind radar spectra, particularly when the atmospheric echoes have low signal-to-noise ratio (SNR) and are contaminated by clutter or multiple spectral peaks. The method combines the adaptive Doppler-window concept of the Adaptive Moments Estimation (AME) method with the cost-function-based profile tracing concept of the Multiparameter Cost Function (MPCF) method. Its main objective is to reduce the computational search space while maintaining reliable wind-profile detection under low-SNR conditions.

The IME procedure consists of three main stages:

1. Preprocessing of the Doppler power spectra
2. Adaptive Doppler-window selection and identification of prospective spectral peaks
3. Grouping, profile tracing, and cost allocation.

2.2.1 Data Preprocessing

Before profile extraction, the Doppler power spectra are processed to suppress unwanted spectral components. First, the zero-frequency region is affected by direct-current (DC) components and ground clutter. These components are suppressed by interpolation, in which the average values of three points around zero frequency are used to replace the contaminated values. Next, a five-point moving-average filter is applied to suppress transient interference while preserving the atmospheric echo characteristics. Finally, the noise power density S_n of each range bin is estimated using the Hildebrand–Sekhon method. The estimated noise level is subtracted from the power spectrum, and negative values are set to zero. The resulting spectrum is therefore more suitable for identifying atmospheric spectral peaks. The preprocessing procedure described in the paper is summarized in Figure 2.3




Figure 2.3: IME Method

These preprocessing operations are important because atmospheric echoes in the surface boundary layer are often weak and may be obscured by random noise, radio-frequency interference, and sidelobe clutter.

2.2.2 Adaptive Doppler Window and Prospective Peak Selection

The IME algorithm starts at the lowest range bin and searches for candidate spectral peaks only within an adaptive Doppler window. Unlike the MPCF method, which selects five prominent peaks from the complete Doppler spectrum, IME restricts the search region using information obtained from the previous range bin. This substantially reduces the number of spectral components that must be considered.

For a selected spectral component, the algorithm determines the peak position and the left and right zero-crossing points, from which the radial velocity, spectral width, and SNR are calculated. A peak is retained as a prospective atmospheric component when its SNR is greater than 0 dB. Up to three prospective peaks are retained for each range bin. The procedure stops earlier when no spectral component with power greater than the estimated noise level remains in the current Doppler window.

For the first range bin, no previous information is available. Therefore, the most prominent spectral component is initially selected and its radial velocity is used as the mean Doppler velocity. The Doppler window for the next range bin is then centered around the candidate whose radial velocity is closest to the previous mean Doppler velocity. This process is repeated sequentially with increasing range. The paper states that the wind Doppler signal is generally not expected to change by more than 20% of the total coherent-filter bandwidth, and therefore the Doppler-window width is restricted to less than 20% of the complete Doppler-axis width.

The adaptive-window procedure is represented in Figure 2.4




Figure 2.4: IME Method

This restriction prevents noise and unrelated spectral components outside the expected velocity region from entering the profile-tracing stage.

2.2.3 Grouping and Cost-Function-Based Profile Tracing

After the prospective peaks have been identified, the algorithm constructs possible traces between adjacent range bins. A trace represents a possible Doppler velocity profile through height. Constructing all possible traces over the complete range would result in a large computational load; therefore, the spectra are divided into small groups containing at least three consecutive range bins. Candidate peaks within each group are then connected from one range bin to the next. For the first group, the initial value is the Doppler velocity of the most prominent peak, while subsequent groups use the velocity at the highest range bin of the preceding group as their initial value. Figure 2.5 shows all links in a group and M_j^r indicates the j th peak of the r th range bin.




Figure 2.5: Grouping and profile tracing. Each circle represents a candidate spectral peak

The cost assigned to a connection between two candidate peaks is based on two characteristics: the continuity of wind shear and the relative SNR of the candidate. The paper determines the maximum allowable radial-velocity shear as

$$|\Delta v_{\mathrm{m}}| \leq 0.05 \sin(\theta) \Delta R \tag{2.1}$$

where Δv_{m} is the maximum radial-velocity shear, θ is the radar beam tilt angle, and ΔR is the range resolution.

To represent the continuity of the Doppler profile, a trapezoidal membership function is used:

$$T(x) = \begin{cases} 1 & |x| \leq \Delta v_{\mathrm{m}} \\ (2\Delta v_{\mathrm{m}} - |x|)/\Delta v_{\mathrm{m}} & \Delta v_{\mathrm{m}} < |x| < 2\Delta v_{\mathrm{m}} \\ 0 & |x| \geq 2\Delta v_{\mathrm{m}} \end{cases} \tag{2.2}$$

Here, x represents the wind-shear difference between two connected candidate peaks. A high membership value indicates that the change in velocity between adjacent range bins is consistent with the expected continuity of the atmospheric wind profile.

The relative SNR of a candidate peak is normalized with respect to the largest candidate SNR in the same range bin:

$$P_{r,j} = \frac{\alpha_{r,j}}{\max(\alpha_r)} \tag{2.3}$$

where $\alpha_{r,j}$ denotes the SNR of the j-th candidate peak in the r-th range bin. The complete link cost is then formed by combining the continuity term and the normalized SNR term:

$$C = w_1 T + w_2 P, \quad w_1 + w_2 = 1. \tag{2.4}$$

The weights determine the relative importance of wind-profile continuity and spectral strength. Based on experiments performed by the authors, the selected values are

$$w_1 = 0.4, \quad w_2 = 0.6.$$

Thus, the IME algorithm gives greater weight to the normalized SNR while still enforcing continuity between adjacent range bins. The total cost of each possible trace is calculated, and the trace

with the largest total cost is selected as the final Doppler velocity profile for the corresponding group. The velocity at the highest range bin of the selected group is then used as the initial value for the next group, allowing the profile to be traced progressively over altitude.

Overall, the IME algorithm can be summarized as

$$\text{cleaned spectra} \rightarrow \text{adaptive Doppler windows} \rightarrow \text{prospective peaks} \rightarrow \text{grouping and trace construction} \rightarrow \text{cost evaluation} \rightarrow \text{maximum-cost Doppler profile.}$$

The main advantage of IME is that it searches only a limited Doppler region and retains at most three prospective peaks per range bin, unlike MPCF, which searches five peaks over the full Doppler spectrum. The paper reports that this reduction in the search space decreases computational time while retaining good profile-extraction performance, particularly for low-SNR atmospheric echoes.

2.3 Hybrid

mixing and matching various algorithms (spectra computing, denoising, moment estimation) of different methods (MCCF, IME, etc.). Is there any better results?

Add figures for comparison of algorithms.

2.4 Verification methods

2.4.1 Radiosonde

2.4.2 Lidar

2.4.3 Synthetic data

Chapter 3:
Synthetic data creation

(5 pages)

Explain how synthetic observations are made, why they are considered, the components of it, and the process (a figure would be nice), comparing the performance of existing algos.

3.1 Primary UVW syntheis

3.1.0.1 Synoptic Background Profile

The synoptic background profile models the smooth logarithmic atmospheric boundary layer wind shear near the surface, decaying exponentially with altitude in the troposphere.

$$u_{\mathrm{bl}} = \left(\frac{u^*_{\mathrm{bg}}}{\kappa_{\mathrm{bg}}}\right) \log\left(\frac{z_m + z_{\mathrm{bg}}}{z_{\mathrm{bg}}}\right) \exp\left(-\frac{h}{L_{\mathrm{bg}}}\right) \tag{3.1}$$

- h : Height bins [km]
- z_m : Height in meters, $z_m = h \cdot 1000$ [m]
- z_{bg} : Surface roughness length for terrain [0.05 m]
- u^*_{bg} : Friction velocity representing surface stress [0.3 m/s]
- κ_{bg} : von Kármán constant [0.4]
- L_{bg} : Boundary layer height scale [1.5 km]

3.1.0.2 Low-Level Somali Jet

The low-level Somali jet models the intense cross-equatorial onshore South-West monsoon flow in the lower troposphere using a Gaussian vertical velocity core centered near 1.5 km altitude.

$$\begin{aligned} u_{\mathrm{llj}} &= u_{\mathrm{sj}} \exp\Big[-\big((h - z_{\mathrm{sj}})/\sigma_{\mathrm{sj}}\big)^2\Big] \\ v_{\mathrm{llj}} &= v_{\mathrm{sj}} \exp\Big[-\big((h - z_{\mathrm{sj}})/\sigma_{\mathrm{sj}}\big)^2\Big] \end{aligned} \tag{3.2}$$

- u_{sj} : Zonal onshore wind speed of the SW monsoon jet [12 m/s]
- v_{sj} : Meridional onshore wind speed of the SW monsoon jet [14 m/s]
- z_{sj} : Altitude of the jet core center [1.5 km]
- σ_{sj} : Gaussian vertical thickness scale of the jet [0.8 km]

3.1.0.3 Tropical Easterly Jet (TEJ)

The Tropical Easterly Jet represents the strong upper-tropospheric easterly (westward) jet stream near the tropopause during the summer monsoon season.

$$\begin{aligned} u_{\mathrm{tej}} &= u_{\mathrm{tej,core}} \exp\Big[-\big((h - z_{\mathrm{tej}})/\sigma_{\mathrm{tej}}\big)^2\Big] \\ v_{\mathrm{tej}} &= v_{\mathrm{tej,core}} \exp\Big[-\big((h - z_{\mathrm{tej}})/\sigma_{\mathrm{tej}}\big)^2\Big] \end{aligned} \tag{3.3}$$

- $u_{\mathrm{tej,core}}$: Peak zonal easterly jet core speed [35 m/s]
- $v_{\mathrm{tej,core}}$: Peak meridional jet core speed [3 m/s]
- z_{tej} : TEJ core altitude [15.0 km]

- σ_{tej} : TEJ core vertical layer thickness scale [2.5 km]

3.1.0.4 Stratospheric Quasi-Biennial Oscillation (QBO)

The Quasi-Biennial Oscillation simulates downward-propagating alternating zonal and meridional wind regimes in the tropical stratosphere using a sinusoidal wave envelope activated above the tropopause.

$$\begin{aligned} u_{\text{qbo}} &= u^*_{\text{qbo}} \sin\left[2\pi\big(h - z_{\text{qbo}}\big)/\lambda_{\text{qbo}}\right] \cdot E_{\text{qbo}} \\ v_{\text{qbo}} &= v^*_{\text{qbo}} \cos\left[2\pi\big(h - z_{\text{qbo}}\big)/\lambda_{\text{qbo}}\right] \cdot E_{\text{qbo}} \end{aligned} \tag{3.4}$$

Where

$$E_{\text{qbo}} = \frac{1}{2}\left[1 + \tanh\big(\big(h - z_{\text{qbo}}\big)/2\big)\right]$$

and

- z_{qbo} : Altitude of QBO onset region [17 km]
- λ_{qbo} : Vertical wavelength of alternating wind regimes [20 km]
- u^*_{qbo} : Peak zonal amplitude of QBO phase shifts [8 m/s]
- v^*_{qbo} : Peak meridional amplitude of QBO phase shifts [3 m/s]

3.1.0.5 Orographic Updraft

The orographic updraft models forced vertical lifting over mountainous terrain features (e.g., Western Ghats ridge) proportional to the mean zonal flow and decaying exponentially with height.

$$w_{\text{oro}} = \max(0, u_{\text{mean}}) \cdot \tan\big(\alpha_{\text{slope}}\big) \exp\left(-\frac{h}{H_{\text{lift}}}\right) \tag{3.5}$$

- u_{mean} : Mean zonal wind profile [m/s]
- α_{slope} : Western Ghats ridge terrain slope angle [$\arctan(1.5/30.0) \approx 0.05$ rad]
- H_{lift} : Vertical decay scale for atmospheric lifting [3.5 km]

3.1.0.6 Continuous Gravity Wave Spectrum

Continuous gravity waves synthesize atmospheric wave perturbations across multiple vertical modes, incorporating amplitude growth with height (density scale height) and high-altitude damping.

$$\begin{aligned} u_{\text{gw}} &= A_{\text{gw}} \cdot A(h) \cdot \text{norm}\left[\sum_{i=1}^{N_{\text{modes}}} \sqrt{E(m_i)}\cos\big(m_i h + \phi_{u,i}\big)\right] \\ v_{\text{gw}} &= A_{\text{gw}} \cdot A(h) \cdot \text{norm}\left[\sum_{i=1}^{N_{\text{modes}}} \sqrt{E(m_i)}\sin\big(m_i h + \phi_{v,i}\big)\right] \\ w_{\text{gw}} &= -c_f \cdot u_{\text{gw}} \end{aligned} \tag{3.6}$$

Where m_i is vector of wavenumbers that range from $\lambda_{\max}$ to 0.4km across N_{modes} bins and

$$A(h) = \exp\left(\frac{h}{2H_s} - \frac{h}{h_{\text{damp}}}\right) \qquad\qquad E(m_i) = \frac{m_i^{-1.5}}{\sum_j m_j^{-1.5}}$$

is the normalized spectral energy density distribution across vertical wavenumbers.

- h : Height bins [in km]
- N_{modes} : Number of continuous gravity wave spectrum modes [20]
- A_{gw} : Scaling factor for horizontal gravity wave velocity [2.5 m/s]
- $\lambda_{\max}$: Upper limit for gravity wave vertical scale [4.0 km]
- h_{damp} : Damping scale height to control upper atmospheric amplitude [12.0 km]
- c_f : Coupling factor deriving vertical wave speed from horizontal wave speed [0.05]
- H_s : Density scale height for wave amplification [7.0 km]
- $\phi_{u,i}, \phi_{v,i}$: vector of random initial phase shifts ($\phi \in [0, 2\pi)$)

3.1.0.7 Convective Thermal Plumes

Convective thermal plumes generate localized vertical updrafts and downdrafts caused by surface solar heating and thermal buoyancy in the lower troposphere.

$$w_{\text{plumes}}(h) = \sum_{p=1}^{N_{\text{plumes}}} w_{\text{peak}}(p) \exp\left[-\left(\frac{z - h_{\text{center}}(p)}{w_{\text{width}}(p)}\right)^2\right] \tag{3.7}$$

- N_{plumes} : Number of random convective updrafts/downdrafts [4]
- $H_{\max}$: Maximum altitude ceiling for thermal plumes [6.0 km]
- $h_{\text{center}}(p)$: Altitude center of plume p, drawn randomly between 0.8 km and $H_{\max}$
- $w_{\text{peak}}(p)$: Peak vertical velocity for plume p, drawn randomly between -0.75 and 1.75
- $w_{\text{width}}(p)$: Vertical thickness scale of plume p, drawn randomly between 0.2 km and 0.6 km

3.1.0.8 Kolmogorov Turbulence and Intermittency

Kolmogorov turbulence introduces sub-grid scale velocity perturbations. It takes generated mean zonal and meridional wind profile profiles $(\bar{u}, \bar{v})$ and adds this terms also.

$$\begin{aligned} u_{\text{kt}} &= \hat{u}_{\text{raw}} \cdot \sigma_{\text{turb}} \\ v_{\text{kt}} &= \hat{v}_{\text{raw}} \cdot \sigma_{\text{turb}} \\ w_{\text{kt}} &= \hat{w}_{\text{raw}} \cdot \sigma_{\text{turb}} \cdot \alpha_{\text{vaf}} \end{aligned} \tag{3.8}$$

Where:

$$\sigma_{\text{turb}} = \left[0.15 + 0.4 \ \text{norm}\left(\sqrt{S}\right)\right] \cdot T_{\text{boost}} \cdot W_{\text{interm}}$$

$$S = \left(\frac{d\bar{u}}{dh}\right)^2 + \left(\frac{d\bar{v}}{dh}\right)^2 + \varepsilon$$

$$T_{\text{boost}} = \begin{cases} B_{\text{kt}} + B_{\text{kt,max}} \cdot \exp\left[-((h - H_{\text{turb}})/d_{\text{turb}})^2\right] & \text{Ri} < \text{Ri}_c \\ B_{\text{kt}} & \text{Ri} \geq \text{Ri}_c \end{cases}$$

$$\text{Ri} = (N_{\text{bv}}^2)/S^2$$

$$W_{\text{interm}} = \exp\left(-\frac{1}{2}\sigma_{\text{interm}}^2 + \sigma_{\text{interm}} \cdot \hat{u}_{\text{raw}}\right)$$

- N_{bv} : Brunt-Väisälä buoyancy frequency [0.012 rad/s]
- Ri_c : Critical Richardson number threshold for dynamic instability [0.25]
- $B_{\text{kt,max}}$: Maximum turbulence boost factor under instability [2.5]

- B_{kt} : Baseline factor for turbulence scaling [1.0]
- H_{turb} : Turbulent layer peak altitude [3.0 km]
- d_{turb} : Vertical thickness scale of turbulent layer [2.5 km]
- σ_{interm} : Intermittency parameter for log-normal weighting [0.5]
- α_{vaf} : Vertical anisotropy scaling factor [0.25]
- $\hat{u}_{\mathrm{raw}}, \hat{v}_{\mathrm{raw}}, \hat{w}_{\mathrm{raw}}$: random initial u,v,w velocities

3.1.0.9 Combining all factors

Final u,v,w is given by:

$$\begin{aligned} u &= \left(\bar{u} + u_{\mathrm{gw}} + u_{\mathrm{kt}}\right)' \\ v &= \left(\bar{v} + v_{\mathrm{gw}} + v_{\mathrm{kt}}\right)' \\ w &= \left(w_{\mathrm{oro}} + w_{\mathrm{gw}} + w_{\mathrm{plumes}} + w_{\mathrm{kt}}\right)' \end{aligned} \tag{3.9}$$

And

$$\begin{aligned} \bar{u} &= \left[u_{\mathrm{llj}} + u_{\mathrm{bl}} + u_{\mathrm{tej}} + u_{\mathrm{qbo}}\right] J \\ \bar{v} &= \left[v_{\mathrm{llj}} + v_{\mathrm{tej}} + v_{\mathrm{qbo}}\right] J \end{aligned}$$

J is some extra jitter added

3.2 Spectrum broadening

[3]

$$\sigma_v = \sqrt{\sigma_{\mathrm{shear}}^2 + \sigma_{\mathrm{beam}}^2 + \sigma_t^2}$$

Wind shear:

$$\sigma_{\mathrm{shear}} = \frac{dv}{dz}\frac{\Delta r}{\sqrt{12}}$$

Beam Broadening:

$$\sigma_{\mathrm{beam}} = \frac{\mathrm{HPBW}}{4\sqrt{\ln 2}} \left|v_{\mathrm{cross}}\right|$$

Where v_{cross} is wind component perpendicular to the beam axis given by:

$$v_{\mathrm{cross}} = \sqrt{U^2 + V^2 + W^2 - v_{\mathrm{radial}}^2}$$

HPBW $= 3.3°$ [4]

Turbulance: $\sigma_{\mathrm{t}} = 0.6$ m/s

3.3 DC clutter

DC spectra is modeled as a gaussian distribution with peak amplitude scaled by r_{DC} times total power of that height range ($P_S = P_{\mathrm{signal}} + P_{\mathrm{noise}}$) with spectral width σ_{DC} which is again normally distributed random variable. This spectra is added to signal to finally obtain BeamData

$$S_{\mathrm{DC}}(f,h) = r_{\mathrm{DC}} P_S \exp\left[-\frac{f^2}{2\sigma^2_{\mathrm{DC}}(h)}\right]\left(\exp\left[\frac{h}{N}\right] - 0.7\right) \tag{3.10}$$

Where N is number of range bins.

3.4 Bright band

Similar to DC clutter, bright bands are also modeled by stretched gaussian distribution.

$$S_{\mathrm{bb}}(f,h) = P_S \cdot 10^{-3.5} \cdot \chi_N \cdot \exp\left(-\frac{f^2}{2\sigma^2_{\mathrm{bb}}(h)}\right) \tag{3.11}$$

χ_N is random variable sampled from range [1, 1.333]. $\sigma^2_{\mathrm{bb}}(h)$ is spectral width of bright band. $10^{-3.5}$ is chosen to account for -30 to -40dB reflectivity of bright band

References

[1] Zaixing Tan et al., "Wind Profile Estimation for K-Band Doppler Radar Based on Mutual Convolution Cost Function Method," *IEEE Sensors Journal*, vol. 24, no. 15, Aug. 2024.

[2] Li et al., "Improved Moments Estimation for Ground-Based K-Band Doppler Radar Using Cost Function Method," *IEEE Access*, vol. 10, Mar. 2022.

[3] Fred E. Nathanson, *Radar Design Principles.* [Online]. Available: https://selasl.wordpress.com/wp-content/uploads/2011/08/mcgraw_hill_-_radar_design_principles.pdf

[4] Titu K. Samson, "Design, Development, Calibration and Validation of 205 MHz Wind Profiler Radar."