

NAME

"maxtime" – run a command with a timeout

SYNOPSIS

```
maxtime [-g] [-k] [-v] [-w] [--] time command [arg1 ...]
```

DESCRIPTION

maxtime allows for an external program to be run with a time limit. The argument *time* must be a positive number of seconds, and may be fractional. If the *command* terminates within this period, **maxtime** reports its exit status. If the command's real (wall clock) time exceeds the time limit, it will be killed with SIGTERM. **maxtime** will then return the value 106 to indicate the timeout (see below under RETURN VALUE).

OPTIONS

- g** The specified *command* will run in its own process group. If the command times out, the entire process group will be killed.
- k** If SIGTERM does not kill *command*, send SIGKILL after a short delay.
- v** Be verbose. If not specified, **maxtime** will not report what it is doing, even if it exits due to an error. However, the exit code will indicate the problem.
- w** Wait for termination of the child process, even if it timed out and was sent a SIGTERM and/or SIGKILL.

ENVIRONMENT

PATH

PATH is traversed in order to find the specified *command*.

RETURN VALUE

maxtime returns the exit status of the external command, unless an error condition occurs, in which case the exit code will be greater than 100.

0 The command completed successfully.

1 to 100

The command was unsuccessful. The exit status is the exit status of the external command.

101 Too few commandline arguments.

102 Invalid command line options.

103 Error while setting the alarm signal handler.

104 Error while forking child process.

105 Error during *exec()*. Probably the command specified is not in the **PATH**.

106 Either the *command* timed out and was killed, or some other process sent it a signal, causing it to terminate. The command did not return a useful exit status.

107 Insufficient memory to perform requested task.

108 The *time* specified was not a valid floating-point number.

109 The specified timer period was negative or zero.

110 The timer could not be set.

128 and up

The command was unsuccessful, and exited due to a signal (e.g. an interrupt was sent from the keyboard).

EXAMPLES

Attempt to download a network file, but allow at most 10 seconds:

```
maxtime 10 wget http://catb.org/jargon/html/index.html
```

Request the status of a Baan shared memory segment, but do not lock up if shared memory is corrupt:

```
maxtime 2 $BSE/bin/shmmanager6.1 -s
```

Allow at most 10 minutes for stopping a Baan software environment:

```
maxtime 600 $BSE/etc/rc.stop
```

BUGS

If the *time* argument is omitted and an *arg* argument is provided, **maxtime** might interpret its commandline arguments wrong. This will only be apparent if **-v** has been used, or if its exit status is tested for value 105.

On some platforms, **maxtime** might confuse options for the external command as options for itself. In these cases is necessary to indicate the end of **maxtime**'s options using **--**.

SEE ALSO

exit (3), *setitimer* (2), *signal* (7), *wait* (2).

VERSION

This manual pertains to version 0.36.

AUTHOR and COPYRIGHT

Copyright © 2004-2019, René Uittenbogaard (ruittenb@users.sourceforge.net).

This program is free software; you can redistribute it and/or modify it under the terms described by the GNU General Public License version 3.

maxtime is distributed without any warranty, even without the implied warranties of merchantability or fitness for a particular purpose.