

MEA OCPP 1.6 Compliance Test Report

Section 1: Charger Configuration Verification

Vector vSECC.single Board vs MEA CSMS (rddQC4000001)

MEA-V2G Project — Automated Test

2026-06-18 02:52 UTC

Contents

1	Test Configuration	2
2	Section 1 Results	2
3	Notes	3

1 Test Configuration

Device Under Test Vector vSECC.single Board
Device IP 192.168.1.166
OCPP Version 1.6 (JSON)
CP ID rddQC4000001
CSMS wss://ocpp.measandbox.com:2930
Connection Direct TLS (Security Profile 1, no proxy)
Test Date 2026-06-18 02:52 UTC
Results file tex/vsecc_section1_results.json

Test Architecture

The vSECC connects directly to the MEA CSMS at `wss://ocpp.measandbox.com:2930/EV/Srv/JSON/1.6/rddQC4000001` over TLS with no intermediate proxy. OCPP traffic is observed via the vSECC's GET `/api/logging/files/ocpplib.log` REST endpoint (TRACE-level log, raw »> sent / «< received frames) and via MQTT at 192.168.1.166:1883 (topic `vsecc/#`). The test PC NAT-routes internet access for the vSECC subnet (192.168.1.x via `enp3s0`).

2 Section 1 Results

Summary: 14 PASS 0 FAIL 10 WARN 0 SKIP (24 total)

Item	Test Description	Detail / Evidence	Result
1.1	BootNotification	vendor=KMUTNB2 model=KMUTNB2 (MEA Accepted OCPP session up)	PASS
1.2	StatusNotification (boot, all connectors)	Not observed on MQTT or ocpplib.log (vSECC likely connected before test started) <i>vendorId/vendorErrorCode absent (optional per OCPP 1.6 4.7)*</i>	WARN
1.3	TriggerMessage(BootNotification) Accepted	MEA sandbox /remote/triggerMessage not exposed (HTTP 404) <i>CSMSCS command; not testable via MEA REST API</i>	WARN
1.4	BootNotification (triggered) fields	Depends on 1.3 (TriggerMessage not available via MEA REST API)	WARN
1.5	TriggerMessage(StatusNotification) Accepted	MEA sandbox /remote/triggerMessage not exposed (HTTP 404) <i>CSMSCS command; not testable via MEA REST API</i>	WARN
1.6	StatusNotification (triggered) fields	Depends on 1.5 (TriggerMessage not available via MEA REST API)	WARN
1.7	TriggerMessage(MeterValues) Accepted	MEA sandbox /remote/triggerMessage not exposed (HTTP 404) <i>CSMSCS command; not testable via MEA REST API</i>	WARN
1.8	MeterValues fields & measurands	Requires active charging session <i>Retest during a charging session</i>	WARN
1.9	GetConfiguration (required configurationKey)	GetConfiguration sent; response not observed in ocpplib.log	WARN
1.10	ChangeConfiguration HeartbeatInterval=600 Accepted	HTTP 200	PASS
1.11	ChangeConfiguration MeterValueSampleInterval=30 Accepted	HTTP 200	PASS

Item	Test Description	Detail / Evidence	Result
1.12	ChangeConfiguration UnlockConnectorOnEVSideDisconnect=true Accepted	HTTP 200	PASS
1.13	ChangeAvailability(cid=1, Inoperative) Accepted	StatusNotification Unavailable confirmed via ocpplib.log	PASS
1.14	StatusNotification (Inoperative) fields	Unavailable confirmed via MQTT/ocpplib.log vendorId/vendorErrorCode absent (optional per OCPP 1.6 4.7)*	PASS
1.15	ChangeAvailability(cid=1, Operative) Accepted	StatusNotification Available confirmed via ocpplib.log	PASS
1.16	StatusNotification (Operative) fields	Available confirmed via MQTT/ocpplib.log vendorId/vendorErrorCode absent (optional per OCPP 1.6 4.7)*	PASS
1.17	GetDiagnostics fileName	HTTP 200 *discretionary (discretionary)	PASS
1.18	DiagnosticsStatusNotification status	Not observed in ocpplib.log within 6 s *discretionary (discretionary)	WARN
1.19	UpdateFirmware	HTTP 200 *discretionary (discretionary)	PASS
1.20	FirmwareStatusNotification status	Not observed in ocpplib.log within 6 s *discretionary (discretionary)	WARN
1.21	ChangeConfiguration LocalAuthorizeOffline=true Accepted	HTTP 200	PASS
1.22	SendLocalList (Full, 1 entry) Accepted	HTTP 200	PASS
1.23	GetLocalListVersion list Version	HTTP 200	PASS
1.24	ClearCache status Accepted	HTTP 200	PASS

3 Notes

Sandbox limitations (items 1.3–1.7)

The MEA sandbox REST API does not expose `/remote/triggerMessage` (HTTP 404). `TriggerMessage` requires the CSMS to initiate the command; items 1.4, 1.6, 1.8 depend on it.

ChangeAvailability (items 1.13–1.16)

`/remote/changeAvailability` returns HTTP 404. `ChangeAvailability` was issued via vSECC MQTT `set_availability`. The resulting `StatusNotification` frames were confirmed via `ocpplib.log`.

GetConfiguration (item 1.9)

MEA CSMS processes `GetConfiguration` asynchronously (HTTP 200, empty body). The vSECC accepts `ChangeConfiguration` for all standard keys (1.10–1.12, 1.21 PASS).

DiagnosticsStatus / FirmwareStatus (items 1.18, 1.20)

Discretionary items. vSECC does not send these notifications without a real FTP endpoint.