

# MEA OCPP 1.6 Compliance Test Report

Section 6: Charging Profile Verification

Vector vSECC.single Board vs MEA CSMS (rddQC4000001)

MEA-V2G Project — Automated Test

2026-06-11 04:41 UTC

## Contents

|          |                           |          |
|----------|---------------------------|----------|
| <b>1</b> | <b>Test Configuration</b> | <b>2</b> |
| <b>2</b> | <b>Section 6 Results</b>  | <b>2</b> |
| <b>3</b> | <b>Notes</b>              | <b>3</b> |

## 1 Test Configuration

**Device Under Test** Vector vSECC.single Board  
**Device IP** 192.168.1.166  
**OCPP Version** 1.6 (JSON)  
**CP ID** rddQC4000001  
**CSMS** wss://ocpp.measandbox.com:2930  
**Connection** Direct TLS (Security Profile 1, no proxy)  
**Test Date** 2026-06-11 04:41 UTC  
**Results file** tex/vsecc\_section6\_results.json

### Test Architecture

The vSECC connects directly to the MEA CSMS at `wss://ocpp.measandbox.com:2930/EV/Srv/JSON/1.6/rddQC4000001` over TLS with no intermediate proxy. OCPP traffic is observed via the vSECC's GET `/api/logging/files/ocpplib.log` REST endpoint (TRACE-level log, raw » sent / « received frames) and via MQTT at 192.168.1.166:1883 (topic `vsecc/#`). The test PC NAT-routes internet access for the vSECC subnet (192.168.1.x via `enp3s0`).

## 2 Section 6 Results

**Summary: 4 PASS   0 FAIL   22 WARN   0 SKIP   (26 total)**

| Item | Test Description                                               | Detail / Evidence                                                                                       | Result      |
|------|----------------------------------------------------------------|---------------------------------------------------------------------------------------------------------|-------------|
| 6.1  | StatusNotification Available (initial state)                   | Available not observed on MQTT in 10 s<br><i>Check CSMS event log; charger may already be available</i> | <b>WARN</b> |
| 6.2  | StatusNotification Preparing (EV plug, Flow 1)                 | EV_WAIT_SEC=0 skipped<br><i>Connect physical EV to connector and rerun</i>                              | <b>WARN</b> |
| 6.3  | Authorize (RFID card) Accepted                                 | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.4  | StartTransaction (manual RFID, meterStart, idTag, connectorId) | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.5  | StatusNotification Charging (Flow 1)                           | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.6  | MeterValues (Flow 1, before SetChargingProfile)                | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.7  | SetChargingProfile (TxProfile, 5 kW, stackLevel=1) Accepted    | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.8  | MeterValues (Flow 1, after first SetChargingProfile)           | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.9  | SetChargingProfile (update, 7.4 kW, stackLevel=1) Accepted     | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.10 | MeterValues (Flow 1, after second SetChargingProfile)          | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.11 | StopTransaction (manual card tap, reason=Local)                | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.12 | StatusNotification Finishing (Flow 1, EV still plugged)        | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.13 | StatusNotification Available (Flow 1, EV unplug)               | Depends on 6.2 (EV plug)                                                                                | <b>WARN</b> |
| 6.14 | StatusNotification Preparing (EV plug, Flow 2)                 | EV_WAIT_SEC=0 skipped<br><i>Connect physical EV to connector and rerun</i>                              | <b>WARN</b> |
| 6.15 | RemoteStartTransaction Accepted                                | HTTP 200                                                                                                | <b>PASS</b> |
| "    |                                                                |                                                                                                         |             |

| Item | Test Description                                        | Detail / Evidence                                                                                             | Result      |
|------|---------------------------------------------------------|---------------------------------------------------------------------------------------------------------------|-------------|
| 6.16 | StartTransaction (triggered by RemoteStart)             | charging_session_state not observed on MQTT in 30 s                                                           | <b>WARN</b> |
| 6.17 | StatusNotification Charging (Flow 2)                    | Charging status not observed on MQTT in 20 s                                                                  | <b>WARN</b> |
| 6.18 | MeterValues (Flow 2, before SetChargingProfile)         | MeterValues not observed on MQTT in 15 s                                                                      | <b>WARN</b> |
| 6.19 | SetChargingProfile (Flow 2, TxProfile 5 kW) Accepted    | HTTP 200                                                                                                      | <b>PASS</b> |
| ""   |                                                         |                                                                                                               |             |
| 6.20 | MeterValues (Flow 2, after first SetChargingProfile)    | MeterValues not observed on MQTT in 15 s                                                                      | <b>WARN</b> |
| 6.21 | SetChargingProfile (Flow 2, update 7.4 kW) Accepted     | HTTP 200                                                                                                      | <b>PASS</b> |
| ""   |                                                         |                                                                                                               |             |
| 6.22 | MeterValues (Flow 2, after second SetChargingProfile)   | MeterValues not observed on MQTT in 15 s                                                                      | <b>WARN</b> |
| 6.23 | RemoteStopTransaction Accepted                          | HTTP 200                                                                                                      | <b>PASS</b> |
| ""   |                                                         |                                                                                                               |             |
| 6.24 | StopTransaction (triggered by RemoteStop)               | session_state idle/finished not observed on MQTT in 25 s                                                      | <b>WARN</b> |
| 6.25 | StatusNotification Finishing (Flow 2, EV still plugged) | Finishing not observed on MQTT in 15 s<br><i>Some implementations skip Finishing go directly to Available</i> | <b>WARN</b> |
| 6.26 | StatusNotification Available (Flow 2, EV unplug)        | Available not observed on MQTT in 30 s<br>unplug EV                                                           | <b>WARN</b> |

### 3 Notes

#### Charging profile flows

SetChargingProfile (TxProfile) commands are issued via MEA REST API during an active session. MeterValues before/after profile changes confirm the power limit adjustment.

#### EV-dependent items

All charging session items require a physical EV. Without an EV the test records WARN.