

Partner: AVPro Edge  
Models: MXNet  
Device Type: Network Switching



## GENERAL INFORMATION

|                                    |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
|------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>SIMPLWINDOWS NAME:</b>          | AVPro Edge MXNet DestinationRouter v2.6                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| <b>CATEGORY:</b>                   | AVPro Edge MXNet                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
| <b>VERSION:</b>                    | 2.6                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| <b>SUMMARY:</b>                    | <p>This module works in conjunction with the AVPro MXNet CommandProcessor v2.6 module and the AVPro MXNet Encoder/Decoder v2.6 modules to process routes between encoders and decoders. The full suite of AVPro MXNet modules includes:</p> <ul style="list-style-type: none"><li>• AVPro MXNet CommandProcessor v2.6</li><li>• AVPro MXNet Encoder v2.6</li><li>• AVPro MXNet Decoder v2.6</li><li>• AVPro MXNet SerialPort v2.6</li><li>• AVPro MXNet IRPort v2.6</li><li>• AVPro MXNet CEC v2.6</li><li>• AVPro MXNet DestinationRouter v2.6</li><li>• AVPro MXNet MultiDestinationRouter v2.6</li><li>• AVPro MXNet VW DecoderAssign v2.6</li><li>• AVPro MXNet VW Layout v2.6</li><li>• AVPro MXNet VW LayoutRecall v2.6</li><li>• AVPro MXNet 10G VW LayoutRecall v2.6</li><li>• AVPro MXNet Matrix PresetRecall v2.6</li><li>• AVPro MXNet Matrix Macro v2.6</li></ul> |
| <b>GENERAL NOTES:</b>              | <p>This module requires one instance of the AVPro MXNet CommandProcessor v2.6 module to register with, a matching instance of the AVPro MXNet Encoder v2.6 for each encoder for source routing, and a matching instance of the AVPro MXNet Decoder v2.6 for the decoder to route to.</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| <b>CRESTRON HARDWARE REQUIRED:</b> | 4-Series processor, 3-Series processor                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                        |
| <b>SETUP OF CRESTRON HARDWARE:</b> | N/A                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| <b>VENDOR FIRMWARE:</b>            | <p>Net 1G Control Box v2.4<br/>MXNet 1G Encoder v3.39<br/>MXNet 1G Decoder v4.21<br/>MXNet 10G Control Box v3.28<br/>MXNet 10G Encoder v1.25<br/>MXNet 10G Decoder v1.25</p>                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
| <b>VENDOR SETUP:</b>               | N/A                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                           |

Partner: AVPro Edge  
Models: MXNet  
Device Type: Network Switching



## PARAMETERS:

|                                 |                                                                                                                                                                                                                                                                                                                                                           |
|---------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Command_Processor_ID</b>     | The unique identifier of the command processor module that this module registers with.                                                                                                                                                                                                                                                                    |
| <b>Matrix_Destination_Index</b> | Specifies the unique index of the decoder this module is associated with.<br>The AVPro MXNet Decoder v2.6 with each associated Destination_Index must be added to the program for the module to know which decoder in your system to route.                                                                                                               |
| <b>MultiRoute Group ID List</b> | Specifies the group ID for this destination router. When assigned a MultiRoute Group ID, this destination router can receive route commands as part of a broadcast from the AVPro MXNet MultiDestinationRouter module. This destination router can be assigned multiple groups, each group ID should be specified in a comma-separated list.<br>EX: 1,5,6 |

Partner: AVPro Edge  
Models: MXNet  
Device Type: Network Switching

**CONTROL:**

|                        |   |                                                                                                                                                                                                              |
|------------------------|---|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                        |   | Analog value specifies the encoder with the matching Matrix Source Index parameter.                                                                                                                          |
| <b>Source_Route</b>    | A | To clear the route, use a 0 on this signal.<br><br>The AVPro MXNet Encoder v2.6 with each associated Source_Index must be added to the program for the module to know which encoder in your system to route. |
| <b>Take_Route</b>      | D | Pulse to send the enabled route types from the encoder specified by the Source_Route analog input to the decoder specified by the Matrix Destination Index.                                                  |
| <b>Enable_Video</b>    | D | Latch high to enable video routing from the source route specified by the <b>Source_Route</b> analog input.                                                                                                  |
| <b>Enable_Audio</b>    | D | Latch high to enable audio routing from the source route specified by the <b>Source_Route</b> analog input.                                                                                                  |
| <b>Enable_USB</b>      | D | Latch high to enable USB routing from the source route specified by the <b>Source_Route</b> analog input.                                                                                                    |
| <b>Enable_Infrared</b> | D | Latch high to enable infrared routing from the source route specified by the <b>Source_Route</b> analog input.                                                                                               |
| <b>Enable_Serial</b>   | D | Latch high to enable serial routing from the source route specified by the <b>Source_Route</b> analog input.                                                                                                 |

Partner: AVPro Edge  
Models: MXNet  
Device Type: Network Switching

**FEEDBACK:**

|                           |   |                                                                                                                                  |
|---------------------------|---|----------------------------------------------------------------------------------------------------------------------------------|
| <b>Is_Initialized</b>     | D | Digital high indicates this module has been initialized with the command processor module.                                       |
| <b>Is_Online_Fb</b>       | D | High to indicate that the matching endpoint is online and available for control. If the device is offline, no control will work. |
| <b>Source_Video_Fb</b>    | A | Integer value indicates the routed video source to decoder with the matching Matrix Destination Index.                           |
| <b>Source_Audio_Fb</b>    | A | Integer value indicates the routed audio source to decoder with the matching Matrix Destination Index.                           |
| <b>Source_USB_Fb</b>      | A | Integer value indicates the routed USB source to decoder with the matching Matrix Destination Index.                             |
| <b>Source_Infrared_Fb</b> | A | Integer value indicates the routed infrared source to decoder with the matching Matrix Destination Index.                        |
| <b>Source_Serial_Fb</b>   | A | Integer value indicates the routed serial source to decoder with the matching Matrix Destination Index.                          |

Partner: AVPro Edge  
Models: MXNet  
Device Type: Network Switching



## TESTING:

|                                         |                                |
|-----------------------------------------|--------------------------------|
|                                         | VC4 v4.0000.00007              |
| <b>OPS USED FOR TESTING:</b>            | CP4 v2.8001.00086.01           |
|                                         | CP3 v1.8001.0214.01            |
| <b>SIMPL WINDOWS USED FOR TESTING:</b>  | 4.2500.04                      |
| <b>CRES DB USED FOR TESTING:</b>        | 219.0500.001.00                |
| <b>DEVICE DATABASE:</b>                 | 200.28000.002.00               |
| <b>SYMBOL LIBRARY USED FOR TESTING:</b> | 1191                           |
| <b>SAMPLE PROGRAM:</b>                  | AVPro Edge MXNet v2.6 Demo.smw |

## REVISION HISTORY:

- v1.0 – Initial Release
- v1.1 – Fixed SerialPort transmitted and received data.
  - Made updates to allow a Wallplate Encoder to initialize with this suite.
- v1.2 – Isolated serial communication queue to provide device control responsiveness.
  - Corrected unsolicited data parsing impacting hotplug detected and resolution.
- v2.0 – Added “Offline” functionality.
  - Polling will happen more frequently but will only poll for one component’s states at a time. This prevents serial control from getting backed up behind a global system poll.
- v2.1 – Added volume support for applicable 10G decoders.
  - Added support for 10G videowall support with “10G VW Layout”
- v2.2 - Change 1G video wall input select to new faster API command
- v2.3 – Added CEC support for Encoders.
- v2.4 – Added Matrix PresetRecall and Matrix Macro module.
- v2.5 – Added video preview urls to encoder module.
- v2.6 – Reconnect time increased from 30 seconds to 90 seconds.