

Partner: AVPro Edge
Models: MXNet
Device Type: Network Switching



GENERAL INFORMATION

SIMPLWINDOWS NAME:	AVPro Edge MXNet Matrix Macro v2.6
CATEGORY:	AVPro Edge MXNet
VERSION:	2.6
SUMMARY:	This module works in conjunction with the AVPro MXNet CommandProcessor v2.6 module and the AVPro MXNet DestinationRouter v2.6 module to generate simultaneous macro route commands to multiple decoders. The full suite of AVPro MXNet modules includes: • AVPro MXNet CommandProcessor v2.6 • AVPro MXNet Encoder v2.6 • AVPro MXNet Decoder v2.6 • AVPro MXNet SerialPort v2.6 • AVPro MXNet IRPort v2.6 • AVPro MXNet CEC v2.6 • AVPro MXNet DestinationRouter v2.6 • AVPro MXNet MultiDestinationRouter v2.6 • AVPro MXNet VW DecoderAssign v2.6 • AVPro MXNet VW Layout v2.6 • AVPro MXNet VW LayoutRecall v2.6 • AVPro MXNet 10G VW LayoutRecall v2.6 • AVPro MXNet Matrix PresetRecall v2.6 • AVPro MXNet Matrix Macro v2.6
GENERAL NOTES:	This module requires one instance of the AVPro MXNet CommandProcessor v2.6 module to register with, and at least one instance of the AVPro MXNet DestinationRouter v2.6 module. Practical applications would require two or more DestinationRouter modules.
CRESTRON HARDWARE REQUIRED:	4-Series processor, 3-Series processor
SETUP OF CRESTRON HARDWARE:	N/A
VENDOR FIRMWARE:	MXNet 1G Control Box v2.4 MXNet 1G Encoder v3.39 MXNet 1G Decoder v4.21 MXNet 10G Control Box v3.28 MXNet 10G Encoder v1.25 MXNet 10G Decoder v1.25
VENDOR SETUP:	N/A

Partner: AVPro Edge
Models: MXNet
Device Type: Network Switching



PARAMETERS:

Command_Processor_ID

The unique identifier of the command processor module that this module registers with.

Partner: AVPro Edge
Models: MXNet
Device Type: Network Switching

**CONTROL:**

Macro_Name	S	Text value specifies the name of the macro to recall.
Macro_Save	D	Pulse to save the macro specified by the Current_Macro_Name serial output.
Macro_Recall	D	Pulse to recall the macro specified by the Current_Macro_Name serial output.

Partner: AVPro Edge
Models: MXNet
Device Type: Network Switching

**FEEDBACK:**

Current_Macro_Name	S	Text value indicates the name of the macro that will be saved and recalled.
Last_Recalled_Macro	S	Text value indicates the name of the last macro recalled.

Partner: AVPro Edge
Models: MXNet
Device Type: Network Switching

**TESTING:**

	VC4 v4.0000.00007
OPS USED FOR TESTING:	CP4 v2.8001.00086.01
	CP3 v1.8001.0214.01

SIMPL WINDOWS USED FOR TESTING:	4.2500.04
--	-----------

CRES DB USED FOR TESTING:	219.0500.001.00
----------------------------------	-----------------

DEVICE DATABASE:	200.28000.002.00
-------------------------	------------------

SYMBOL LIBRARY USED FOR TESTING:	1191
---	------

SAMPLE PROGRAM:	AVPro Edge MXNet v2.6 Demo.smw
------------------------	--------------------------------

REVISION HISTORY:

- v1.0 – Initial Release
- v1.1 – Fixed SerialPort transmitted and received data.
 - Made updates to allow a Wallplate Encoder to initialize with this suite.
- v1.2 – Isolated serial communication queue to provide device control responsiveness.
 - Corrected unsolicited data parsing impacting hotplug detected and resolution.
- v2.0 – Added “Offline” functionality.
 - Polling will happen more frequently but will only poll for one component’s states at a time. This prevents serial control from getting backed up behind a global system poll.
- v2.1 – Added volume support for applicable 10G decoders.
 - Added support for 10G videowall support with “10G VW Layout”
- v2.2 - Change 1G video wall input select to new faster API command
- v2.3 – Added CEC support for Encoders.
- v2.4 – Added Matrix PresetRecall and Matrix Macro module.
- V2.5 – Added preview urls to encoder module.
- v2.6 – Reconnect time increased from 30 seconds to 90 seconds.