

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Building Management Systems
Manufacturer: Acuity
Firmware Version: N/A
Model(s): Fresco FCS AVI

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
2.08.0001-b006	1.4.2

Version History

Module Version	Date	Notes
1_0_0_0	3/5/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='Fresco FCS AVI')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='Fresco FCS AVI')</code>

Set Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command ChannelLevel	Value 0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
Qualifier Key 'Area'	Qualifier Value '1' – '255'	Qualifier Value 'Current Area'	
Qualifier Key 'Room'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
	'D'	'E'	'F'
	'G'	'H'	'I'
	'J'	'K'	'L'
	'M'	'N'	'O'
	'P'	'Q'	'R'
	'S'	'T'	'U'
	'V'	'W'	'X'
	'Current Room'		
Qualifier Key 'Fade'	Qualifier Value 0 to 1000 in steps of 1		
# ChannelLevel example InterfaceName.Set('ChannelLevel', 100, {'ID': '1', 'Area': '1', 'Room': 'A', 'Fade': 1000})			
Command InputLevel	Value 0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
# InputLevel example InterfaceName.Set('InputLevel', 100, {'ID': '1'})			
Command InputShadeControl	Value 'Raise'	Value 'Lower'	Value 'Stop'
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
# InputShadeControl example InterfaceName.Set('InputShadeControl', 'Raise', {'ID': '1'})			

Command RoomLinkCommand	Value 'String'		
# RoomLinkCommand example InterfaceName.Set('RoomLinkCommand', 'String')			
Command RoomUnlinkCommand	Value 'String'		
# RoomUnlinkCommand example InterfaceName.Set('RoomUnlinkCommand', 'String')			
Command SceneLevel	Value 0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
Qualifier Key 'Area'	Qualifier Value '1' – '255'	Qualifier Value 'Current Area'	
Qualifier Key 'Room'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
	'D'	'E'	'F'
	'G'	'H'	'I'
	'J'	'K'	'L'
	'M'	'N'	'O'
	'P'	'Q'	'R'
	'S'	'T'	'U'
	'V'	'W'	'X'
	'Current Room'		
# SceneLevel example InterfaceName.Set('SceneLevel', 100, {'ID': '1', 'Area': '1', 'Room': 'A'})			
Command ZoneIntensity	Value 0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value 1 to 65535 in steps of 1		
Qualifier Key 'Fade'	Qualifier Value 0 to 1000 in steps of 1		
# ZoneIntensity example InterfaceName.Set('ZoneIntensity', 100, {'ID': 65535, 'Fade': 1000})			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command ChannelLevelStatus	Value 0 – 100		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
Qualifier Key 'Area'	Qualifier Value '1' – '255'	Qualifier Value 'Current Area'	
Qualifier Key 'Room'	Qualifier Value 'A'	Qualifier Value 'B'	Qualifier Value 'C'
	'D'	'E'	'F'
	'G'	'H'	'I'
	'J'	'K'	'L'
	'M'	'N'	'O'
	'P'	'Q'	'R'
	'S'	'T'	'U'
	'V'	'W'	'X'
	'Current Room'		
# ChannelLevelStatus examples InterfaceName.Update('ChannelLevelStatus', {'ID': '1', 'Area': '1', 'Room': 'A'}) Value = InterfaceName.ReadStatus('ChannelLevelStatus', {'ID': '1', 'Area': '1', 'Room': 'A'}) InterfaceName.SubscribeStatus('ChannelLevelStatus', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'		Value 'Disconnected'
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command	Value		

Global Scripter Module Communication Sheet

InputLevel	0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
# InputLevel examples InterfaceName.Update('InputLevel', {'ID': '1'}) Value = InterfaceName.ReadStatus('InputLevel', {'ID': '1'}) InterfaceName.SubscribeStatus('InputLevel', None, FeedbackHandler)			
Command SceneLevel	Value 0 to 100 in steps of 1		
Qualifier Key 'ID'	Qualifier Value '1' – '36'		
Qualifier Key 'Area'	Qualifier Value '1' – '255'	Qualifier Value 'Current Area'	
Qualifier Key 'Room'	Qualifier Value 'A' 'D' 'G' 'J' 'M' 'P' 'S' 'V' 'Current Room'	Qualifier Value 'B' 'E' 'H' 'K' 'N' 'Q' 'T' 'W'	Qualifier Value 'C' 'F' 'I' 'L' 'O' 'R' 'U' 'X'
# SceneLevel examples InterfaceName.Update('SceneLevel', {'ID': '1', 'Area': '1', 'Room': 'A'}) Value = InterfaceName.ReadStatus('SceneLevel', {'ID': '1', 'Area': '1', 'Room': 'A'}) InterfaceName.SubscribeStatus('SceneLevel', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to Captive Screw

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Signal
TxD		TxD
RxD		RxD
GND		GND



Appendix A. Set Commands

Channel Level 0 Area 1 Fade 0 ID 1 Room A	channel 1 0 1 A 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room A	channel 1 100 1 A 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room A	channel 1 0 1 A 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room A	channel 1 100 1 A 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room B	channel 1 0 1 B 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room B	channel 1 100 1 B 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room B	channel 1 0 1 B 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room B	channel 1 100 1 B 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room C	channel 1 0 1 C 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room C	channel 1 100 1 C 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room C	channel 1 0 1 C 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room C	channel 1 100 1 C 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room Current Room	channel 1 0 1 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room Current Room	channel 1 100 1 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room Current Room	channel 1 0 1 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room Current Room	channel 1 100 1 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room D	channel 1 0 1 D 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room D	channel 1 100 1 D 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room D	channel 1 0 1 D 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room D	channel 1 100 1 D 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room E	channel 1 0 1 E 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room E	channel 1 100 1 E 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room E	channel 1 0 1 E 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room E	channel 1 100 1 E 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room F	channel 1 0 1 F 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room F	channel 1 100 1 F 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room F	channel 1 0 1 F 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room F	channel 1 100 1 F 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room G	channel 1 0 1 G 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room G	channel 1 100 1 G 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room G	channel 1 0 1 G 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room G	channel 1 100 1 G 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room H	channel 1 0 1 H 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area 1 Fade 0 ID 1 Room H	channel 1 100 1 H 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room H	channel 1 0 1 H 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room H	channel 1 100 1 H 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room I	channel 1 0 1 I 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room I	channel 1 100 1 I 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room I	channel 1 0 1 I 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room I	channel 1 100 1 I 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room J	channel 1 0 1 J 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room J	channel 1 100 1 J 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room J	channel 1 0 1 J 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room J	channel 1 100 1 J 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room K	channel 1 0 1 K 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room K	channel 1 100 1 K 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room K	channel 1 0 1 K 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room K	channel 1 100 1 K 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room L	channel 1 0 1 L 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room L	channel 1 100 1 L 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room L	channel 1 0 1 L 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room L	channel 1 100 1 L 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room M	channel 1 0 1 M 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room M	channel 1 100 1 M 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room M	channel 1 0 1 M 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room M	channel 1 100 1 M 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room N	channel 1 0 1 N 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room N	channel 1 100 1 N 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room N	channel 1 0 1 N 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room N	channel 1 100 1 N 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room O	channel 1 0 1 O 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room O	channel 1 100 1 O 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room O	channel 1 0 1 O 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room O	channel 1 100 1 O 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room P	channel 1 0 1 P 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room P	channel 1 100 1 P 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room P	channel 1 0 1 P 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room P	channel 1 100 1 P 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room Q	channel 1 0 1 Q 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room Q	channel 1 100 1 Q 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room Q	channel 1 0 1 Q 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room Q	channel 1 100 1 Q 1000\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area 1 Fade 0 ID 1 Room R	channel 1 0 1 R 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room R	channel 1 100 1 R 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room R	channel 1 0 1 R 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room R	channel 1 100 1 R 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room S	channel 1 0 1 S 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room S	channel 1 100 1 S 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room S	channel 1 0 1 S 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room S	channel 1 100 1 S 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room T	channel 1 0 1 T 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room T	channel 1 100 1 T 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room T	channel 1 0 1 T 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room T	channel 1 100 1 T 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room U	channel 1 0 1 U 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room U	channel 1 100 1 U 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room U	channel 1 0 1 U 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room U	channel 1 100 1 U 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room V	channel 1 0 1 V 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room V	channel 1 100 1 V 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room V	channel 1 0 1 V 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room V	channel 1 100 1 V 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room W	channel 1 0 1 W 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room W	channel 1 100 1 W 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room W	channel 1 0 1 W 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room W	channel 1 100 1 W 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 1 Room X	channel 1 0 1 X 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 1 Room X	channel 1 100 1 X 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 1 Room X	channel 1 0 1 X 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 1 Room X	channel 1 100 1 X 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room A	channel 1 0 255 A 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room A	channel 1 100 255 A 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room A	channel 1 0 255 A 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room A	channel 1 100 255 A 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room B	channel 1 0 255 B 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room B	channel 1 100 255 B 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room B	channel 1 0 255 B 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room B	channel 1 100 255 B 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room C	channel 1 0 255 C 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room C	channel 1 100 255 C 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room C	channel 1 0 255 C 1000\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area 255 Fade 1000 ID 1 Room C	channel 1 100 255 C 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room Current Room	channel 1 0 255 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room Current Room	channel 1 100 255 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room Current Room	channel 1 0 255 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room Current Room	channel 1 100 255 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room D	channel 1 0 255 D 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room D	channel 1 100 255 D 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room D	channel 1 0 255 D 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room D	channel 1 100 255 D 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room E	channel 1 0 255 E 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room E	channel 1 100 255 E 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room E	channel 1 0 255 E 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room E	channel 1 100 255 E 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room F	channel 1 0 255 F 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room F	channel 1 100 255 F 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room F	channel 1 0 255 F 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room F	channel 1 100 255 F 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room G	channel 1 0 255 G 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room G	channel 1 100 255 G 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room G	channel 1 0 255 G 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room G	channel 1 100 255 G 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room H	channel 1 0 255 H 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room H	channel 1 100 255 H 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room H	channel 1 0 255 H 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room H	channel 1 100 255 H 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room I	channel 1 0 255 I 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room I	channel 1 100 255 I 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room I	channel 1 0 255 I 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room I	channel 1 100 255 I 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room J	channel 1 0 255 J 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room J	channel 1 100 255 J 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room J	channel 1 0 255 J 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room J	channel 1 100 255 J 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room K	channel 1 0 255 K 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room K	channel 1 100 255 K 0\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level 0 Area 255 Fade 1000 ID 1 Room K	channel 1 0 255 K 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room K	channel 1 100 255 K 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room L	channel 1 0 255 L 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room L	channel 1 100 255 L 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room L	channel 1 0 255 L 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room L	channel 1 100 255 L 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room M	channel 1 0 255 M 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room M	channel 1 100 255 M 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room M	channel 1 0 255 M 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room M	channel 1 100 255 M 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room N	channel 1 0 255 N 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room N	channel 1 100 255 N 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room N	channel 1 0 255 N 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room N	channel 1 100 255 N 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room O	channel 1 0 255 O 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room O	channel 1 100 255 O 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room O	channel 1 0 255 O 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room O	channel 1 100 255 O 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room P	channel 1 0 255 P 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room P	channel 1 100 255 P 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room P	channel 1 0 255 P 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room P	channel 1 100 255 P 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room Q	channel 1 0 255 Q 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room Q	channel 1 100 255 Q 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room Q	channel 1 0 255 Q 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room Q	channel 1 100 255 Q 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room R	channel 1 0 255 R 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room R	channel 1 100 255 R 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room R	channel 1 0 255 R 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room R	channel 1 100 255 R 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room S	channel 1 0 255 S 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room S	channel 1 100 255 S 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room S	channel 1 0 255 S 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room S	channel 1 100 255 S 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room T	channel 1 0 255 T 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room T	channel 1 100 255 T 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room T	channel 1 0 255 T 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room T	channel 1 100 255 T 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room U	channel 1 0 255 U 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area 255 Fade 0 ID 1 Room U	channel 1 100 255 U 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room U	channel 1 0 255 U 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room U	channel 1 100 255 U 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room V	channel 1 0 255 V 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room V	channel 1 100 255 V 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room V	channel 1 0 255 V 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room V	channel 1 100 255 V 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room W	channel 1 0 255 W 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room W	channel 1 100 255 W 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room W	channel 1 0 255 W 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room W	channel 1 100 255 W 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 1 Room X	channel 1 0 255 X 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 1 Room X	channel 1 100 255 X 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 1 Room X	channel 1 0 255 X 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 1 Room X	channel 1 100 255 X 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room A	channel 1 0 A 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room A	channel 1 100 A 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room A	channel 1 0 A 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room A	channel 1 100 A 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room B	channel 1 0 B 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room B	channel 1 100 B 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room B	channel 1 0 B 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room B	channel 1 100 B 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room C	channel 1 0 C 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room C	channel 1 100 C 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room C	channel 1 0 C 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room C	channel 1 100 C 1000\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 0 ID 1 Room Current Room	channel 1 0 0 \x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room Current Room	channel 1 100 0 \x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room Current Room	channel 1 0 1000 \x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room Current Room	channel 1 100 1000 \x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room D	channel 1 0 D 0 \x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room D	channel 1 100 D 0 \x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room D	channel 1 0 D 1000 \x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room D	channel 1 100 D 1000 \x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room E	channel 1 0 E 0 \x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room E	channel 1 100 E 0 \x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room E	channel 1 0 E 1000 \x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room E	channel 1 100 E 1000 \x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room F	channel 1 0 F 0 \x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room F	channel 1 100 F 0 \x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room F	channel 1 0 F 1000 \x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room F	channel 1 100 F 1000 \x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room G	channel 1 0 G 0 \x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room G	channel 1 100 G 0 \x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room G	channel 1 0 G 1000 \x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room G	channel 1 100 G 1000 \x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 0 ID 1 Room H	channel 1 0 H 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room H	channel 1 100 H 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room H	channel 1 0 H 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room H	channel 1 100 H 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room I	channel 1 0 I 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room I	channel 1 100 I 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room I	channel 1 0 I 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room I	channel 1 100 I 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room J	channel 1 0 J 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room J	channel 1 100 J 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room J	channel 1 0 J 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room J	channel 1 100 J 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room K	channel 1 0 K 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room K	channel 1 100 K 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room K	channel 1 0 K 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room K	channel 1 100 K 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room L	channel 1 0 L 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room L	channel 1 100 L 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room L	channel 1 0 L 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room L	channel 1 100 L 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room M	channel 1 0 M 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area Current Area Fade 0 ID 1 Room M	channel 1 100 M 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room M	channel 1 0 M 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room M	channel 1 100 M 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room N	channel 1 0 N 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room N	channel 1 100 N 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room N	channel 1 0 N 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room N	channel 1 100 N 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room O	channel 1 0 0 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room O	channel 1 100 0 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room O	channel 1 0 0 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room O	channel 1 100 0 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room P	channel 1 0 P 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room P	channel 1 100 P 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room P	channel 1 0 P 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room P	channel 1 100 P 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room Q	channel 1 0 Q 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room Q	channel 1 100 Q 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room Q	channel 1 0 Q 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room Q	channel 1 100 Q 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room R	channel 1 0 R 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area Current Area Fade 0 ID 1 Room R	channel 1 100 R 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room R	channel 1 0 R 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room R	channel 1 100 R 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room S	channel 1 0 S 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room S	channel 1 100 S 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room S	channel 1 0 S 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room S	channel 1 100 S 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room T	channel 1 0 T 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room T	channel 1 100 T 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room T	channel 1 0 T 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room T	channel 1 100 T 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room U	channel 1 0 U 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room U	channel 1 100 U 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room U	channel 1 0 U 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room U	channel 1 100 U 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room V	channel 1 0 V 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room V	channel 1 100 V 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room V	channel 1 0 V 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room V	channel 1 100 V 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room W	channel 1 0 W 0\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level 100 Area Current Area Fade 0 ID 1 Room W	channel 1 100 W 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room W	channel 1 0 W 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room W	channel 1 100 W 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 1 Room X	channel 1 0 X 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 1 Room X	channel 1 100 X 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 1 Room X	channel 1 0 X 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 1 Room X	channel 1 100 X 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room A	channel 36 0 1 A 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room A	channel 36 100 1 A 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room A	channel 36 0 1 A 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room A	channel 36 100 1 A 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room B	channel 36 0 1 B 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room B	channel 36 100 1 B 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room B	channel 36 0 1 B 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room B	channel 36 100 1 B 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room C	channel 36 0 1 C 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room C	channel 36 100 1 C 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room C	channel 36 0 1 C 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room C	channel 36 100 1 C 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room Current Room	channel 36 0 1 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room Current Room	channel 36 100 1 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room Current Room	channel 36 0 1 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room Current Room	channel 36 100 1 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room D	channel 36 0 1 D 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room D	channel 36 100 1 D 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room D	channel 36 0 1 D 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room D	channel 36 100 1 D 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room E	channel 36 0 1 E 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room E	channel 36 100 1 E 0\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level 0 Area 1 Fade 1000 ID 36 Room E	channel 36 0 1 E 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room E	channel 36 100 1 E 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room F	channel 36 0 1 F 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room F	channel 36 100 1 F 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room F	channel 36 0 1 F 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room F	channel 36 100 1 F 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room G	channel 36 0 1 G 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room G	channel 36 100 1 G 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room G	channel 36 0 1 G 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room G	channel 36 100 1 G 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room H	channel 36 0 1 H 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room H	channel 36 100 1 H 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room H	channel 36 0 1 H 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room H	channel 36 100 1 H 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room I	channel 36 0 1 I 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room I	channel 36 100 1 I 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room I	channel 36 0 1 I 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room I	channel 36 100 1 I 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room J	channel 36 0 1 J 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room J	channel 36 100 1 J 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room J	channel 36 0 1 J 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room J	channel 36 100 1 J 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room K	channel 36 0 1 K 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room K	channel 36 100 1 K 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room K	channel 36 0 1 K 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room K	channel 36 100 1 K 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room L	channel 36 0 1 L 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room L	channel 36 100 1 L 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room L	channel 36 0 1 L 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room L	channel 36 100 1 L 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room M	channel 36 0 1 M 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room M	channel 36 100 1 M 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room M	channel 36 0 1 M 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room M	channel 36 100 1 M 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room N	channel 36 0 1 N 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room N	channel 36 100 1 N 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room N	channel 36 0 1 N 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room N	channel 36 100 1 N 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room O	channel 36 0 1 O 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area 1 Fade 0 ID 36 Room O	channel 36 100 1 0 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room O	channel 36 0 1 0 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room O	channel 36 100 1 0 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room P	channel 36 0 1 P 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room P	channel 36 100 1 P 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room P	channel 36 0 1 P 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room P	channel 36 100 1 P 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room Q	channel 36 0 1 Q 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room Q	channel 36 100 1 Q 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room Q	channel 36 0 1 Q 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room Q	channel 36 100 1 Q 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room R	channel 36 0 1 R 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room R	channel 36 100 1 R 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room R	channel 36 0 1 R 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room R	channel 36 100 1 R 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room S	channel 36 0 1 S 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room S	channel 36 100 1 S 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room S	channel 36 0 1 S 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room S	channel 36 100 1 S 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room T	channel 36 0 1 T 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room T	channel 36 100 1 T 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room T	channel 36 0 1 T 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room T	channel 36 100 1 T 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room U	channel 36 0 1 U 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room U	channel 36 100 1 U 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room U	channel 36 0 1 U 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room U	channel 36 100 1 U 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room V	channel 36 0 1 V 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room V	channel 36 100 1 V 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room V	channel 36 0 1 V 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room V	channel 36 100 1 V 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room W	channel 36 0 1 W 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room W	channel 36 100 1 W 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room W	channel 36 0 1 W 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room W	channel 36 100 1 W 1000\x0D\x0A
Channel Level 0 Area 1 Fade 0 ID 36 Room X	channel 36 0 1 X 0\x0D\x0A
Channel Level 100 Area 1 Fade 0 ID 36 Room X	channel 36 100 1 X 0\x0D\x0A
Channel Level 0 Area 1 Fade 1000 ID 36 Room X	channel 36 0 1 X 1000\x0D\x0A
Channel Level 100 Area 1 Fade 1000 ID 36 Room X	channel 36 100 1 X 1000\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level 0 Area 255 Fade 0 ID 36 Room A	channel 36 0 255 A 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room A	channel 36 100 255 A 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room A	channel 36 0 255 A 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room A	channel 36 100 255 A 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room B	channel 36 0 255 B 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room B	channel 36 100 255 B 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room B	channel 36 0 255 B 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room B	channel 36 100 255 B 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room C	channel 36 0 255 C 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room C	channel 36 100 255 C 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room C	channel 36 0 255 C 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room C	channel 36 100 255 C 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room Current Room	channel 36 0 255 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room Current Room	channel 36 100 255 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room Current Room	channel 36 0 255 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room Current Room	channel 36 100 255 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room D	channel 36 0 255 D 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room D	channel 36 100 255 D 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room D	channel 36 0 255 D 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room D	channel 36 100 255 D 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room E	channel 36 0 255 E 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room E	channel 36 100 255 E 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room E	channel 36 0 255 E 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room E	channel 36 100 255 E 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room F	channel 36 0 255 F 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room F	channel 36 100 255 F 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room F	channel 36 0 255 F 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room F	channel 36 100 255 F 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room G	channel 36 0 255 G 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room G	channel 36 100 255 G 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room G	channel 36 0 255 G 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room G	channel 36 100 255 G 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room H	channel 36 0 255 H 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room H	channel 36 100 255 H 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room H	channel 36 0 255 H 1000\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 100 Area 255 Fade 1000 ID 36 Room H	channel 36 100 255 H 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room I	channel 36 0 255 I 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room I	channel 36 100 255 I 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room I	channel 36 0 255 I 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room I	channel 36 100 255 I 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room J	channel 36 0 255 J 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room J	channel 36 100 255 J 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room J	channel 36 0 255 J 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room J	channel 36 100 255 J 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room K	channel 36 0 255 K 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room K	channel 36 100 255 K 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room K	channel 36 0 255 K 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room K	channel 36 100 255 K 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room L	channel 36 0 255 L 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room L	channel 36 100 255 L 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room L	channel 36 0 255 L 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room L	channel 36 100 255 L 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room M	channel 36 0 255 M 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room M	channel 36 100 255 M 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room M	channel 36 0 255 M 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room M	channel 36 100 255 M 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room N	channel 36 0 255 N 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room N	channel 36 100 255 N 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room N	channel 36 0 255 N 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room N	channel 36 100 255 N 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room O	channel 36 0 255 O 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room O	channel 36 100 255 O 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room O	channel 36 0 255 O 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room O	channel 36 100 255 O 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room P	channel 36 0 255 P 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room P	channel 36 100 255 P 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room P	channel 36 0 255 P 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room P	channel 36 100 255 P 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room Q	channel 36 0 255 Q 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room Q	channel 36 100 255 Q 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room Q	channel 36 0 255 Q 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room Q	channel 36 100 255 Q 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room R	channel 36 0 255 R 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room R	channel 36 100 255 R 0\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level 0 Area 255 Fade 1000 ID 36 Room R	channel 36 0 255 R 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room R	channel 36 100 255 R 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room S	channel 36 0 255 S 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room S	channel 36 100 255 S 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room S	channel 36 0 255 S 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room S	channel 36 100 255 S 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room T	channel 36 0 255 T 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room T	channel 36 100 255 T 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room T	channel 36 0 255 T 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room T	channel 36 100 255 T 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room U	channel 36 0 255 U 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room U	channel 36 100 255 U 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room U	channel 36 0 255 U 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room U	channel 36 100 255 U 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room V	channel 36 0 255 V 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room V	channel 36 100 255 V 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room V	channel 36 0 255 V 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room V	channel 36 100 255 V 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room W	channel 36 0 255 W 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room W	channel 36 100 255 W 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room W	channel 36 0 255 W 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room W	channel 36 100 255 W 1000\x0D\x0A
Channel Level 0 Area 255 Fade 0 ID 36 Room X	channel 36 0 255 X 0\x0D\x0A
Channel Level 100 Area 255 Fade 0 ID 36 Room X	channel 36 100 255 X 0\x0D\x0A
Channel Level 0 Area 255 Fade 1000 ID 36 Room X	channel 36 0 255 X 1000\x0D\x0A
Channel Level 100 Area 255 Fade 1000 ID 36 Room X	channel 36 100 255 X 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room A	channel 36 0 A 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room A	channel 36 100 A 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room A	channel 36 0 A 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room A	channel 36 100 A 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room B	channel 36 0 B 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room B	channel 36 100 B 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 1000 ID 36 Room B	channel 36 0 B 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room B	channel 36 100 B 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room C	channel 36 0 C 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room C	channel 36 100 C 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room C	channel 36 0 C 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room C	channel 36 100 C 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room Current Room	channel 36 0 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room Current Room	channel 36 100 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room Current Room	channel 36 0 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room Current Room	channel 36 100 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room D	channel 36 0 D 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room D	channel 36 100 D 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room D	channel 36 0 D 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room D	channel 36 100 D 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room E	channel 36 0 E 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room E	channel 36 100 E 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room E	channel 36 0 E 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room E	channel 36 100 E 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room F	channel 36 0 F 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room F	channel 36 100 F 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 1000 ID 36 Room F	channel 36 0 F 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room F	channel 36 100 F 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room G	channel 36 0 G 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room G	channel 36 100 G 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room G	channel 36 0 G 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room G	channel 36 100 G 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room H	channel 36 0 H 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room H	channel 36 100 H 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room H	channel 36 0 H 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room H	channel 36 100 H 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room I	channel 36 0 I 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room I	channel 36 100 I 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room I	channel 36 0 I 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room I	channel 36 100 I 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room J	channel 36 0 J 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room J	channel 36 100 J 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room J	channel 36 0 J 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room J	channel 36 100 J 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room K	channel 36 0 K 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room K	channel 36 100 K 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 1000 ID 36 Room K	channel 36 0 K 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room K	channel 36 100 K 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room L	channel 36 0 L 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room L	channel 36 100 L 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room L	channel 36 0 L 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room L	channel 36 100 L 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room M	channel 36 0 M 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room M	channel 36 100 M 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room M	channel 36 0 M 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room M	channel 36 100 M 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room N	channel 36 0 N 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room N	channel 36 100 N 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room N	channel 36 0 N 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room N	channel 36 100 N 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room O	channel 36 0 O 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room O	channel 36 100 O 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room O	channel 36 0 O 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room O	channel 36 100 O 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room P	channel 36 0 P 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room P	channel 36 100 P 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 1000 ID 36 Room P	channel 36 0 P 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room P	channel 36 100 P 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room Q	channel 36 0 Q 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room Q	channel 36 100 Q 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room Q	channel 36 0 Q 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room Q	channel 36 100 Q 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room R	channel 36 0 R 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room R	channel 36 100 R 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room R	channel 36 0 R 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room R	channel 36 100 R 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room S	channel 36 0 S 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room S	channel 36 100 S 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room S	channel 36 0 S 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room S	channel 36 100 S 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room T	channel 36 0 T 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room T	channel 36 100 T 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room T	channel 36 0 T 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room T	channel 36 100 T 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room U	channel 36 0 U 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room U	channel 36 100 U 0\x0D\x0A

Global Scripter Module Communication Sheet

Channel Level 0 Area Current Area Fade 1000 ID 36 Room U	channel 36 0 U 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room U	channel 36 100 U 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room V	channel 36 0 V 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room V	channel 36 100 V 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room V	channel 36 0 V 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room V	channel 36 100 V 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room W	channel 36 0 W 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room W	channel 36 100 W 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room W	channel 36 0 W 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room W	channel 36 100 W 1000\x0D\x0A
Channel Level 0 Area Current Area Fade 0 ID 36 Room X	channel 36 0 X 0\x0D\x0A
Channel Level 100 Area Current Area Fade 0 ID 36 Room X	channel 36 100 X 0\x0D\x0A
Channel Level 0 Area Current Area Fade 1000 ID 36 Room X	channel 36 0 X 1000\x0D\x0A
Channel Level 100 Area Current Area Fade 1000 ID 36 Room X	channel 36 100 X 1000\x0D\x0A
Input Level 0 ID 1	input 1 0\x0D\x0A
Input Level 100 ID 1	input 1 100\x0D\x0A
Input Level 0 ID 36	input 36 0\x0D\x0A
Input Level 100 ID 36	input 36 100\x0D\x0A
Input Shade Control Lower ID 1	input 1 lower\x0D\x0A
Input Shade Control Raise ID 1	input 1 raise\x0D\x0A
Input Shade Control Stop ID 1	input 1 stop\x0D\x0A
Input Shade Control Lower ID 36	input 36 lower\x0D\x0A
Input Shade Control Raise ID 36	input 36 raise\x0D\x0A
Input Shade Control Stop ID 36	input 36 stop\x0D\x0A
Scene Level 0 Area 1 ID 1 Room A	scene 1 0 1 A\x0D\x0A
Scene Level 100 Area 1 ID 1 Room A	scene 1 100 1 A\x0D\x0A

Global Scripter Module Communication Sheet

Scene Level 0 Area 1 ID 1 Room B	scene 1 0 1 B\x0D\x0A
Scene Level 100 Area 1 ID 1 Room B	scene 1 100 1 B\x0D\x0A
Scene Level 0 Area 1 ID 1 Room C	scene 1 0 1 C\x0D\x0A
Scene Level 100 Area 1 ID 1 Room C	scene 1 100 1 C\x0D\x0A
Scene Level 0 Area 1 ID 1 Room Current Room	scene 1 0 1\x0D\x0A
Scene Level 100 Area 1 ID 1 Room Current Room	scene 1 100 1\x0D\x0A
Scene Level 0 Area 1 ID 1 Room D	scene 1 0 1 D\x0D\x0A
Scene Level 100 Area 1 ID 1 Room D	scene 1 100 1 D\x0D\x0A
Scene Level 0 Area 1 ID 1 Room E	scene 1 0 1 E\x0D\x0A
Scene Level 100 Area 1 ID 1 Room E	scene 1 100 1 E\x0D\x0A
Scene Level 0 Area 1 ID 1 Room F	scene 1 0 1 F\x0D\x0A
Scene Level 100 Area 1 ID 1 Room F	scene 1 100 1 F\x0D\x0A
Scene Level 0 Area 1 ID 1 Room G	scene 1 0 1 G\x0D\x0A
Scene Level 100 Area 1 ID 1 Room G	scene 1 100 1 G\x0D\x0A
Scene Level 0 Area 1 ID 1 Room H	scene 1 0 1 H\x0D\x0A
Scene Level 100 Area 1 ID 1 Room H	scene 1 100 1 H\x0D\x0A
Scene Level 0 Area 1 ID 1 Room I	scene 1 0 1 I\x0D\x0A
Scene Level 100 Area 1 ID 1 Room I	scene 1 100 1 I\x0D\x0A
Scene Level 0 Area 1 ID 1 Room J	scene 1 0 1 J\x0D\x0A
Scene Level 100 Area 1 ID 1 Room J	scene 1 100 1 J\x0D\x0A
Scene Level 0 Area 1 ID 1 Room K	scene 1 0 1 K\x0D\x0A
Scene Level 100 Area 1 ID 1 Room K	scene 1 100 1 K\x0D\x0A
Scene Level 0 Area 1 ID 1 Room L	scene 1 0 1 L\x0D\x0A
Scene Level 100 Area 1 ID 1 Room L	scene 1 100 1 L\x0D\x0A
Scene Level 0 Area 1 ID 1 Room M	scene 1 0 1 M\x0D\x0A
Scene Level 100 Area 1 ID 1 Room M	scene 1 100 1 M\x0D\x0A
Scene Level 0 Area 1 ID 1 Room N	scene 1 0 1 N\x0D\x0A
Scene Level 100 Area 1 ID 1 Room N	scene 1 100 1 N\x0D\x0A
Scene Level 0 Area 1 ID 1 Room O	scene 1 0 1 O\x0D\x0A
Scene Level 100 Area 1 ID 1 Room O	scene 1 100 1 O\x0D\x0A
Scene Level 0 Area 1 ID 1 Room P	scene 1 0 1 P\x0D\x0A
Scene Level 100 Area 1 ID 1 Room P	scene 1 100 1 P\x0D\x0A
Scene Level 0 Area 1 ID 1 Room Q	scene 1 0 1 Q\x0D\x0A
Scene Level 100 Area 1 ID 1 Room Q	scene 1 100 1 Q\x0D\x0A
Scene Level 0 Area 1 ID 1 Room R	scene 1 0 1 R\x0D\x0A
Scene Level 100 Area 1 ID 1 Room R	scene 1 100 1 R\x0D\x0A
Scene Level 0 Area 1 ID 1 Room S	scene 1 0 1 S\x0D\x0A
Scene Level 100 Area 1 ID 1 Room S	scene 1 100 1 S\x0D\x0A
Scene Level 0 Area 1 ID 1 Room T	scene 1 0 1 T\x0D\x0A

Global Scripter Module Communication Sheet

Scene Level 100 Area 1 ID 1 Room T	scene 1 100 1 T\x0D\x0A
Scene Level 0 Area 1 ID 1 Room U	scene 1 0 1 U\x0D\x0A
Scene Level 100 Area 1 ID 1 Room U	scene 1 100 1 U\x0D\x0A
Scene Level 0 Area 1 ID 1 Room V	scene 1 0 1 V\x0D\x0A
Scene Level 100 Area 1 ID 1 Room V	scene 1 100 1 V\x0D\x0A
Scene Level 0 Area 1 ID 1 Room W	scene 1 0 1 W\x0D\x0A
Scene Level 100 Area 1 ID 1 Room W	scene 1 100 1 W\x0D\x0A
Scene Level 0 Area 1 ID 1 Room X	scene 1 0 1 X\x0D\x0A
Scene Level 100 Area 1 ID 1 Room X	scene 1 100 1 X\x0D\x0A
Scene Level 0 Area 255 ID 1 Room A	scene 1 0 255 A\x0D\x0A
Scene Level 100 Area 255 ID 1 Room A	scene 1 100 255 A\x0D\x0A
Scene Level 0 Area 255 ID 1 Room B	scene 1 0 255 B\x0D\x0A
Scene Level 100 Area 255 ID 1 Room B	scene 1 100 255 B\x0D\x0A
Scene Level 0 Area 255 ID 1 Room C	scene 1 0 255 C\x0D\x0A
Scene Level 100 Area 255 ID 1 Room C	scene 1 100 255 C\x0D\x0A
Scene Level 0 Area 255 ID 1 Room Current Room	scene 1 0 255\x0D\x0A
Scene Level 100 Area 255 ID 1 Room Current Room	scene 1 100 255\x0D\x0A
Scene Level 0 Area 255 ID 1 Room D	scene 1 0 255 D\x0D\x0A
Scene Level 100 Area 255 ID 1 Room D	scene 1 100 255 D\x0D\x0A
Scene Level 0 Area 255 ID 1 Room E	scene 1 0 255 E\x0D\x0A
Scene Level 100 Area 255 ID 1 Room E	scene 1 100 255 E\x0D\x0A
Scene Level 0 Area 255 ID 1 Room F	scene 1 0 255 F\x0D\x0A
Scene Level 100 Area 255 ID 1 Room F	scene 1 100 255 F\x0D\x0A
Scene Level 0 Area 255 ID 1 Room G	scene 1 0 255 G\x0D\x0A
Scene Level 100 Area 255 ID 1 Room G	scene 1 100 255 G\x0D\x0A
Scene Level 0 Area 255 ID 1 Room H	scene 1 0 255 H\x0D\x0A
Scene Level 100 Area 255 ID 1 Room H	scene 1 100 255 H\x0D\x0A
Scene Level 0 Area 255 ID 1 Room I	scene 1 0 255 I\x0D\x0A
Scene Level 100 Area 255 ID 1 Room I	scene 1 100 255 I\x0D\x0A
Scene Level 0 Area 255 ID 1 Room J	scene 1 0 255 J\x0D\x0A
Scene Level 100 Area 255 ID 1 Room J	scene 1 100 255 J\x0D\x0A
Scene Level 0 Area 255 ID 1 Room K	scene 1 0 255 K\x0D\x0A
Scene Level 100 Area 255 ID 1 Room K	scene 1 100 255 K\x0D\x0A
Scene Level 0 Area 255 ID 1 Room L	scene 1 0 255 L\x0D\x0A
Scene Level 100 Area 255 ID 1 Room L	scene 1 100 255 L\x0D\x0A
Scene Level 0 Area 255 ID 1 Room M	scene 1 0 255 M\x0D\x0A
Scene Level 100 Area 255 ID 1 Room M	scene 1 100 255 M\x0D\x0A
Scene Level 0 Area 255 ID 1 Room N	scene 1 0 255 N\x0D\x0A
Scene Level 100 Area 255 ID 1 Room N	scene 1 100 255 N\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level 0 Area 255 ID 1 Room O	scene 1 0 255 O\x0D\x0A
Scene Level 100 Area 255 ID 1 Room O	scene 1 100 255 O\x0D\x0A
Scene Level 0 Area 255 ID 1 Room P	scene 1 0 255 P\x0D\x0A
Scene Level 100 Area 255 ID 1 Room P	scene 1 100 255 P\x0D\x0A
Scene Level 0 Area 255 ID 1 Room Q	scene 1 0 255 Q\x0D\x0A
Scene Level 100 Area 255 ID 1 Room Q	scene 1 100 255 Q\x0D\x0A
Scene Level 0 Area 255 ID 1 Room R	scene 1 0 255 R\x0D\x0A
Scene Level 100 Area 255 ID 1 Room R	scene 1 100 255 R\x0D\x0A
Scene Level 0 Area 255 ID 1 Room S	scene 1 0 255 S\x0D\x0A
Scene Level 100 Area 255 ID 1 Room S	scene 1 100 255 S\x0D\x0A
Scene Level 0 Area 255 ID 1 Room T	scene 1 0 255 T\x0D\x0A
Scene Level 100 Area 255 ID 1 Room T	scene 1 100 255 T\x0D\x0A
Scene Level 0 Area 255 ID 1 Room U	scene 1 0 255 U\x0D\x0A
Scene Level 100 Area 255 ID 1 Room U	scene 1 100 255 U\x0D\x0A
Scene Level 0 Area 255 ID 1 Room V	scene 1 0 255 V\x0D\x0A
Scene Level 100 Area 255 ID 1 Room V	scene 1 100 255 V\x0D\x0A
Scene Level 0 Area 255 ID 1 Room W	scene 1 0 255 W\x0D\x0A
Scene Level 100 Area 255 ID 1 Room W	scene 1 100 255 W\x0D\x0A
Scene Level 0 Area 255 ID 1 Room X	scene 1 0 255 X\x0D\x0A
Scene Level 100 Area 255 ID 1 Room X	scene 1 100 255 X\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room A	scene 1 0 A\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room A	scene 1 100 A\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room B	scene 1 0 B\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room B	scene 1 100 B\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room C	scene 1 0 C\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room C	scene 1 100 C\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room Current Room	scene 1 0\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room Current Room	scene 1 100\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room D	scene 1 0 D\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room D	scene 1 100 D\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room E	scene 1 0 E\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room E	scene 1 100 E\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room F	scene 1 0 F\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room F	scene 1 100 F\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room G	scene 1 0 G\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room G	scene 1 100 G\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room H	scene 1 0 H\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level 100 Area Current Area ID 1 Room H	scene 1 100 H\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room I	scene 1 0 I\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room I	scene 1 100 I\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room J	scene 1 0 J\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room J	scene 1 100 J\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room K	scene 1 0 K\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room K	scene 1 100 K\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room L	scene 1 0 L\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room L	scene 1 100 L\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room M	scene 1 0 M\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room M	scene 1 100 M\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room N	scene 1 0 N\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room N	scene 1 100 N\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room O	scene 1 0 O\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room O	scene 1 100 O\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room P	scene 1 0 P\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room P	scene 1 100 P\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room Q	scene 1 0 Q\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room Q	scene 1 100 Q\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room R	scene 1 0 R\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room R	scene 1 100 R\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room S	scene 1 0 S\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room S	scene 1 100 S\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room T	scene 1 0 T\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room T	scene 1 100 T\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room U	scene 1 0 U\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room U	scene 1 100 U\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room V	scene 1 0 V\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room V	scene 1 100 V\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room W	scene 1 0 W\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room W	scene 1 100 W\x0D\x0A
Scene Level 0 Area Current Area ID 1 Room X	scene 1 0 X\x0D\x0A
Scene Level 100 Area Current Area ID 1 Room X	scene 1 100 X\x0D\x0A
Scene Level 0 Area 1 ID 36 Room A	scene 36 0 1 A\x0D\x0A
Scene Level 100 Area 1 ID 36 Room A	scene 36 100 1 A\x0D\x0A
Scene Level 0 Area 1 ID 36 Room B	scene 36 0 1 B\x0D\x0A
Scene Level 100 Area 1 ID 36 Room B	scene 36 100 1 B\x0D\x0A
Scene Level 0 Area 1 ID 36 Room C	scene 36 0 1 C\x0D\x0A
Scene Level 100 Area 1 ID 36 Room C	scene 36 100 1 C\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level 0 Area 1 ID 36 Room Current Room	scene 36 0 1 \x0D\x0A
Scene Level 100 Area 1 ID 36 Room Current Room	scene 36 100 1 \x0D\x0A
Scene Level 0 Area 1 ID 36 Room D	scene 36 0 1 D \x0D\x0A
Scene Level 100 Area 1 ID 36 Room D	scene 36 100 1 D \x0D\x0A
Scene Level 0 Area 1 ID 36 Room E	scene 36 0 1 E \x0D\x0A
Scene Level 100 Area 1 ID 36 Room E	scene 36 100 1 E \x0D\x0A
Scene Level 0 Area 1 ID 36 Room F	scene 36 0 1 F \x0D\x0A
Scene Level 100 Area 1 ID 36 Room F	scene 36 100 1 F \x0D\x0A
Scene Level 0 Area 1 ID 36 Room G	scene 36 0 1 G \x0D\x0A
Scene Level 100 Area 1 ID 36 Room G	scene 36 100 1 G \x0D\x0A
Scene Level 0 Area 1 ID 36 Room H	scene 36 0 1 H \x0D\x0A
Scene Level 100 Area 1 ID 36 Room H	scene 36 100 1 H \x0D\x0A
Scene Level 0 Area 1 ID 36 Room I	scene 36 0 1 I \x0D\x0A
Scene Level 100 Area 1 ID 36 Room I	scene 36 100 1 I \x0D\x0A
Scene Level 0 Area 1 ID 36 Room J	scene 36 0 1 J \x0D\x0A
Scene Level 100 Area 1 ID 36 Room J	scene 36 100 1 J \x0D\x0A
Scene Level 0 Area 1 ID 36 Room K	scene 36 0 1 K \x0D\x0A
Scene Level 100 Area 1 ID 36 Room K	scene 36 100 1 K \x0D\x0A
Scene Level 0 Area 1 ID 36 Room L	scene 36 0 1 L \x0D\x0A
Scene Level 100 Area 1 ID 36 Room L	scene 36 100 1 L \x0D\x0A
Scene Level 0 Area 1 ID 36 Room M	scene 36 0 1 M \x0D\x0A
Scene Level 100 Area 1 ID 36 Room M	scene 36 100 1 M \x0D\x0A
Scene Level 0 Area 1 ID 36 Room N	scene 36 0 1 N \x0D\x0A
Scene Level 100 Area 1 ID 36 Room N	scene 36 100 1 N \x0D\x0A
Scene Level 0 Area 1 ID 36 Room O	scene 36 0 1 O \x0D\x0A
Scene Level 100 Area 1 ID 36 Room O	scene 36 100 1 O \x0D\x0A
Scene Level 0 Area 1 ID 36 Room P	scene 36 0 1 P \x0D\x0A
Scene Level 100 Area 1 ID 36 Room P	scene 36 100 1 P \x0D\x0A
Scene Level 0 Area 1 ID 36 Room Q	scene 36 0 1 Q \x0D\x0A
Scene Level 100 Area 1 ID 36 Room Q	scene 36 100 1 Q \x0D\x0A
Scene Level 0 Area 1 ID 36 Room R	scene 36 0 1 R \x0D\x0A
Scene Level 100 Area 1 ID 36 Room R	scene 36 100 1 R \x0D\x0A
Scene Level 0 Area 1 ID 36 Room S	scene 36 0 1 S \x0D\x0A
Scene Level 100 Area 1 ID 36 Room S	scene 36 100 1 S \x0D\x0A
Scene Level 0 Area 1 ID 36 Room T	scene 36 0 1 T \x0D\x0A
Scene Level 100 Area 1 ID 36 Room T	scene 36 100 1 T \x0D\x0A
Scene Level 0 Area 1 ID 36 Room U	scene 36 0 1 U \x0D\x0A
Scene Level 100 Area 1 ID 36 Room U	scene 36 100 1 U \x0D\x0A
Scene Level 0 Area 1 ID 36 Room V	scene 36 0 1 V \x0D\x0A

Global Scripter Module Communication Sheet

Scene Level 100 Area 1 ID 36 Room V	scene 36 100 1 V\x0D\x0A
Scene Level 0 Area 1 ID 36 Room W	scene 36 0 1 W\x0D\x0A
Scene Level 100 Area 1 ID 36 Room W	scene 36 100 1 W\x0D\x0A
Scene Level 0 Area 1 ID 36 Room X	scene 36 0 1 X\x0D\x0A
Scene Level 100 Area 1 ID 36 Room X	scene 36 100 1 X\x0D\x0A
Scene Level 0 Area 255 ID 36 Room A	scene 36 0 255 A\x0D\x0A
Scene Level 100 Area 255 ID 36 Room A	scene 36 100 255 A\x0D\x0A
Scene Level 0 Area 255 ID 36 Room B	scene 36 0 255 B\x0D\x0A
Scene Level 100 Area 255 ID 36 Room B	scene 36 100 255 B\x0D\x0A
Scene Level 0 Area 255 ID 36 Room C	scene 36 0 255 C\x0D\x0A
Scene Level 100 Area 255 ID 36 Room C	scene 36 100 255 C\x0D\x0A
Scene Level 0 Area 255 ID 36 Room Current Room	scene 36 0 255\x0D\x0A
Scene Level 100 Area 255 ID 36 Room Current Room	scene 36 100 255\x0D\x0A
Scene Level 0 Area 255 ID 36 Room D	scene 36 0 255 D\x0D\x0A
Scene Level 100 Area 255 ID 36 Room D	scene 36 100 255 D\x0D\x0A
Scene Level 0 Area 255 ID 36 Room E	scene 36 0 255 E\x0D\x0A
Scene Level 100 Area 255 ID 36 Room E	scene 36 100 255 E\x0D\x0A
Scene Level 0 Area 255 ID 36 Room F	scene 36 0 255 F\x0D\x0A
Scene Level 100 Area 255 ID 36 Room F	scene 36 100 255 F\x0D\x0A
Scene Level 0 Area 255 ID 36 Room G	scene 36 0 255 G\x0D\x0A
Scene Level 100 Area 255 ID 36 Room G	scene 36 100 255 G\x0D\x0A
Scene Level 0 Area 255 ID 36 Room H	scene 36 0 255 H\x0D\x0A
Scene Level 100 Area 255 ID 36 Room H	scene 36 100 255 H\x0D\x0A
Scene Level 0 Area 255 ID 36 Room I	scene 36 0 255 I\x0D\x0A
Scene Level 100 Area 255 ID 36 Room I	scene 36 100 255 I\x0D\x0A
Scene Level 0 Area 255 ID 36 Room J	scene 36 0 255 J\x0D\x0A
Scene Level 100 Area 255 ID 36 Room J	scene 36 100 255 J\x0D\x0A
Scene Level 0 Area 255 ID 36 Room K	scene 36 0 255 K\x0D\x0A
Scene Level 100 Area 255 ID 36 Room K	scene 36 100 255 K\x0D\x0A
Scene Level 0 Area 255 ID 36 Room L	scene 36 0 255 L\x0D\x0A
Scene Level 100 Area 255 ID 36 Room L	scene 36 100 255 L\x0D\x0A
Scene Level 0 Area 255 ID 36 Room M	scene 36 0 255 M\x0D\x0A
Scene Level 100 Area 255 ID 36 Room M	scene 36 100 255 M\x0D\x0A
Scene Level 0 Area 255 ID 36 Room N	scene 36 0 255 N\x0D\x0A
Scene Level 100 Area 255 ID 36 Room N	scene 36 100 255 N\x0D\x0A
Scene Level 0 Area 255 ID 36 Room O	scene 36 0 255 O\x0D\x0A
Scene Level 100 Area 255 ID 36 Room O	scene 36 100 255 O\x0D\x0A
Scene Level 0 Area 255 ID 36 Room P	scene 36 0 255 P\x0D\x0A
Scene Level 100 Area 255 ID 36 Room P	scene 36 100 255 P\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level 0 Area 255 ID 36 Room Q	scene 36 0 255 Q\x0D\x0A
Scene Level 100 Area 255 ID 36 Room Q	scene 36 100 255 Q\x0D\x0A
Scene Level 0 Area 255 ID 36 Room R	scene 36 0 255 R\x0D\x0A
Scene Level 100 Area 255 ID 36 Room R	scene 36 100 255 R\x0D\x0A
Scene Level 0 Area 255 ID 36 Room S	scene 36 0 255 S\x0D\x0A
Scene Level 100 Area 255 ID 36 Room S	scene 36 100 255 S\x0D\x0A
Scene Level 0 Area 255 ID 36 Room T	scene 36 0 255 T\x0D\x0A
Scene Level 100 Area 255 ID 36 Room T	scene 36 100 255 T\x0D\x0A
Scene Level 0 Area 255 ID 36 Room U	scene 36 0 255 U\x0D\x0A
Scene Level 100 Area 255 ID 36 Room U	scene 36 100 255 U\x0D\x0A
Scene Level 0 Area 255 ID 36 Room V	scene 36 0 255 V\x0D\x0A
Scene Level 100 Area 255 ID 36 Room V	scene 36 100 255 V\x0D\x0A
Scene Level 0 Area 255 ID 36 Room W	scene 36 0 255 W\x0D\x0A
Scene Level 100 Area 255 ID 36 Room W	scene 36 100 255 W\x0D\x0A
Scene Level 0 Area 255 ID 36 Room X	scene 36 0 255 X\x0D\x0A
Scene Level 100 Area 255 ID 36 Room X	scene 36 100 255 X\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room A	scene 36 0 A\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room A	scene 36 100 A\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room B	scene 36 0 B\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room B	scene 36 100 B\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room C	scene 36 0 C\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room C	scene 36 100 C\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room Current Room	scene 36 0\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room Current Room	scene 36 100\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room D	scene 36 0 D\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room D	scene 36 100 D\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room E	scene 36 0 E\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room E	scene 36 100 E\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room F	scene 36 0 F\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room F	scene 36 100 F\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room G	scene 36 0 G\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room G	scene 36 100 G\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room H	scene 36 0 H\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room H	scene 36 100 H\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room I	scene 36 0 I\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room I	scene 36 100 I\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room J	scene 36 0 J\x0D\x0A

Global Scripter Module Communication Sheet

Scene Level 100 Area Current Area ID 36 Room J	scene 36 100 J\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room K	scene 36 0 K\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room K	scene 36 100 K\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room L	scene 36 0 L\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room L	scene 36 100 L\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room M	scene 36 0 M\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room M	scene 36 100 M\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room N	scene 36 0 N\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room N	scene 36 100 N\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room O	scene 36 0 O\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room O	scene 36 100 O\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room P	scene 36 0 P\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room P	scene 36 100 P\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room Q	scene 36 0 Q\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room Q	scene 36 100 Q\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room R	scene 36 0 R\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room R	scene 36 100 R\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room S	scene 36 0 S\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room S	scene 36 100 S\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room T	scene 36 0 T\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room T	scene 36 100 T\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room U	scene 36 0 U\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room U	scene 36 100 U\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room V	scene 36 0 V\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room V	scene 36 100 V\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room W	scene 36 0 W\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room W	scene 36 100 W\x0D\x0A
Scene Level 0 Area Current Area ID 36 Room X	scene 36 0 X\x0D\x0A
Scene Level 100 Area Current Area ID 36 Room X	scene 36 100 X\x0D\x0A
Zone Intensity 0 Fade 0 ID 1	zone 1 0 0\x0D\x0A
Zone Intensity 100 Fade 0 ID 1	zone 1 100 0\x0D\x0A
Zone Intensity 0 Fade 1000 ID 1	zone 1 0 1000\x0D\x0A
Zone Intensity 100 Fade 1000 ID 1	zone 1 100 1000\x0D\x0A
Zone Intensity 0 Fade 0 ID 65535	zone 65535 0 0\x0D\x0A
Zone Intensity 100 Fade 0 ID 65535	zone 65535 100 0\x0D\x0A
Zone Intensity 0 Fade 1000 ID 65535	zone 65535 0 1000\x0D\x0A
Zone Intensity 100 Fade 1000 ID 65535	zone 65535 100 1000\x0D\x0A

Appendix B. Update Commands

Channel Level Status Area 1 ID 1 Room A	status channel ALL 1 A\x0D\x0A
Channel Level Status Area 1 ID 1 Room B	status channel ALL 1 B\x0D\x0A
Channel Level Status Area 1 ID 1 Room C	status channel ALL 1 C\x0D\x0A
Channel Level Status Area 1 ID 1 Room Current Room	status channel ALL 1\x0D\x0A
Channel Level Status Area 1 ID 1 Room D	status channel ALL 1 D\x0D\x0A
Channel Level Status Area 1 ID 1 Room E	status channel ALL 1 E\x0D\x0A
Channel Level Status Area 1 ID 1 Room F	status channel ALL 1 F\x0D\x0A
Channel Level Status Area 1 ID 1 Room G	status channel ALL 1 G\x0D\x0A
Channel Level Status Area 1 ID 1 Room H	status channel ALL 1 H\x0D\x0A
Channel Level Status Area 1 ID 1 Room I	status channel ALL 1 I\x0D\x0A
Channel Level Status Area 1 ID 1 Room J	status channel ALL 1 J\x0D\x0A
Channel Level Status Area 1 ID 1 Room K	status channel ALL 1 K\x0D\x0A
Channel Level Status Area 1 ID 1 Room L	status channel ALL 1 L\x0D\x0A
Channel Level Status Area 1 ID 1 Room M	status channel ALL 1 M\x0D\x0A
Channel Level Status Area 1 ID 1 Room N	status channel ALL 1 N\x0D\x0A
Channel Level Status Area 1 ID 1 Room O	status channel ALL 1 O\x0D\x0A
Channel Level Status Area 1 ID 1 Room P	status channel ALL 1 P\x0D\x0A
Channel Level Status Area 1 ID 1 Room Q	status channel ALL 1 Q\x0D\x0A
Channel Level Status Area 1 ID 1 Room R	status channel ALL 1 R\x0D\x0A
Channel Level Status Area 1 ID 1 Room S	status channel ALL 1 S\x0D\x0A
Channel Level Status Area 1 ID 1 Room T	status channel ALL 1 T\x0D\x0A
Channel Level Status Area 1 ID 1 Room U	status channel ALL 1 U\x0D\x0A
Channel Level Status Area 1 ID 1 Room V	status channel ALL 1 V\x0D\x0A
Channel Level Status Area 1 ID 1 Room W	status channel ALL 1 W\x0D\x0A
Channel Level Status Area 1 ID 1 Room X	status channel ALL 1 X\x0D\x0A
Channel Level Status Area 255 ID 1 Room A	status channel ALL 255 A\x0D\x0A
Channel Level Status Area 255 ID 1 Room B	status channel ALL 255 B\x0D\x0A
Channel Level Status Area 255 ID 1 Room C	status channel ALL 255 C\x0D\x0A
Channel Level Status Area 255 ID 1 Room Current Room	status channel ALL 255\x0D\x0A
Channel Level Status Area 255 ID 1 Room D	status channel ALL 255 D\x0D\x0A
Channel Level Status Area 255 ID 1 Room E	status channel ALL 255 E\x0D\x0A
Channel Level Status Area 255 ID 1 Room F	status channel ALL 255 F\x0D\x0A
Channel Level Status Area 255 ID 1 Room G	status channel ALL 255 G\x0D\x0A
Channel Level Status Area 255 ID 1 Room H	status channel ALL 255 H\x0D\x0A
Channel Level Status Area 255 ID 1 Room I	status channel ALL 255 I\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level Status Area 255 ID 1 Room J	status channel ALL 255 J\x0D\x0A
Channel Level Status Area 255 ID 1 Room K	status channel ALL 255 K\x0D\x0A
Channel Level Status Area 255 ID 1 Room L	status channel ALL 255 L\x0D\x0A
Channel Level Status Area 255 ID 1 Room M	status channel ALL 255 M\x0D\x0A
Channel Level Status Area 255 ID 1 Room N	status channel ALL 255 N\x0D\x0A
Channel Level Status Area 255 ID 1 Room O	status channel ALL 255 O\x0D\x0A
Channel Level Status Area 255 ID 1 Room P	status channel ALL 255 P\x0D\x0A
Channel Level Status Area 255 ID 1 Room Q	status channel ALL 255 Q\x0D\x0A
Channel Level Status Area 255 ID 1 Room R	status channel ALL 255 R\x0D\x0A
Channel Level Status Area 255 ID 1 Room S	status channel ALL 255 S\x0D\x0A
Channel Level Status Area 255 ID 1 Room T	status channel ALL 255 T\x0D\x0A
Channel Level Status Area 255 ID 1 Room U	status channel ALL 255 U\x0D\x0A
Channel Level Status Area 255 ID 1 Room V	status channel ALL 255 V\x0D\x0A
Channel Level Status Area 255 ID 1 Room W	status channel ALL 255 W\x0D\x0A
Channel Level Status Area 255 ID 1 Room X	status channel ALL 255 X\x0D\x0A
Channel Level Status Area Current Area ID 1 Room A	status channel ALL A\x0D\x0A
Channel Level Status Area Current Area ID 1 Room B	status channel ALL B\x0D\x0A
Channel Level Status Area Current Area ID 1 Room C	status channel ALL C\x0D\x0A
Channel Level Status Area Current Area ID 1 Room Current Room	status channel ALL \x0D\x0A
Channel Level Status Area Current Area ID 1 Room D	status channel ALL D\x0D\x0A
Channel Level Status Area Current Area ID 1 Room E	status channel ALL E\x0D\x0A
Channel Level Status Area Current Area ID 1 Room F	status channel ALL F\x0D\x0A
Channel Level Status Area Current Area ID 1 Room G	status channel ALL G\x0D\x0A
Channel Level Status Area Current Area ID 1 Room H	status channel ALL H\x0D\x0A
Channel Level Status Area Current Area ID 1 Room I	status channel ALL I\x0D\x0A
Channel Level Status Area Current Area ID 1 Room J	status channel ALL J\x0D\x0A
Channel Level Status Area Current Area ID 1 Room K	status channel ALL K\x0D\x0A
Channel Level Status Area Current Area ID 1 Room L	status channel ALL L\x0D\x0A
Channel Level Status Area Current Area ID 1 Room M	status channel ALL M\x0D\x0A
Channel Level Status Area Current Area ID 1 Room N	status channel ALL N\x0D\x0A
Channel Level Status Area Current Area ID 1 Room O	status channel ALL O\x0D\x0A
Channel Level Status Area Current Area ID 1 Room P	status channel ALL P\x0D\x0A
Channel Level Status Area Current Area ID 1 Room Q	status channel ALL Q\x0D\x0A
Channel Level Status Area Current Area ID 1 Room R	status channel ALL R\x0D\x0A
Channel Level Status Area Current Area ID 1 Room S	status channel ALL S\x0D\x0A
Channel Level Status Area Current Area ID 1 Room T	status channel ALL T\x0D\x0A
Channel Level Status Area Current Area ID 1 Room U	status channel ALL U\x0D\x0A
Channel Level Status Area Current Area ID 1 Room V	status channel ALL V\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level Status Area Current Area ID 1 Room W	status channel ALL W\x0D\x0A
Channel Level Status Area Current Area ID 1 Room X	status channel ALL X\x0D\x0A
Channel Level Status Area 1 ID 36 Room A	status channel ALL 1 A\x0D\x0A
Channel Level Status Area 1 ID 36 Room B	status channel ALL 1 B\x0D\x0A
Channel Level Status Area 1 ID 36 Room C	status channel ALL 1 C\x0D\x0A
Channel Level Status Area 1 ID 36 Room Current Room	status channel ALL 1\x0D\x0A
Channel Level Status Area 1 ID 36 Room D	status channel ALL 1 D\x0D\x0A
Channel Level Status Area 1 ID 36 Room E	status channel ALL 1 E\x0D\x0A
Channel Level Status Area 1 ID 36 Room F	status channel ALL 1 F\x0D\x0A
Channel Level Status Area 1 ID 36 Room G	status channel ALL 1 G\x0D\x0A
Channel Level Status Area 1 ID 36 Room H	status channel ALL 1 H\x0D\x0A
Channel Level Status Area 1 ID 36 Room I	status channel ALL 1 I\x0D\x0A
Channel Level Status Area 1 ID 36 Room J	status channel ALL 1 J\x0D\x0A
Channel Level Status Area 1 ID 36 Room K	status channel ALL 1 K\x0D\x0A
Channel Level Status Area 1 ID 36 Room L	status channel ALL 1 L\x0D\x0A
Channel Level Status Area 1 ID 36 Room M	status channel ALL 1 M\x0D\x0A
Channel Level Status Area 1 ID 36 Room N	status channel ALL 1 N\x0D\x0A
Channel Level Status Area 1 ID 36 Room O	status channel ALL 1 O\x0D\x0A
Channel Level Status Area 1 ID 36 Room P	status channel ALL 1 P\x0D\x0A
Channel Level Status Area 1 ID 36 Room Q	status channel ALL 1 Q\x0D\x0A
Channel Level Status Area 1 ID 36 Room R	status channel ALL 1 R\x0D\x0A
Channel Level Status Area 1 ID 36 Room S	status channel ALL 1 S\x0D\x0A
Channel Level Status Area 1 ID 36 Room T	status channel ALL 1 T\x0D\x0A
Channel Level Status Area 1 ID 36 Room U	status channel ALL 1 U\x0D\x0A
Channel Level Status Area 1 ID 36 Room V	status channel ALL 1 V\x0D\x0A
Channel Level Status Area 1 ID 36 Room W	status channel ALL 1 W\x0D\x0A
Channel Level Status Area 1 ID 36 Room X	status channel ALL 1 X\x0D\x0A
Channel Level Status Area 255 ID 36 Room A	status channel ALL 255 A\x0D\x0A
Channel Level Status Area 255 ID 36 Room B	status channel ALL 255 B\x0D\x0A
Channel Level Status Area 255 ID 36 Room C	status channel ALL 255 C\x0D\x0A
Channel Level Status Area 255 ID 36 Room Current Room	status channel ALL 255\x0D\x0A
Channel Level Status Area 255 ID 36 Room D	status channel ALL 255 D\x0D\x0A
Channel Level Status Area 255 ID 36 Room E	status channel ALL 255 E\x0D\x0A
Channel Level Status Area 255 ID 36 Room F	status channel ALL 255 F\x0D\x0A
Channel Level Status Area 255 ID 36 Room G	status channel ALL 255 G\x0D\x0A
Channel Level Status Area 255 ID 36 Room H	status channel ALL 255 H\x0D\x0A
Channel Level Status Area 255 ID 36 Room I	status channel ALL 255 I\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level Status Area 255 ID 36 Room J	status channel ALL 255 J\x0D\x0A
Channel Level Status Area 255 ID 36 Room K	status channel ALL 255 K\x0D\x0A
Channel Level Status Area 255 ID 36 Room L	status channel ALL 255 L\x0D\x0A
Channel Level Status Area 255 ID 36 Room M	status channel ALL 255 M\x0D\x0A
Channel Level Status Area 255 ID 36 Room N	status channel ALL 255 N\x0D\x0A
Channel Level Status Area 255 ID 36 Room O	status channel ALL 255 O\x0D\x0A
Channel Level Status Area 255 ID 36 Room P	status channel ALL 255 P\x0D\x0A
Channel Level Status Area 255 ID 36 Room Q	status channel ALL 255 Q\x0D\x0A
Channel Level Status Area 255 ID 36 Room R	status channel ALL 255 R\x0D\x0A
Channel Level Status Area 255 ID 36 Room S	status channel ALL 255 S\x0D\x0A
Channel Level Status Area 255 ID 36 Room T	status channel ALL 255 T\x0D\x0A
Channel Level Status Area 255 ID 36 Room U	status channel ALL 255 U\x0D\x0A
Channel Level Status Area 255 ID 36 Room V	status channel ALL 255 V\x0D\x0A
Channel Level Status Area 255 ID 36 Room W	status channel ALL 255 W\x0D\x0A
Channel Level Status Area 255 ID 36 Room X	status channel ALL 255 X\x0D\x0A
Channel Level Status Area Current Area ID 36 Room A	status channel ALL A\x0D\x0A
Channel Level Status Area Current Area ID 36 Room B	status channel ALL B\x0D\x0A
Channel Level Status Area Current Area ID 36 Room C	status channel ALL C\x0D\x0A
Channel Level Status Area Current Area ID 36 Room Current Room	status channel ALL \x0D\x0A
Channel Level Status Area Current Area ID 36 Room D	status channel ALL D\x0D\x0A
Channel Level Status Area Current Area ID 36 Room E	status channel ALL E\x0D\x0A
Channel Level Status Area Current Area ID 36 Room F	status channel ALL F\x0D\x0A
Channel Level Status Area Current Area ID 36 Room G	status channel ALL G\x0D\x0A
Channel Level Status Area Current Area ID 36 Room H	status channel ALL H\x0D\x0A
Channel Level Status Area Current Area ID 36 Room I	status channel ALL I\x0D\x0A
Channel Level Status Area Current Area ID 36 Room J	status channel ALL J\x0D\x0A
Channel Level Status Area Current Area ID 36 Room K	status channel ALL K\x0D\x0A
Channel Level Status Area Current Area ID 36 Room L	status channel ALL L\x0D\x0A
Channel Level Status Area Current Area ID 36 Room M	status channel ALL M\x0D\x0A
Channel Level Status Area Current Area ID 36 Room N	status channel ALL N\x0D\x0A
Channel Level Status Area Current Area ID 36 Room O	status channel ALL O\x0D\x0A
Channel Level Status Area Current Area ID 36 Room P	status channel ALL P\x0D\x0A
Channel Level Status Area Current Area ID 36 Room Q	status channel ALL Q\x0D\x0A
Channel Level Status Area Current Area ID 36 Room R	status channel ALL R\x0D\x0A
Channel Level Status Area Current Area ID 36 Room S	status channel ALL S\x0D\x0A
Channel Level Status Area Current Area ID 36 Room T	status channel ALL T\x0D\x0A
Channel Level Status Area Current Area ID 36 Room U	status channel ALL U\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Channel Level Status Area Current Area ID 36 Room V	status channel ALL V\x0D\x0A
Channel Level Status Area Current Area ID 36 Room W	status channel ALL W\x0D\x0A
Channel Level Status Area Current Area ID 36 Room X	status channel ALL X\x0D\x0A
Heartbeat	?\x0D\x0A
Input Level ID 1	status input ALL \x0D\x0A
Input Level ID 36	status input ALL \x0D\x0A
Scene Level Area 1 ID 1 Room A	status scene ALL 1 A\x0D\x0A
Scene Level Area 1 ID 1 Room B	status scene ALL 1 B\x0D\x0A
Scene Level Area 1 ID 1 Room C	status scene ALL 1 C\x0D\x0A
Scene Level Area 1 ID 1 Room Current Room	status scene ALL 1\x0D\x0A
Scene Level Area 1 ID 1 Room D	status scene ALL 1 D\x0D\x0A
Scene Level Area 1 ID 1 Room E	status scene ALL 1 E\x0D\x0A
Scene Level Area 1 ID 1 Room F	status scene ALL 1 F\x0D\x0A
Scene Level Area 1 ID 1 Room G	status scene ALL 1 G\x0D\x0A
Scene Level Area 1 ID 1 Room H	status scene ALL 1 H\x0D\x0A
Scene Level Area 1 ID 1 Room I	status scene ALL 1 I\x0D\x0A
Scene Level Area 1 ID 1 Room J	status scene ALL 1 J\x0D\x0A
Scene Level Area 1 ID 1 Room K	status scene ALL 1 K\x0D\x0A
Scene Level Area 1 ID 1 Room L	status scene ALL 1 L\x0D\x0A
Scene Level Area 1 ID 1 Room M	status scene ALL 1 M\x0D\x0A
Scene Level Area 1 ID 1 Room N	status scene ALL 1 N\x0D\x0A
Scene Level Area 1 ID 1 Room O	status scene ALL 1 O\x0D\x0A
Scene Level Area 1 ID 1 Room P	status scene ALL 1 P\x0D\x0A
Scene Level Area 1 ID 1 Room Q	status scene ALL 1 Q\x0D\x0A
Scene Level Area 1 ID 1 Room R	status scene ALL 1 R\x0D\x0A
Scene Level Area 1 ID 1 Room S	status scene ALL 1 S\x0D\x0A
Scene Level Area 1 ID 1 Room T	status scene ALL 1 T\x0D\x0A
Scene Level Area 1 ID 1 Room U	status scene ALL 1 U\x0D\x0A
Scene Level Area 1 ID 1 Room V	status scene ALL 1 V\x0D\x0A
Scene Level Area 1 ID 1 Room W	status scene ALL 1 W\x0D\x0A
Scene Level Area 1 ID 1 Room X	status scene ALL 1 X\x0D\x0A
Scene Level Area 255 ID 1 Room A	status scene ALL 255 A\x0D\x0A
Scene Level Area 255 ID 1 Room B	status scene ALL 255 B\x0D\x0A
Scene Level Area 255 ID 1 Room C	status scene ALL 255 C\x0D\x0A
Scene Level Area 255 ID 1 Room Current Room	status scene ALL 255\x0D\x0A
Scene Level Area 255 ID 1 Room D	status scene ALL 255 D\x0D\x0A
Scene Level Area 255 ID 1 Room E	status scene ALL 255 E\x0D\x0A
Scene Level Area 255 ID 1 Room F	status scene ALL 255 F\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level Area 255 ID 1 Room G	status scene ALL 255 G\x0D\x0A
Scene Level Area 255 ID 1 Room H	status scene ALL 255 H\x0D\x0A
Scene Level Area 255 ID 1 Room I	status scene ALL 255 I\x0D\x0A
Scene Level Area 255 ID 1 Room J	status scene ALL 255 J\x0D\x0A
Scene Level Area 255 ID 1 Room K	status scene ALL 255 K\x0D\x0A
Scene Level Area 255 ID 1 Room L	status scene ALL 255 L\x0D\x0A
Scene Level Area 255 ID 1 Room M	status scene ALL 255 M\x0D\x0A
Scene Level Area 255 ID 1 Room N	status scene ALL 255 N\x0D\x0A
Scene Level Area 255 ID 1 Room O	status scene ALL 255 O\x0D\x0A
Scene Level Area 255 ID 1 Room P	status scene ALL 255 P\x0D\x0A
Scene Level Area 255 ID 1 Room Q	status scene ALL 255 Q\x0D\x0A
Scene Level Area 255 ID 1 Room R	status scene ALL 255 R\x0D\x0A
Scene Level Area 255 ID 1 Room S	status scene ALL 255 S\x0D\x0A
Scene Level Area 255 ID 1 Room T	status scene ALL 255 T\x0D\x0A
Scene Level Area 255 ID 1 Room U	status scene ALL 255 U\x0D\x0A
Scene Level Area 255 ID 1 Room V	status scene ALL 255 V\x0D\x0A
Scene Level Area 255 ID 1 Room W	status scene ALL 255 W\x0D\x0A
Scene Level Area 255 ID 1 Room X	status scene ALL 255 X\x0D\x0A
Scene Level Area Current Area ID 1 Room A	status scene ALL A\x0D\x0A
Scene Level Area Current Area ID 1 Room B	status scene ALL B\x0D\x0A
Scene Level Area Current Area ID 1 Room C	status scene ALL C\x0D\x0A
Scene Level Area Current Area ID 1 Room Current Room	status scene ALL \x0D\x0A
Scene Level Area Current Area ID 1 Room D	status scene ALL D\x0D\x0A
Scene Level Area Current Area ID 1 Room E	status scene ALL E\x0D\x0A
Scene Level Area Current Area ID 1 Room F	status scene ALL F\x0D\x0A
Scene Level Area Current Area ID 1 Room G	status scene ALL G\x0D\x0A
Scene Level Area Current Area ID 1 Room H	status scene ALL H\x0D\x0A
Scene Level Area Current Area ID 1 Room I	status scene ALL I\x0D\x0A
Scene Level Area Current Area ID 1 Room J	status scene ALL J\x0D\x0A
Scene Level Area Current Area ID 1 Room K	status scene ALL K\x0D\x0A
Scene Level Area Current Area ID 1 Room L	status scene ALL L\x0D\x0A
Scene Level Area Current Area ID 1 Room M	status scene ALL M\x0D\x0A
Scene Level Area Current Area ID 1 Room N	status scene ALL N\x0D\x0A
Scene Level Area Current Area ID 1 Room O	status scene ALL O\x0D\x0A
Scene Level Area Current Area ID 1 Room P	status scene ALL P\x0D\x0A
Scene Level Area Current Area ID 1 Room Q	status scene ALL Q\x0D\x0A
Scene Level Area Current Area ID 1 Room R	status scene ALL R\x0D\x0A
Scene Level Area Current Area ID 1 Room S	status scene ALL S\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level Area Current Area ID 1 Room T	status scene ALL T\x0D\x0A
Scene Level Area Current Area ID 1 Room U	status scene ALL U\x0D\x0A
Scene Level Area Current Area ID 1 Room V	status scene ALL V\x0D\x0A
Scene Level Area Current Area ID 1 Room W	status scene ALL W\x0D\x0A
Scene Level Area Current Area ID 1 Room X	status scene ALL X\x0D\x0A
Scene Level Area 1 ID 36 Room A	status scene ALL 1 A\x0D\x0A
Scene Level Area 1 ID 36 Room B	status scene ALL 1 B\x0D\x0A
Scene Level Area 1 ID 36 Room C	status scene ALL 1 C\x0D\x0A
Scene Level Area 1 ID 36 Room Current Room	status scene ALL 1\x0D\x0A
Scene Level Area 1 ID 36 Room D	status scene ALL 1 D\x0D\x0A
Scene Level Area 1 ID 36 Room E	status scene ALL 1 E\x0D\x0A
Scene Level Area 1 ID 36 Room F	status scene ALL 1 F\x0D\x0A
Scene Level Area 1 ID 36 Room G	status scene ALL 1 G\x0D\x0A
Scene Level Area 1 ID 36 Room H	status scene ALL 1 H\x0D\x0A
Scene Level Area 1 ID 36 Room I	status scene ALL 1 I\x0D\x0A
Scene Level Area 1 ID 36 Room J	status scene ALL 1 J\x0D\x0A
Scene Level Area 1 ID 36 Room K	status scene ALL 1 K\x0D\x0A
Scene Level Area 1 ID 36 Room L	status scene ALL 1 L\x0D\x0A
Scene Level Area 1 ID 36 Room M	status scene ALL 1 M\x0D\x0A
Scene Level Area 1 ID 36 Room N	status scene ALL 1 N\x0D\x0A
Scene Level Area 1 ID 36 Room O	status scene ALL 1 O\x0D\x0A
Scene Level Area 1 ID 36 Room P	status scene ALL 1 P\x0D\x0A
Scene Level Area 1 ID 36 Room Q	status scene ALL 1 Q\x0D\x0A
Scene Level Area 1 ID 36 Room R	status scene ALL 1 R\x0D\x0A
Scene Level Area 1 ID 36 Room S	status scene ALL 1 S\x0D\x0A
Scene Level Area 1 ID 36 Room T	status scene ALL 1 T\x0D\x0A
Scene Level Area 1 ID 36 Room U	status scene ALL 1 U\x0D\x0A
Scene Level Area 1 ID 36 Room V	status scene ALL 1 V\x0D\x0A
Scene Level Area 1 ID 36 Room W	status scene ALL 1 W\x0D\x0A
Scene Level Area 1 ID 36 Room X	status scene ALL 1 X\x0D\x0A
Scene Level Area 255 ID 36 Room A	status scene ALL 255 A\x0D\x0A
Scene Level Area 255 ID 36 Room B	status scene ALL 255 B\x0D\x0A
Scene Level Area 255 ID 36 Room C	status scene ALL 255 C\x0D\x0A
Scene Level Area 255 ID 36 Room Current Room	status scene ALL 255\x0D\x0A
Scene Level Area 255 ID 36 Room D	status scene ALL 255 D\x0D\x0A
Scene Level Area 255 ID 36 Room E	status scene ALL 255 E\x0D\x0A
Scene Level Area 255 ID 36 Room F	status scene ALL 255 F\x0D\x0A
Scene Level Area 255 ID 36 Room G	status scene ALL 255 G\x0D\x0A
Scene Level Area 255 ID 36 Room H	status scene ALL 255 H\x0D\x0A

Global Scripter Module Communication Sheet

Revision: 3/5/2018

Scene Level Area 255 ID 36 Room I	status scene ALL 255 I\x0D\x0A
Scene Level Area 255 ID 36 Room J	status scene ALL 255 J\x0D\x0A
Scene Level Area 255 ID 36 Room K	status scene ALL 255 K\x0D\x0A
Scene Level Area 255 ID 36 Room L	status scene ALL 255 L\x0D\x0A
Scene Level Area 255 ID 36 Room M	status scene ALL 255 M\x0D\x0A
Scene Level Area 255 ID 36 Room N	status scene ALL 255 N\x0D\x0A
Scene Level Area 255 ID 36 Room O	status scene ALL 255 O\x0D\x0A
Scene Level Area 255 ID 36 Room P	status scene ALL 255 P\x0D\x0A
Scene Level Area 255 ID 36 Room Q	status scene ALL 255 Q\x0D\x0A
Scene Level Area 255 ID 36 Room R	status scene ALL 255 R\x0D\x0A
Scene Level Area 255 ID 36 Room S	status scene ALL 255 S\x0D\x0A
Scene Level Area 255 ID 36 Room T	status scene ALL 255 T\x0D\x0A
Scene Level Area 255 ID 36 Room U	status scene ALL 255 U\x0D\x0A
Scene Level Area 255 ID 36 Room V	status scene ALL 255 V\x0D\x0A
Scene Level Area 255 ID 36 Room W	status scene ALL 255 W\x0D\x0A
Scene Level Area 255 ID 36 Room X	status scene ALL 255 X\x0D\x0A
Scene Level Area Current Area ID 36 Room A	status scene ALL A\x0D\x0A
Scene Level Area Current Area ID 36 Room B	status scene ALL B\x0D\x0A
Scene Level Area Current Area ID 36 Room C	status scene ALL C\x0D\x0A
Scene Level Area Current Area ID 36 Room Current Room	status scene ALL\x0D\x0A
Scene Level Area Current Area ID 36 Room D	status scene ALL D\x0D\x0A
Scene Level Area Current Area ID 36 Room E	status scene ALL E\x0D\x0A
Scene Level Area Current Area ID 36 Room F	status scene ALL F\x0D\x0A
Scene Level Area Current Area ID 36 Room G	status scene ALL G\x0D\x0A
Scene Level Area Current Area ID 36 Room H	status scene ALL H\x0D\x0A
Scene Level Area Current Area ID 36 Room I	status scene ALL I\x0D\x0A
Scene Level Area Current Area ID 36 Room J	status scene ALL J\x0D\x0A
Scene Level Area Current Area ID 36 Room K	status scene ALL K\x0D\x0A
Scene Level Area Current Area ID 36 Room L	status scene ALL L\x0D\x0A
Scene Level Area Current Area ID 36 Room M	status scene ALL M\x0D\x0A
Scene Level Area Current Area ID 36 Room N	status scene ALL N\x0D\x0A
Scene Level Area Current Area ID 36 Room O	status scene ALL O\x0D\x0A
Scene Level Area Current Area ID 36 Room P	status scene ALL P\x0D\x0A
Scene Level Area Current Area ID 36 Room Q	status scene ALL Q\x0D\x0A
Scene Level Area Current Area ID 36 Room R	status scene ALL R\x0D\x0A
Scene Level Area Current Area ID 36 Room S	status scene ALL S\x0D\x0A
Scene Level Area Current Area ID 36 Room T	status scene ALL T\x0D\x0A
Scene Level Area Current Area ID 36 Room U	status scene ALL U\x0D\x0A

Global Scriptor Module Communication Sheet

Revision: 3/5/2018

Scene Level Area Current Area ID 36 Room V	status scene ALL V\x0D\x0A
Scene Level Area Current Area ID 36 Room X	status scene ALL X\x0D\x0A