

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: KVM Switch
Manufacturer: Adder
Firmware Version: N/A
Model(s): Infinity Management Server

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/12/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Ethernet support using HTTP protocol, HTTPClass must be used. Example: InterfaceName = ModuleName.HTTPClass ('192.168.254.254', 'admin', 'password', Model = 'ModelName')
- The Transmitter ID, Receiver ID and Channel ID values need to be obtained from the device internal web page

Control Commands, States, and Qualifiers:

ConnectChanneltoReceiver	0 – 999
['Channel ID']	0 to 99999999 in steps of 1
['Mode']	'Video Only' 'Shared' 'Exclusive' 'Private'
DisconnectReceiver	0 – 999
Login ¹	None
SetPreset	0 – 999

¹ Login command should be sent before sending any other command to the device.

Status Available:

ConnectionStatus	'Connected' 'Disconnected'
Heartbeat ¹	None

¹ Supports Update only and is used only to trigger ConnectionStatus.

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type: Ethernet

Default Port: 80

Logon Credentials Supported: Yes

Multi-Connection Capabilities: Yes

Port Changeability: Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device: