
This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scripter Modules, refer to the "[Guide to Using Scripter Modules](#)" document.

Device Specifications

Device Type: Display
Manufacturer: AG Neovo
Firmware Version: N/A
Model(s): QD-84

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scripter Version
2.06.0002-b002	1.4.1

Version History

Module Version	Date	Notes
1_0_0_0	1/8/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='QD-84')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='QD-84')</code>

Set Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AspectRatio	Value 'Normal' 'Full'	Value 'Custom' '21:9'	Value 'Real'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# AspectRatio example InterfaceName.Set('AspectRatio', 'Normal', {'Monitor ID': '1'})			
Command AutoImage	Value None		
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# AutoImage example InterfaceName.Set('AutoImage', None, {'Monitor ID': '1'})			
Command Input	Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Value 'Component' 'HDMI 2' 'Card OPS'	Value 'VGA' 'HDMI 3' 'USB'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# Input example InterfaceName.Set('Input', 'Video', {'Monitor ID': '1'})			
Command PictureInPicture	Value 'Bottom Left' 'Bottom Right'	Value 'Top Left' 'Off'	Value 'Top Right'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# PictureInPicture example InterfaceName.Set('PictureInPicture', 'Bottom Left', {'Monitor ID': '1'})			
Command PictureInPictureSourceSet	Value None		
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Qualifier Key 'Quadrant 2'	Qualifier Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Qualifier Value 'Component' 'HDMI 2' 'Card OPS'	Qualifier Value 'VGA' 'HDMI 3' 'USB'
Qualifier Key 'Quadrant 3'	Qualifier Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Qualifier Value 'Component' 'HDMI 2' 'Card OPS'	Qualifier Value 'VGA' 'HDMI 3' 'USB'
Qualifier Key 'Quadrant 4'	Qualifier Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Qualifier Value 'Component' 'HDMI 2' 'Card OPS'	Qualifier Value 'VGA' 'HDMI 3' 'USB'
# PictureInPictureSourceSet example InterfaceName.Set('PictureInPictureSourceSet', None, {'Monitor ID': '1', 'Quadrant 2': 'Video', 'Quadrant 3': 'Video', 'Quadrant 4': 'Video'})			
Command Power	Value 'On'	Value 'Off'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# Power example InterfaceName.Set('Power', 'On', {'Monitor ID': '1'})			
Command TilingSet	Value 'Yes'	Value 'No'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
Qualifier Key 'Frame comp'	Qualifier Value 'Yes'	Qualifier Value 'No'	Qualifier Value 'Keep Previous Value'
Qualifier Key 'Position'	Qualifier Value '1' – '25'	Qualifier Value 'Keep Previous Value'	
Qualifier Key 'H Monitors'	Qualifier Value '1' – '5'	Qualifier Value 'Keep Previous Value'	
Qualifier Key 'V Monitors'	Qualifier Value '1' – '5'	Qualifier Value 'Keep Previous Value'	
# TilingSet example InterfaceName.Set('TilingSet', 'Yes', {'Monitor ID': '1', 'Frame comp': 'Yes', 'Position': '1', 'H Monitors': '1', 'V Monitors': '1'})			
Command	Value		

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Volume	0 to 100 in steps of 1
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'
# Volume example InterfaceName.Set('Volume', 100, {'Monitor ID': '1'})	

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AspectRatio	Value 'Normal' 'Full'	Value 'Custom' '21:9'	Value 'Real'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# AspectRatio examples InterfaceName.Update('AspectRatio', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('AspectRatio', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('AspectRatio', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
# ConnectionStatus examples Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command Input	Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Value 'Component' 'HDMI 2' 'Card OPS'	Value 'VGA' 'HDMI 3' 'USB'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# Input examples InterfaceName.Update('Input', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('Input', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)			
Command OperationHours	Value 0 –		

Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# OperationHours examples InterfaceName.Update('OperationHours', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('OperationHours', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('OperationHours', None, FeedbackHandler)			
Command PictureInPicture	Value 'Bottom Left' 'Bottom Right'	Value 'Top Left' 'Other'	Value 'Top Right' 'Off'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# PictureInPicture examples InterfaceName.Update('PictureInPicture', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('PictureInPicture', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('PictureInPicture', None, FeedbackHandler)			
Command PictureInPictureSourceStatus	Value 'Video' 'HDMI 1' 'DisplayPort' 'DVI-D'	Value 'Component' 'HDMI 2' 'Card OPS'	Value 'VGA' 'HDMI 3' 'USB'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
Qualifier Key 'Quadrant'	Qualifier Value '2' – '4'		
# PictureInPictureSourceStatus examples InterfaceName.Update('PictureInPictureSourceStatus', {'Monitor ID': '1', 'Quadrant': '2'}) Value = InterfaceName.ReadStatus('PictureInPictureSourceStatus', {'Monitor ID': '1', 'Quadrant': '2'}) InterfaceName.SubscribeStatus('PictureInPictureSourceStatus', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# Power examples InterfaceName.Update('Power', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('Power', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command TilingEnableStatus	Value 'Yes'	Value 'No'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'		
# TilingEnableStatus examples InterfaceName.Update('TilingEnableStatus', {'Monitor ID': '1'})			

Value = InterfaceName.ReadStatus('TilingEnableStatus', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('TilingEnableStatus', None, FeedbackHandler)		
Command TilingFrameCompStatus	Value 'Yes'	Value 'No'
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'	
# TilingFrameCompStatus examples InterfaceName.Update('TilingFrameCompStatus', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('TilingFrameCompStatus', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('TilingFrameCompStatus', None, FeedbackHandler)		
Command TilingPositionStatus	Value '1' – '25'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'	
# TilingPositionStatus examples InterfaceName.Update('TilingPositionStatus', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('TilingPositionStatus', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('TilingPositionStatus', None, FeedbackHandler)		
Command TilingVandHMonitorsStatus	Value '1' – '5'	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'	
Qualifier Key 'Type'	Qualifier Value 'H Monitors'	Qualifier Value 'V Monitors'
# TilingVandHMonitorsStatus examples InterfaceName.Update('TilingVandHMonitorsStatus', {'Monitor ID': '1', 'Type': 'H Monitors'}) Value = InterfaceName.ReadStatus('TilingVandHMonitorsStatus', {'Monitor ID': '1', 'Type': 'H Monitors'}) InterfaceName.SubscribeStatus('TilingVandHMonitorsStatus', None, FeedbackHandler)		
Command Volume	Value 0 to 100 in steps of 1	
Qualifier Key 'Monitor ID'	Qualifier Value '1' – '255'	
# Volume examples InterfaceName.Update('Volume', {'Monitor ID': '1'}) Value = InterfaceName.ReadStatus('Volume', {'Monitor ID': '1'}) InterfaceName.SubscribeStatus('Volume', None, FeedbackHandler)		

Cable and Adapter Requirements

Captive Screw to TRS RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 9600


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
RXD	←	T	TXD
TXD	→	R	RXD
GND		S	GND



Appendix A. Set Commands

Aspect Ratio 21:9 Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01:\x04\x9C
Aspect Ratio Custom Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01:\x01\x99
Aspect Ratio Full Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01:\x03\x9B
Aspect Ratio Normal Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01:\x00\x98
Aspect Ratio Real Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01:\x02\x9A
Aspect Ratio 21:9 Monitor ID 99	\xA6c\x00\x00\x00\x04\x01:\x04\xFE
Aspect Ratio Custom Monitor ID 99	\xA6c\x00\x00\x00\x04\x01:\x01\xFB
Aspect Ratio Full Monitor ID 99	\xA6c\x00\x00\x00\x04\x01:\x03\xF9
Aspect Ratio Normal Monitor ID 99	\xA6c\x00\x00\x00\x04\x01:\x00\xFA
Aspect Ratio Real Monitor ID 99	\xA6c\x00\x00\x00\x04\x01:\x02\xF8
Auto Image None Monitor ID 1	\xA6\x01\x00\x00\x00\x05\x01p@\x00\x93
Auto Image None Monitor ID 99	\xA6c\x00\x00\x00\x05\x01p@\x00\xF1
Input Card OPS Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0B\x00\x00\x00\x06
Input Component Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x03\x00\x00\x00\x0E
Input DVI-D Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0E\x00\x00\x00\x03
Input DisplayPort Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0A\x00\x00\x00\x07
Input HDMI 1 Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0D\x00\x00\x00\x00
Input HDMI 2 Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x06\x00\x00\x00\x0B
Input HDMI 3 Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0F\x00\x00\x00\x02
Input USB Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x0C\x00\x00\x00\x01
Input VGA Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x05\x00\x00\x00\x08
Input Video Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01\xAC\x01\x00\x00\x00\x0C
Input Card OPS Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0B\x00\x00\x00d
Input Component Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x03\x00\x00\x001
Input DVI-D Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0E\x00\x00\x00a
Input DisplayPort Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0A\x00\x00\x00e
Input HDMI 1 Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0D\x00\x00\x00b
Input HDMI 2 Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x06\x00\x00\x00i
Input HDMI 3 Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0F\x00\x00\x00`
Input USB Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x0C\x00\x00\x00c
Input VGA Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x05\x00\x00\x00j

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Input Video Monitor ID 99	\xA6c\x00\x00\x00\x07\x01\xAC\x01\x00\x00\x00n
Picture In Picture Bottom Left Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01<\x01\x00\x00\x00\x9C
Picture In Picture Bottom Right Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01<\x01\x03\x00\x00\x9F
Picture In Picture Off Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01<\x00\x00\x00\x00\x9D
Picture In Picture Top Left Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01<\x01\x01\x00\x00\x9D
Picture In Picture Top Right Monitor ID 1	\xA6\x01\x00\x00\x00\x07\x01<\x01\x02\x00\x00\x9E
Picture In Picture Bottom Left Monitor ID 99	\xA6c\x00\x00\x00\x07\x01<\x01\x00\x00\x00\xFE
Picture In Picture Bottom Right Monitor ID 99	\xA6c\x00\x00\x00\x07\x01<\x01\x03\x00\x00\xFD
Picture In Picture Off Monitor ID 99	\xA6c\x00\x00\x00\x07\x01<\x00\x00\x00\x00\xFF
Picture In Picture Top Left Monitor ID 99	\xA6c\x00\x00\x00\x07\x01<\x01\x01\x00\x00\xFF
Picture In Picture Top Right Monitor ID 99	\xA6c\x00\x00\x00\x07\x01<\x01\x02\x00\x00\xFC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x05\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0D\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x05\xD5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0E\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0D\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x06\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0C\xD1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0E\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0B\xD2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0E\xD7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0D\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0F\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0A\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x06\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x05\xDB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0D\x01\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x03\xD6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0A\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0F\xDA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0E\xD2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0F\xD3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x05\xD9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0E\xD1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0A\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x06\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0C\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0C\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x0C\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0F\xD9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x0C\xDA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x05\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x01\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x01\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x01\x0E\xDC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x01\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0B\x01\x0D\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0F\xDD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 Card OPS	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x01\xD3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0D\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x05\xD5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x03\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0A\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0F\xDA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0B\xDA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0E\xDF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0A\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0D\xDC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0A\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0A\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0A\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0A\x05\xD4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0A\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0F\xD9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x0D\x0C\xDA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0E\xD3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0D\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x06\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0C\xD1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0B\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0E\xDA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0B\xDC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0A\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0D\xDA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x05\xD2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x01\xD6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x06\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x05\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x05\x01\xDF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x0C\xD6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 Component	\xA6\x01\x00\x00\x07\x01\x84\xFD\x03\x01\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0E\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0D\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x06\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0C\xD1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0B\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x03\xD6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x0A\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x03\x0F\xDA

Global Scripter Module Communication Sheet

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0E\xD2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0F\xD3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x05\xD9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0E\xD5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x06\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0C\xD7

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0D\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0D\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0D\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x05\xD5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x06\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0B\xD2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0E\xD7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0D\xD4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0F\xD6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0F\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0C\xD6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x0C\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x05\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x05\x03\xD0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0E\x05\x0E\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0D\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x06\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x05\xD6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0B\xDC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0A\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0D\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x05\xD2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 DVI-D	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x01\xD6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0B\xD2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0E\xD7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0D\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0F\xD6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0B\xDA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0E\xDF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0A\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0D\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x05\xD4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0E\xD2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0F\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0E\x05\xD9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0E\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0A\x01\xD9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0E\xD1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0A\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x06\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0C\xD3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0B\xDF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0E\xDA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x06\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0E\xD3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0D\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0A\x0F\x06\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0C\xD1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x06\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x05\xDB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x01\xDF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0B\xDC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0A\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0D\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x05\xD2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x01\xD6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x03\xD0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0E\xDD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0D\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x06\xD5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x05\xD6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x06\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x05\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x01\xDF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0F\xD9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0C\xDA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0E\xD5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x06\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0C\xD7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0E\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0E\xD1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0A\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x06\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0C\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x03\xD0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0E\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x0D\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x06\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x05\xD6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x06\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0C\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0F\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0B\xD2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0E\xD7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0D\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0F\xD6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x0C\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0D\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x05\xD5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x05\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0B\xDF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0E\xDA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0D\x01\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0B\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0B\x03\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0A\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0F\xDA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0E\xD3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0D\xD0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x03\x06\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x03\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x03\x0C\xD1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x03\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x03\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0D\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x05\xD5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0E\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0B\xDF

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0E\xDA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0A\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x03\xD0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0E\xDD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0D\xDE

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x06\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x05\xD6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0D\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x06\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0B\xDA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0E\xDF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0A\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0D\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x05\xD4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0F\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x0E\xDC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x0D\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x07\x01\x84\xFD\x06\x0C\x0F\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x01\xD3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0E\xD5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x06\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0C\xD7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0E\xD1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0A\xD5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x06\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0C\xD3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0E\xD2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0F\xD3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x05\xD9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0B\xDF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0E\xDA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0B\xD2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0E\xD7

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0D\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0F\xD6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0E\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0B\xD6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x03\xDE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0E\xD3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0A\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0D\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x06\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0F\xD2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0C\xD1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x05\xD8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x01\xDC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0C\xD6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0B\xDA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0E\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x0A\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x0D\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x05\xD4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x06\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0C\xD4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0F\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0E\xD5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x06\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0C\xD7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x0C\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0E\xDC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0D\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0F\xDD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x05\x01\xD3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0F\xD9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x0C\xDA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0F\x01\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x0B\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0E\xD1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0A\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x06\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0C\xD3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0B\xDC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0A\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0D\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x05\xD2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x01\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0C\xD6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x06\xD8

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x05\xDB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x01\xDF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0B\xD2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x03\xDA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0E\xD7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0A\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0D\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x06\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0F\xD6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0C\xD5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x05\xDC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x01\xD8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0E\xDC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0D\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0F\xDD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x01\xD3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0E\xD5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x06\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0C\xD7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0B\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0B\xDA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0E\xDF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0A\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0D\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x05\xD4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x05\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x03\xD6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0A\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0F\xDA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 USB	\xA6\x01\x00\x00\x07\x01\x84\xFD\x0C\x01\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0B\x0F\xD9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0C\xDA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0B\xD5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x03\xDD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0E\xD0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0A\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0D\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x06\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0F\xD1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0C\xD2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x05\xDB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x01\xDF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x03\xD0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x0E\xDD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x0D\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x06\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x05\xD6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0E\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0B\xDC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0A\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0D\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0A\x05\xD2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x01\xD6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0B\xDB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x03\xD3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0E\xDE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0A\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0D\xDD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x06\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0F\xDF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0C\xDC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x05\xD5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x01\xD1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0B\xD0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x03\xD8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0E\xD5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0A\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0D\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x06\xDD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x06\x0F\xD4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x06\x0C\xD7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x06\x05\xDE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x06\x01\xDA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0E\xDC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0D\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0F\xDD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0F\x01\xD3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0B\xDA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x03\xD2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0E\xDF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0A\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0D\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x06\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0F\xDE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x0C\xDD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x05\xD4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x0C\x01\xD0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x03\xDB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x05\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x01\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x01\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x07\x01\x84\xFD\x05\x01\x0E\xD2

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0F\xD3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x05\xD9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 VGA	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0B\xD9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x03\xD1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0E\xDC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0A\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0D\xDF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x06\xD4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0F\xDD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0C\xDE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x05\xD7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Card OPS Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x01\xD3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0B\xD1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x03\xD9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0E\xD4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0A\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0D\xD7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x06\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0F\xD5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0C\xD6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x05\xDF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Component Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x01\xDB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0B\xDC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x03\xD4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0E\xD9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0A\xDD

Global Scripter Module Communication Sheet

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0D\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x06\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0F\xD8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0C\xDB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x05\xD2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DVI-D Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x01\xD6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0B\xD8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x03\xD0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0E\xDD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0A\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0D\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x06\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0F\xDC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0C\xDF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x05\xD6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0A\x01\xD2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0B\xDF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x03\xD7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0E\xDA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0A\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0D\xD9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x06\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0F\xDB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x0C\xD8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x05\xD1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0D\x01\xD5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0B\xD4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x03\xDC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0E\xD1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0A\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0D\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x06\xD9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0F\xD0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x0C\xD3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x05\xDA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x06\x01\xDE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0B\xDD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x03\xD5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0E\xD8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0A\xDC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0D\xDB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x06\xD0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0F\xD9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x0C\xDA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x05\xD3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0F\x01\xD7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0B\xDE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x03\xD6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0E\xDB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0A\xDF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0D\xD8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x06\xD3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0F\xDA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x0C\xD9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x05\xD0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 USB Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x0C\x01\xD4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0B\xD7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x03\xDF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0E\xD2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0A\xD6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0D\xD1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x06\xDA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0F\xD3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x0C\xD0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x05\xD9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 VGA Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x05\x01\xDD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0B\xD3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x03\xDB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0E\xD6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0A\xD2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0D\xD5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x06\xDE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0F\xD7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x0C\xD4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x05\xDD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 1 Quadrant 3 Video Quadrant 2 Video	\xA6\x01\x00\x00\x07\x01\x84\xFD\x01\x01\x01\xD9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x07\x01\x84\xFD\x0B\x0B\x0C\xB6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0B\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0B\xB9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0E\xBC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x03\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0B\xB4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0D\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x06\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0F\xB0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x05\xBA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0E\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0B\xB0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0A\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x06\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0A\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0B\xB7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0D\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0F\xB3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x0C\xB0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x05\xB9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0D\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0B\xBC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x06\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x0C\xBB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x05\xB2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x06\x01\xB6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0B\xB5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0F\xB1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x05\xBB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0F\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x03\xBE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0E\xB3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0A\xB7

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x06\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x0C\xB1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x0C\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x03\xB7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0E\xBA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0A\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0F\xBB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x05\x01\xB5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0A\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0D\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 Card OPS	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0B\x01\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0B\xB9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0E\xBC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0B\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x06\xBC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x03\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0B\xBC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x06\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x0C\xBB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x05\xB2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0E\x01\xB6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0B\xB8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0A\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0A\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x03\xB7

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0E\xBA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0A\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0F\xBB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0D\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0B\xB4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0D\xB2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0F\xB0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x05\xBA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x06\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0B\xBD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0E\xB8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0A\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x0C\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0F\x01\xB7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0F\xBA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x0C\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0B\xB7

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0D\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0F\xB3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x0C\xB0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x05\xB9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x05\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0E\xB6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0A\xB2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x0C\xB4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 Component	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x03\x01\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0B\xB4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0D\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x06\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0F\xB0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x05\xBA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0B\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0B\xBC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x06\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x0C\xBB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x05\xB2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x03\x01\xB6

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0E\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0B\xB5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x06\xB8

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0F\xB1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x05\xBB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0A\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0E\xB7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0D\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0D\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0B\xB9

Global Scriptor Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0E\xBC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x06\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0B\xB0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0A\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI- D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x06\xBD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0F\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0E\xB6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0A\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x0C\xB4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x0C\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0B\xBA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x03\xB2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0E\xBF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0A\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0F\xBE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x05\xB4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x05\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0F\xBA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 DVI-D	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0E\x01\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0B\xB0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0A\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x06\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0B\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0B\xB8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0A\xB9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x03\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0B\xB5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0F\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x05\xBB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0E\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0A\x01\xBB

Global Scriptor Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x03\xBE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0E\xB3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0A\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x06\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x0C\xB1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0D\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0B\xBD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0E\xB8

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0A\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x0C\xBA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x06\x01\xB7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0B\xB4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0D\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x06\xB9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0F\xB0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x05\xBA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0F\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0B\xB7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0D\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0F\xB3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x0C\xB0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x05\xB9

Global Scripter Module Communication Sheet

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x0C\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0F\xBA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x05\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0B\xBA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x03\xB2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0E\xBF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0A\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0F\xBE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x05\xB4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 DisplayPort	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0A\x01\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0B\xB7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0D\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0F\xB3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x0C\xB0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x05\xB9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0B\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x03\xB7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0E\xBA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0A\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0F\xBB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x0C\xB8

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x03\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0E\xB7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0D\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0E\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x03\xBE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0E\xB3

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0A\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x06\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x0C\xB1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0A\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x06\xBC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0D\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0B\xBA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x03\xB2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0F\xBE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x05\xB4

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x06\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0E\xB6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0A\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x0C\xB4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0F\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0B\xB0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0E\xB5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0A\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x06\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x0C\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0B\xB9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0E\xBC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x05\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0B\xBD

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0E\xB8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0A\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x0C\xBA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 1	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0D\x01\x01\xB7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0B\xBC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x06\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x05\xB2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0B\x01\xB6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0B\xB4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0D\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x06\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0F\xB0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x05\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x03\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0B\xB9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0E\xBC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0E\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0B\xBD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0E\xB8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0A\xBC

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x0C\xBA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0A\x01\xB7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0B\xBA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x03\xB2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0E\xBF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0A\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0F\xBE

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x05\xB4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0D\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x06\x01\xBB

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0B\xB8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0A\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0F\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0A\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0D\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x0C\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0E\xB7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0D\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x05\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x03\xBE

Global Scripter Module Communication Sheet

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0E\xB3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0A\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x0C\xB1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 2	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x06\x01\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0B\xB5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0F\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0B\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0B\xBD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0E\xB8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0A\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x0C\xBA
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x03\x01\xB7

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0B\xB0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0A\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x06\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0E\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0B\xB4
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x03\xBC
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0E\xB1
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0A\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0D\xB2

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x06\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0F\xB0
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x0C\xB3
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x05\xBA
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0A\x01\xBE
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0E\xB6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0A\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x0C\xB4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0D\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0B\xB8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0A\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x06\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0B\xB1

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0F\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0E\xB7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0D\xB4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x0C\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0A\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0D\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x05\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x03\xB7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0E\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0A\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0F\xBB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 HDMI 3	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0F\x01\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x03\xBE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0E\xB3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0A\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x06\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x0C\xB1

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0B\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0F\xBA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x03\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0E\xB6

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0A\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x0C\xB4
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0E\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0B\xB7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0D\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0F\xB3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x0C\xB0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x05\xB9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0A\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0B\xB0
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x03\xB8
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0E\xB5
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0A\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0D\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x06\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0F\xB4
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x0C\xB7
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x05\xBE
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0D\x01\xBA
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0A\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0D\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x06\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0E\xB7
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0D\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0F\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x03\xB9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x05\xBF
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x0C\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0B\xB8
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0A\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x05\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0B\xBC

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x06\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x0C\xBB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x05\xB2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 USB	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x0C\x01\x01\xB6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x03\xB7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0E\xBA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0A\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0F\xBB

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0B\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0B\xB7
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x03\xBF
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0E\xB2
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0A\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0D\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x06\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0F\xB3
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x0C\xB0
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x05\xB9
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x03\x01\xBD
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0B\xBA

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x03\xB2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0E\xBF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0A\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0F\xBE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x05\xB4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0E\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0F\xBA

Global Scripter Module Communication Sheet

Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0A\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0B\xB9
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x03\xB1
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0E\xBC
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0A\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0D\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x06\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0F\xBD
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x0C\xBE
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x05\xB7
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0D\x01\xB3
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0B\xB2
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x03\xBA
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0E\xB7

Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0A\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0D\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x06\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0F\xB6
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x0C\xB5
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x05\xBC
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x06\x01\xB8
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0A\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0D\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0F\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0B\xB8

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x03\xB0
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0E\xBD
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0A\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0D\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x06\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0F\xBC
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x0C\xBF
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x05\xB6
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x0C\x01\xB2
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x05\xBF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x05\x01\xBB
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0B\xB5
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0F\xB1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x05\xBB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 VGA	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x05\x01\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0B\xBB
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x03\xB3
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0E\xBE
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0A\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0D\xBD

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x06\xB6
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0F\xBF
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x0C\xBC
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x05\xB5
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Card OPS Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0B\x01\xB1
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0B\xB3
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x03\xBB
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0E\xB6
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0A\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0D\xB5
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x06\xBE
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0F\xB7
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x0C\xB4

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x05\xBD
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Component Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x03\x01\xB9
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0B\xBE
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x03\xB6
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0E\xBB
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0A\xBF
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0D\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x06\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0F\xBA
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x0C\xB9
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x05\xB0
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DVI-D Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0E\x01\xB4
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0B\xBA
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x03\xB2
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0E\xBF
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0A\xBB

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0D\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x06\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0F\xBE
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x0C\xBD
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x05\xB4
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 DisplayPort Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0A\x01\xB0
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0B\xBD
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x03\xB5
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0E\xB8
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0A\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0D\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x06\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0F\xB9
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x0C\xBA

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x05\xB3
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 1 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0D\x01\xB7
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0B\xB6
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x03\xBE
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0E\xB3
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0A\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0D\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x06\xBB
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0F\xB2
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x0C\xB1
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x05\xB8
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 2 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x06\x01\xBC
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0B\xBF
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x03\xB7
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0E\xBA
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0A\xBE

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0D\xB9
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x06\xB2
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0F\xBB
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x0C\xB8
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x05\xB1
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 HDMI 3 Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0F\x01\xB5
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0B\xBC
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x03\xB4
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0E\xB9
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0A\xBD
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0D\xBA
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x06\xB1
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0F\xB8
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x0C\xBB
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x05\xB2
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 USB Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x0C\x01\xB6
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0B\xB5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x03\xBD
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0E\xB0
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0A\xB4
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0D\xB3
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x06\xB8
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0F\xB1
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x0C\xB2
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x05\xBB
Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 VGA Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x05\x01\xBF
Picture In Picture Source Set None Quadrant 4 Card OPS Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0B\xB1
Picture In Picture Source Set None Quadrant 4 Component Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x03\xB9
Picture In Picture Source Set None Quadrant 4 DVI-D Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0E\xB4
Picture In Picture Source Set None Quadrant 4 DisplayPort Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0A\xB0
Picture In Picture Source Set None Quadrant 4 HDMI 1 Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0D\xB7
Picture In Picture Source Set None Quadrant 4 HDMI 2 Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x06\xBC
Picture In Picture Source Set None Quadrant 4 HDMI 3 Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0F\xB5
Picture In Picture Source Set None Quadrant 4 USB Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x0C\xB6
Picture In Picture Source Set None Quadrant 4 VGA Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x05\xBF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Picture In Picture Source Set None Quadrant 4 Video Monitor ID 99 Quadrant 3 Video Quadrant 2 Video	\xA6c\x00\x00\x00\x07\x01\x84\xFD\x01\x01\x01\xBB
Power Off Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01\x18\x01\xBB
Power On Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01\x18\x02\xB8
Power Off Monitor ID 99	\xA6c\x00\x00\x00\x04\x01\x18\x01\xD9
Power On Monitor ID 99	\xA6c\x00\x00\x00\x04\x01\x18\x02\xDA
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x01\x81
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x01\x80
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x15\x95
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x15\x94
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\xFC
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\xFC}
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x05\x85
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x05\x84
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x19\x99
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x19\x98
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x00\x80
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x00\x81
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x00\x80
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x00\x81

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x14\x94
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x14\x95
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x01\x00\x80
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x01\x00\x81
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x01\x99
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x01\x98
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x15\x8D
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x15\x8C
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\xFCd
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\xFCe
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x05\x9D
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x05\x9C
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x19\x81
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x19\x80
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x00\x98
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x00\x99

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x00\x98
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x00\x99
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x14\x8C
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x14\x8D
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x19\x00\x98
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x19\x00\x99
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x01\x80
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x01\x81
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x15\x94
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x15\x95
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\xFC}
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\xFC
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x05\x84

Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x05\x85
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x19\x98
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x19\x99
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x00\x81
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x00\x80
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x00\x81
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x00\x80
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x14\x95
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x14\x94
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x00\x02\x00\x00\x81
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6\x01\x00\x00\x00\x07\x01"\x01\x02\x00\x00\x80
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x01\x83
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x01\x82
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x15\x97

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x15\x96
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\xFC~
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\xFC\x7F
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x05\x87
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x05\x86
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x19\x9B
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x19\x9A
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x00\x82
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x00\x83
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x00\x82
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x00\x83
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x14\x96
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x14\x97
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x01\x00\x82
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x01\x00\x83
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x01\x9B
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x01\x9A
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x15\x8F
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x15\x8E

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\xFCf
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\xFCg
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x05\x9F
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x05\x9E
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x19\x83
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x19\x82
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x00\x9A
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x00\x9B
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x00\x9A
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x00\x9B
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x14\x8E
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x14\x8F
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x19\x00\x9A
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x19\x00\x9B
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x00\x01\x82
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x00\x01\x83
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x00\x15\x96
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x01\x00\x00\x15\x97
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x00\x07\x01"\x00\x00\x00\xFC\x7F

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\xFC~
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x05\x86
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x05\x87
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x19\x9A
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x19\x9B
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x00\x83
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x00\x82
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x00\x83
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x00\x82
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x14\x97
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x14\x96
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x07\x01"\x00\x00\x00\x00\x83
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6\x01\x00\x00\x07\x01"\x01\x00\x00\x00\x82
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x01\x82
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x01\x83
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x15\x96

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x15\x97
Tiling Set No Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\xFC\x7F
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\xFC~
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x05\x86
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x05\x87
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x19\x9A
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x19\x9B
Tiling Set No Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x00\x83
Tiling Set Yes Position 1 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x00\x82
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x00\x83
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x00\x82
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x14\x97
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x14\x96
Tiling Set No Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x01\x00\x83
Tiling Set Yes Position 1 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x01\x00\x82
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x19\x01\x9A
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x19\x01\x9B
Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x19\x15\x8E
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x19\x15\x8F

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\xFCg
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\xFCf
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x05\x9E
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x05\x9F
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x19\x82
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x19\x83
Tiling Set No Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x00\x9B
Tiling Set Yes Position 25 Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x00\x9A
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x00\x9B
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x00\x9A
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x14\x8F
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x14\x8E
Tiling Set No Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x19\x00\x9B
Tiling Set Yes Position 25 Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x19\x00\x9A
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x00\x01\x83
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x00\x01\x82
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x00\x15\x97
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x01\x01\x00\x15\x96
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x00\x07\x01"\x00\x01\x00\xFC~

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\xFC\x7F
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x05\x87
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x05\x86
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x19\x9B
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x19\x9A
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x00\x82
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x00\x83
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x00\x82
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x00\x83
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x14\x96
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x14\x97
Tiling Set No Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x00\x01\x00\x00\x82
Tiling Set Yes Position Keep Previous Value Monitor ID 1 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6\x01\x00\x00\x07\x01"\x01\x01\x00\x00\x83
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x01\xE3
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x01\xE2
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x15\xF7

Global Scripter Module Communication Sheet

Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x15\xF6
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\xFC\x1E
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\xFC\x1F
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x05\xE7
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x05\xE6
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x19\xFB
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x19\xFA
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x00\xE2
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x00\xE3
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x00\xE2
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x00\xE3
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x14\xF6
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x14\xF7
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x01\x00\xE2
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x01\x00\xE3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x01\xFB
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x01\xFA
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x15\xEF
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x15\xEE
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\xFC\x06
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\xFC\x07
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x05\xFF
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x05\xFE
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x19\xE3
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x19\xE2
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x00\xFA
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x00\xFB
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x00\xFA
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x00\xFB
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x14\xEE
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x14\xEF

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x19\x00\xFA
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x19\x00\xFB
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x01\xE2
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x01\xE3
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x15\xF6
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x15\xF7
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\xFC\x1F
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\xFC\x1E
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x05\xE6
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x05\xE7
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x19\xFA
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x19\xFB
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x00\xE3

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x00\xE2
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x00\xE3
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x00\xE2
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x14\xF7
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x14\xF6
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x00\x02\x00\x00\xE3
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Keep Previous Value	\xA6c\x00\x00\x00\x07\x01"\x01\x02\x00\x00\xE2
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x01\xE1
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x01\xE0
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x15\xF5
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x15\xF4
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\xFC\x1C
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\xFC\x1D
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x05\xE5
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x05\xE4
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x19\xF9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x19\xF8
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x00\xE0
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x00\xE1
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x00\xE0
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x00\xE1
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x14\xF4
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x14\xF5
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x01\x00\xE0
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x01\x00\xE1
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x01\xF9
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x01\xF8
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x15\xED
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x15\xEC
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\xFC\x04
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\xFC\x05
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x05\xFD
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x05\xFC
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x19\xE1
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x19\xE0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x00\xF8
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x00\xF9
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x00\xF8
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x00\xF9
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x14\xEC
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x14\xED
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x19\x00\xF8
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x19\x00\xF9
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x01\xE0
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x01\xE1
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x15\xF4
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x15\xF5
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\xFC\x1D
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\xFC\x1C
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x05\xE4
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x05\xE5
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x19\xF8
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x19\xF9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x00\xE1
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x00\xE0
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x00\xE1
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x00\xE0
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x14\xF5
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x14\xF4
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x00\x00\x00\x00\xE1
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp No	\xA6c\x00\x00\x00\x07\x01"\x01\x00\x00\x00\xE0
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x01\xE0
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x01\xE1
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x15\xF4
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x15\xF5
Tiling Set No Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\xFC\x1D
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\xFC\x1C
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x05\xE4
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x05\xE5

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x19\xF8
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x19\xF9
Tiling Set No Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x00\xE1
Tiling Set Yes Position 1 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x00\xE0
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x00\xE1
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x00\xE0
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x14\xF5
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x14\xF4
Tiling Set No Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x01\x00\xE1
Tiling Set Yes Position 1 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x01\x00\xE0
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x01\xF8
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x01\xF9
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x15\xEC
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x15\xED
Tiling Set No Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\xFC\x05
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\xFC\x04
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x05\xFC
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x05\xFD
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x19\xE0

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x19\xE1
Tiling Set No Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x00\xF9
Tiling Set Yes Position 25 Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x00\xF8
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x00\xF9
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x00\xF8
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x14\xED
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x14\xEC
Tiling Set No Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x19\x00\xF9
Tiling Set Yes Position 25 Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x19\x00\xF8
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x01\xE1
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x01\xE0
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x15\xF5
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x15\xF4
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\xFC\x1C
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 1 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\xFC\x1D
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x05\xE5
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x05\xE4
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x19\xF9

Global Scripter Module Communication Sheet

Revision: 1/8/2018

Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x19\xF8
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x00\xE0
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors 5 V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x00\xE1
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x00\xE0
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 1 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x00\xE1
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x14\xF4
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors 5 Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x14\xF5
Tiling Set No Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x00\x01\x00\x00\xE0
Tiling Set Yes Position Keep Previous Value Monitor ID 99 H Monitors Keep Previous Value V Monitors Keep Previous Value Frame comp Yes	\xA6c\x00\x00\x00\x07\x01"\x01\x01\x00\x00\xE1
Volume 0 Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01D\x00\xE6
Volume 100 Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01Dd\x82
Volume 0 Monitor ID 99	\xA6c\x00\x00\x00\x04\x01D\x00\x84
Volume 100 Monitor ID 99	\xA6c\x00\x00\x00\x04\x01Dd\xE0

Appendix B. Update Commands

Aspect Ratio Monitor ID 1	\xA6\x01\x00\x00\x03\x01;\x9E
Aspect Ratio Monitor ID 99	\xA6c\x00\x00\x00\x03\x01;\xFC
Input Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01\xAD\x08
Input Monitor ID 99	\xA6c\x00\x00\x00\x03\x01\xADj
Operation Hours Monitor ID 1	\xA6\x01\x00\x00\x00\x04\x01\x0F\x02\xAF
Operation Hours Monitor ID 99	\xA6c\x00\x00\x00\x04\x01\x0F\x02\xCD
Picture In Picture Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01=\x98
Picture In Picture Monitor ID 99	\xA6c\x00\x00\x00\x03\x01=\xFA
Picture In Picture Source Status Quadrant 2 Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01\x85
Picture In Picture Source Status Quadrant 4 Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01\x85
Picture In Picture Source Status Quadrant 2 Monitor ID 99	\xA6c\x00\x00\x00\x03\x01\x85B
Picture In Picture Source Status Quadrant 4 Monitor ID 99	\xA6c\x00\x00\x00\x03\x01\x85B
Power Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01\x19\xBC
Power Monitor ID 99	\xA6c\x00\x00\x00\x03\x01\x19\xDE
Tiling Enable Status Monitor ID 1	\xA6\x01\x00\x00\x00\x03\x01#\x86
Tiling Enable Status Monitor ID 99	\xA6c\x00\x00\x00\x03\x01#\xE4
Volume Monitor ID 99	\xA6c\x00\x00\x00\x03\x01E\x82