

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Audio Processor
Manufacturer: Allen and Heath
Firmware Version: N/A
Model(s): QU-16, QU-32, QU-24, QU-Pac, QU-SB

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.04.0001-b002	2.3.1

Version History

Module Version	Date	Notes
1_4_0_0	3/20/2020	Fixed DCA Fader Level, FX Fader Level, Input Level, Master Volume Level, Mix Fader and Send Level commands. Added model QU-SB. Added Remote Shutdown command. Fixed Mix Mute. Added Status. Changed Volume Range to -50 to 10. Added MIDI Channel as Driver Parameter. Removed Midi Channel qualifier from all commands. Changed Mix Level to Send Level. Fixed DCA Mute, Mix Mute, Group Mute and Mix Fader. Added Mix Assign. Changed Mute Input to Input Mute. Fixed DCA Mute and FX Mute commands. Added Mute Group command.
1_1_3_0	12/1/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- MIDIDChannel variable must be set accordingly. MIDIDChannel ranges from 1' to '16'.
Example: `InterfaceName.MIDIDChannel = '1'`

Supported Class and Example

EthernetClass

<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 51325, Model='QU-16')</code>
--

Control Commands

Format with Qualifier:

InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})

Format with Qualifier:

InterfaceName.Set(Command, Value)

Command	Value	
DCAFaderLevel	-50 to 10 in steps of 1	
Qualifier Key	Qualifier Value	
'DCA'	'1' – '4'	
# DCAFaderLevel example InterfaceName.Set('DCAFaderLevel', 10, {'DCA': '1'})		
Command	Value	Value
DCAMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'DCA'	'1' – '4'	
# DCAMute example InterfaceName.Set('DCAMute', 'On', {'DCA': '1'})		
Command	Value	
FXFaderLevel	-50 to 10 in steps of 1	
Qualifier Key	Qualifier Value	
'FX Number'	'1' – '4'	
Qualifier Key	Qualifier Value	Qualifier Value
'FX Type'	'Send'	'Return'
# FXFaderLevel example InterfaceName.Set('FXFaderLevel', 10, {'FX Number': '1', 'FX Type': 'Send'})		
Command	Value	Value
FXMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'FX Number'	'1' – '4'	
Qualifier Key	Qualifier Value	Qualifier Value
'FX Type'	'Send'	'Return'
# FXMute example InterfaceName.Set('FXMute', 'On', {'FX Number': '1', 'FX Type': 'Send'})		
Command	Value	
InputLevel	-50 to 10 in steps of 1	
Qualifier Key	Qualifier Value	
'Input'	'1' – '32'	
# InputLevel example InterfaceName.Set('InputLevel', 10, {'Input': '1'})		
Command	Value	Value
InputMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Input'	'1' – '32'	
# InputMute example InterfaceName.Set('InputMute', 'On', {'Input': '1'})		
Command	Value	Value
MasterMute	'On'	'Off'
# MasterMute example InterfaceName.Set('MasterMute', 'On')		
Command	Value	

MasterVolumeLevel	-50 to 10 in steps of 1		
# MasterVolumeLevel example InterfaceName.Set('MasterVolumeLevel', 10)			
Command MixAssign	Value 'On'	Value 'Off'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2' 'FX send 2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4' 'FX send 3'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8' 'FX send 1' 'FX send 4'
# MixAssign example InterfaceName.Set('MixAssign', 'On', {'Input': '1', 'Mix': '1'})			
Command MixFader	Value -50 to 10 in steps of 1		
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8'
# MixFader example InterfaceName.Set('MixFader', 10, {'Mix': '1'})			
Command MixMute	Value 'On'	Value 'Off'	
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8'
# MixMute example InterfaceName.Set('MixMute', 'On', {'Mix': '1'})			
Command MuteGroup	Value 'On'	Value 'Off'	
Qualifier Key 'Group'	Qualifier Value '1' – '4'		
# MuteGroup example InterfaceName.Set('MuteGroup', 'On', {'Group': '1'})			
Command RemoteShutdown ⁶	Value None		
# RemoteShutdown example InterfaceName.Set('RemoteShutdown', None)			
Command SceneRecall	Value '1' – '100'		
# SceneRecall example InterfaceName.Set('SceneRecall', '1')			
Command SendLevel	Value -50 to 10 in steps of 1		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Mix'	Qualifier Value '1' – '4'	Qualifier Value '5-6'	Qualifier Value '7-8'

Global Scripter Module Communication Sheet

	'9-10'	'FX send 1'	'FX send 2'
	'Grp1-2'	'Grp3-4'	'Grp5-6'
	'Grp7-8'	'MTX1-2'	'MTX3-4'
	'FX send 3'	'FX send 4'	
<pre># SendLevel example InterfaceName.Set('SendLevel', 10, {'Input': '1', 'Mix': '1'})</pre>			

¹ The QU mixer will require a hard power reset to switch on the mixer and for the driver to work.

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus, DCAFaderLevel, DCAMute, FXFaderLevel, FXMute, InputLevel, InputMute, MasterMute, MixAssign, MixFader, MixMute, MuteGroup, SceneRecall, and SendLevel do not support the Update function. ConnectionStatus is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus example InterfaceName.Update('ConnectionStatus') Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	
DCAFaderLevel	-50 to 10 in steps of 1	
Qualifier Key	Qualifier Value	
'DCA'	'1' – '4'	
# DCAFaderLevel example InterfaceName.Update('DCAFaderLevel', {'DCA': '1'}) Value = InterfaceName.ReadStatus('DCAFaderLevel', {'DCA': '1'}) InterfaceName.SubscribeStatus('DCAFaderLevel', None, FeedbackHandler)		
Command	Value	Value
DCAMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'DCA'	'1' – '4'	
# DCAMute example InterfaceName.Update('DCAMute', {'DCA': '1'}) Value = InterfaceName.ReadStatus('DCAMute', {'DCA': '1'}) InterfaceName.SubscribeStatus('DCAMute', None, FeedbackHandler)		
Command	Value	
FXFaderLevel	-50 to 10 in steps of 1	
Qualifier Key	Qualifier Value	
'FX Number'	'1' – '4'	
Qualifier Key	Qualifier Value	Qualifier Value
'FX Type'	'Send'	'Return'
# FXFaderLevel example InterfaceName.Update('FXFaderLevel', {'FX Number': '1', 'FX Type': 'Send'}) Value = InterfaceName.ReadStatus('FXFaderLevel', {'FX Number': '1', 'FX Type': 'Send'}) InterfaceName.SubscribeStatus('FXFaderLevel', None, FeedbackHandler)		
Command	Value	Value
FXMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'FX Number'	'1' – '4'	

Global Scriptor Module Communication Sheet

Qualifier Key 'FX Type'	Qualifier Value 'Send'	Qualifier Value 'Return'	
# FXMute example InterfaceName.Update('FXMute', {'FX Number': '1', 'FX Type': 'Send'}) Value = InterfaceName.ReadStatus('FXMute', {'FX Number': '1', 'FX Type': 'Send'}) InterfaceName.SubscribeStatus('FXMute', None, FeedbackHandler)			
Command InputLevel	Value -50 to 10 in steps of 1		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
# InputLevel example InterfaceName.Update('InputLevel', {'Input': '1'}) Value = InterfaceName.ReadStatus('InputLevel', {'Input': '1'}) InterfaceName.SubscribeStatus('InputLevel', None, FeedbackHandler)			
Command InputMute	Value 'On'	Value 'Off'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
# InputMute example InterfaceName.Update('InputMute', {'Input': '1'}) Value = InterfaceName.ReadStatus('InputMute', {'Input': '1'}) InterfaceName.SubscribeStatus('InputMute', None, FeedbackHandler)			
Command MasterMute	Value 'On'	Value 'Off'	
# MasterMute example InterfaceName.Update('MasterMute') Value = InterfaceName.ReadStatus('MasterMute') InterfaceName.SubscribeStatus('MasterMute', None, FeedbackHandler)			
Command MasterVolumeLevel *	Value -50 to 10 in steps of 1		
# MasterVolumeLevel example InterfaceName.Update('MasterVolumeLevel') Value = InterfaceName.ReadStatus('MasterVolumeLevel') InterfaceName.SubscribeStatus('MasterVolumeLevel', None, FeedbackHandler)			
Command MixAssign	Value 'On'	Value 'Off'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2' 'FX send 2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4' 'FX send 3'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8' 'FX send 1' 'FX send 4'
# MixAssign example InterfaceName.Update('MixAssign', {'Input': '1', 'Mix': '1'}) Value = InterfaceName.ReadStatus('MixAssign', {'Input': '1', 'Mix': '1'}) InterfaceName.SubscribeStatus('MixAssign', None, FeedbackHandler)			
Command MixFader	Value -50 to 10 in steps of 1		
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8'

Global Scripter Module Communication Sheet

<pre># MixFader example InterfaceName.Update('MixFader', {'Mix': '1'}) Value = InterfaceName.ReadStatus('MixFader', {'Mix': '1'}) InterfaceName.SubscribeStatus('MixFader', None, FeedbackHandler)</pre>			
Command MixMute	Value 'On'	Value 'Off'	
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp3-4' 'MTX1-2'	Qualifier Value '5-6' 'LR' 'Grp5-6' 'MTX3-4'	Qualifier Value '7-8' 'Grp1-2' 'Grp7-8'
<pre># MixMute example InterfaceName.Update('MixMute', {'Mix': '1'}) Value = InterfaceName.ReadStatus('MixMute', {'Mix': '1'}) InterfaceName.SubscribeStatus('MixMute', None, FeedbackHandler)</pre>			
Command MuteGroup	Value 'On'	Value 'Off'	
Qualifier Key 'Group'	Qualifier Value '1' – '4'		
<pre># MuteGroup example InterfaceName.Update('MuteGroup', {'Group': '1'}) Value = InterfaceName.ReadStatus('MuteGroup', {'Group': '1'}) InterfaceName.SubscribeStatus('MuteGroup', None, FeedbackHandler)</pre>			
Command SceneRecall	Value '1' – '100'		
<pre># SceneRecall example InterfaceName.Update('SceneRecall') Value = InterfaceName.ReadStatus('SceneRecall') InterfaceName.SubscribeStatus('SceneRecall', None, FeedbackHandler)</pre>			
Command SendLevel	Value -50 to 10 in steps of 1		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Mix'	Qualifier Value '1' – '4' '9-10' 'Grp1-2' 'Grp7-8' 'FX send 3'	Qualifier Value '5-6' 'FX send 1' 'Grp3-4' 'MTX1-2' 'FX send 4'	Qualifier Value '7-8' 'FX send 2' 'Grp5-6' 'MTX3-4'
<pre># SendLevel example InterfaceName.Update('SendLevel', {'Input': '1', 'Mix': '1'}) Value = InterfaceName.ReadStatus('SendLevel', {'Input': '1', 'Mix': '1'}) InterfaceName.SubscribeStatus('SendLevel', None, FeedbackHandler)</pre>			

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet

Default Port: 51325

Logon Credentials Supported: No

Multi-Connection Capabilities: No

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

QU-SB requires an iPad running the Qu-Pad app to view or change its IP address. Please refer to section 6.4 of Qu-SB Getting Started Guide (http://www.allen-heath.com/media/Qu-SB-Getting-Started-Guide-AP10287_2.pdf).

Appendix A. Set Commands

DCA Fader Level 10 DCA 1	\xB1c\x10\xB1b\x17\xB1\x06\x7F\xB1&\x07
DCA Fader Level 10 DCA 4	\xB1c\x13\xB1b\x17\xB1\x06\x7F\xB1&\x07
DCA Fader Level -50 DCA 1	\xB1c\x10\xB1b\x17\xB1\x06\x00\xB1&\x07
DCA Fader Level -50 DCA 4	\xB1c\x13\xB1b\x17\xB1\x06\x00\xB1&\x07
DCA Mute Off DCA 1	\x91\x10?\x81\x10\x00
DCA Mute Off DCA 4	\x91\x13?\x81\x13\x00
DCA Mute On DCA 1	\x91\x10\x7F\x81\x10\x00
DCA Mute On DCA 4	\x91\x13\x7F\x81\x13\x00
FX Fader Level 10 FX Number 1 FX Type Return	\xB1c\x08\xB1b\x17\xB1\x06\x7F\xB1&\x07
FX Fader Level 10 FX Number 4 FX Type Return	\xB1c\x0B\xB1b\x17\xB1\x06\x7F\xB1&\x07
FX Fader Level -50 FX Number 1 FX Type Return	\xB1c\x08\xB1b\x17\xB1\x06\x00\xB1&\x07
FX Fader Level -50 FX Number 4 FX Type Return	\xB1c\x0B\xB1b\x17\xB1\x06\x00\xB1&\x07
FX Mute Off FX Number 1 FX Type Return	\x91\x08?\x81\x08\x00
FX Mute Off FX Number 1 FX Type Send	\x91\x00?\x81\x00\x00
FX Mute Off FX Number 4 FX Type Return	\x91\x0B?\x81\x0B\x00
FX Mute Off FX Number 4 FX Type Send	\x91\x03?\x81\x03\x00
FX Mute On FX Number 1 FX Type Return	\x91\x08\x7F\x81\x08\x00
FX Mute On FX Number 1 FX Type Send	\x91\x00\x7F\x81\x00\x00
FX Mute On FX Number 4 FX Type Return	\x91\x0B\x7F\x81\x0B\x00
FX Mute On FX Number 4 FX Type Send	\x91\x03\x7F\x81\x03\x00
Input Level 10 Input 1	\xB1c \xB1b\x17\xB1\x06\x7F\xB1&\x07
Input Level 10 Input 16	\xB1c/\xB1b\x17\xB1\x06\x7F\xB1&\x07
Input Level 10 Input 24	\xB1c7\xB1b\x17\xB1\x06\x7F\xB1&\x07
Input Level 10 Input 32	\xB1c?\xB1b\x17\xB1\x06\x7F\xB1&\x07
Input Level -50 Input 1	\xB1c \xB1b\x17\xB1\x06\x00\xB1&\x07
Input Level -50 Input 16	\xB1c/\xB1b\x17\xB1\x06\x00\xB1&\x07
Input Level -50 Input 24	\xB1c7\xB1b\x17\xB1\x06\x00\xB1&\x07
Input Level -50 Input 32	\xB1c?\xB1b\x17\xB1\x06\x00\xB1&\x07
Input Mute Off Input 1	\x91 ?\x81 \x00
Input Mute Off Input 16	\x91/?\x81/\x00
Input Mute Off Input 24	\x917?\x817\x00
Input Mute Off Input 32	\x91??\x81?\x00
Input Mute On Input 1	\x91 \x7F\x81 \x00
Input Mute On Input 16	\x91/\x7F\x81/\x00
Input Mute On Input 24	\x917\x7F\x817\x00
Input Mute On Input 32	\x91?\x7F\x81?\x00
Master Mute Off	\x91g?\x81g\x00
Master Mute On	\x91g\x7F\x81g\x00
Master Volume Level 10	\xB1cg\xB1b\x17\xB1\x06\x7F\xB1&\x07
Master Volume Level -50	\xB1cg\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Assign Off Mix 1 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x00
Mix Assign Off Mix 1 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x00

Global Scriptor Module Communication Sheet

Mix Assign Off Mix 1 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x00
Mix Assign Off Mix 1 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x00
Mix Assign Off Mix 4 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x03
Mix Assign Off Mix 4 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x03
Mix Assign Off Mix 4 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x03
Mix Assign Off Mix 4 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x03
Mix Assign Off Mix 5-6 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x04
Mix Assign Off Mix 5-6 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x04
Mix Assign Off Mix 5-6 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x04
Mix Assign Off Mix 5-6 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x04
Mix Assign Off Mix 7-8 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x05
Mix Assign Off Mix 7-8 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x05
Mix Assign Off Mix 7-8 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x05
Mix Assign Off Mix 7-8 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x05
Mix Assign Off Mix 9-10 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x06
Mix Assign Off Mix 9-10 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x06
Mix Assign Off Mix 9-10 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x06
Mix Assign Off Mix 9-10 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x06
Mix Assign Off Mix FX send 1 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x10
Mix Assign Off Mix FX send 1 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x10
Mix Assign Off Mix FX send 1 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x10
Mix Assign Off Mix FX send 1 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x10
Mix Assign Off Mix FX send 2 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x11
Mix Assign Off Mix FX send 2 Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x11
Mix Assign Off Mix FX send 2 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x11
Mix Assign Off Mix FX send 2 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x11
Mix Assign Off Mix FX send 3 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x12
Mix Assign Off Mix FX send 3 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x12
Mix Assign Off Mix FX send 3 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x12
Mix Assign Off Mix FX send 4 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x13
Mix Assign Off Mix FX send 4 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x13
Mix Assign Off Mix FX send 4 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x13
Mix Assign Off Mix Grp1-2 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x08
Mix Assign Off Mix Grp1-2 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x08
Mix Assign Off Mix Grp1-2 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x08
Mix Assign Off Mix Grp3-4 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x09
Mix Assign Off Mix Grp3-4 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x09
Mix Assign Off Mix Grp3-4 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x09
Mix Assign Off Mix Grp5-6 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x0A
Mix Assign Off Mix Grp5-6 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x0A
Mix Assign Off Mix Grp5-6 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x0A
Mix Assign Off Mix Grp7-8 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x0B
Mix Assign Off Mix Grp7-8 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x0B
Mix Assign Off Mix Grp7-8 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x0B

Global Scriptor Module Communication Sheet

Revision: 3/20/2020

Mix Assign Off Mix LR Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x07
Mix Assign Off Mix LR Input 16	\xB1c/\xB1bU\xB1\x06\x00\xB1&\x07
Mix Assign Off Mix LR Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x07
Mix Assign Off Mix LR Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x07
Mix Assign Off Mix MTX1-2 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x0C
Mix Assign Off Mix MTX1-2 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x0C
Mix Assign Off Mix MTX1-2 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x0C
Mix Assign Off Mix MTX3-4 Input 1	\xB1c \xB1bU\xB1\x06\x00\xB1&\x0D
Mix Assign Off Mix MTX3-4 Input 24	\xB1c7\xB1bU\xB1\x06\x00\xB1&\x0D
Mix Assign Off Mix MTX3-4 Input 32	\xB1c?\xB1bU\xB1\x06\x00\xB1&\x0D
Mix Assign On Mix 1 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x00
Mix Assign On Mix 1 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x00
Mix Assign On Mix 1 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x00
Mix Assign On Mix 1 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x00
Mix Assign On Mix 4 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x03
Mix Assign On Mix 4 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x03
Mix Assign On Mix 4 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x03
Mix Assign On Mix 4 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x03
Mix Assign On Mix 5-6 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x04
Mix Assign On Mix 5-6 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x04
Mix Assign On Mix 5-6 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x04
Mix Assign On Mix 5-6 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x04
Mix Assign On Mix 7-8 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x05
Mix Assign On Mix 7-8 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x05
Mix Assign On Mix 7-8 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x05
Mix Assign On Mix 7-8 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x05
Mix Assign On Mix 9-10 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x06
Mix Assign On Mix 9-10 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x06
Mix Assign On Mix 9-10 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x06
Mix Assign On Mix 9-10 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x06
Mix Assign On Mix FX send 1 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x10
Mix Assign On Mix FX send 1 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x10
Mix Assign On Mix FX send 1 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x10
Mix Assign On Mix FX send 1 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x10
Mix Assign On Mix FX send 2 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x11
Mix Assign On Mix FX send 2 Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x11
Mix Assign On Mix FX send 2 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x11
Mix Assign On Mix FX send 2 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x11
Mix Assign On Mix FX send 3 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x12
Mix Assign On Mix FX send 3 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x12
Mix Assign On Mix FX send 3 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x12
Mix Assign On Mix FX send 4 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x13
Mix Assign On Mix FX send 4 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x13
Mix Assign On Mix FX send 4 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x13

Global Scriptor Module Communication Sheet

Mix Assign On Mix Grp1-2 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x08
Mix Assign On Mix Grp1-2 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x08
Mix Assign On Mix Grp1-2 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x08
Mix Assign On Mix Grp3-4 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x09
Mix Assign On Mix Grp3-4 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x09
Mix Assign On Mix Grp3-4 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x09
Mix Assign On Mix Grp5-6 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x0A
Mix Assign On Mix Grp5-6 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x0A
Mix Assign On Mix Grp5-6 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x0A
Mix Assign On Mix Grp7-8 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x0B
Mix Assign On Mix Grp7-8 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x0B
Mix Assign On Mix Grp7-8 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x0B
Mix Assign On Mix LR Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x07
Mix Assign On Mix LR Input 16	\xB1c/\xB1bU\xB1\x06\x01\xB1&\x07
Mix Assign On Mix LR Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x07
Mix Assign On Mix LR Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x07
Mix Assign On Mix MTX1-2 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x0C
Mix Assign On Mix MTX1-2 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x0C
Mix Assign On Mix MTX1-2 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x0C
Mix Assign On Mix MTX3-4 Input 1	\xB1c \xB1bU\xB1\x06\x01\xB1&\x0D
Mix Assign On Mix MTX3-4 Input 24	\xB1c7\xB1bU\xB1\x06\x01\xB1&\x0D
Mix Assign On Mix MTX3-4 Input 32	\xB1c?\xB1bU\xB1\x06\x01\xB1&\x0D
Mix Fader 10 Mix 1	\xB1c` \xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix 4	\xB1cc\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix 5-6	\xB1cd\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix 7-8	\xB1ce\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix 9-10	\xB1cf\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix Grp1-2	\xB1ch\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix Grp3-4	\xB1ci\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix Grp5-6	\xB1cj\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix Grp7-8	\xB1ck\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix LR	\xB1cg\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix MTX1-2	\xB1cl\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader 10 Mix MTX3-4	\xB1cm\xB1b\x17\xB1\x06\x7F\xB1&\x07
Mix Fader -50 Mix 1	\xB1c` \xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix 4	\xB1cc\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix 5-6	\xB1cd\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix 7-8	\xB1ce\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix 9-10	\xB1cf\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix Grp1-2	\xB1ch\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix Grp3-4	\xB1ci\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix Grp5-6	\xB1cj\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix Grp7-8	\xB1ck\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix LR	\xB1cg\xB1b\x17\xB1\x06\x00\xB1&\x07

Global Scripter Module Communication Sheet

Revision: 3/20/2020

Mix Fader -50 Mix MTX1-2	\xB1c1\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Fader -50 Mix MTX3-4	\xB1cm\xB1b\x17\xB1\x06\x00\xB1&\x07
Mix Mute Off Mix 1	\x91`?\x81`\x00
Mix Mute Off Mix 4	\x91c?\x81c\x00
Mix Mute Off Mix 5-6	\x91d?\x81d\x00
Mix Mute Off Mix 7-8	\x91e?\x81e\x00
Mix Mute Off Mix 9-10	\x91f?\x81f\x00
Mix Mute Off Mix Grp1-2	\x91h?\x81h\x00
Mix Mute Off Mix Grp3-4	\x91i?\x81i\x00
Mix Mute Off Mix Grp5-6	\x91j?\x81j\x00
Mix Mute Off Mix Grp7-8	\x91k?\x81k\x00
Mix Mute Off Mix LR	\x91g?\x81g\x00
Mix Mute Off Mix MTX1-2	\x91l?\x81l\x00
Mix Mute Off Mix MTX3-4	\x91m?\x81m\x00
Mix Mute On Mix 1	\x91`\x7F\x81`\x00
Mix Mute On Mix 4	\x91c\x7F\x81c\x00
Mix Mute On Mix 5-6	\x91d\x7F\x81d\x00
Mix Mute On Mix 7-8	\x91e\x7F\x81e\x00
Mix Mute On Mix 9-10	\x91f\x7F\x81f\x00
Mix Mute On Mix Grp1-2	\x91h\x7F\x81h\x00
Mix Mute On Mix Grp3-4	\x91i\x7F\x81i\x00
Mix Mute On Mix Grp5-6	\x91j\x7F\x81j\x00
Mix Mute On Mix Grp7-8	\x91k\x7F\x81k\x00
Mix Mute On Mix LR	\x91g\x7F\x81g\x00
Mix Mute On Mix MTX1-2	\x91l\x7F\x81l\x00
Mix Mute On Mix MTX3-4	\x91m\x7F\x81m\x00
Mute Group Off Group 1	\x91P?\x81P\x00
Mute Group Off Group 4	\x91S?\x81S\x00
Mute Group On Group 1	\x91P\x7F\x81P\x00
Mute Group On Group 4	\x91S\x7F\x81S\x00
Remote Shutdown None	\xB1c\x00\xB1b_\xB1\x06\x00\xB1&\x00
Scene Recall 1	\xB1\x00\x00\xB1 \x00\xC1\x00
Scene Recall 100	\xB1\x00\x00\xB1 \x00\xC1c
Send Level 10 Mix 1 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x00
Send Level 10 Mix 1 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x00
Send Level 10 Mix 1 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x00
Send Level 10 Mix 1 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x00
Send Level 10 Mix 4 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x03
Send Level 10 Mix 4 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x03
Send Level 10 Mix 4 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x03
Send Level 10 Mix 4 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x03
Send Level 10 Mix 5-6 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x04
Send Level 10 Mix 5-6 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x04
Send Level 10 Mix 5-6 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x04

Global Scriptor Module Communication Sheet

Revision: 3/20/2020

Send Level 10 Mix 5-6 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x04
Send Level 10 Mix 7-8 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x05
Send Level 10 Mix 7-8 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x05
Send Level 10 Mix 7-8 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x05
Send Level 10 Mix 7-8 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x05
Send Level 10 Mix 9-10 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x06
Send Level 10 Mix 9-10 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x06
Send Level 10 Mix 9-10 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x06
Send Level 10 Mix 9-10 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x06
Send Level 10 Mix FX send 1 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x10
Send Level 10 Mix FX send 1 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x10
Send Level 10 Mix FX send 1 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x10
Send Level 10 Mix FX send 1 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x10
Send Level 10 Mix FX send 2 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x11
Send Level 10 Mix FX send 2 Input 16	\xB1c/\xB1b \xB1\x06\x7F\xB1&\x11
Send Level 10 Mix FX send 2 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x11
Send Level 10 Mix FX send 2 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x11
Send Level 10 Mix FX send 3 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x12
Send Level 10 Mix FX send 3 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x12
Send Level 10 Mix FX send 3 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x12
Send Level 10 Mix FX send 4 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x13
Send Level 10 Mix FX send 4 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x13
Send Level 10 Mix FX send 4 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x13
Send Level 10 Mix Grp1-2 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x08
Send Level 10 Mix Grp1-2 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x08
Send Level 10 Mix Grp1-2 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x08
Send Level 10 Mix Grp3-4 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x09
Send Level 10 Mix Grp3-4 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x09
Send Level 10 Mix Grp3-4 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x09
Send Level 10 Mix Grp5-6 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x0A
Send Level 10 Mix Grp5-6 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x0A
Send Level 10 Mix Grp5-6 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x0A
Send Level 10 Mix Grp7-8 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x0B
Send Level 10 Mix Grp7-8 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x0B
Send Level 10 Mix Grp7-8 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x0B
Send Level 10 Mix MTX1-2 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x0C
Send Level 10 Mix MTX1-2 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x0C
Send Level 10 Mix MTX1-2 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x0C
Send Level 10 Mix MTX3-4 Input 1	\xB1c \xB1b \xB1\x06\x7F\xB1&\x0D
Send Level 10 Mix MTX3-4 Input 24	\xB1c7\xB1b \xB1\x06\x7F\xB1&\x0D
Send Level 10 Mix MTX3-4 Input 32	\xB1c?\xB1b \xB1\x06\x7F\xB1&\x0D
Send Level -50 Mix 1 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x00
Send Level -50 Mix 1 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x00
Send Level -50 Mix 1 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x00

Global Scriptor Module Communication Sheet

Revision: 3/20/2020

Send Level -50 Mix 1 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x00
Send Level -50 Mix 4 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x03
Send Level -50 Mix 4 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x03
Send Level -50 Mix 4 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x03
Send Level -50 Mix 4 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x03
Send Level -50 Mix 5-6 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x04
Send Level -50 Mix 5-6 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x04
Send Level -50 Mix 5-6 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x04
Send Level -50 Mix 5-6 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x04
Send Level -50 Mix 7-8 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x05
Send Level -50 Mix 7-8 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x05
Send Level -50 Mix 7-8 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x05
Send Level -50 Mix 7-8 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x05
Send Level -50 Mix 9-10 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x06
Send Level -50 Mix 9-10 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x06
Send Level -50 Mix 9-10 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x06
Send Level -50 Mix 9-10 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x06
Send Level -50 Mix FX send 1 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x10
Send Level -50 Mix FX send 1 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x10
Send Level -50 Mix FX send 1 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x10
Send Level -50 Mix FX send 1 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x10
Send Level -50 Mix FX send 2 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x11
Send Level -50 Mix FX send 2 Input 16	\xB1c/\xB1b \xB1\x06\x00\xB1&\x11
Send Level -50 Mix FX send 2 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x11
Send Level -50 Mix FX send 2 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x11
Send Level -50 Mix FX send 3 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x12
Send Level -50 Mix FX send 3 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x12
Send Level -50 Mix FX send 3 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x12
Send Level -50 Mix FX send 4 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x13
Send Level -50 Mix FX send 4 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x13
Send Level -50 Mix FX send 4 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x13
Send Level -50 Mix Grp1-2 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x08
Send Level -50 Mix Grp1-2 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x08
Send Level -50 Mix Grp1-2 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x08
Send Level -50 Mix Grp3-4 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x09
Send Level -50 Mix Grp3-4 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x09
Send Level -50 Mix Grp3-4 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x09
Send Level -50 Mix Grp5-6 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x0A
Send Level -50 Mix Grp5-6 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x0A
Send Level -50 Mix Grp5-6 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x0A
Send Level -50 Mix Grp7-8 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x0B
Send Level -50 Mix Grp7-8 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x0B
Send Level -50 Mix Grp7-8 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x0B
Send Level -50 Mix MTX1-2 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x0C

Global Scripter Module Communication Sheet

Send Level -50 Mix MTX1-2 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x0C
Send Level -50 Mix MTX1-2 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x0C
Send Level -50 Mix MTX3-4 Input 1	\xB1c \xB1b \xB1\x06\x00\xB1&\x0D
Send Level -50 Mix MTX3-4 Input 24	\xB1c7\xB1b \xB1\x06\x00\xB1&\x0D
Send Level -50 Mix MTX3-4 Input 32	\xB1c?\xB1b \xB1\x06\x00\xB1&\x0D

Appendix B. Update Commands

Master Volume Level *	<code>\xF0\x00\x00\x1A\x11\x01\x00\x7F\x10\x00\xF7</code>
------------------------------	---

*This command string will provide status for all commands listed in the Status Table.

