

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

## Device Specifications

Device Type: Audio Processor  
Manufacturer: Allen and Heath  
Firmware Version: N/A  
Model(s): QU-16, QU-32, QU-24, QU-Pac, QU-SB

## Tested on the Following Software and Firmware Versions

| IP Link Pro Control Processor Firmware | Global Scriptor Version |
|----------------------------------------|-------------------------|
| 3.09.0000-b009                         | 2.5.0                   |

## Version History

| Module Version | Date      | Notes                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
|----------------|-----------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1_4_1_0        | 7/22/2020 | Added MMC Transport Control command.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| 1_4_0_0        | 3/20/2020 | Fixed DCA Fader Level, FX Fader Level, Input Level, Master Volume Level, Mix Fader and Send Level commands. Added model QU-SB. Added Remote Shutdown command. Fixed Mix Mute. Added Status. Changed Volume Range to -50 to 10. Added MIDI Channel as Driver Parameter. Removed Midi Channel qualifier from all commands. Changed Mix Level to Send Level. Fixed DCA Mute, Mix Mute, Group Mute and Mix Fader. Added Mix Assign. Changed Mute Input to Input Mute. Fixed DCA Mute and FX Mute commands. Added Mute Group command. |
| 1_1_3_0        | 12/1/2016 | Initial Version                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

---

## Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.  
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.  
Example: `InterfaceName.connectionCounter = 5`
- MIDIDChannel variable must be set accordingly. MIDIDChannel ranges from 1' to '16'.  
Example: `InterfaceName.MIDIDChannel = '1'`

## Supported Class and Example

|                                                                                                |
|------------------------------------------------------------------------------------------------|
| <b>EthernetClass</b>                                                                           |
| <code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 51325, Model='QU-16')</code> |

## Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

|                                                                                                        |                         |                         |                         |
|--------------------------------------------------------------------------------------------------------|-------------------------|-------------------------|-------------------------|
| Command                                                                                                | Value                   |                         |                         |
| DCAFaderLevel                                                                                          | -50 to 10 in steps of 1 |                         |                         |
| Qualifier Key                                                                                          | Qualifier Value         |                         |                         |
| 'DCA'                                                                                                  | '1' – '4'               |                         |                         |
| # DCAFaderLevel example<br>InterfaceName.Set('DCAFaderLevel', 10, {'DCA': '1'})                        |                         |                         |                         |
| Command                                                                                                | Value                   |                         | Value                   |
| DCAMute                                                                                                | 'On'                    |                         | 'Off'                   |
| Qualifier Key                                                                                          | Qualifier Value         |                         |                         |
| 'DCA'                                                                                                  | '1' – '4'               |                         |                         |
| # DCAMute example<br>InterfaceName.Set('DCAMute', 'On', {'DCA': '1'})                                  |                         |                         |                         |
| Command                                                                                                | Value                   |                         |                         |
| FXFaderLevel                                                                                           | -50 to 10 in steps of 1 |                         |                         |
| Qualifier Key                                                                                          | Qualifier Value         |                         |                         |
| 'FX Number'                                                                                            | '1' – '4'               |                         |                         |
| Qualifier Key                                                                                          | Qualifier Value         | Qualifier Value         |                         |
| 'FX Type'                                                                                              | 'Send'                  | 'Return'                |                         |
| # FXFaderLevel example<br>InterfaceName.Set('FXFaderLevel', 10, {'FX Number': '1', 'FX Type': 'Send'}) |                         |                         |                         |
| Command                                                                                                | Value                   |                         | Value                   |
| FXMute                                                                                                 | 'On'                    |                         | 'Off'                   |
| Qualifier Key                                                                                          | Qualifier Value         |                         |                         |
| 'FX Number'                                                                                            | '1' – '4'               |                         |                         |
| Qualifier Key                                                                                          | Qualifier Value         | Qualifier Value         |                         |
| 'FX Type'                                                                                              | 'Send'                  | 'Return'                |                         |
| # FXMute example<br>InterfaceName.Set('FXMute', 'On', {'FX Number': '1', 'FX Type': 'Send'})           |                         |                         |                         |
| Command                                                                                                | Value                   |                         |                         |
| InputLevel                                                                                             | -50 to 10 in steps of 1 |                         |                         |
| Qualifier Key                                                                                          | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Input'                                                                                                | '1' – '16' <sup>1</sup> | '1' – '24' <sup>2</sup> | '1' – '32' <sup>3</sup> |
| # InputLevel example<br>InterfaceName.Set('InputLevel', 10, {'Input': '1'})                            |                         |                         |                         |
| Command                                                                                                | Value                   |                         | Value                   |
| InputMute                                                                                              | 'On'                    |                         | 'Off'                   |
| Qualifier Key                                                                                          | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Input'                                                                                                | '1' – '16' <sup>1</sup> | '1' – '24' <sup>2</sup> | '1' – '32' <sup>3</sup> |
| # InputMute example<br>InterfaceName.Set('InputMute', 'On', {'Input': '1'})                            |                         |                         |                         |
| Command                                                                                                | Value                   |                         | Value                   |
| MasterMute                                                                                             | 'On'                    |                         | 'Off'                   |
| # MasterMute example<br>InterfaceName.Set('MasterMute', 'On')                                          |                         |                         |                         |
| Command                                                                                                | Value                   |                         |                         |

|                                                                                         |                         |                         |                         |
|-----------------------------------------------------------------------------------------|-------------------------|-------------------------|-------------------------|
| MasterVolumeLevel                                                                       |                         | -50 to 10 in steps of 1 |                         |
| # MasterVolumeLevel example<br>InterfaceName.Set('MasterVolumeLevel', 10)               |                         |                         |                         |
| Command                                                                                 | Value                   | Value                   |                         |
| MixAssign                                                                               | 'On'                    | 'Off'                   |                         |
| Qualifier Key                                                                           | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Input'                                                                                 | '1' – '16' <sup>1</sup> | '1' – '24' <sup>2</sup> | '1' – '32' <sup>3</sup> |
| Qualifier Key                                                                           | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Mix'                                                                                   | '1' – '4'               | '5-6'                   | '7-8'                   |
|                                                                                         | '9-10'                  | 'LR'                    | 'Grp1-2'                |
|                                                                                         | 'Grp3-4'                | 'Grp5-6'                | 'Grp7-8'                |
|                                                                                         | 'MTX1-2'                | 'MTX3-4'                | 'FX send 1'             |
|                                                                                         | 'FX send 2'             | 'FX send 3'             | 'FX send 4'             |
| # MixAssign example<br>InterfaceName.Set('MixAssign', 'On', {'Input': '1', 'Mix': '1'}) |                         |                         |                         |
| Command                                                                                 | Value                   |                         |                         |
| MixFader                                                                                | -50 to 10 in steps of 1 |                         |                         |
| Qualifier Key                                                                           | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Mix'                                                                                   | '1' – '4'               | '5-6'                   | '7-8'                   |
|                                                                                         | '9-10'                  | 'LR'                    | 'Grp1-2'                |
|                                                                                         | 'Grp3-4'                | 'Grp5-6'                | 'Grp7-8'                |
|                                                                                         | 'MTX1-2'                | 'MTX3-4'                |                         |
| # MixFader example<br>InterfaceName.Set('MixFader', 10, {'Mix': '1'})                   |                         |                         |                         |
| Command                                                                                 | Value                   | Value                   |                         |
| MixMute                                                                                 | 'On'                    | 'Off'                   |                         |
| Qualifier Key                                                                           | Qualifier Value         | Qualifier Value         | Qualifier Value         |
| 'Mix'                                                                                   | '1' – '4'               | '5-6'                   | '7-8'                   |
|                                                                                         | '9-10'                  | 'LR'                    | 'Grp1-2' <sup>2,3</sup> |
|                                                                                         | 'Grp3-4' <sup>2,3</sup> | 'Grp5-6' <sup>2,3</sup> | 'Grp7-8' <sup>2,3</sup> |
|                                                                                         | 'MTX1-2'                | 'MTX3-4'                |                         |
| # MixMute example<br>InterfaceName.Set('MixMute', 'On', {'Mix': '1'})                   |                         |                         |                         |
| Command                                                                                 | Value                   | Value                   | Value                   |
| MMCTransportControl                                                                     | 'Stop'                  | 'Play'                  | 'Fast Forward'          |
|                                                                                         | 'Rewind'                | 'Record Strobe'         | 'Pause'                 |
| # MMCTransportControl example<br>InterfaceName.Set('MMCTransportControl', 'Stop')       |                         |                         |                         |
| Command                                                                                 | Value                   | Value                   |                         |
| MuteGroup                                                                               | 'On'                    | 'Off'                   |                         |
| Qualifier Key                                                                           | Qualifier Value         |                         |                         |
| 'Group'                                                                                 | '1' – '4'               |                         |                         |
| # MuteGroup example<br>InterfaceName.Set('MuteGroup', 'On', {'Group': '1'})             |                         |                         |                         |
| Command                                                                                 | Value                   |                         |                         |
| RemoteShutdown                                                                          | None                    |                         |                         |
| # RemoteShutdown example<br>InterfaceName.Set('RemoteShutdown', None)                   |                         |                         |                         |
| Command                                                                                 | Value                   |                         |                         |
| SceneRecall                                                                             | '1' – '100'             |                         |                         |
| # SceneRecall example<br>InterfaceName.Set('SceneRecall', '1')                          |                         |                         |                         |
| Command                                                                                 | Value                   |                         |                         |

## Global Scriptor Module Communication Sheet

|                                                                                       |                                                                                                                            |                                                                                                                             |                                                                                               |
|---------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------|
| <b>SendLevel</b>                                                                      | -50 to 10 in steps of 1                                                                                                    |                                                                                                                             |                                                                                               |
| <b>Qualifier Key</b><br><b>'Input'</b>                                                | Qualifier Value<br>'1' – '16' <sup>1</sup>                                                                                 | Qualifier Value<br>'1' – '24' <sup>2</sup>                                                                                  | Qualifier Value<br>'1' – '32' <sup>3</sup>                                                    |
| <b>Qualifier Key</b><br><b>'Mix'</b>                                                  | Qualifier Value<br>'1' – '4'<br>'9-10'<br>'Grp1-2' <sup>2,3</sup><br>'Grp7-8' <sup>2,3</sup><br>'FX send 3' <sup>2,3</sup> | Qualifier Value<br>'5-6'<br>'FX send 1'<br>'Grp3-4' <sup>2,3</sup><br>'MTX1-2' <sup>2,3</sup><br>'FX send 4' <sup>2,3</sup> | Qualifier Value<br>'7-8'<br>'FX send 2'<br>'Grp5-6' <sup>2,3</sup><br>'MTX3-4' <sup>2,3</sup> |
| # SendLevel example<br>InterfaceName.Set('SendLevel', 10, {'Input': '1', 'Mix': '1'}) |                                                                                                                            |                                                                                                                             |                                                                                               |

<sup>1</sup> QU-16 model only

<sup>2</sup> QU-24 model only

<sup>3</sup> QU-32, QU-Pac, and QU-SB models only

The QU mixer will require a hard power reset to switch on the mixer and for the driver to work.

## Status Available

For all commands, call Update to receive the latest status. ConnectionStatus, DCAFaderLevel, DCAMute, FXFaderLevel, FXMute, InputLevel, InputMute, MasterMute, MixAssign, MixFader, MixMute, MuteGroup, SceneRecall, and SendLevel do not support the Update function. ConnectionStatus is triggered by the device providing a successful response to other Update function calls.

### Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

### FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

### Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

|                                                                                                                                                                                                                                                                          |                         |                 |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------|-----------------|
| Command                                                                                                                                                                                                                                                                  | Value                   | Value           |
| ConnectionStatus                                                                                                                                                                                                                                                         | 'Connected'             | 'Disconnected'  |
| # ConnectionStatus example<br>InterfaceName.Update('ConnectionStatus')<br>Value = InterfaceName.ReadStatus('ConnectionStatus')<br>InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)                                                               |                         |                 |
| Command                                                                                                                                                                                                                                                                  | Value                   |                 |
| DCAFaderLevel                                                                                                                                                                                                                                                            | -50 to 10 in steps of 1 |                 |
| Qualifier Key                                                                                                                                                                                                                                                            | Qualifier Value         |                 |
| 'DCA'                                                                                                                                                                                                                                                                    | '1' – '4'               |                 |
| # DCAFaderLevel example<br>InterfaceName.Update('DCAFaderLevel', {'DCA': '1'})<br>Value = InterfaceName.ReadStatus('DCAFaderLevel', {'DCA': '1'})<br>InterfaceName.SubscribeStatus('DCAFaderLevel', None, FeedbackHandler)                                               |                         |                 |
| Command                                                                                                                                                                                                                                                                  | Value                   | Value           |
| DCAMute                                                                                                                                                                                                                                                                  | 'On'                    | 'Off'           |
| Qualifier Key                                                                                                                                                                                                                                                            | Qualifier Value         |                 |
| 'DCA'                                                                                                                                                                                                                                                                    | '1' – '4'               |                 |
| # DCAMute example<br>InterfaceName.Update('DCAMute', {'DCA': '1'})<br>Value = InterfaceName.ReadStatus('DCAMute', {'DCA': '1'})<br>InterfaceName.SubscribeStatus('DCAMute', None, FeedbackHandler)                                                                       |                         |                 |
| Command                                                                                                                                                                                                                                                                  | Value                   |                 |
| FXFaderLevel                                                                                                                                                                                                                                                             | -50 to 10 in steps of 1 |                 |
| Qualifier Key                                                                                                                                                                                                                                                            | Qualifier Value         |                 |
| 'FX Number'                                                                                                                                                                                                                                                              | '1' – '4'               |                 |
| Qualifier Key                                                                                                                                                                                                                                                            | Qualifier Value         | Qualifier Value |
| 'FX Type'                                                                                                                                                                                                                                                                | 'Send'                  | 'Return'        |
| # FXFaderLevel example<br>InterfaceName.Update('FXFaderLevel', {'FX Number': '1', 'FX Type': 'Send'})<br>Value = InterfaceName.ReadStatus('FXFaderLevel', {'FX Number': '1', 'FX Type': 'Send'})<br>InterfaceName.SubscribeStatus('FXFaderLevel', None, FeedbackHandler) |                         |                 |
| Command                                                                                                                                                                                                                                                                  | Value                   | Value           |
| FXMute                                                                                                                                                                                                                                                                   | 'On'                    | 'Off'           |
| Qualifier Key                                                                                                                                                                                                                                                            | Qualifier Value         |                 |
| 'FX Number'                                                                                                                                                                                                                                                              | '1' – '4'               |                 |

## Global Scriptor Module Communication Sheet

|                                                                                                                                                                                                                                                  |                                                                                                             |                                                                                                                      |                                                                                                                             |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------|
| Qualifier Key<br>'FX Type'                                                                                                                                                                                                                       | Qualifier Value<br>'Send'                                                                                   | Qualifier Value<br>'Return'                                                                                          |                                                                                                                             |
| # FXMute example<br>InterfaceName.Update('FXMute', {'FX Number': '1', 'FX Type': 'Send'})<br>Value = InterfaceName.ReadStatus('FXMute', {'FX Number': '1', 'FX Type': 'Send'})<br>InterfaceName.SubscribeStatus('FXMute', None, FeedbackHandler) |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>InputLevel                                                                                                                                                                                                                            | Value<br>-50 to 10 in steps of 1                                                                            |                                                                                                                      |                                                                                                                             |
| Qualifier Key<br>'Input'                                                                                                                                                                                                                         | Qualifier Value<br>'1' – '16' <sup>1</sup>                                                                  | Qualifier Value<br>'1' – '24' <sup>2</sup>                                                                           | Qualifier Value<br>'1' – '32' <sup>3</sup>                                                                                  |
| # InputLevel example<br>InterfaceName.Update('InputLevel', {'Input': '1'})<br>Value = InterfaceName.ReadStatus('InputLevel', {'Input': '1'})<br>InterfaceName.SubscribeStatus('InputLevel', None, FeedbackHandler)                               |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>InputMute                                                                                                                                                                                                                             | Value<br>'On'                                                                                               | Value<br>'Off'                                                                                                       |                                                                                                                             |
| Qualifier Key<br>'Input'                                                                                                                                                                                                                         | Qualifier Value<br>'1' – '16' <sup>1</sup>                                                                  | Qualifier Value<br>'1' – '24' <sup>2</sup>                                                                           | Qualifier Value<br>'1' – '32' <sup>3</sup>                                                                                  |
| # InputMute example<br>InterfaceName.Update('InputMute', {'Input': '1'})<br>Value = InterfaceName.ReadStatus('InputMute', {'Input': '1'})<br>InterfaceName.SubscribeStatus('InputMute', None, FeedbackHandler)                                   |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>MasterMute                                                                                                                                                                                                                            | Value<br>'On'                                                                                               | Value<br>'Off'                                                                                                       |                                                                                                                             |
| # MasterMute example<br>InterfaceName.Update('MasterMute')<br>Value = InterfaceName.ReadStatus('MasterMute')<br>InterfaceName.SubscribeStatus('MasterMute', None, FeedbackHandler)                                                               |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>MasterVolumeLevel *                                                                                                                                                                                                                   | Value<br>-50 to 10 in steps of 1                                                                            |                                                                                                                      |                                                                                                                             |
| # MasterVolumeLevel example<br>InterfaceName.Update('MasterVolumeLevel')<br>Value = InterfaceName.ReadStatus('MasterVolumeLevel')<br>InterfaceName.SubscribeStatus('MasterVolumeLevel', None, FeedbackHandler)                                   |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>MixAssign                                                                                                                                                                                                                             | Value<br>'On'                                                                                               | Value<br>'Off'                                                                                                       |                                                                                                                             |
| Qualifier Key<br>'Input'                                                                                                                                                                                                                         | Qualifier Value<br>'1' – '16' <sup>1</sup>                                                                  | Qualifier Value<br>'1' – '24' <sup>2</sup>                                                                           | Qualifier Value<br>'1' – '32' <sup>3</sup>                                                                                  |
| Qualifier Key<br>'Mix'                                                                                                                                                                                                                           | Qualifier Value<br>'1' – '4'<br>'9-10'<br>'Grp3-4' <sup>2,3</sup><br>'MTX1-2' <sup>2,3</sup><br>'FX send 2' | Qualifier Value<br>'5-6'<br>'LR'<br>'Grp5-6' <sup>2,3</sup><br>'MTX3-4' <sup>2,3</sup><br>'FX send 3' <sup>2,3</sup> | Qualifier Value<br>'7-8'<br>'Grp1-2' <sup>2,3</sup><br>'Grp7-8' <sup>2,3</sup><br>'FX send 1'<br>'FX send 4' <sup>2,3</sup> |
| # MixAssign example<br>InterfaceName.Update('MixAssign', {'Input': '1', 'Mix': '1'})<br>Value = InterfaceName.ReadStatus('MixAssign', {'Input': '1', 'Mix': '1'})<br>InterfaceName.SubscribeStatus('MixAssign', None, FeedbackHandler)           |                                                                                                             |                                                                                                                      |                                                                                                                             |
| Command<br>MixFader                                                                                                                                                                                                                              | Value<br>-50 to 10 in steps of 1                                                                            |                                                                                                                      |                                                                                                                             |
| Qualifier Key<br>'Mix'                                                                                                                                                                                                                           | Qualifier Value<br>'1' – '4'<br>'9-10'<br>'Grp3-4' <sup>2,3</sup><br>'MTX1-2' <sup>2,3</sup>                | Qualifier Value<br>'5-6'<br>'LR'<br>'Grp5-6' <sup>2,3</sup><br>'MTX3-4' <sup>2,3</sup>                               | Qualifier Value<br>'7-8'<br>'Grp1-2' <sup>2,3</sup><br>'Grp7-8' <sup>2,3</sup>                                              |

|                                                                                                                                                                                                                                        |                                                                                                                            |                                                                                                                             |                                                                                               |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------|
| # MixFader example<br>InterfaceName.Update('MixFader', {'Mix': '1'})<br>Value = InterfaceName.ReadStatus('MixFader', {'Mix': '1'})<br>InterfaceName.SubscribeStatus('MixFader', None, FeedbackHandler)                                 |                                                                                                                            |                                                                                                                             |                                                                                               |
| <b>Command</b><br><b>MixMute</b>                                                                                                                                                                                                       | Value<br>'On'                                                                                                              | Value<br>'Off'                                                                                                              |                                                                                               |
| <b>Qualifier Key</b><br><b>'Mix'</b>                                                                                                                                                                                                   | Qualifier Value<br>'1' – '4'<br>'9-10'<br>'Grp3-4' <sup>2,3</sup><br>'MTX1-2' <sup>2,3</sup>                               | Qualifier Value<br>'5-6'<br>'LR'<br>'Grp5-6' <sup>2,3</sup><br>'MTX3-4' <sup>2,3</sup>                                      | Qualifier Value<br>'7-8'<br>'Grp1-2' <sup>2,3</sup><br>'Grp7-8' <sup>2,3</sup>                |
| # MixMute example<br>InterfaceName.Update('MixMute', {'Mix': '1'})<br>Value = InterfaceName.ReadStatus('MixMute', {'Mix': '1'})<br>InterfaceName.SubscribeStatus('MixMute', None, FeedbackHandler)                                     |                                                                                                                            |                                                                                                                             |                                                                                               |
| <b>Command</b><br><b>MuteGroup</b>                                                                                                                                                                                                     | Value<br>'On'                                                                                                              | Value<br>'Off'                                                                                                              |                                                                                               |
| <b>Qualifier Key</b><br><b>'Group'</b>                                                                                                                                                                                                 | Qualifier Value<br>'1' – '4'                                                                                               |                                                                                                                             |                                                                                               |
| # MuteGroup example<br>InterfaceName.Update('MuteGroup', {'Group': '1'})<br>Value = InterfaceName.ReadStatus('MuteGroup', {'Group': '1'})<br>InterfaceName.SubscribeStatus('MuteGroup', None, FeedbackHandler)                         |                                                                                                                            |                                                                                                                             |                                                                                               |
| <b>Command</b><br><b>SceneRecall</b>                                                                                                                                                                                                   | Value<br>'1' – '100'                                                                                                       |                                                                                                                             |                                                                                               |
| # SceneRecall example<br>InterfaceName.Update('SceneRecall')<br>Value = InterfaceName.ReadStatus('SceneRecall')<br>InterfaceName.SubscribeStatus('SceneRecall', None, FeedbackHandler)                                                 |                                                                                                                            |                                                                                                                             |                                                                                               |
| <b>Command</b><br><b>SendLevel</b>                                                                                                                                                                                                     | Value<br>-50 to 10 in steps of 1                                                                                           |                                                                                                                             |                                                                                               |
| <b>Qualifier Key</b><br><b>'Input'</b>                                                                                                                                                                                                 | Qualifier Value<br>'1' – '16' <sup>1</sup>                                                                                 | Qualifier Value<br>'1' – '24' <sup>2</sup>                                                                                  | Qualifier Value<br>'1' – '32' <sup>3</sup>                                                    |
| <b>Qualifier Key</b><br><b>'Mix'</b>                                                                                                                                                                                                   | Qualifier Value<br>'1' – '4'<br>'9-10'<br>'Grp1-2' <sup>2,3</sup><br>'Grp7-8' <sup>2,3</sup><br>'FX send 3' <sup>2,3</sup> | Qualifier Value<br>'5-6'<br>'FX send 1'<br>'Grp3-4' <sup>2,3</sup><br>'MTX1-2' <sup>2,3</sup><br>'FX send 4' <sup>2,3</sup> | Qualifier Value<br>'7-8'<br>'FX send 2'<br>'Grp5-6' <sup>2,3</sup><br>'MTX3-4' <sup>2,3</sup> |
| # SendLevel example<br>InterfaceName.Update('SendLevel', {'Input': '1', 'Mix': '1'})<br>Value = InterfaceName.ReadStatus('SendLevel', {'Input': '1', 'Mix': '1'})<br>InterfaceName.SubscribeStatus('SendLevel', None, FeedbackHandler) |                                                                                                                            |                                                                                                                             |                                                                                               |

<sup>1</sup> QU-16 model only<sup>2</sup> QU-24 model only<sup>3</sup> QU-32, QU-Pac, and QU-SB models only



---

---

## Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

**Port Type:** Ethernet

**Default Port:** 51325

**Logon Credentials Supported:** No

**Multi-Connection Capabilities:** No

**Port Changeability:** No

---

---

## Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

## Notes for the Device

QU-SB requires an iPad running the Qu-Pad app to view or change its IP address. Please refer to section 6.4 of Qu-SB Getting Started Guide ([http://www.allen-heath.com/media/Qu-SB-Getting-Started-Guide-AP10287\\_2.pdf](http://www.allen-heath.com/media/Qu-SB-Getting-Started-Guide-AP10287_2.pdf)).

## Appendix A. Set Commands

|                                               |                                         |
|-----------------------------------------------|-----------------------------------------|
| DCA Fader Level 10 DCA 1                      | \xB1c\x10\xB1b\x17\xB1\x06\x7F\xB1&\x07 |
| DCA Fader Level 10 DCA 4                      | \xB1c\x13\xB1b\x17\xB1\x06\x7F\xB1&\x07 |
| DCA Fader Level -50 DCA 1                     | \xB1c\x10\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| DCA Fader Level -50 DCA 4                     | \xB1c\x13\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| DCA Mute Off DCA 1                            | \x91\x10?\x81\x10\x00                   |
| DCA Mute Off DCA 4                            | \x91\x13?\x81\x13\x00                   |
| DCA Mute On DCA 1                             | \x91\x10\x7F\x81\x10\x00                |
| DCA Mute On DCA 4                             | \x91\x13\x7F\x81\x13\x00                |
| FX Fader Level 10 FX Number 1 FX Type Return  | \xB1c\x08\xB1b\x17\xB1\x06\x7F\xB1&\x07 |
| FX Fader Level 10 FX Number 4 FX Type Return  | \xB1c\x0B\xB1b\x17\xB1\x06\x7F\xB1&\x07 |
| FX Fader Level -50 FX Number 1 FX Type Return | \xB1c\x08\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| FX Fader Level -50 FX Number 4 FX Type Return | \xB1c\x0B\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| FX Mute Off FX Number 1 FX Type Return        | \x91\x08?\x81\x08\x00                   |
| FX Mute Off FX Number 1 FX Type Send          | \x91\x00?\x81\x00\x00                   |
| FX Mute Off FX Number 4 FX Type Return        | \x91\x0B?\x81\x0B\x00                   |
| FX Mute Off FX Number 4 FX Type Send          | \x91\x03?\x81\x03\x00                   |
| FX Mute On FX Number 1 FX Type Return         | \x91\x08\x7F\x81\x08\x00                |
| FX Mute On FX Number 1 FX Type Send           | \x91\x00\x7F\x81\x00\x00                |
| FX Mute On FX Number 4 FX Type Return         | \x91\x0B\x7F\x81\x0B\x00                |
| FX Mute On FX Number 4 FX Type Send           | \x91\x03\x7F\x81\x03\x00                |
| Input Level 10 Input 1                        | \xB1c \xB1b\x17\xB1\x06\x7F\xB1&\x07    |
| Input Level 10 Input 16                       | \xB1c/\xB1b\x17\xB1\x06\x7F\xB1&\x07    |
| Input Level 10 Input 24                       | \xB1c7\xB1b\x17\xB1\x06\x7F\xB1&\x07    |
| Input Level 10 Input 32                       | \xB1c?\xB1b\x17\xB1\x06\x7F\xB1&\x07    |
| Input Level -50 Input 1                       | \xB1c \xB1b\x17\xB1\x06\x00\xB1&\x07    |
| Input Level -50 Input 16                      | \xB1c/\xB1b\x17\xB1\x06\x00\xB1&\x07    |
| Input Level -50 Input 24                      | \xB1c7\xB1b\x17\xB1\x06\x00\xB1&\x07    |
| Input Level -50 Input 32                      | \xB1c?\xB1b\x17\xB1\x06\x00\xB1&\x07    |
| Input Mute Off Input 1                        | \x91 ?\x81 \x00                         |
| Input Mute Off Input 16                       | \x91/?\x81/\x00                         |
| Input Mute Off Input 24                       | \x917?\x817\x00                         |
| Input Mute Off Input 32                       | \x91??\x81?\x00                         |
| Input Mute On Input 1                         | \x91 \x7F\x81 \x00                      |
| Input Mute On Input 16                        | \x91/\x7F\x81/\x00                      |
| Input Mute On Input 24                        | \x917\x7F\x817\x00                      |
| Input Mute On Input 32                        | \x91?\x7F\x81?\x00                      |
| Master Mute Off                               | \x91g?\x81g\x00                         |
| Master Mute On                                | \x91g\x7F\x81g\x00                      |
| Master Volume Level 10                        | \xB1cg\xB1b\x17\xB1\x06\x7F\xB1&\x07    |
| Master Volume Level -50                       | \xB1cg\xB1b\x17\xB1\x06\x00\xB1&\x07    |
| Mix Assign Off Mix 1 Input 1                  | \xB1c \xB1bU\xB1\x06\x00\xB1&\x00       |
| Mix Assign Off Mix 1 Input 16                 | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x00       |

## Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                       |                                   |
|---------------------------------------|-----------------------------------|
| Mix Assign Off Mix 1 Input 24         | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x00 |
| Mix Assign Off Mix 1 Input 32         | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x00 |
| Mix Assign Off Mix 4 Input 1          | \xB1c \xB1bU\xB1\x06\x00\xB1&\x03 |
| Mix Assign Off Mix 4 Input 16         | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x03 |
| Mix Assign Off Mix 4 Input 24         | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x03 |
| Mix Assign Off Mix 4 Input 32         | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x03 |
| Mix Assign Off Mix 5-6 Input 1        | \xB1c \xB1bU\xB1\x06\x00\xB1&\x04 |
| Mix Assign Off Mix 5-6 Input 16       | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x04 |
| Mix Assign Off Mix 5-6 Input 24       | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x04 |
| Mix Assign Off Mix 5-6 Input 32       | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x04 |
| Mix Assign Off Mix 7-8 Input 1        | \xB1c \xB1bU\xB1\x06\x00\xB1&\x05 |
| Mix Assign Off Mix 7-8 Input 16       | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x05 |
| Mix Assign Off Mix 7-8 Input 24       | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x05 |
| Mix Assign Off Mix 7-8 Input 32       | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x05 |
| Mix Assign Off Mix 9-10 Input 1       | \xB1c \xB1bU\xB1\x06\x00\xB1&\x06 |
| Mix Assign Off Mix 9-10 Input 16      | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x06 |
| Mix Assign Off Mix 9-10 Input 24      | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x06 |
| Mix Assign Off Mix 9-10 Input 32      | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x06 |
| Mix Assign Off Mix FX send 1 Input 1  | \xB1c \xB1bU\xB1\x06\x00\xB1&\x10 |
| Mix Assign Off Mix FX send 1 Input 16 | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x10 |
| Mix Assign Off Mix FX send 1 Input 24 | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x10 |
| Mix Assign Off Mix FX send 1 Input 32 | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x10 |
| Mix Assign Off Mix FX send 2 Input 1  | \xB1c \xB1bU\xB1\x06\x00\xB1&\x11 |
| Mix Assign Off Mix FX send 2 Input 16 | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x11 |
| Mix Assign Off Mix FX send 2 Input 24 | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x11 |
| Mix Assign Off Mix FX send 2 Input 32 | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x11 |
| Mix Assign Off Mix FX send 3 Input 1  | \xB1c \xB1bU\xB1\x06\x00\xB1&\x12 |
| Mix Assign Off Mix FX send 3 Input 24 | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x12 |
| Mix Assign Off Mix FX send 3 Input 32 | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x12 |
| Mix Assign Off Mix FX send 4 Input 1  | \xB1c \xB1bU\xB1\x06\x00\xB1&\x13 |
| Mix Assign Off Mix FX send 4 Input 24 | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x13 |
| Mix Assign Off Mix FX send 4 Input 32 | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x13 |
| Mix Assign Off Mix Grp1-2 Input 1     | \xB1c \xB1bU\xB1\x06\x00\xB1&\x08 |
| Mix Assign Off Mix Grp1-2 Input 24    | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x08 |
| Mix Assign Off Mix Grp1-2 Input 32    | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x08 |
| Mix Assign Off Mix Grp3-4 Input 1     | \xB1c \xB1bU\xB1\x06\x00\xB1&\x09 |
| Mix Assign Off Mix Grp3-4 Input 24    | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x09 |
| Mix Assign Off Mix Grp3-4 Input 32    | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x09 |
| Mix Assign Off Mix Grp5-6 Input 1     | \xB1c \xB1bU\xB1\x06\x00\xB1&\x0A |
| Mix Assign Off Mix Grp5-6 Input 24    | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x0A |
| Mix Assign Off Mix Grp5-6 Input 32    | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x0A |
| Mix Assign Off Mix Grp7-8 Input 1     | \xB1c \xB1bU\xB1\x06\x00\xB1&\x0B |
| Mix Assign Off Mix Grp7-8 Input 24    | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x0B |
| Mix Assign Off Mix Grp7-8 Input 32    | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x0B |

## Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                      |                                   |
|--------------------------------------|-----------------------------------|
| Mix Assign Off Mix LR Input 1        | \xB1c \xB1bU\xB1\x06\x00\xB1&\x07 |
| Mix Assign Off Mix LR Input 16       | \xB1c/\xB1bU\xB1\x06\x00\xB1&\x07 |
| Mix Assign Off Mix LR Input 24       | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x07 |
| Mix Assign Off Mix LR Input 32       | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x07 |
| Mix Assign Off Mix MTX1-2 Input 1    | \xB1c \xB1bU\xB1\x06\x00\xB1&\x0C |
| Mix Assign Off Mix MTX1-2 Input 24   | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x0C |
| Mix Assign Off Mix MTX1-2 Input 32   | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x0C |
| Mix Assign Off Mix MTX3-4 Input 1    | \xB1c \xB1bU\xB1\x06\x00\xB1&\x0D |
| Mix Assign Off Mix MTX3-4 Input 24   | \xB1c7\xB1bU\xB1\x06\x00\xB1&\x0D |
| Mix Assign Off Mix MTX3-4 Input 32   | \xB1c?\xB1bU\xB1\x06\x00\xB1&\x0D |
| Mix Assign On Mix 1 Input 1          | \xB1c \xB1bU\xB1\x06\x01\xB1&\x00 |
| Mix Assign On Mix 1 Input 16         | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x00 |
| Mix Assign On Mix 1 Input 24         | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x00 |
| Mix Assign On Mix 1 Input 32         | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x00 |
| Mix Assign On Mix 4 Input 1          | \xB1c \xB1bU\xB1\x06\x01\xB1&\x03 |
| Mix Assign On Mix 4 Input 16         | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x03 |
| Mix Assign On Mix 4 Input 24         | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x03 |
| Mix Assign On Mix 4 Input 32         | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x03 |
| Mix Assign On Mix 5-6 Input 1        | \xB1c \xB1bU\xB1\x06\x01\xB1&\x04 |
| Mix Assign On Mix 5-6 Input 16       | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x04 |
| Mix Assign On Mix 5-6 Input 24       | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x04 |
| Mix Assign On Mix 5-6 Input 32       | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x04 |
| Mix Assign On Mix 7-8 Input 1        | \xB1c \xB1bU\xB1\x06\x01\xB1&\x05 |
| Mix Assign On Mix 7-8 Input 16       | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x05 |
| Mix Assign On Mix 7-8 Input 24       | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x05 |
| Mix Assign On Mix 7-8 Input 32       | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x05 |
| Mix Assign On Mix 9-10 Input 1       | \xB1c \xB1bU\xB1\x06\x01\xB1&\x06 |
| Mix Assign On Mix 9-10 Input 16      | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x06 |
| Mix Assign On Mix 9-10 Input 24      | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x06 |
| Mix Assign On Mix 9-10 Input 32      | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x06 |
| Mix Assign On Mix FX send 1 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x10 |
| Mix Assign On Mix FX send 1 Input 16 | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x10 |
| Mix Assign On Mix FX send 1 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x10 |
| Mix Assign On Mix FX send 1 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x10 |
| Mix Assign On Mix FX send 2 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x11 |
| Mix Assign On Mix FX send 2 Input 16 | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x11 |
| Mix Assign On Mix FX send 2 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x11 |
| Mix Assign On Mix FX send 2 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x11 |
| Mix Assign On Mix FX send 3 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x12 |
| Mix Assign On Mix FX send 3 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x12 |
| Mix Assign On Mix FX send 3 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x12 |
| Mix Assign On Mix FX send 4 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x13 |
| Mix Assign On Mix FX send 4 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x13 |
| Mix Assign On Mix FX send 4 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x13 |

## Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                   |                                       |
|-----------------------------------|---------------------------------------|
| Mix Assign On Mix Grp1-2 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x08     |
| Mix Assign On Mix Grp1-2 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x08     |
| Mix Assign On Mix Grp1-2 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x08     |
| Mix Assign On Mix Grp3-4 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x09     |
| Mix Assign On Mix Grp3-4 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x09     |
| Mix Assign On Mix Grp3-4 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x09     |
| Mix Assign On Mix Grp5-6 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x0A     |
| Mix Assign On Mix Grp5-6 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x0A     |
| Mix Assign On Mix Grp5-6 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x0A     |
| Mix Assign On Mix Grp7-8 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x0B     |
| Mix Assign On Mix Grp7-8 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x0B     |
| Mix Assign On Mix Grp7-8 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x0B     |
| Mix Assign On Mix LR Input 1      | \xB1c \xB1bU\xB1\x06\x01\xB1&\x07     |
| Mix Assign On Mix LR Input 16     | \xB1c/\xB1bU\xB1\x06\x01\xB1&\x07     |
| Mix Assign On Mix LR Input 24     | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x07     |
| Mix Assign On Mix LR Input 32     | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x07     |
| Mix Assign On Mix MTX1-2 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x0C     |
| Mix Assign On Mix MTX1-2 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x0C     |
| Mix Assign On Mix MTX1-2 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x0C     |
| Mix Assign On Mix MTX3-4 Input 1  | \xB1c \xB1bU\xB1\x06\x01\xB1&\x0D     |
| Mix Assign On Mix MTX3-4 Input 24 | \xB1c7\xB1bU\xB1\x06\x01\xB1&\x0D     |
| Mix Assign On Mix MTX3-4 Input 32 | \xB1c?\xB1bU\xB1\x06\x01\xB1&\x0D     |
| Mix Fader 10 Mix 1                | \xB1c` \xB1b\x17\xB1\x06\x7F\xB1&\x07 |
| Mix Fader 10 Mix 4                | \xB1cc\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix 5-6              | \xB1cd\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix 7-8              | \xB1ce\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix 9-10             | \xB1cf\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix Grp1-2           | \xB1ch\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix Grp3-4           | \xB1ci\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix Grp5-6           | \xB1cj\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix Grp7-8           | \xB1ck\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix LR               | \xB1cg\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix MTX1-2           | \xB1cl\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader 10 Mix MTX3-4           | \xB1cm\xB1b\x17\xB1\x06\x7F\xB1&\x07  |
| Mix Fader -50 Mix 1               | \xB1c` \xB1b\x17\xB1\x06\x00\xB1&\x07 |
| Mix Fader -50 Mix 4               | \xB1cc\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix 5-6             | \xB1cd\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix 7-8             | \xB1ce\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix 9-10            | \xB1cf\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix Grp1-2          | \xB1ch\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix Grp3-4          | \xB1ci\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix Grp5-6          | \xB1cj\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix Grp7-8          | \xB1ck\xB1b\x17\xB1\x06\x00\xB1&\x07  |
| Mix Fader -50 Mix LR              | \xB1cg\xB1b\x17\xB1\x06\x00\xB1&\x07  |

## Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                     |                                      |
|-------------------------------------|--------------------------------------|
| Mix Fader -50 Mix MTX1-2            | \xB1c1\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| Mix Fader -50 Mix MTX3-4            | \xB1cm\xB1b\x17\xB1\x06\x00\xB1&\x07 |
| Mix Mute Off Mix 1                  | \x91`\x81`\x00                       |
| Mix Mute Off Mix 4                  | \x91c?\x81c\x00                      |
| Mix Mute Off Mix 5-6                | \x91d?\x81d\x00                      |
| Mix Mute Off Mix 7-8                | \x91e?\x81e\x00                      |
| Mix Mute Off Mix 9-10               | \x91f?\x81f\x00                      |
| Mix Mute Off Mix Grp1-2             | \x91h?\x81h\x00                      |
| Mix Mute Off Mix Grp3-4             | \x91i?\x81i\x00                      |
| Mix Mute Off Mix Grp5-6             | \x91j?\x81j\x00                      |
| Mix Mute Off Mix Grp7-8             | \x91k?\x81k\x00                      |
| Mix Mute Off Mix LR                 | \x91g?\x81g\x00                      |
| Mix Mute Off Mix MTX1-2             | \x91l?\x81l\x00                      |
| Mix Mute Off Mix MTX3-4             | \x91m?\x81m\x00                      |
| Mix Mute On Mix 1                   | \x91`\x7F\x81`\x00                   |
| Mix Mute On Mix 4                   | \x91c\x7F\x81c\x00                   |
| Mix Mute On Mix 5-6                 | \x91d\x7F\x81d\x00                   |
| Mix Mute On Mix 7-8                 | \x91e\x7F\x81e\x00                   |
| Mix Mute On Mix 9-10                | \x91f\x7F\x81f\x00                   |
| Mix Mute On Mix Grp1-2              | \x91h\x7F\x81h\x00                   |
| Mix Mute On Mix Grp3-4              | \x91i\x7F\x81i\x00                   |
| Mix Mute On Mix Grp5-6              | \x91j\x7F\x81j\x00                   |
| Mix Mute On Mix Grp7-8              | \x91k\x7F\x81k\x00                   |
| Mix Mute On Mix LR                  | \x91g\x7F\x81g\x00                   |
| Mix Mute On Mix MTX1-2              | \x91l\x7F\x81l\x00                   |
| Mix Mute On Mix MTX3-4              | \x91m\x7F\x81m\x00                   |
| Mute Group Off Group 1              | \x91P?\x81P\x00                      |
| Mute Group Off Group 4              | \x91S?\x81S\x00                      |
| Mute Group On Group 1               | \x91P\x7F\x81P\x00                   |
| Mute Group On Group 4               | \x91S\x7F\x81S\x00                   |
| MMC Transport Control Fast Forward  | \xF0\x7F\x7F\x06\x04\xF7             |
| MMC Transport Control Pause         | \xF0\x7F\x7F\x06\x09\xF7             |
| MMC Transport Control Play          | \xF0\x7F\x7F\x06\x02\xF7             |
| MMC Transport Control Record Strobe | \xF0\x7F\x7F\x06\x06\xF7             |
| MMC Transport Control Rewind        | \xF0\x7F\x7F\x06\x05\xF7             |
| MMC Transport Control Stop          | \xF0\x7F\x7F\x06\x01\xF7             |
| Remote Shutdown None                | \xB1c\x00\xB1b_\xB1\x06\x00\xB1&\x00 |
| Scene Recall 1                      | \xB1\x00\x00\xB1 \x00\xC1\x00        |
| Scene Recall 100                    | \xB1\x00\x00\xB1 \x00\xC1c           |
| Send Level 10 Mix 1 Input 1         | \xB1c \xB1b \xB1\x06\x7F\xB1&\x00    |
| Send Level 10 Mix 1 Input 16        | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x00    |
| Send Level 10 Mix 1 Input 24        | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x00    |
| Send Level 10 Mix 1 Input 32        | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x00    |
| Send Level 10 Mix 4 Input 1         | \xB1c \xB1b \xB1\x06\x7F\xB1&\x03    |

## Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                      |                                   |
|--------------------------------------|-----------------------------------|
| Send Level 10 Mix 4 Input 16         | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x03 |
| Send Level 10 Mix 4 Input 24         | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x03 |
| Send Level 10 Mix 4 Input 32         | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x03 |
| Send Level 10 Mix 5-6 Input 1        | \xB1c \xB1b \xB1\x06\x7F\xB1&\x04 |
| Send Level 10 Mix 5-6 Input 16       | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x04 |
| Send Level 10 Mix 5-6 Input 24       | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x04 |
| Send Level 10 Mix 5-6 Input 32       | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x04 |
| Send Level 10 Mix 7-8 Input 1        | \xB1c \xB1b \xB1\x06\x7F\xB1&\x05 |
| Send Level 10 Mix 7-8 Input 16       | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x05 |
| Send Level 10 Mix 7-8 Input 24       | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x05 |
| Send Level 10 Mix 7-8 Input 32       | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x05 |
| Send Level 10 Mix 9-10 Input 1       | \xB1c \xB1b \xB1\x06\x7F\xB1&\x06 |
| Send Level 10 Mix 9-10 Input 16      | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x06 |
| Send Level 10 Mix 9-10 Input 24      | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x06 |
| Send Level 10 Mix 9-10 Input 32      | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x06 |
| Send Level 10 Mix FX send 1 Input 1  | \xB1c \xB1b \xB1\x06\x7F\xB1&\x10 |
| Send Level 10 Mix FX send 1 Input 16 | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x10 |
| Send Level 10 Mix FX send 1 Input 24 | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x10 |
| Send Level 10 Mix FX send 1 Input 32 | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x10 |
| Send Level 10 Mix FX send 2 Input 1  | \xB1c \xB1b \xB1\x06\x7F\xB1&\x11 |
| Send Level 10 Mix FX send 2 Input 16 | \xB1c/\xB1b \xB1\x06\x7F\xB1&\x11 |
| Send Level 10 Mix FX send 2 Input 24 | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x11 |
| Send Level 10 Mix FX send 2 Input 32 | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x11 |
| Send Level 10 Mix FX send 3 Input 1  | \xB1c \xB1b \xB1\x06\x7F\xB1&\x12 |
| Send Level 10 Mix FX send 3 Input 24 | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x12 |
| Send Level 10 Mix FX send 3 Input 32 | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x12 |
| Send Level 10 Mix FX send 4 Input 1  | \xB1c \xB1b \xB1\x06\x7F\xB1&\x13 |
| Send Level 10 Mix FX send 4 Input 24 | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x13 |
| Send Level 10 Mix FX send 4 Input 32 | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x13 |
| Send Level 10 Mix Grp1-2 Input 1     | \xB1c \xB1b \xB1\x06\x7F\xB1&\x08 |
| Send Level 10 Mix Grp1-2 Input 24    | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x08 |
| Send Level 10 Mix Grp1-2 Input 32    | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x08 |
| Send Level 10 Mix Grp3-4 Input 1     | \xB1c \xB1b \xB1\x06\x7F\xB1&\x09 |
| Send Level 10 Mix Grp3-4 Input 24    | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x09 |
| Send Level 10 Mix Grp3-4 Input 32    | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x09 |
| Send Level 10 Mix Grp5-6 Input 1     | \xB1c \xB1b \xB1\x06\x7F\xB1&\x0A |
| Send Level 10 Mix Grp5-6 Input 24    | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x0A |
| Send Level 10 Mix Grp5-6 Input 32    | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x0A |
| Send Level 10 Mix Grp7-8 Input 1     | \xB1c \xB1b \xB1\x06\x7F\xB1&\x0B |
| Send Level 10 Mix Grp7-8 Input 24    | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x0B |
| Send Level 10 Mix Grp7-8 Input 32    | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x0B |
| Send Level 10 Mix MTX1-2 Input 1     | \xB1c \xB1b \xB1\x06\x7F\xB1&\x0C |
| Send Level 10 Mix MTX1-2 Input 24    | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x0C |
| Send Level 10 Mix MTX1-2 Input 32    | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x0C |

# Global Scriptor Module Communication Sheet

Revision: 7/22/2020

|                                       |                                   |
|---------------------------------------|-----------------------------------|
| Send Level 10 Mix MTX3-4 Input 1      | \xB1c \xB1b \xB1\x06\x7F\xB1&\x0D |
| Send Level 10 Mix MTX3-4 Input 24     | \xB1c7\xB1b \xB1\x06\x7F\xB1&\x0D |
| Send Level 10 Mix MTX3-4 Input 32     | \xB1c?\xB1b \xB1\x06\x7F\xB1&\x0D |
| Send Level -50 Mix 1 Input 1          | \xB1c \xB1b \xB1\x06\x00\xB1&\x00 |
| Send Level -50 Mix 1 Input 16         | \xB1c/\xB1b \xB1\x06\x00\xB1&\x00 |
| Send Level -50 Mix 1 Input 24         | \xB1c7\xB1b \xB1\x06\x00\xB1&\x00 |
| Send Level -50 Mix 1 Input 32         | \xB1c?\xB1b \xB1\x06\x00\xB1&\x00 |
| Send Level -50 Mix 4 Input 1          | \xB1c \xB1b \xB1\x06\x00\xB1&\x03 |
| Send Level -50 Mix 4 Input 16         | \xB1c/\xB1b \xB1\x06\x00\xB1&\x03 |
| Send Level -50 Mix 4 Input 24         | \xB1c7\xB1b \xB1\x06\x00\xB1&\x03 |
| Send Level -50 Mix 4 Input 32         | \xB1c?\xB1b \xB1\x06\x00\xB1&\x03 |
| Send Level -50 Mix 5-6 Input 1        | \xB1c \xB1b \xB1\x06\x00\xB1&\x04 |
| Send Level -50 Mix 5-6 Input 16       | \xB1c/\xB1b \xB1\x06\x00\xB1&\x04 |
| Send Level -50 Mix 5-6 Input 24       | \xB1c7\xB1b \xB1\x06\x00\xB1&\x04 |
| Send Level -50 Mix 5-6 Input 32       | \xB1c?\xB1b \xB1\x06\x00\xB1&\x04 |
| Send Level -50 Mix 7-8 Input 1        | \xB1c \xB1b \xB1\x06\x00\xB1&\x05 |
| Send Level -50 Mix 7-8 Input 16       | \xB1c/\xB1b \xB1\x06\x00\xB1&\x05 |
| Send Level -50 Mix 7-8 Input 24       | \xB1c7\xB1b \xB1\x06\x00\xB1&\x05 |
| Send Level -50 Mix 7-8 Input 32       | \xB1c?\xB1b \xB1\x06\x00\xB1&\x05 |
| Send Level -50 Mix 9-10 Input 1       | \xB1c \xB1b \xB1\x06\x00\xB1&\x06 |
| Send Level -50 Mix 9-10 Input 16      | \xB1c/\xB1b \xB1\x06\x00\xB1&\x06 |
| Send Level -50 Mix 9-10 Input 24      | \xB1c7\xB1b \xB1\x06\x00\xB1&\x06 |
| Send Level -50 Mix 9-10 Input 32      | \xB1c?\xB1b \xB1\x06\x00\xB1&\x06 |
| Send Level -50 Mix FX send 1 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x10 |
| Send Level -50 Mix FX send 1 Input 16 | \xB1c/\xB1b \xB1\x06\x00\xB1&\x10 |
| Send Level -50 Mix FX send 1 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x10 |
| Send Level -50 Mix FX send 1 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x10 |
| Send Level -50 Mix FX send 2 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x11 |
| Send Level -50 Mix FX send 2 Input 16 | \xB1c/\xB1b \xB1\x06\x00\xB1&\x11 |
| Send Level -50 Mix FX send 2 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x11 |
| Send Level -50 Mix FX send 2 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x11 |
| Send Level -50 Mix FX send 3 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x12 |
| Send Level -50 Mix FX send 3 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x12 |
| Send Level -50 Mix FX send 3 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x12 |
| Send Level -50 Mix FX send 4 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x13 |
| Send Level -50 Mix FX send 4 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x13 |
| Send Level -50 Mix FX send 4 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x13 |
| Send Level -50 Mix Grp1-2 Input 1     | \xB1c \xB1b \xB1\x06\x00\xB1&\x08 |
| Send Level -50 Mix Grp1-2 Input 24    | \xB1c7\xB1b \xB1\x06\x00\xB1&\x08 |
| Send Level -50 Mix Grp1-2 Input 32    | \xB1c?\xB1b \xB1\x06\x00\xB1&\x08 |
| Send Level -50 Mix Grp3-4 Input 1     | \xB1c \xB1b \xB1\x06\x00\xB1&\x09 |
| Send Level -50 Mix Grp3-4 Input 24    | \xB1c7\xB1b \xB1\x06\x00\xB1&\x09 |
| Send Level -50 Mix Grp3-4 Input 32    | \xB1c?\xB1b \xB1\x06\x00\xB1&\x09 |
| Send Level -50 Mix Grp5-6 Input 1     | \xB1c \xB1b \xB1\x06\x00\xB1&\x0A |



## Global Scriptor Module Communication Sheet

|                                    |                                   |
|------------------------------------|-----------------------------------|
| Send Level -50 Mix Grp5-6 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x0A |
| Send Level -50 Mix Grp5-6 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x0A |
| Send Level -50 Mix Grp7-8 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x0B |
| Send Level -50 Mix Grp7-8 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x0B |
| Send Level -50 Mix Grp7-8 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x0B |
| Send Level -50 Mix MTX1-2 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x0C |
| Send Level -50 Mix MTX1-2 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x0C |
| Send Level -50 Mix MTX1-2 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x0C |
| Send Level -50 Mix MTX3-4 Input 1  | \xB1c \xB1b \xB1\x06\x00\xB1&\x0D |
| Send Level -50 Mix MTX3-4 Input 24 | \xB1c7\xB1b \xB1\x06\x00\xB1&\x0D |
| Send Level -50 Mix MTX3-4 Input 32 | \xB1c?\xB1b \xB1\x06\x00\xB1&\x0D |

### Appendix B. Update Commands

|                       |                                               |
|-----------------------|-----------------------------------------------|
| Master Volume Level * | \xF0\x00\x00\x1AP\x11\x01\x00\x7F\x10\x00\xF7 |
|-----------------------|-----------------------------------------------|

\*This command string will provide status for all commands listed in the Status Table.