

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Audio Processor
Manufacturer: Allen and Heath
Firmware Version: N/A
Model(s): SQ-5, SQ-6, SQ-7

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.09.0000-b009	2.5.0

Version History

Module Version	Date	Notes
1_0_0_0	7/8/2020	Initial Version

Module Notes

- Status is not supported.

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 51325, Model='SQ-5')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value		
LevelControl ²	-90 to 10 in steps of 1 ¹		
Qualifier Key	Qualifier Value		
'MIDI Channel'	'1' – '16'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Source'	'Input 1'	'Input 2'	'Input 3'
	'Input 4'	'Input 5'	'Input 6'
	'Input 7'	'Input 8'	'Input 9'
	'Input 10'	'Input 11'	'Input 12'
	'Input 13'	'Input 14'	'Input 15'
	'Input 16'	'Input 17'	'Input 18'
	'Input 19'	'Input 20'	'Input 21'
	'Input 22'	'Input 23'	'Input 24'
	'Input 25'	'Input 26'	'Input 27'
	'Input 28'	'Input 29'	'Input 30'
	'Input 31'	'Input 32'	'Input 33'
	'Input 34'	'Input 35'	'Input 36'
	'Input 37'	'Input 38'	'Input 39'
	'Input 40'	'Input 41'	'Input 42'
	'Input 43'	'Input 44'	'Input 45'
	'Input 46'	'Input 47'	'Input 48'
	'Group 1'	'Group 2'	'Group 3'
	'Group 4'	'Group 5'	'Group 6'
	'Group 7'	'Group 8'	'Group 9'
	'Group 10'	'Group 11'	'Group 12'
	'FX 1 Return'	'FX 2 Return'	'FX 3 Return'
	'FX 4 Return'	'FX 5 Return'	'FX 6 Return'
	'FX 7 Return'	'FX 8 Return'	'LR'
	'AUX 1'	'AUX 2'	'AUX 3'
	'AUX 4'	'AUX 5'	'AUX 6'
	'AUX 7'	'AUX 8'	'AUX 9'
	'AUX 10'	'AUX 11'	'AUX 12'
	'FX 1 Send'	'FX 2 Send'	'FX 3 Send'
	'FX 4 Send'	'Matrix 1'	'Matrix 2'
	'Matrix 3'	'DCA 1'	'DCA 2'
	'DCA 3'	'DCA 4'	'DCA 5'
	'DCA 6'	'DCA 7'	'DCA 8'
	'Master Group 1'	'Master Group 2'	'Master Group 3'
	'Master Group 4'	'Master Group 5'	'Master Group 6'
	'Master Group 7'	'Master Group 8'	
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Destination'	'LR'	'AUX 1'	'AUX 2'

Global Scripter Module Communication Sheet

	'AUX 3'	'AUX 4'	'AUX 5'
	'AUX 6'	'AUX 7'	'AUX 8'
	'AUX 9'	'AUX 10'	'AUX 11'
	'AUX 12'	'Group 1'	'Group 2'
	'Group 3'	'Group 4'	'Group 5'
	'Group 6'	'Group 7'	'Group 8'
	'Group 9'	'Group 10'	'Group 11'
	'Group 12'	'FX 1 Send'	'FX 2 Send'
	'FX 3 Send'	'FX 4 Send'	'Matrix 1'
	'Matrix 2'	'Matrix 3'	'Output'
	'Control'		
# LevelControl example InterfaceName.Set('LevelControl', 10, {'MIDI Channel': '1', 'Source': 'Input 1', 'Destination': 'LR'})			
Command	Value	Value	
MuteControl	'On'	'Off'	
Qualifier Key	Qualifier Value		
'MIDI Channel'	'1' – '16'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Source'	'Input 1'	'Input 2'	'Input 3'
	'Input 4'	'Input 5'	'Input 6'
	'Input 7'	'Input 8'	'Input 9'
	'Input 10'	'Input 11'	'Input 12'
	'Input 13'	'Input 14'	'Input 15'
	'Input 16'	'Input 17'	'Input 18'
	'Input 19'	'Input 20'	'Input 21'
	'Input 22'	'Input 23'	'Input 24'
	'Input 25'	'Input 26'	'Input 27'
	'Input 28'	'Input 29'	'Input 30'
	'Input 31'	'Input 32'	'Input 33'
	'Input 34'	'Input 35'	'Input 36'
	'Input 37'	'Input 38'	'Input 39'
	'Input 40'	'Input 41'	'Input 42'
	'Input 43'	'Input 44'	'Input 45'
	'Input 46'	'Input 47'	'Input 48'
	'Group 1'	'Group 2'	'Group 3'
	'Group 4'	'Group 5'	'Group 6'
	'Group 7'	'Group 8'	'Group 9'
	'Group 10'	'Group 11'	'Group 12'
	'FX 1 Return'	'FX 2 Return'	'FX 3 Return'
	'FX 4 Return'	'FX 5 Return'	'FX 6 Return'
	'FX 7 Return'	'FX 8 Return'	'LR'
	'AUX 1'	'AUX 2'	'AUX 3'
	'AUX 4'	'AUX 5'	'AUX 6'
	'AUX 7'	'AUX 8'	'AUX 9'
	'AUX 10'	'AUX 11'	'AUX 12'
	'FX 1 Send'	'FX 2 Send'	'FX 3 Send'
	'FX 4 Send'	'Matrix 1'	'Matrix 2'
	'Matrix 3'	'DCA 1'	'DCA 2'
	'DCA 3'	'DCA 4'	'DCA 5'

Global Scriptor Module Communication Sheet

	'DCA 6'	'DCA 7'	'DCA 8'
	'Master Group 1'	'Master Group 2'	'Master Group 3'
	'Master Group 4'	'Master Group 5'	'Master Group 6'
	'Master Group 7'	'Master Group 8'	
# MuteControl example InterfaceName.Set('MuteControl', 'On', {'MIDI Channel': '1', 'Source': 'Input 1'})			
Command	Value		
SceneRecall	1 – 300		
Qualifier Key	Qualifier Value		
'MIDI Channel'	'1' – '16'		
# SceneRecall example InterfaceName.Set('SceneRecall', 300, {'MIDI Channel': '1'})			

¹ -90 dB represents negative infinity

² The following combinations are not supported:

- Group 1 to AUX 12
- Group 2 to AUX 11 – 12
- Group 3 to AUX 10 – 12
- Group 4 to AUX 9 – 12
- Group 5 to AUX 8 – 12
- Group 6 to AUX 7 – 12
- Group 7 to AUX 6 – 12
- Group 8 to AUX 5 – 12
- Group 9 to AUX 4 – 12
- Group 10 to AUX 3 – 12
- Group 11 to AUX 2 – 12
- Group 12 to AUX 1 – 12

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface.

Port Type: Ethernet

Default Port: 51325

Logon Credentials Supported: No

Multi-Connection Capabilities: Yes

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 10	\xB0cE\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 11	\xB0cE\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 4	\xB0cE\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 5	\xB0cE\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 6	\xB0cE\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 7	\xB0cE\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 8	\xB0cE\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Group 9	\xB0cE\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 1	\xB0c@\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 10	\xB0cA\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 11	\xB0cA\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1	\xB0cA\xB0bH\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 12	
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 13	\xB0cA\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 14	\xB0cA\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 15	\xB0cA\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 16	\xB0cA\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 2	\xB0c@\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 20	\xB0cB\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 21	\xB0cB\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 22	\xB0cB\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 23	\xB0cB\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 24	\xB0cB\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 25	\xB0cB\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 26	\xB0cB\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 27	\xB0cB\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 3	\xB0c@\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 30	\xB0cC\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 31	\xB0cC\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 32	\xB0cC\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 33	\xB0cC\xB0bD\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 34	\xB0cC\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 35	\xB0cC\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 36	\xB0cC\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 37	\xB0cC\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 4	\xB0c@\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 41	\xB0cD\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 42	\xB0cD\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 43	\xB0cD\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 44	\xB0cD\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 45	\xB0cD\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 46	\xB0cD\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 47	\xB0cD\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 48	\xB0cD\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 5	\xB0c@\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 1 Source Input 9	\xB0cA\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16	\xBFcF\xBFb, \xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source FX 3 Return	
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 10	\xBFcE\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 11	\xBFcE\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 4	\xBFcE\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 5	\xBFcE\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 6	\xBFcE\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 7	\xBFcE\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 8	\xBFcE\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Group 9	\xBFcE\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 1	\xBFc@\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 10	\xBFcA\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 11	\xBFcA\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 12	\xBFcA\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 13	\xBFcA\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 14	\xBFcA\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 15	\xBFcA\xBFb1\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 16	\xBFcA\xBFb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 2	\xBFc@\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 20	\xBFcB\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 21	\xBFcB\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 22	\xBFcB\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 23	\xBFcB\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 24	\xBFcB\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 25	\xBFcB\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 26	\xBFcB\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 27	\xBFcB\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 3	\xBFc@\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 30	\xBFcC\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 31	\xBFcC\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 32	\xBFcC\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 33	\xBFcC\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 34	\xBFcC\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 35	\xBFcC\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 36	\xBFcC\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16	\xBFcC\xBFbt\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 37	
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 4	\xBFc@\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 41	\xBFcD\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 42	\xBFcD\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 43	\xBFcD\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 44	\xBFcD\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 45	\xBFcD\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 46	\xBFcD\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 47	\xBFcD\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 48	\xBFcD\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 5	\xBFc@\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 1 MIDI Channel 16 Source Input 9	\xBFcA\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bY\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 1	\xB0c@\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 10	\xB0cA\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 11	\xB0cA\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 12	\xB0cA\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 13	\xB0cA\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 14	\xB0cA\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 15	\xB0cA\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 19	\xB0cB\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 2	\xB0c@\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 20	\xB0cB\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 21	\xB0cB\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 22	\xB0cB\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 23	\xB0cB\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 24	\xB0cB\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 25	\xB0cB\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 26	\xB0cB\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1	\xB0cC\xB0b\x05\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 27	
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 3	\xB0c@\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 30	\xB0cC\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 31	\xB0cC\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 32	\xB0cC\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 33	\xB0cC\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 34	\xB0cC\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 35	\xB0cC\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 36	\xB0cC\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 37	\xB0cC\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 4	\xB0c@\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 40	\xB0cD\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 41	\xB0cD\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 42	\xB0cD\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 43	\xB0cD\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 44	\xB0cD\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 45	\xB0cD\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 46	\xB0cD\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 47	\xB0cD\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x01\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 5	\xB0c@\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 8	\xB0cA\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 1 Source Input 9	\xB0cA\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 1	\xBFc@\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 10	\xBFcA\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 11	\xBFcA\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 12	\xBFcA\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 13	\xBFcA\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 14	\xBFcA\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 15	\xBFcA\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel	\xBFcB\xBFb\x0D\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Input 17	
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 19	\xBFcB\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 2	\xBFc@\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 20	\xBFcB\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 21	\xBFcB\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 22	\xBFcB\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 23	\xBFcB\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 24	\xBFcB\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 25	\xBFcB\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 26	\xBFcB\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 3	\xBFc@\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 30	\xBFcC\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 31	\xBFcC\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 32	\xBFcC\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 33	\xBFcC\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 34	\xBFcC\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 35	\xBFcC\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 36	\xBFcC\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 37	\xBFcC\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x09\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 4	\xBFc@\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 40	\xBFcD\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 41	\xBFcD\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 42	\xBFcD\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 43	\xBFcD\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 44	\xBFcD\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 45	\xBFcD\xBFb]\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 46	\xBFcD\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 47	\xBFcD\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 5	\xBFc@\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 8	\xBFcA\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 10 MIDI Channel 16 Source Input 9	\xBFcA\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1	\xB0cF\xB0br\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 8 Return	
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 1	\xB0c@\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 10	\xB0cA\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 11	\xB0cA\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 12	\xB0cA\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 13	\xB0cA\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 14	\xB0cA\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 15	\xB0cA\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 19	\xB0cB\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 2	\xB0c@\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 20	\xB0cB\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 21	\xB0cB\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 22	\xB0cB\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 23	\xB0cB\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 24	\xB0cB\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 25	\xB0cB\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 26	\xB0cB\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1E\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 3	\xB0c@\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 30	\xB0cC\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 31	\xB0cC\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 32	\xB0cC\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 33	\xB0cC\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 34	\xB0cC\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 35	\xB0cC\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 36	\xB0cC\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 37	\xB0cC\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 4	\xB0c@\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 40	\xB0cD\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 41	\xB0cD\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 42	\xB0cD\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 43	\xB0cD\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 44	\xB0cD\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 45	\xB0cD\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 46	\xB0cD\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 47	\xB0cD\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 5	\xB0c@\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1	\xB0cA\xB0b\x16\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 7	
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 8	\xB0cA\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 1 Source Input 9	\xB0cA\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 1	\xBFc@\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 10	\xBFcA\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 11	\xBFcA\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 12	\xBFcA\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 13	\xBFcA\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 14	\xBFcA\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 15	\xBFcA\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 19	\xBFcB\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 2	\xBFc@\xBFbZ\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 20	\xBFcB\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 21	\xBFcB\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 22	\xBFcB\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 23	\xBFcB\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 24	\xBFcB\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 25	\xBFcB\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 26	\xBFcB\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 3	\xBFc@\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 30	\xBFcC\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 31	\xBFcC\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 32	\xBFcC\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 33	\xBFcC\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 34	\xBFcC\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 35	\xBFcC\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 36	\xBFcC\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 37	\xBFcC\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 4	\xBFc@\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 40	\xBFcD\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel	\xBFcD\xBFb.\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

16 Source Input 41	
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 42	\xBFcD\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 43	\xBFcD\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 44	\xBFcD\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 45	\xBFcD\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 46	\xBFcD\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 47	\xBFcD\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 5	\xBFc@\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 8	\xBFcA\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 11 MIDI Channel 16 Source Input 9	\xBFcA\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 1	\xB0c@\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 10	\xB0cA\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 11	\xB0cA\xB0bG\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 12	\xB0cA\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 13	\xB0cA\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 14	\xB0cA\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 15	\xB0cA\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 19	\xB0cB\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 2	\xB0c@\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 20	\xB0cB\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 21	\xB0cB\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 22	\xB0cB\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 23	\xB0cB\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 24	\xB0cB\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 25	\xB0cB\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 26	\xB0cB\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 3	\xB0c@\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 30	\xB0cC\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 31	\xB0cC\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 32	\xB0cC\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1	\xB0cC\xB0b0\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 33	
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 34	\xB0cC\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 35	\xB0cC\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 36	\xB0cC\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 37	\xB0cC\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 4	\xB0c@\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 40	\xB0cD\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 41	\xB0cD\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 42	\xB0cD\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 43	\xB0cD\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 44	\xB0cD\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 45	\xB0cD\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 46	\xB0cD\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 47	\xB0cD\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 5	\xB0c@\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 8	\xB0cA\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 1 Source Input 9	\xB0cA\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb+\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 1	\xBFc@\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 10	\xBFcA\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 11	\xBFcA\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 12	\xBFcA\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 13	\xBFcA\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 14	\xBFcA\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 15	\xBFcA\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 19	\xBFcB\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 2	\xBFc@\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 20	\xBFcB\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 21	\xBFcB\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 22	\xBFcB\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 23	\xBFcB\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 24	\xBFcB\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel	\xBFcB\xBFbo\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Input 25	
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 26	\xBFcB\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 3	\xBFc@\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 30	\xBFcC\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 31	\xBFcC\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 32	\xBFcC\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 33	\xBFcC\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 34	\xBFcC\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 35	\xBFcC\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 36	\xBFcC\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 37	\xBFcC\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 4	\xBFc@\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 40	\xBFcD\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 41	\xBFcD\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 42	\xBFcD\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 43	\xBFcD\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 44	\xBFcD\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 45	\xBFcD\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 46	\xBFcD\xBFbk\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 47	\xBFcD\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 5	\xBFc@\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 8	\xBFcA\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 12 MIDI Channel 16 Source Input 9	\xBFcA\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 10	\xB0cE\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 4	\xB0cE\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 5	\xB0cE\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 6	\xB0cE\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 7	\xB0cE\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1	\xB0cE\xB0bY\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Group 8	
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Group 9	\xB0cE\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 1	\xB0c@\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 10	\xB0cA\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 11	\xB0cA\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 12	\xB0cA\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 13	\xB0cA\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 14	\xB0cA\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 15	\xB0cA\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 16	\xB0cA\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 2	\xB0c@\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 20	\xB0cB\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 21	\xB0cB\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 22	\xB0cB\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 23	\xB0cB\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 24	\xB0cB\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 25	\xB0cB\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 26	\xB0cB\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 27	\xB0cB\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x15\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 3	\xB0c@\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 30	\xB0cC\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 31	\xB0cC\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 32	\xB0cC\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 33	\xB0cC\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 34	\xB0cC\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 35	\xB0cC\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 36	\xB0cC\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 37	\xB0cC\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 4	\xB0c@\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 41	\xB0cD\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 42	\xB0cD\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 43	\xB0cD\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 44	\xB0cD\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 45	\xB0cD\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 46	\xB0cD\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 47	\xB0cD\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 48	\xB0cD\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 5	\xB0c@\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1	\xB0cA\xB0b\x0D\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 7	
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 1 Source Input 9	\xB0cA\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 10	\xBFcE\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 4	\xBFcE\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 5	\xBFcE\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 6	\xBFcE\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 7	\xBFcE\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 8	\xBFcE\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Group 9	\xBFcE\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 1	\xBFc@\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 10	\xBFcA\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 11	\xBFcA\xBFb=\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 12	\xBFcA\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 13	\xBFcA\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 14	\xBFcA\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 15	\xBFcA\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 16	\xBFcA\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 2	\xBFc@\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 20	\xBFcB\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 21	\xBFcB\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 22	\xBFcB\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 23	\xBFcB\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 24	\xBFcB\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 25	\xBFcB\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 26	\xBFcB\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 27	\xBFcB\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 3	\xBFc@\xBFb]\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 30	\xBFcC\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 31	\xBFcC\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 32	\xBFcC\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16	\xBFcC\xBFbE\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 33	
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 34	\xBFcC\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 35	\xBFcC\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 36	\xBFcC\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 37	\xBFcC\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 4	\xBFc@\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 41	\xBFcD\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 42	\xBFcD\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 43	\xBFcD\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 44	\xBFcD\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 45	\xBFcD\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 46	\xBFcD\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 47	\xBFcD\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 48	\xBFcD\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 5	\xBFc@\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 2 MIDI Channel 16 Source Input 9	\xBFcA\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b"\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 4	\xB0cE\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 5	\xB0cE\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 6	\xB0cE\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 7	\xB0cE\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 8	\xB0cE\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Group 9	\xB0cE\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 1	\xB0c@\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 10	\xB0cA\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 11	\xB0cA\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 12	\xB0cA\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 13	\xB0cA\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 14	\xB0cA\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 15	\xB0cA\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 16	\xB0cA\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1	\xB0cB\xB0b\x06\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 17	
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 2	\xB0c@\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 20	\xB0cB\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 21	\xB0cB\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 22	\xB0cB\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 23	\xB0cB\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 24	\xB0cB\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 25	\xB0cB\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 26	\xB0cB\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 27	\xB0cB\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 3	\xB0c@\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 30	\xB0cC\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 31	\xB0cC\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 32	\xB0cC\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 33	\xB0cC\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 34	\xB0cC\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 35	\xB0cC\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 36	\xB0cC\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 37	\xB0cC\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x02\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 4	\xB0c@\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 41	\xB0cD\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 42	\xB0cD\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 43	\xB0cD\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 44	\xB0cD\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 45	\xB0cD\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 46	\xB0cD\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 47	\xB0cD\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 48	\xB0cD\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 5	\xB0c@\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 1 Source Input 9	\xB0cA\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16	\xBFcF\xBFbj\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Source FX 8 Return	
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 4	\xBFcE\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 5	\xBFcE\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 6	\xBFcE\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 7	\xBFcE\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 8	\xBFcE\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Group 9	\xBFcE\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 1	\xBFc@\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 10	\xBFcA\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 11	\xBFcA\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 12	\xBFcA\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 13	\xBFcA\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 14	\xBFcA\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 15	\xBFcA\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 16	\xBFcA\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 2	\xBFc@\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 20	\xBFcB\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 21	\xBFcB\xBFb6\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 22	\xBFcB\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 23	\xBFcB\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 24	\xBFcB\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 25	\xBFcB\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 26	\xBFcB\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 27	\xBFcB\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 3	\xBFc@\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 30	\xBFcC\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 31	\xBFcC\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 32	\xBFcC\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 33	\xBFcC\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 34	\xBFcC\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 35	\xBFcC\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 36	\xBFcC\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 37	\xBFcC\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 4	\xBFc@\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 41	\xBFcD\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 42	\xBFcD\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16	\xBFcD\xBFb>\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 43	
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 44	\xBFcD\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 45	\xBFcD\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 46	\xBFcD\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 47	\xBFcD\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 48	\xBFcD\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 5	\xBFc@\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 3 MIDI Channel 16 Source Input 9	\xBFcA\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 4	\xB0cE\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 5	\xB0cE\xB0b7\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 6	\xB0cE\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 7	\xB0cE\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Group 8	\xB0cE\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 1	\xB0c@\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 10	\xB0cA\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 11	\xB0cA\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 12	\xB0cA\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 13	\xB0cA\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 14	\xB0cA\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 15	\xB0cA\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 16	\xB0cA\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 2	\xB0c@\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 20	\xB0cB\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 21	\xB0cB\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 22	\xB0cB\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 23	\xB0cB\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 24	\xB0cB\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 25	\xB0cB\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 26	\xB0cB\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 27	\xB0cB\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1	\xB0cC\xB0b\x0B\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Source Input 28	
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 3	\xB0c@\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 30	\xB0cC\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 31	\xB0cC\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 32	\xB0cC\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 33	\xB0cC\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 34	\xB0cC\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 35	\xB0cC\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 36	\xB0cC\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 37	\xB0cC\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 4	\xB0c@\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 41	\xB0cD\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 42	\xB0cD\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 43	\xB0cD\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 44	\xB0cD\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 45	\xB0cD\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 46	\xB0cD\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 47	\xB0cD\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 48	\xB0cD\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 5	\xB0c@\xB0bw\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 1 Source Input 9	\xB0cA\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 4	\xBFcE\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 5	\xBFcE\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 6	\xBFcE\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 7	\xBFcE\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Group 8	\xBFcE\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 1	\xBFc@\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 10	\xBFcA\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 11	\xBFcA\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16	\xBFcA\xBFbK\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 12	
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 13	\xBFcA\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 14	\xBFcA\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 15	\xBFcA\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 16	\xBFcA\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 2	\xBFc@\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 20	\xBFcB\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 21	\xBFcB\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 22	\xBFcB\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 23	\xBFcB\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 24	\xBFcB\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 25	\xBFcB\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 26	\xBFcB\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 27	\xBFcB\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 3	\xBFc@\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 30	\xBFcC\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 31	\xBFcC\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 32	\xBFcC\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 33	\xBFcC\xBFbG\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 34	\xBFcC\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 35	\xBFcC\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 36	\xBFcC\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 37	\xBFcC\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 4	\xBFc@\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 41	\xBFcD\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 42	\xBFcD\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 43	\xBFcD\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 44	\xBFcD\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 45	\xBFcD\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 46	\xBFcD\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 47	\xBFcD\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 48	\xBFcD\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 5	\xBFc@\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 4 MIDI Channel 16 Source Input 9	\xBFcA\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1	\xB0cF\xB0b0\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 3 Return	
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 3	\xB0cE\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 4	\xB0cE\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 5	\xB0cE\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 6	\xB0cE\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Group 7	\xB0cE\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 1	\xB0c@\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 10	\xB0cA\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 11	\xB0cA\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 12	\xB0cA\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 13	\xB0cA\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 14	\xB0cA\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 15	\xB0cA\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 16	\xB0cA\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 19	\xB0cB\xB0b \xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 2	\xB0c@\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 20	\xB0cB\xB0b,\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 21	\xB0cB\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 22	\xB0cB\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 23	\xB0cB\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 24	\xB0cB\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 25	\xB0cB\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 26	\xB0cB\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 3	\xB0c@\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 30	\xB0cC\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 31	\xB0cC\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 32	\xB0cC\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 33	\xB0cC\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 34	\xB0cC\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 35	\xB0cC\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 36	\xB0cC\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 37	\xB0cC\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 4	\xB0c@\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1	\xB0cD\xB0b\x1C\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 40	
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 41	\xB0cD\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 42	\xB0cD\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 43	\xB0cD\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 44	\xB0cD\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 45	\xB0cD\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 46	\xB0cD\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 47	\xB0cD\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 48	\xB0cD\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 5	\xB0c@\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 1 Source Input 9	\xB0cA\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x14\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 3	\xBFcE\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 4	\xBFcE\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 5	\xBFcE\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 6	\xBFcE\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Group 7	\xBFcE\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 1	\xBFc@\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 10	\xBFcA\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 11	\xBFcA\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 12	\xBFcA\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 13	\xBFcA\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 14	\xBFcA\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 15	\xBFcA\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 16	\xBFcA\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 19	\xBFcB\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 2	\xBFc@\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 20	\xBFcB\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 21	\xBFcB\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 22	\xBFcB\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 23	\xBFcB\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 24	\xBFcB\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 25	\xBFcB\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16	\xBFcB\xBFbt\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 26	
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 3	\xBFc@\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 30	\xBFcC\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 31	\xBFcC\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 32	\xBFcC\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 33	\xBFcC\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 34	\xBFcC\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 35	\xBFcC\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 36	\xBFcC\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 37	\xBFcC\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 4	\xBFc@\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 41	\xBFcD\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 42	\xBFcD\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 43	\xBFcD\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 44	\xBFcD\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 45	\xBFcD\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 46	\xBFcD\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 47	\xBFcD\xBFbp\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 48	\xBFcD\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 5	\xBFc@\xBFb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 5 MIDI Channel 16 Source Input 9	\xBFcA\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 3	\xB0cE\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 4	\xB0cE\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 5	\xB0cE\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Group 6	\xB0cE\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 1	\xB0c@\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 10	\xB0cA\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 11	\xB0cA\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1	\xB0cA\xB0bM\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 12	
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 13	\xB0cA\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 14	\xB0cA\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 15	\xB0cA\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 16	\xB0cA\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 19	\xB0cB\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 2	\xB0c@\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 20	\xB0cB\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 21	\xB0cB\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 22	\xB0cB\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 23	\xB0cB\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 24	\xB0cB\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 25	\xB0cB\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 26	\xB0cB\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 3	\xB0c@\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 30	\xB0cC\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 31	\xB0cC\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 32	\xB0cC\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 33	\xB0cC\xB0bI\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 34	\xB0cC\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 35	\xB0cC\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 36	\xB0cC\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 37	\xB0cC\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 4	\xB0c@\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 41	\xB0cD\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 42	\xB0cD\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 43	\xB0cD\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 44	\xB0cD\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 45	\xB0cD\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 46	\xB0cD\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 47	\xB0cD\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 48	\xB0cD\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 5	\xB0c@\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 1 Source Input 9	\xB0cA\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16	\xBFcF\xBFb1\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Source FX 3 Return	
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 3	\xBFcE\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 4	\xBFcE\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 5	\xBFcE\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Group 6	\xBFcE\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 1	\xBFc@\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 10	\xBFcA\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 11	\xBFcA\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 12	\xBFcA\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 13	\xBFcA\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 14	\xBFcA\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 15	\xBFcA\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 16	\xBFcA\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 19	\xBFcB\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 2	\xBFc@\xBFbU\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 20	\xBFcB\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 21	\xBFcB\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 22	\xBFcB\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 23	\xBFcB\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 24	\xBFcB\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 25	\xBFcB\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 26	\xBFcB\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 3	\xBFc@\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 30	\xBFcC\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 31	\xBFcC\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 32	\xBFcC\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 33	\xBFcC\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 34	\xBFcC\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 35	\xBFcC\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 36	\xBFcC\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 37	\xBFcC\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 4	\xBFc@\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16	\xBFcD\xBFb)\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 41	
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 42	\xBFcD\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 43	\xBFcD\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 44	\xBFcD\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 45	\xBFcD\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 46	\xBFcD\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 47	\xBFcD\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 48	\xBFcD\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 5	\xBFc@\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 6 MIDI Channel 16 Source Input 9	\xBFcA\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Group 3	\xB0cE\xB0b"\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 7 MIDI Channel 1 Source Group 4	\xB0cE\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Group 5	\xB0cE\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 1	\xB0c@\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 10	\xB0cA\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 11	\xB0cA\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 12	\xB0cA\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 13	\xB0cA\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 14	\xB0cA\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 15	\xB0cA\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 16	\xB0cA\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 19	\xB0cB\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 2	\xB0c@\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 20	\xB0cB\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 21	\xB0cB\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 22	\xB0cB\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 23	\xB0cB\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 24	\xB0cB\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 25	\xB0cB\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 26	\xB0cB\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1	\xB0cC\xB0b\x1A\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 29	
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 3	\xB0c@\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 30	\xB0cC\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 31	\xB0cC\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 32	\xB0cC\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 33	\xB0cC\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 34	\xB0cC\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 35	\xB0cC\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 36	\xB0cC\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 37	\xB0cC\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 4	\xB0c@\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 41	\xB0cD\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 42	\xB0cD\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 43	\xB0cD\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 44	\xB0cD\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 45	\xB0cD\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 46	\xB0cD\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 47	\xB0cD\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 48	\xB0cD\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 5	\xB0c@\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x06\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 1 Source Input 9	\xB0cA\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Group 3	\xBFcE\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Group 4	\xBFcE\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Group 5	\xBFcE\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 1	\xBFc@\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 10	\xBFcA\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 11	\xBFcA\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 12	\xBFcA\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 13	\xBFcA\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 14	\xBFcA\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 15	\xBFcA\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16	\xBFcA\xBFb~\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 16	
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 19	\xBFcB\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 2	\xBFc@\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 20	\xBFcB\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 21	\xBFcB\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 22	\xBFcB\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 23	\xBFcB\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 24	\xBFcB\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 25	\xBFcB\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 26	\xBFcB\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 3	\xBFc@\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 30	\xBFcC\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 31	\xBFcC\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 32	\xBFcC\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 33	\xBFcC\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 34	\xBFcC\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 35	\xBFcC\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 36	\xBFcC\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 37	\xBFcC\xBFbz\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 4	\xBFc@\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 41	\xBFcD\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 42	\xBFcD\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 43	\xBFcD\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 44	\xBFcD\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 45	\xBFcD\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 46	\xBFcD\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 47	\xBFcD\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 48	\xBFcD\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 5	\xBFc@\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 7 MIDI Channel 16 Source Input 9	\xBFcA\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1	\xB0cF\xB0bc\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 7 Return	
Level Control 10 Destination AUX 8 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Group 3	\xB0cE\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Group 4	\xB0cE\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 1	\xB0c@\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 10	\xB0cA\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 11	\xB0cA\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 12	\xB0cA\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 13	\xB0cA\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 14	\xB0cA\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 15	\xB0cA\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 16	\xB0cA\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 19	\xB0cB\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 2	\xB0c@\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 20	\xB0cB\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 21	\xB0cB\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 22	\xB0cB\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 23	\xB0cB\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 24	\xB0cB\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 25	\xB0cB\xB0bk\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 26	\xB0cB\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 3	\xB0c@\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 30	\xB0cC\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 31	\xB0cC\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 32	\xB0cC\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 33	\xB0cC\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 34	\xB0cC\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 35	\xB0cC\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 36	\xB0cC\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 37	\xB0cC\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 4	\xB0c@\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 41	\xB0cD\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 42	\xB0cD\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 43	\xB0cD\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 44	\xB0cD\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 45	\xB0cD\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 46	\xB0cD\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1	\xB0cD\xB0bs\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 47	
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 48	\xB0cD\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 5	\xB0c@\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 1 Source Input 9	\xB0cA\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Group 3	\xBFcE\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Group 4	\xBFcE\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 1	\xBFc@\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 10	\xBFcA\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 11	\xBFcA\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 12	\xBFcA\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 13	\xBFcA\xBFb[\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 14	\xBFcA\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 15	\xBFcA\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 16	\xBFcA\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 19	\xBFcB\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 2	\xBFc@\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 20	\xBFcB\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 21	\xBFcB\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 22	\xBFcB\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 23	\xBFcB\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 24	\xBFcB\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 25	\xBFcB\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 26	\xBFcB\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 3	\xBFc@\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 30	\xBFcC\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 31	\xBFcC\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 32	\xBFcC\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 33	\xBFcC\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 34	\xBFcC\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16	\xBFcC\xBFbc\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 35	
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 36	\xBFcC\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 37	\xBFcC\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 4	\xBFc@\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 41	\xBFcD\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 42	\xBFcD\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 43	\xBFcD\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 44	\xBFcD\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 45	\xBFcD\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 46	\xBFcD\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 47	\xBFcD\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 48	\xBFcD\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 5	\xBFc@\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 8 MIDI Channel 16 Source Input 9	\xBFcA\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b@\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 1	\xB0c@\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 10	\xB0cA\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 11	\xB0cA\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 12	\xB0cA\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 13	\xB0cA\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 14	\xB0cA\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 15	\xB0cA\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 2	\xB0c@\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 20	\xB0cB\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 21	\xB0cB\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 22	\xB0cB\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 23	\xB0cB\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1	\xB0cB\xB0b` \xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 24	
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 25	\xB0cB\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 26	\xB0cB\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 3	\xB0c@\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 30	\xB0cC\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 31	\xB0cC\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 32	\xB0cC\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 33	\xB0cC\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 34	\xB0cC\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 35	\xB0cC\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 36	\xB0cC\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 37	\xB0cC\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 4	\xB0c@\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 40	\xB0cD\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 41	\xB0cD\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 42	\xB0cD\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 43	\xB0cD\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 44	\xB0cD\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 45	\xB0cD\xB0b\ \xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 46	\xB0cD\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 47	\xB0cD\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 5	\xB0c@\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 8	\xB0cA\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 1 Source Input 9	\xB0cA\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 1	\xBFc@\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 10	\xBFcA\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 11	\xBFcA\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 12	\xBFcA\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16	\xBFcA\xBFb\ \xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 13	
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 14	\xBFcA\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 15	\xBFcA\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 2	\xBFc@\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 20	\xBFcB\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 21	\xBFcB\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 22	\xBFcB\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 23	\xBFcB\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 24	\xBFcB\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 25	\xBFcB\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 26	\xBFcB\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 3	\xBFc@\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 30	\xBFcC\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 31	\xBFcC\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 32	\xBFcC\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 33	\xBFcC\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 34	\xBFcC\xBFbX\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 35	\xBFcC\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 36	\xBFcC\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 37	\xBFcC\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 4	\xBFc@\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 40	\xBFcD\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 41	\xBFcD\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 42	\xBFcD\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 43	\xBFcD\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 44	\xBFcD\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 45	\xBFcD\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 46	\xBFcD\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 47	\xBFcD\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 5	\xBFc@\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 8	\xBFcA\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination AUX 9 MIDI Channel 16 Source Input 9	\xBFcA\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 1	\xB0c0\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 2	\xB0c0\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 3	\xB0c0\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1	\xB0c0\xB0b#\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source DCA 4	
Level Control 10 Destination Control MIDI Channel 1 Source DCA 5	\xB0c0\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 6	\xB0c0\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 7	\xB0c0\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 1 Source DCA 8	\xB0c0\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 1	\xBFc0\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 2	\xBFc0\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 3	\xBFc0\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 4	\xBFc0\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 5	\xBFc0\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 6	\xBFc0\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 7	\xBFc0\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Control MIDI Channel 16 Source DCA 8	\xBFc0\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b \xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b\\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b\\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel	\xB0cL\xB0bh\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source Input 22	
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b,\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b<\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b,\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel	\xBFcM\xBFb\\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Group 3	
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb\ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbp\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb,\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel	\xBFcM\xBFbH\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

16 Source Input 46	
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb,\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 1 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0be\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel	\xB0cL\xB0b}\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source Input 27	
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bQ\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb]\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel	\xBFcM\xBFbq\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Group 8	
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb]\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbq\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x05\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel	\xBFcL\xBFb-\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

16 Source Input 7	
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 2 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 1	\xBFcL\xB0b\x16\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel	\xB0cM\xB0b\x0E\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source Input 31	
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b6\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb^ \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel	\xBFcL\xBFbB\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Input 12	
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x16\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb&\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 3 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel	\xB0cN\xB0b\x0F\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source FX 3 Return	
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bK\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bs\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel	\xB0cM\xB0b#\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source Input 36	
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bO\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x17\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbO\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel	\xBFcL\xBFbw\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source Input 17	
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb+\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbO\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination FX 4 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bp\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 1 MIDI Channel 1	\xB0cL\xB0b\x08\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 8 Return	
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbp\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 1 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0by\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbI\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFby\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x05\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Group 10 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bz\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbz\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 11 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bo\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0b{\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel	\xB0cL\xB0b\x07\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source FX 7 Return	
Level Control 10 Destination Group 12 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbo\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFb{\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 12 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bq\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b}\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbq\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb}\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 2 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0br\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b~\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbr\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb~\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 3 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1	\xB0cK\xB0bs\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 6 Return	
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b\x7F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbs\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb\x7F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 4 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bt\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbh\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbt\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 5 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bu\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbu\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 6 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1	\xB0cK\xB0bj\xB0\x06\x7F\xB0&\x7F

Global Scriptor Module Communication Sheet

Source FX 5 Return	
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bv\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbv\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 7 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bG\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b_\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bw\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb_\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbw\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 8 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bx\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbx\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Group 9 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 1 Return	\xB0c@\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 2 Return	\xB0c@\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 3 Return	\xB0c@\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1	\xB0c@\xB0b?\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source FX 4 Return	
Level Control 10 Destination LR MIDI Channel 1 Source FX 5 Return	\xB0c@\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 6 Return	\xB0c@\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 7 Return	\xB0c@\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source FX 8 Return	\xB0c@\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 1	\xB0c@\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 10	\xB0c@\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 11	\xB0c@\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 12	\xB0c@\xB0b;\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 2	\xB0c@\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 3	\xB0c@\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 4	\xB0c@\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 5	\xB0c@\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 6	\xB0c@\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 7	\xB0c@\xB0b6\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 8	\xB0c@\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Group 9	\xB0c@\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 1	\xB0c@\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 10	\xB0c@\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 11	\xB0c@\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 12	\xB0c@\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 13	\xB0c@\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 14	\xB0c@\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 15	\xB0c@\xB0b\x0E\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination LR MIDI Channel 1 Source Input 16	\xB0c@\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 17	\xB0c@\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 18	\xB0c@\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 19	\xB0c@\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 2	\xB0c@\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 20	\xB0c@\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 21	\xB0c@\xB0b\x14\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 22	\xB0c@\xB0b\x15\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 23	\xB0c@\xB0b\x16\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 24	\xB0c@\xB0b\x17\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 25	\xB0c@\xB0b\x18\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 26	\xB0c@\xB0b\x19\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 27	\xB0c@\xB0b\x1A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 28	\xB0c@\xB0b\x1B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 29	\xB0c@\xB0b\x1C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 3	\xB0c@\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 30	\xB0c@\xB0b\x1D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 31	\xB0c@\xB0b\x1E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 32	\xB0c@\xB0b\x1F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 33	\xB0c@\xB0b \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 34	\xB0c@\xB0b!\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 35	\xB0c@\xB0b"\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 36	\xB0c@\xB0b#\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1	\xB0c@\xB0b\$\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

Source Input 37	
Level Control 10 Destination LR MIDI Channel 1 Source Input 38	\xB0c@\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 39	\xB0c@\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 4	\xB0c@\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 40	\xB0c@\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 41	\xB0c@\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 42	\xB0c@\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 43	\xB0c@\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 44	\xB0c@\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 45	\xB0c@\xB0b,\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 46	\xB0c@\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 47	\xB0c@\xB0b.\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 48	\xB0c@\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 5	\xB0c@\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 6	\xB0c@\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 7	\xB0c@\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 8	\xB0c@\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 1 Source Input 9	\xB0c@\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 1 Return	\xBFc@\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 2 Return	\xBFc@\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 3 Return	\xBFc@\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 4 Return	\xBFc@\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 5 Return	\xBFc@\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 6 Return	\xBFc@\xBFbA\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination LR MIDI Channel 16 Source FX 7 Return	\xBFc@\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source FX 8 Return	\xBFc@\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 1	\xBFc@\xBFb0\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 10	\xBFc@\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 11	\xBFc@\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 12	\xBFc@\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 2	\xBFc@\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 3	\xBFc@\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 4	\xBFc@\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 5	\xBFc@\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 6	\xBFc@\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 7	\xBFc@\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 8	\xBFc@\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Group 9	\xBFc@\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 1	\xBFc@\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 10	\xBFc@\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 11	\xBFc@\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 12	\xBFc@\xBFb\x0B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 13	\xBFc@\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 14	\xBFc@\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 15	\xBFc@\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 16	\xBFc@\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 17	\xBFc@\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16	\xBFc@\xBFb\x11\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Source Input 18	
Level Control 10 Destination LR MIDI Channel 16 Source Input 19	\xBFc@\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 2	\xBFc@\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 20	\xBFc@\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 21	\xBFc@\xBFb\x14\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 22	\xBFc@\xBFb\x15\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 23	\xBFc@\xBFb\x16\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 24	\xBFc@\xBFb\x17\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 25	\xBFc@\xBFb\x18\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 26	\xBFc@\xBFb\x19\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 27	\xBFc@\xBFb\x1A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 28	\xBFc@\xBFb\x1B\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 29	\xBFc@\xBFb\x1C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 3	\xBFc@\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 30	\xBFc@\xBFb\x1D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 31	\xBFc@\xBFb\x1E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 32	\xBFc@\xBFb\x1F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 33	\xBFc@\xBFb \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 34	\xBFc@\xBFb!\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 35	\xBFc@\xBFb"\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 36	\xBFc@\xBFb#\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 37	\xBFc@\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 38	\xBFc@\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 39	\xBFc@\xBFb&\xBF\x06\x7F\xBF&\x7F

Global Scriptor Module Communication Sheet

Level Control 10 Destination LR MIDI Channel 16 Source Input 4	\xBFc@\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 40	\xBFc@\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 41	\xBFc@\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 42	\xBFc@\xBFb)\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 43	\xBFc@\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 44	\xBFc@\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 45	\xBFc@\xBFb,\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 46	\xBFc@\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 47	\xBFc@\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 48	\xBFc@\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 5	\xBFc@\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 6	\xBFc@\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 7	\xBFc@\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 8	\xBFc@\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination LR MIDI Channel 16 Source Input 9	\xBFc@\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b'\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bB\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 11	\xB0cN\xB0bE\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bH\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b*\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 3	\xB0cN\xB0b-\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b0\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b3\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel	\xB0cN\xB0b6\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source AUX 6	
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b9\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b<\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source AUX 9	\xB0cN\xB0b?\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 1	\xB0cN\xB0bK\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 10	\xB0cN\xB0bf\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 11	\xB0cN\xB0bi\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 12	\xB0cN\xB0bl\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 2	\xB0cN\xB0bN\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 3	\xB0cN\xB0bQ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 4	\xB0cN\xB0bT\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 5	\xB0cN\xB0bW\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 6	\xB0cN\xB0bZ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 7	\xB0cN\xB0b]\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 8	\xB0cN\xB0b` \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source Group 9	\xB0cN\xB0bc\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 1 Source LR	\xB0cN\xB0b\$\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb'\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbB\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbE\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbH\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb*\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb-\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb0\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb3\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 6	\xBFcN\xBFb6\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb9\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb<\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source AUX 9	\xBFcN\xBFb?\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 1	\xBFcN\xBFbK\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 10	\xBFcN\xBFbf\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 11	\xBFcN\xBFbi\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 12	\xBFcN\xBFbl\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 2	\xBFcN\xBFbN\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 3	\xBFcN\xBFbQ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 4	\xBFcN\xBFbT\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 5	\xBFcN\xBFbW\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 6	\xBFcN\xBFbZ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 7	\xBFcN\xBFb]\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 8	\xBFcN\xBFb` \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source Group 9	\xBFcN\xBFbc\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 1 MIDI Channel 16 Source LR	\xBFcN\xBFb\$\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b(\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bC\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 11	\xB0cN\xB0bF\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bI\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b+\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel	\xB0cN\xB0b. \xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source AUX 3	
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b1\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b4\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 6	\xB0cN\xB0b7\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b:\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b=\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source AUX 9	\xB0cN\xB0b@\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 1	\xB0cN\xB0bL\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 10	\xB0cN\xB0bg\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 11	\xB0cN\xB0bj\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 12	\xB0cN\xB0bm\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 2	\xB0cN\xB0bO\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 3	\xB0cN\xB0bR\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 4	\xB0cN\xB0bU\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 5	\xB0cN\xB0bX\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 6	\xB0cN\xB0b[\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 7	\xB0cN\xB0b^\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 8	\xB0cN\xB0ba\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source Group 9	\xB0cN\xB0bd\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 1 Source LR	\xB0cN\xB0b%\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb(\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbC\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbF\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbI\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb+\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb.\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb1\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb4\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 6	\xBFcN\xBFb7\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb:\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb=\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source AUX 9	\xBFcN\xBFb@\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 1	\xBFcN\xBFbL\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 10	\xBFcN\xBFbg\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 11	\xBFcN\xBFbj\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 12	\xBFcN\xBFbm\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 2	\xBFcN\xBFbO\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 3	\xBFcN\xBFbR\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 4	\xBFcN\xBFbU\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 5	\xBFcN\xBFbX\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 6	\xBFcN\xBFb[\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 7	\xBFcN\xBFb^\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 8	\xBFcN\xBFba\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source Group 9	\xBFcN\xBFbd\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 2 MIDI Channel 16 Source LR	\xBFcN\xBFb%\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b)\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bD\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel	\xB0cN\xB0bG\xB0\x06\x7F\xB0&\x7F

Global Scripter Module Communication Sheet

1 Source AUX 11	
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bJ\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b, \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 3	\xB0cN\xB0b/\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b2\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b5\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 6	\xB0cN\xB0b8\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b; \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b>\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source AUX 9	\xB0cN\xB0bA\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 1	\xB0cN\xB0bM\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 10	\xB0cN\xB0bh\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 11	\xB0cN\xB0bk\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 12	\xB0cN\xB0bn\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 2	\xB0cN\xB0bP\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 3	\xB0cN\xB0bS\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 4	\xB0cN\xB0bV\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 5	\xB0cN\xB0bY\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 6	\xB0cN\xB0b\ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 7	\xB0cN\xB0b_ \xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 8	\xB0cN\xB0bb\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source Group 9	\xB0cN\xB0be\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 1 Source LR	\xB0cN\xB0b&\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb)\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbD\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbG\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbJ\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb, \xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb/\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb2\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb5\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 6	\xBFcN\xBFb8\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb;\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb>\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source AUX 9	\xBFcN\xBFbA\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 1	\xBFcN\xBFbM\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 10	\xBFcN\xBFbh\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 11	\xBFcN\xBFbk\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 12	\xBFcN\xBFbn\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 2	\xBFcN\xBFbP\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 3	\xBFcN\xBFbS\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 4	\xBFcN\xBFbV\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 5	\xBFcN\xBFbY\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 6	\xBFcN\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 7	\xBFcN\xBFb_\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 8	\xBFcN\xBFbb\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel 16 Source Group 9	\xBFcN\xBFbe\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Matrix 3 MIDI Channel	\xBFcN\xBFb&\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

16 Source LR	
Level Control 10 Destination Output MIDI Channel 1 Source AUX 1	\xB0c0\xB0b\x01\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 10	\xB0c0\xB0b\x0A\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 11	\xB0c0\xB0b\x0B\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 12	\xB0c0\xB0b\x0C\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 2	\xB0c0\xB0b\x02\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 3	\xB0c0\xB0b\x03\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 4	\xB0c0\xB0b\x04\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 5	\xB0c0\xB0b\x05\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 6	\xB0c0\xB0b\x06\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 7	\xB0c0\xB0b\x07\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 8	\xB0c0\xB0b\x08\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source AUX 9	\xB0c0\xB0b\x09\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source FX 1 Send	\xB0c0\xB0b\x0D\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source FX 2 Send	\xB0c0\xB0b\x0E\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source FX 3 Send	\xB0c0\xB0b\x0F\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source FX 4 Send	\xB0c0\xB0b\x10\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source LR	\xB0c0\xB0b\x00\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source Matrix 1	\xB0c0\xB0b\x11\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source Matrix 2	\xB0c0\xB0b\x12\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 1 Source Matrix 3	\xB0c0\xB0b\x13\xB0\x06\x7F\xB0&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 1	\xBFc0\xBFb\x01\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 10	\xBFc0\xBFb\x0A\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 11	\xBFc0\xBFb\x0B\xBF\x06\x7F\xBF&\x7F

Global Scripter Module Communication Sheet

Level Control 10 Destination Output MIDI Channel 16 Source AUX 12	\xBFc0\xBFb\x0C\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 2	\xBFc0\xBFb\x02\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 3	\xBFc0\xBFb\x03\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 4	\xBFc0\xBFb\x04\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 5	\xBFc0\xBFb\x05\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 6	\xBFc0\xBFb\x06\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 7	\xBFc0\xBFb\x07\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 8	\xBFc0\xBFb\x08\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source AUX 9	\xBFc0\xBFb\x09\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source FX 1 Send	\xBFc0\xBFb\x0D\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source FX 2 Send	\xBFc0\xBFb\x0E\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source FX 3 Send	\xBFc0\xBFb\x0F\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source FX 4 Send	\xBFc0\xBFb\x10\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source LR	\xBFc0\xBFb\x00\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source Matrix 1	\xBFc0\xBFb\x11\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source Matrix 2	\xBFc0\xBFb\x12\xBF\x06\x7F\xBF&\x7F
Level Control 10 Destination Output MIDI Channel 16 Source Matrix 3	\xBFc0\xBFb\x13\xBF\x06\x7F\xBF&\x7F
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b, \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1	\xB0cF\xB0b\ \xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Source FX 7 Return	
Level Control -90 Destination AUX 1 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 10	\xB0cE\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 11	\xB0cE\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 4	\xB0cE\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 5	\xB0cE\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 6	\xB0cE\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 7	\xB0cE\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 8	\xB0cE\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Group 9	\xB0cE\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 1	\xB0c@\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 10	\xB0cA\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 11	\xB0cA\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 12	\xB0cA\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 13	\xB0cA\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 14	\xB0cA\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 15	\xB0cA\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 16	\xB0cA\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1C\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 2	\xB0c@\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 20	\xB0cB\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 21	\xB0cB\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 22	\xB0cB\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 23	\xB0cB\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 24	\xB0cB\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 25	\xB0cB\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 26	\xB0cB\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 27	\xB0cB\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 3	\xB0c@\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 30	\xB0cC\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 31	\xB0cC\xB0b, \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 32	\xB0cC\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 33	\xB0cC\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 34	\xB0cC\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 35	\xB0cC\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 36	\xB0cC\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 37	\xB0cC\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 4	\xB0c@\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1	\xB0cD\xB0b\x18\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 40	
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 41	\xB0cD\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 42	\xB0cD\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 43	\xB0cD\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 44	\xB0cD\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 45	\xB0cD\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 46	\xB0cD\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 47	\xB0cD\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 48	\xB0cD\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 5	\xB0c@\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 1 Source Input 9	\xB0cA\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 10	\xBFcE\xBFbp\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 11	\xBFcE\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 4	\xBFcE\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 5	\xBFcE\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 6	\xBFcE\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 7	\xBFcE\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 8	\xBFcE\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Group 9	\xBFcE\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 1	\xBFc@\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 10	\xBFcA\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 11	\xBFcA\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 12	\xBFcA\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 13	\xBFcA\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 14	\xBFcA\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 15	\xBFcA\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 16	\xBFcA\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 2	\xBFc@\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 20	\xBFcB\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 21	\xBFcB\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16	\xBFcB\xBFb@\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 22	
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 23	\xBFcB\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 24	\xBFcB\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 25	\xBFcB\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 26	\xBFcB\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 27	\xBFcB\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 3	\xBFc@\xBFb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 30	\xBFcC\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 31	\xBFcC\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 32	\xBFcC\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 33	\xBFcC\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 34	\xBFcC\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 35	\xBFcC\xBFb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 36	\xBFcC\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 37	\xBFcC\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 4	\xBFc@\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 41	\xBFcD\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 42	\xBFcD\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 43	\xBFcD\xBFb<\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 44	\xBFcD\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 45	\xBFcD\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 46	\xBFcD\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 47	\xBFcD\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 48	\xBFcD\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 5	\xBFc@\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 1 MIDI Channel 16 Source Input 9	\xBFcA\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 1	\xB0c@\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 10	\xB0cA\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 11	\xB0cA\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1	\xB0cA\xB0bQ\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 12	
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 13	\xB0cA\xB0b]\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 14	\xB0cA\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 15	\xB0cA\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 19	\xB0cB\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 2	\xB0c@\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 20	\xB0cB\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 21	\xB0cB\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 22	\xB0cB\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 23	\xB0cB\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 24	\xB0cB\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 25	\xB0cB\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 26	\xB0cB\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 3	\xB0c@\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 30	\xB0cC\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 31	\xB0cC\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 32	\xB0cC\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 33	\xB0cC\xB0bM\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 34	\xB0cC\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 35	\xB0cC\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 36	\xB0cC\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 37	\xB0cC\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 4	\xB0c@\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 40	\xB0cD\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 41	\xB0cD\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 42	\xB0cD\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 43	\xB0cD\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 44	\xB0cD\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 45	\xB0cD\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 46	\xB0cD\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 47	\xB0cD\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 5	\xB0c@\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 8	\xB0cA\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 1 Source Input 9	\xB0cA\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel	\xBFcF\xBFb5\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

16 Source FX 3 Return	
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 1	\xBFc@\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 10	\xBFcA\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 11	\xBFcA\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 12	\xBFcA\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 13	\xBFcA\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 14	\xBFcA\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 15	\xBFcA\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 19	\xBFcB\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 2	\xBFc@\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 20	\xBFcB\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 21	\xBFcB\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 22	\xBFcB\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 23	\xBFcB\xBFbU\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 24	\xBFcB\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 25	\xBFcB\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 26	\xBFcB\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 3	\xBFc@\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 30	\xBFcC\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 31	\xBFcC\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 32	\xBFcC\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 33	\xBFcC\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 34	\xBFcC\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 35	\xBFcC\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 36	\xBFcC\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 37	\xBFcC\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 4	\xBFc@\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 40	\xBFcD\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 41	\xBFcD\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 42	\xBFcD\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 43	\xBFcD\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 44	\xBFcD\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel	\xBFcD\xBFb]\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

16 Source Input 45	
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 46	\xBFCd\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 47	\xBFCd\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 48	\xBFCE\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 5	\xBFc@\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 6	\xBFCA\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 7	\xBFCA\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 8	\xBFCA\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 10 MIDI Channel 16 Source Input 9	\xBFCA\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 1	\xB0c@\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 10	\xB0cA\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 11	\xB0cA\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 12	\xB0cA\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 13	\xB0cA\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 14	\xB0cA\xB0bj\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 15	\xB0cA\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 19	\xB0cB\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 2	\xB0c@\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 20	\xB0cB\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 21	\xB0cB\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 22	\xB0cB\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 23	\xB0cB\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 24	\xB0cB\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 25	\xB0cB\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 26	\xB0cB\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 3	\xB0c@\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 30	\xB0cC\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 31	\xB0cC\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 32	\xB0cC\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 33	\xB0cC\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 34	\xB0cC\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 35	\xB0cC\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1	\xB0cC\xB0br\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 36	
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 37	\xB0cC\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 4	\xB0c@\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 40	\xB0cD\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 41	\xB0cD\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 42	\xB0cD\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 43	\xB0cD\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 44	\xB0cD\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 45	\xB0cD\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 46	\xB0cD\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 47	\xB0cD\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 5	\xB0c@\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 8	\xB0cA\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 1 Source Input 9	\xB0cA\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbN\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 1	\xBFc@\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 10	\xBFcA\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 11	\xBFcA\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 12	\xBFcA\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 13	\xBFcA\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 14	\xBFcA\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 15	\xBFcA\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 19	\xBFcB\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 2	\xBFc@\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 20	\xBFcB\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 21	\xBFcB\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 22	\xBFcB\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 23	\xBFcB\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 24	\xBFcB\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 25	\xBFcB\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 26	\xBFcB\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel	\xBFcC\xBFb\x06\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

16 Source Input 27	
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 3	\xBFc@\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 30	\xBFcC\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 31	\xBFcC\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 32	\xBFcC\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 33	\xBFcC\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 34	\xBFcC\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 35	\xBFcC\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 36	\xBFcC\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 37	\xBFcC\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 4	\xBFc@\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 40	\xBFcD\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 41	\xBFcD\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 42	\xBFcD\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 43	\xBFcD\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 44	\xBFcD\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 45	\xBFcD\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 46	\xBFcD\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 47	\xBFcD\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x02\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 5	\xBFc@\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 8	\xBFcA\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 11 MIDI Channel 16 Source Input 9	\xBFcA\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 1	\xB0c@\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 10	\xB0cA\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 11	\xB0cA\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 12	\xB0cA\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 13	\xB0cA\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 14	\xB0cA\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 15	\xB0cA\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1	\xB0cB\xB0b'\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 19	
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 2	\xB0c@\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 20	\xB0cB\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 21	\xB0cB\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 22	\xB0cB\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 23	\xB0cB\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 24	\xB0cB\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 25	\xB0cB\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 26	\xB0cB\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 3	\xB0c@\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 30	\xB0cC\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 31	\xB0cC\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 32	\xB0cC\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 33	\xB0cC\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 34	\xB0cC\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 35	\xB0cC\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 36	\xB0cC\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 37	\xB0cC\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 4	\xB0c@\xB0bs\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 40	\xB0cD\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 41	\xB0cD\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 42	\xB0cD\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 43	\xB0cD\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 44	\xB0cD\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 45	\xB0cD\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 46	\xB0cD\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 47	\xB0cD\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 5	\xB0c@\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 8	\xB0cA\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 1 Source Input 9	\xB0cA\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 1	\xBFc@\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel	\xBFcA\xBFb;\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

16 Source Input 10	
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 11	\xBFcA\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 12	\xBFcA\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 13	\xBFcA\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 14	\xBFcA\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 15	\xBFcA\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 19	\xBFcB\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 2	\xBFc@\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 20	\xBFcB\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 21	\xBFcB\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 22	\xBFcB\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 23	\xBFcB\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 24	\xBFcB\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 25	\xBFcB\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 26	\xBFcB\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 3	\xBFc@\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 30	\xBFcC\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 31	\xBFcC\xBFb7\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 32	\xBFcC\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 33	\xBFcC\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 34	\xBFcC\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 35	\xBFcC\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 36	\xBFcC\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 37	\xBFcC\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 4	\xBFc@\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 40	\xBFcD\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 41	\xBFcD\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 42	\xBFcD\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 43	\xBFcD\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 44	\xBFcD\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 45	\xBFcD\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 46	\xBFcD\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 47	\xBFcD\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 5	\xBFc@\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 8	\xBFcA\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 12 MIDI Channel 16 Source Input 9	\xBFcA\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1	\xB0cF\xB0b\x15\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source FX 1 Return	
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 10	\xB0cE\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 4	\xB0cE\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 5	\xB0cE\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 6	\xB0cE\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 7	\xB0cE\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 8	\xB0cE\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Group 9	\xB0cE\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 1	\xB0c@\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 10	\xB0cA\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 11	\xB0cA\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 12	\xB0cA\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 13	\xB0cA\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 14	\xB0cA\xB0ba\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 15	\xB0cA\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 16	\xB0cA\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 2	\xB0c@\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 20	\xB0cB\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 21	\xB0cB\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 22	\xB0cB\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 23	\xB0cB\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 24	\xB0cB\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 25	\xB0cB\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 26	\xB0cB\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 27	\xB0cB\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 3	\xB0c@\xB0b]\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 30	\xB0cC\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 31	\xB0cC\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 32	\xB0cC\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 33	\xB0cC\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 34	\xB0cC\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 35	\xB0cC\xB0b]\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1	\xB0cC\xB0bi\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 36	
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 37	\xB0cC\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 4	\xB0c@\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 41	\xB0cD\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 42	\xB0cD\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 43	\xB0cD\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 44	\xB0cD\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 45	\xB0cD\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 46	\xB0cD\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 47	\xB0cD\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 48	\xB0cD\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 5	\xB0c@\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 1 Source Input 9	\xB0cA\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbE\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 10	\xBFcE\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 4	\xBFcE\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 5	\xBFcE\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 6	\xBFcE\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 7	\xBFcE\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 8	\xBFcE\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Group 9	\xBFcE\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 1	\xBFc@\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 10	\xBFcA\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 11	\xBFcA\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 12	\xBFcA\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 13	\xBFcA\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 14	\xBFcA\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 15	\xBFcA\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 16	\xBFcA\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16	\xBFcB\xBFb\x1D\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 19	
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 2	\xBFc@\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 20	\xBFcB\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 21	\xBFcB\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 22	\xBFcB\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 23	\xBFcB\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 24	\xBFcB\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 25	\xBFcB\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 26	\xBFcB\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 27	\xBFcB\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 3	\xBFc@\xBFb]\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 30	\xBFcC\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 31	\xBFcC\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 32	\xBFcC\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 33	\xBFcC\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 34	\xBFcC\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 35	\xBFcC\xBFb]\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 36	\xBFcC\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 37	\xBFcC\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 4	\xBFc@\xBFbi\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 41	\xBFcD\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 42	\xBFcD\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 43	\xBFcD\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 44	\xBFcD\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 45	\xBFcD\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 46	\xBFcD\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 47	\xBFcD\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 48	\xBFcD\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 5	\xBFc@\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 2 MIDI Channel 16 Source Input 9	\xBFcA\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1	\xB0cE\xB0b\x12\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Group 2	
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 4	\xB0cE\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 5	\xB0cE\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 6	\xB0cE\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 7	\xB0cE\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 8	\xB0cE\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Group 9	\xB0cE\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 1	\xB0c@\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 10	\xB0cA\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 11	\xB0cA\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 12	\xB0cA\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 13	\xB0cA\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 14	\xB0cA\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 15	\xB0cA\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 16	\xB0cA\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 2	\xB0c@\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 20	\xB0cB\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 21	\xB0cB\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 22	\xB0cB\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 23	\xB0cB\xB0bN\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 24	\xB0cB\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 25	\xB0cB\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 26	\xB0cB\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 27	\xB0cB\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 3	\xB0c@\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 30	\xB0cC\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 31	\xB0cC\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 32	\xB0cC\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 33	\xB0cC\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 34	\xB0cC\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 35	\xB0cC\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 36	\xB0cC\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 37	\xB0cC\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 4	\xB0c@\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 41	\xB0cD\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 42	\xB0cD\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 43	\xB0cD\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 44	\xB0cD\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1	\xB0cD\xB0bV\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 45	
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 46	\xB0cD\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 47	\xB0cD\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 48	\xB0cD\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 5	\xB0c@\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 1 Source Input 9	\xB0cA\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 4	\xBFcE\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 5	\xBFcE\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 6	\xBFcE\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 7	\xBFcE\xBFbN\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 8	\xBFcE\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Group 9	\xBFcE\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 1	\xBFc@\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 10	\xBFcA\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 11	\xBFcA\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 12	\xBFcA\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 13	\xBFcA\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 14	\xBFcA\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 15	\xBFcA\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 16	\xBFcA\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 2	\xBFc@\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 20	\xBFcB\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 21	\xBFcB\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 22	\xBFcB\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 23	\xBFcB\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 24	\xBFcB\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 25	\xBFcB\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 26	\xBFcB\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 27	\xBFcB\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16	\xBFcC\xBFb\x16\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 29	
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 3	\xBFc@\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 30	\xBFcC\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 31	\xBFcC\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 32	\xBFcC\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 33	\xBFcC\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 34	\xBFcC\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 35	\xBFcC\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 36	\xBFcC\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 37	\xBFcC\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 4	\xBFc@\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 41	\xBFcD\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 42	\xBFcD\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 43	\xBFcD\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 44	\xBFcD\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 45	\xBFcD\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 46	\xBFcD\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 47	\xBFcD\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 48	\xBFcD\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 5	\xBFc@\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x02\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 3 MIDI Channel 16 Source Input 9	\xBFcA\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 4	\xB0cE\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 5	\xB0cE\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 6	\xB0cE\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 7	\xB0cE\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Group 8	\xB0cE\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 1	\xB0c@\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 10	\xB0cA\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 11	\xB0cA\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 12	\xB0cA\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1	\xB0cA\xB0bW\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 13	
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 14	\xB0cA\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 15	\xB0cA\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 16	\xB0cA\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 2	\xB0c@\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 20	\xB0cB\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 21	\xB0cB\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 22	\xB0cB\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 23	\xB0cB\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 24	\xB0cB\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 25	\xB0cB\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 26	\xB0cB\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 27	\xB0cB\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 3	\xB0c@\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 30	\xB0cC\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 31	\xB0cC\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 32	\xB0cC\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 33	\xB0cC\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 34	\xB0cC\xB0bS\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 35	\xB0cC\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 36	\xB0cC\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 37	\xB0cC\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 4	\xB0c@\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 41	\xB0cD\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 42	\xB0cD\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 43	\xB0cD\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 44	\xB0cD\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 45	\xB0cD\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 46	\xB0cD\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 47	\xB0cD\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 48	\xB0cD\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 5	\xB0c@\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 1 Source Input 9	\xB0cA\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16	\xBFcF\xBFb;\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source FX 4 Return	
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 4	\xBFcE\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 5	\xBFcE\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 6	\xBFcE\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 7	\xBFcE\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Group 8	\xBFcE\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 1	\xBFc@\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 10	\xBFcA\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 11	\xBFcA\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 12	\xBFcA\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 13	\xBFcA\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 14	\xBFcA\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 15	\xBFcA\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 16	\xBFcA\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\x1F\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 2	\xBFc@\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 20	\xBFcB\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 21	\xBFcB\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 22	\xBFcB\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 23	\xBFcB\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 24	\xBFcB\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 25	\xBFcB\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 26	\xBFcB\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 27	\xBFcB\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 3	\xBFc@\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 30	\xBFcC\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 31	\xBFcC\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 32	\xBFcC\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 33	\xBFcC\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 34	\xBFcC\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 35	\xBFcC\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 36	\xBFcC\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 37	\xBFcC\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 4	\xBFc@\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16	\xBFcD\xBFb\x1B\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 40	
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 41	\xBFcD\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 42	\xBFcD\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 43	\xBFcD\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 44	\xBFcD\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 45	\xBFcD\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 46	\xBFcD\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 47	\xBFcD\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 48	\xBFcD\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 5	\xBFc@\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 4 MIDI Channel 16 Source Input 9	\xBFcA\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x14\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 3	\xB0cE\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 4	\xB0cE\xB0b, \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 5	\xB0cE\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 6	\xB0cE\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Group 7	\xB0cE\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 1	\xB0c@\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 10	\xB0cA\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 11	\xB0cA\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 12	\xB0cA\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 13	\xB0cA\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 14	\xB0cA\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 15	\xB0cA\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 16	\xB0cA\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 19	\xB0cB\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 2	\xB0c@\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 20	\xB0cB\xB0b, \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 21	\xB0cB\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 22	\xB0cB\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 23	\xB0cB\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 24	\xB0cB\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 25	\xB0cB\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1	\xB0cB\xB0bt\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 26	
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 3	\xB0c@\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 30	\xB0cC\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 31	\xB0cC\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 32	\xB0cC\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 33	\xB0cC\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 34	\xB0cC\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 35	\xB0cC\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 36	\xB0cC\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 37	\xB0cC\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 4	\xB0c@\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 41	\xB0cD\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 42	\xB0cD\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 43	\xB0cD\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 44	\xB0cD\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 45	\xB0cD\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 46	\xB0cD\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 47	\xB0cD\xB0bp\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 48	\xB0cD\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 5	\xB0c@\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 1 Source Input 9	\xB0cA\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 3	\xBFcE\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 4	\xBFcE\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 5	\xBFcE\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 6	\xBFcE\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Group 7	\xBFcE\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 1	\xBFc@\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 10	\xBFcA\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16	\xBFcA\xBFb@\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 11	
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 12	\xBFcA\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 13	\xBFcA\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 14	\xBFcA\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 15	\xBFcA\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 16	\xBFcA\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 19	\xBFcB\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 2	\xBFc@\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 20	\xBFcB\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 21	\xBFcB\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 22	\xBFcB\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 23	\xBFcB\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 24	\xBFcB\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 25	\xBFcB\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 26	\xBFcB\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 3	\xBFc@\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 30	\xBFcC\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 31	\xBFcC\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 32	\xBFcC\xBFb<\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 33	\xBFcC\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 34	\xBFcC\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 35	\xBFcC\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 36	\xBFcC\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 37	\xBFcC\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 4	\xBFc@\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 41	\xBFcD\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 42	\xBFcD\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 43	\xBFcD\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 44	\xBFcD\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 45	\xBFcD\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 46	\xBFcD\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 47	\xBFcD\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 48	\xBFcD\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 5	\xBFc@\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 5 MIDI Channel 16 Source Input 9	\xBFcA\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1	\xB0cF\xB0b%\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source FX 2 Return	
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 3	\xB0cE\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 4	\xB0cE\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 5	\xB0cE\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Group 6	\xB0cE\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 1	\xB0c@\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 10	\xB0cA\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 11	\xB0cA\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 12	\xB0cA\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 13	\xB0cA\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 14	\xB0cA\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 15	\xB0cA\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 16	\xB0cA\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 19	\xB0cB\xB0b!\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 2	\xB0c@\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 20	\xB0cB\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 21	\xB0cB\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 22	\xB0cB\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 23	\xB0cB\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 24	\xB0cB\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 25	\xB0cB\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 26	\xB0cB\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 3	\xB0c@\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 30	\xB0cC\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 31	\xB0cC\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 32	\xB0cC\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 33	\xB0cC\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 34	\xB0cC\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 35	\xB0cC\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 36	\xB0cC\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 37	\xB0cC\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 4	\xB0c@\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1	\xB0cD\xB0b\x1D\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 40	
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 41	\xB0cD\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 42	\xB0cD\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 43	\xB0cD\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 44	\xB0cD\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 45	\xB0cD\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 46	\xB0cD\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 47	\xB0cD\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 48	\xB0cD\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 5	\xB0c@\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 1 Source Input 9	\xB0cA\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x15\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 3	\xBFcE\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 4	\xBFcE\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 5	\xBFcE\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Group 6	\xBFcE\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 1	\xBFc@\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 10	\xBFcA\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 11	\xBFcA\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 12	\xBFcA\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 13	\xBFcA\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 14	\xBFcA\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 15	\xBFcA\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 16	\xBFcA\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 19	\xBFcB\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 2	\xBFc@\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 20	\xBFcB\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 21	\xBFcB\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 22	\xBFcB\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 23	\xBFcB\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 24	\xBFcB\xBFb]\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 25	\xBFcB\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 26	\xBFcB\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16	\xBFcC\xBFb\x01\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 27	
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 3	\xBFc@\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 30	\xBFcC\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 31	\xBFcC\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 32	\xBFcC\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 33	\xBFcC\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 34	\xBFcC\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 35	\xBFcC\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 36	\xBFcC\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 37	\xBFcC\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 4	\xBFc@\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 41	\xBFcD\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 42	\xBFcD\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 43	\xBFcD\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 44	\xBFcD\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 45	\xBFcD\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 46	\xBFcD\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 47	\xBFcD\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 48	\xBFcD\xBFb}\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 5	\xBFc@\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 6 MIDI Channel 16 Source Input 9	\xBFcA\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Group 3	\xB0cE\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Group 4	\xB0cE\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Group 5	\xB0cE\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 1	\xB0c@\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 10	\xB0cA\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 11	\xB0cA\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 12	\xB0cA\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 13	\xB0cA\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1	\xB0cA\xB0bf\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 14	
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 15	\xB0cA\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 16	\xB0cA\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 19	\xB0cB\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 2	\xB0c@\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 20	\xB0cB\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 21	\xB0cB\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 22	\xB0cB\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 23	\xB0cB\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 24	\xB0cB\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 25	\xB0cB\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 26	\xB0cB\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 3	\xB0c@\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 30	\xB0cC\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 31	\xB0cC\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 32	\xB0cC\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 33	\xB0cC\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 34	\xB0cC\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 35	\xB0cC\xB0bb\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 36	\xB0cC\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 37	\xB0cC\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 4	\xB0c@\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 41	\xB0cD\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 42	\xB0cD\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 43	\xB0cD\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 44	\xB0cD\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 45	\xB0cD\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 46	\xB0cD\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 47	\xB0cD\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 48	\xB0cD\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 5	\xB0c@\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 1 Source Input 9	\xB0cA\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16	\xBFcF\xBFbJ\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Source FX 5 Return	
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Group 3	\xBFcE\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Group 4	\xBFcE\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Group 5	\xBFcE\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 1	\xBFc@\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 10	\xBFcA\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 11	\xBFcA\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 12	\xBFcA\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 13	\xBFcA\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 14	\xBFcA\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 15	\xBFcA\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 16	\xBFcA\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 19	\xBFcB\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 2	\xBFc@\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 20	\xBFcB\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 21	\xBFcB\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 22	\xBFcB\xBFbF\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 23	\xBFcB\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 24	\xBFcB\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 25	\xBFcB\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 26	\xBFcB\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 3	\xBFc@\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 30	\xBFcC\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 31	\xBFcC\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 32	\xBFcC\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 33	\xBFcC\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 34	\xBFcC\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 35	\xBFcC\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 36	\xBFcC\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 37	\xBFcC\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 4	\xBFc@\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 41	\xBFcD\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 42	\xBFcD\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 43	\xBFcD\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16	\xBFcD\xBFbN\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Source Input 44	
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 45	\xBFcD\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 46	\xBFcD\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 47	\xBFcD\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 48	\xBFcD\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 5	\xBFc@\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 7 MIDI Channel 16 Source Input 9	\xBFcA\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Group 3	\xB0cE\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Group 4	\xB0cE\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 1	\xB0c@\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 10	\xB0cA\xB0b7\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 11	\xB0cA\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 12	\xB0cA\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 13	\xB0cA\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 14	\xB0cA\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 15	\xB0cA\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 16	\xB0cA\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 19	\xB0cB\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 2	\xB0c@\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 20	\xB0cB\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 21	\xB0cB\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 22	\xB0cB\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 23	\xB0cB\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 24	\xB0cB\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 25	\xB0cB\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 26	\xB0cB\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 3	\xB0c@\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 30	\xB0cC\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 31	\xB0cC\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1	\xB0cC\xB0b?\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 32	
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 33	\xB0cC\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 34	\xB0cC\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 35	\xB0cC\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 36	\xB0cC\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 37	\xB0cC\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 4	\xB0c@\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 40	\xB0cD\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 41	\xB0cD\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 42	\xB0cD\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 43	\xB0cD\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 44	\xB0cD\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 45	\xB0cD\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 46	\xB0cD\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 47	\xB0cD\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 48	\xB0cD\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 5	\xB0c@\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 8	\xB0cA\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 1 Source Input 9	\xB0cA\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1B\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Group 3	\xBFcE\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Group 4	\xBFcE\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 1	\xBFc@\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 10	\xBFcA\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 11	\xBFcA\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 12	\xBFcA\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 13	\xBFcA\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 14	\xBFcA\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 15	\xBFcA\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 16	\xBFcA\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 19	\xBFcB\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 2	\xBFc@\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16	\xBFcB\xBFb/\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 20	
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 21	\xBFcB\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 22	\xBFcB\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 23	\xBFcB\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 24	\xBFcB\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 25	\xBFcB\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 26	\xBFcB\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 3	\xBFc@\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 30	\xBFcC\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 31	\xBFcC\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 32	\xBFcC\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 33	\xBFcC\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 34	\xBFcC\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 35	\xBFcC\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 36	\xBFcC\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 37	\xBFcC\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 4	\xBFc@\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 40	\xBFcD\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 41	\xBFcD\xBFb+\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 42	\xBFcD\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 43	\xBFcD\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 44	\xBFcD\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 45	\xBFcD\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 46	\xBFcD\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 47	\xBFcD\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 48	\xBFcD\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 5	\xBFc@\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 8	\xBFcA\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 8 MIDI Channel 16 Source Input 9	\xBFcA\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 1 Return	\xB0cF\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 2 Return	\xB0cF\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 3 Return	\xB0cF\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 4 Return	\xB0cF\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 5 Return	\xB0cF\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 6 Return	\xB0cF\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 7 Return	\xB0cF\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source FX 8 Return	\xB0cF\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Group 1	\xB0cE\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Group 2	\xB0cE\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Group 3	\xB0cE\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1	\xB0c@\xB0bL\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 1	
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 10	\xB0cA\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 11	\xB0cA\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 12	\xB0cA\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 13	\xB0cA\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 14	\xB0cA\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 15	\xB0cA\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 16	\xB0cB\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 17	\xB0cB\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 18	\xB0cB\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 19	\xB0cB\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 2	\xB0c@\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 20	\xB0cB\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 21	\xB0cB\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 22	\xB0cB\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 23	\xB0cB\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 24	\xB0cB\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 25	\xB0cB\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 26	\xB0cB\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 27	\xB0cC\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 28	\xB0cC\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 29	\xB0cC\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 3	\xB0c@\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 30	\xB0cC\xB0b(\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 31	\xB0cC\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 32	\xB0cC\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 33	\xB0cC\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 34	\xB0cC\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 35	\xB0cC\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 36	\xB0cC\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 37	\xB0cC\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 38	\xB0cD\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 39	\xB0cD\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 4	\xB0c@\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 40	\xB0cD\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 41	\xB0cD\xB0b, \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 42	\xB0cD\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 43	\xB0cD\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 44	\xB0cD\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 45	\xB0cD\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 46	\xB0cD\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 47	\xB0cD\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 48	\xB0cE\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 5	\xB0c@\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 6	\xB0cA\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 7	\xB0cA\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1 Source Input 8	\xB0cA\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination AUX 9 MIDI Channel 1	\xB0cA\xB0b, \xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Source Input 9	
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 1 Return	\xBFcF\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 2 Return	\xBFcF\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 3 Return	\xBFcF\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 4 Return	\xBFcF\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 5 Return	\xBFcF\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 6 Return	\xBFcF\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 7 Return	\xBFcF\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source FX 8 Return	\xBFcF\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Group 1	\xBFcE\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Group 2	\xBFcE\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Group 3	\xBFcE\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 1	\xBFc@\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 10	\xBFcA\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 11	\xBFcA\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 12	\xBFcA\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 13	\xBFcA\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 14	\xBFcA\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 15	\xBFcA\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 16	\xBFcB\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 17	\xBFcB\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 18	\xBFcB\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 19	\xBFcB\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 2	\xBFc@\xBFbX\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 20	\xBFcB\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 21	\xBFcB\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 22	\xBFcB\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 23	\xBFcB\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 24	\xBFcB\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 25	\xBFcB\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 26	\xBFcB\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 27	\xBFcC\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 28	\xBFcC\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 29	\xBFcC\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 3	\xBFc@\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 30	\xBFcC\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 31	\xBFcC\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 32	\xBFcC\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 33	\xBFcC\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 34	\xBFcC\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 35	\xBFcC\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 36	\xBFcC\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 37	\xBFcC\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 38	\xBFcD\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 39	\xBFcD\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 4	\xBFc@\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 40	\xBFcD\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16	\xBFcD\xBFb, \xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 41	
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 42	\xBFcD\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 43	\xBFcD\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 44	\xBFcD\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 45	\xBFcD\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 46	\xBFcD\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 47	\xBFcD\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 48	\xBFcE\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 5	\xBFc@\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 6	\xBFcA\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 7	\xBFcA\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 8	\xBFcA\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination AUX 9 MIDI Channel 16 Source Input 9	\xBFcA\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 1	\xB0c0\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 2	\xB0c0\xB0b! \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 3	\xB0c0\xB0b" \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 4	\xB0c0\xB0b# \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 5	\xB0c0\xB0b\$ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 6	\xB0c0\xB0b% \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 7	\xB0c0\xB0b& \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 1 Source DCA 8	\xB0c0\xB0b' \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 1	\xBFc0\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 2	\xBFc0\xBFb! \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 3	\xBFc0\xBFb" \xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Control MIDI Channel 16 Source DCA 4	\xBFc0\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 5	\xBFc0\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 6	\xBFc0\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 7	\xBFc0\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Control MIDI Channel 16 Source DCA 8	\xBFc0\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI	\xB0cM\xB0bp\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Channel 1 Source Group 8	
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0b` \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x04\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x14\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b,\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI	\xB0cL\xB0b,\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Channel 1 Source Input 7	
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x14\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbl\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI	\xBFcM\xBFb\x0C\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Channel 16 Source Input 31	
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb,\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb,\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 1 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb4\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b]\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x15\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI	\xB0cL\xB0bA\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Channel 1 Source Input 12	
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x15\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI	\xBFcN\xBFb\x0D\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Channel 16 Source FX 3 Return	
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbI\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI	\xBFcM\xBFb!\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Channel 16 Source Input 36	
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 2 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x16\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI	\xB0cL\xB0bV\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Channel 1 Source Input 17	
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 21	\xB0cL\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0br\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b*\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI	\xBFcN\xBFb"\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Channel 16 Source FX 8 Return	
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 2	\xBFcM\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb^\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI	\xBFcM\xBFb2\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Channel 16 Source Input 40	
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 45	\xBFcM\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 5	\BFcL\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 6	\BFcL\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 7	\BFcL\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 8	\BFcL\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 3 Send MIDI Channel 16 Source Input 9	\BFcL\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 1 Return	\xB0cN\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 2 Return	\xB0cN\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 3 Return	\xB0cN\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 4 Return	\xB0cN\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 5 Return	\xB0cN\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 6 Return	\xB0cN\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 7 Return	\xB0cN\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source FX 8 Return	\xB0cN\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 1	\xB0cM\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 10	\xB0cM\xB0b{\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 11	\xB0cM\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 12	\xB0cN\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 2	\xB0cM\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 3	\xB0cM\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 4	\xB0cM\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 5	\xB0cM\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 6	\xB0cM\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 7	\xB0cM\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 8	\xB0cM\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Group 9	\xB0cM\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 1	\xB0cL\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 10	\xB0cL\xB0b;\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 11	\xB0cL\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 12	\xB0cL\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 13	\xB0cL\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 14	\xB0cL\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 15	\xB0cL\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 16	\xB0cL\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 17	\xB0cL\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 18	\xB0cL\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 19	\xB0cL\xB0b_\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 2	\xB0cL\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 20	\xB0cL\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI	\xB0cL\xB0bg\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Channel 1 Source Input 21	
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 22	\xB0cL\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 23	\xB0cL\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 24	\xB0cL\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 25	\xB0cL\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 26	\xB0cL\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 27	\xB0cL\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 28	\xB0cM\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 29	\xB0cM\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 3	\xB0cL\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 30	\xB0cM\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 31	\xB0cM\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 32	\xB0cM\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 33	\xB0cM\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 34	\xB0cM\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 35	\xB0cM\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 36	\xB0cM\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 37	\xB0cM\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 38	\xB0cM\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 39	\xB0cM\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 4	\xB0cL\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 40	\xB0cM\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 41	\xB0cM\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 42	\xB0cM\xB0b;\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 43	\xB0cM\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 44	\xB0cM\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 45	\xB0cM\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 46	\xB0cM\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 47	\xB0cM\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 48	\xB0cM\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 5	\xB0cL\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 6	\xB0cL\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 7	\xB0cL\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 8	\xB0cL\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 1 Source Input 9	\xB0cL\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 1 Return	\xBFcN\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 2 Return	\xBFcN\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 3 Return	\xBFcN\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 4 Return	\xBFcN\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 5 Return	\xBFcN\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 6 Return	\xBFcN\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 7 Return	\xBFcN\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source FX 8 Return	\xBFcN\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 1	\xBFcM\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 10	\xBFcM\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 11	\xBFcM\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 12	\xBFcN\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI	\xBFcM\xBFb[\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Channel 16 Source Group 2	
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 3	\xBFcM\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 4	\xBFcM\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 5	\xBFcM\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 6	\xBFcM\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 7	\xBFcM\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 8	\xBFcM\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Group 9	\xBFcM\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 1	\xBFcL\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 10	\xBFcL\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 11	\xBFcL\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 12	\xBFcL\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 13	\xBFcL\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 14	\xBFcL\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 15	\xBFcL\xBFbO\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 16	\xBFcL\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 17	\xBFcL\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 18	\xBFcL\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 19	\xBFcL\xBFb_\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 2	\xBFcL\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 20	\xBFcL\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 21	\xBFcL\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 22	\xBFcL\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 23	\xBFcL\xBFbo\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 24	\xBFcL\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 25	\xBFcL\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 26	\xBFcL\xBFb{\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 27	\xBFcL\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 28	\xBFcM\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 29	\xBFcM\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 3	\xBFcL\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 30	\xBFcM\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 31	\xBFcM\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 32	\xBFcM\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 33	\xBFcM\xBFb\x17\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 34	\xBFcM\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 35	\xBFcM\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 36	\xBFcM\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 37	\xBFcM\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 38	\xBFcM\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 39	\xBFcM\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 4	\xBFcL\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 40	\xBFcM\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 41	\xBFcM\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 42	\xBFcM\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 43	\xBFcM\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 44	\xBFcM\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI	\xBFcM\xBFbG\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Channel 16 Source Input 45	
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 46	\xBFcM\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 47	\xBFcM\xBFbO\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 48	\xBFcM\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 5	\xBFcL\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 6	\xBFcL\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 7	\xBFcL\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 8	\xBFcL\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination FX 4 Send MIDI Channel 16 Source Input 9	\xBFcL\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bL\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bp\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbp\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb \xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Group 1 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0by\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFby\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 10 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bz\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel	\xB0cL\xB0b\x06\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

1 Source FX 7 Return	
Level Control -90 Destination Group 11 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbV\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbn\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbz\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 11 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bo\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0b{\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbo\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFb{\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 12 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bq\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b}\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbM\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbY\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbe\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbq\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb}\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 2 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel	\xB0cK\xB0br\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

1 Source FX 6 Return	
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b~\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbr\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb~\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 3 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bs\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 7 Return	\xB0cK\xB0b\x7F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbg\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbs\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 7 Return	\xBFcK\xBFb\x7F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 4 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bt\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbP\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbh\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbt\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 5 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel	\xB0cK\xB0bi\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

1 Source FX 5 Return	
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bu\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x01\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbi\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbu\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 6 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bv\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb^\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbv\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 7 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b; \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 4 Return	\xB0cK\xB0b_ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bw\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb; \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbS\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb_ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFbk\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbw\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 8 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 1 Return	\xB0cK\xB0b< \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 2 Return	\xB0cK\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 3 Return	\xB0cK\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel	\xB0cK\xB0b` \xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

1 Source FX 4 Return	
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 5 Return	\xB0cK\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 6 Return	\xB0cK\xB0bx\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 7 Return	\xB0cL\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 1 Source FX 8 Return	\xB0cL\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 1 Return	\xBFcK\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 2 Return	\xBFcK\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 3 Return	\xBFcK\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 4 Return	\xBFcK\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 5 Return	\xBFcK\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 6 Return	\xBFcK\xBFbx\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 7 Return	\xBFcL\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Group 9 MIDI Channel 16 Source FX 8 Return	\xBFcL\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 1 Return	\xB0c@\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 2 Return	\xB0c@\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 3 Return	\xB0c@\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 4 Return	\xB0c@\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 5 Return	\xB0c@\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 6 Return	\xB0c@\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 7 Return	\xB0c@\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source FX 8 Return	\xB0c@\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 1	\xB0c@\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 10	\xB0c@\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 11	\xB0c@\xB0b:\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination LR MIDI Channel 1 Source Group 12	\xB0c@\xB0b; \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 2	\xB0c@\xB0b1 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 3	\xB0c@\xB0b2 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 4	\xB0c@\xB0b3 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 5	\xB0c@\xB0b4 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 6	\xB0c@\xB0b5 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 7	\xB0c@\xB0b6 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 8	\xB0c@\xB0b7 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Group 9	\xB0c@\xB0b8 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 1	\xB0c@\xB0b\x00 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 10	\xB0c@\xB0b\x09 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 11	\xB0c@\xB0b\x0A \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 12	\xB0c@\xB0b\x0B \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 13	\xB0c@\xB0b\x0C \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 14	\xB0c@\xB0b\x0D \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 15	\xB0c@\xB0b\x0E \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 16	\xB0c@\xB0b\x0F \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 17	\xB0c@\xB0b\x10 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 18	\xB0c@\xB0b\x11 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 19	\xB0c@\xB0b\x12 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 2	\xB0c@\xB0b\x01 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 20	\xB0c@\xB0b\x13 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 21	\xB0c@\xB0b\x14 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1	\xB0c@\xB0b\x15 \xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Source Input 22	
Level Control -90 Destination LR MIDI Channel 1 Source Input 23	\xB0c@\xB0b\x16\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 24	\xB0c@\xB0b\x17\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 25	\xB0c@\xB0b\x18\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 26	\xB0c@\xB0b\x19\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 27	\xB0c@\xB0b\x1A\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 28	\xB0c@\xB0b\x1B\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 29	\xB0c@\xB0b\x1C\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 3	\xB0c@\xB0b\x02\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 30	\xB0c@\xB0b\x1D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 31	\xB0c@\xB0b\x1E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 32	\xB0c@\xB0b\x1F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 33	\xB0c@\xB0b \xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 34	\xB0c@\xB0b!\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 35	\xB0c@\xB0b"\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 36	\xB0c@\xB0b#\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 37	\xB0c@\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 38	\xB0c@\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 39	\xB0c@\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 4	\xB0c@\xB0b\x03\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 40	\xB0c@\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 41	\xB0c@\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 42	\xB0c@\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 43	\xB0c@\xB0b*\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination LR MIDI Channel 1 Source Input 44	\xB0c@\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 45	\xB0c@\xB0b,\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 46	\xB0c@\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 47	\xB0c@\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 48	\xB0c@\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 5	\xB0c@\xB0b\x04\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 6	\xB0c@\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 7	\xB0c@\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 8	\xB0c@\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 1 Source Input 9	\xB0c@\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 1 Return	\xBFc@\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 2 Return	\xBFc@\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 3 Return	\xBFc@\xBFb>\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 4 Return	\xBFc@\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 5 Return	\xBFc@\xBFb@\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 6 Return	\xBFc@\xBFbA\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 7 Return	\xBFc@\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source FX 8 Return	\xBFc@\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 1	\xBFc@\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 10	\xBFc@\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 11	\xBFc@\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 12	\xBFc@\xBFb;\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 2	\xBFc@\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16	\xBFc@\xBFb2\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Source Group 3	
Level Control -90 Destination LR MIDI Channel 16 Source Group 4	\xBFc@\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 5	\xBFc@\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 6	\xBFc@\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 7	\xBFc@\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 8	\xBFc@\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Group 9	\xBFc@\xBFb8\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 1	\xBFc@\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 10	\xBFc@\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 11	\xBFc@\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 12	\xBFc@\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 13	\xBFc@\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 14	\xBFc@\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 15	\xBFc@\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 16	\xBFc@\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 17	\xBFc@\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 18	\xBFc@\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 19	\xBFc@\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 2	\xBFc@\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 20	\xBFc@\xBFb\x13\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 21	\xBFc@\xBFb\x14\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 22	\xBFc@\xBFb\x15\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 23	\xBFc@\xBFb\x16\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 24	\xBFc@\xBFb\x17\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination LR MIDI Channel 16 Source Input 25	\xBFc@\xBFb\x18\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 26	\xBFc@\xBFb\x19\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 27	\xBFc@\xBFb\x1A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 28	\xBFc@\xBFb\x1B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 29	\xBFc@\xBFb\x1C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 3	\xBFc@\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 30	\xBFc@\xBFb\x1D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 31	\xBFc@\xBFb\x1E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 32	\xBFc@\xBFb\x1F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 33	\xBFc@\xBFb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 34	\xBFc@\xBFb!\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 35	\xBFc@\xBFb"\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 36	\xBFc@\xBFb#\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 37	\xBFc@\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 38	\xBFc@\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 39	\xBFc@\xBFb&\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 4	\xBFc@\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 40	\xBFc@\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 41	\xBFc@\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 42	\xBFc@\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 43	\xBFc@\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 44	\xBFc@\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 45	\xBFc@\xBFb,\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16	\xBFc@\xBFb-\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

Source Input 46	
Level Control -90 Destination LR MIDI Channel 16 Source Input 47	\xBFc@\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 48	\xBFc@\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 5	\xBFc@\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 6	\xBFc@\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 7	\xBFc@\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 8	\xBFc@\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination LR MIDI Channel 16 Source Input 9	\xBFc@\xBFb\x08\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b'\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bB\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 11	\xB0cN\xB0bE\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bH\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b*\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 3	\xB0cN\xB0b-\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b0\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b3\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 6	\xB0cN\xB0b6\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b9\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b<\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source AUX 9	\xB0cN\xB0b?\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 1	\xB0cN\xB0bK\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 10	\xB0cN\xB0bf\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 11	\xB0cN\xB0bi\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 12	\xB0cN\xB0bl\xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 2	\xB0cN\xB0bN\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 3	\xB0cN\xB0bQ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 4	\xB0cN\xB0bT\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 5	\xB0cN\xB0bW\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 6	\xB0cN\xB0bZ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 7	\xB0cN\xB0b]\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 8	\xB0cN\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source Group 9	\xB0cN\xB0bc\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 1 Source LR	\xB0cN\xB0b\$\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb'\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbB\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbE\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbH\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb*\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb-\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb0\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb3\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 6	\xBFcN\xBFb6\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb9\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb<\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source AUX 9	\xBFcN\xBFb?\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 1	\xBFcN\xBFbK\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 10	\xBFcN\xBFbf\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel	\xBFcN\xBFbi\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

16 Source Group 11	
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 12	\xBFcN\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 2	\xBFcN\xBFbN\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 3	\xBFcN\xBFbQ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 4	\xBFcN\xBFbT\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 5	\xBFcN\xBFbW\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 6	\xBFcN\xBFbZ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 7	\xBFcN\xBFb] \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 8	\xBFcN\xBFb` \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source Group 9	\xBFcN\xBFbc\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 1 MIDI Channel 16 Source LR	\xBFcN\xBFb\$\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b(\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bC\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 11	\xB0cN\xB0bF\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bI\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b+\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 3	\xB0cN\xB0b.\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b1\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b4\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 6	\xB0cN\xB0b7\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b:\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b=\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source AUX 9	\xB0cN\xB0b@\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 1	\xB0cN\xB0bL\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 10	\xB0cN\xB0bg\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 11	\xB0cN\xB0bj\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 12	\xB0cN\xB0bm\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 2	\xB0cN\xB0bO\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 3	\xB0cN\xB0bR\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 4	\xB0cN\xB0bU\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 5	\xB0cN\xB0bX\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 6	\xB0cN\xB0b[\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 7	\xB0cN\xB0b^\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 8	\xB0cN\xB0ba\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source Group 9	\xB0cN\xB0bd\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 1 Source LR	\xB0cN\xB0b%\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb(\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbC\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbF\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbI\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb+\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb.\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb1\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb4\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 6	\xBFcN\xBFb7\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb:\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb=\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel	\xBFcN\xBFb@\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

16 Source AUX 9	
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 1	\xBFcN\xBFbL\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 10	\xBFcN\xBFbg\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 11	\xBFcN\xBFbj\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 12	\xBFcN\xBFbm\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 2	\xBFcN\xBFbO\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 3	\xBFcN\xBFbR\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 4	\xBFcN\xBFbU\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 5	\xBFcN\xBFbX\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 6	\xBFcN\xBFb[\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 7	\xBFcN\xBFb^\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 8	\xBFcN\xBFba\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source Group 9	\xBFcN\xBFbd\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 2 MIDI Channel 16 Source LR	\xBFcN\xBFb%\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 1	\xB0cN\xB0b)\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 10	\xB0cN\xB0bD\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 11	\xB0cN\xB0bG\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 12	\xB0cN\xB0bJ\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 2	\xB0cN\xB0b,\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 3	\xB0cN\xB0b/\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 4	\xB0cN\xB0b2\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 5	\xB0cN\xB0b5\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 6	\xB0cN\xB0b8\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 7	\xB0cN\xB0b;\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 8	\xB0cN\xB0b>\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source AUX 9	\xB0cN\xB0bA\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 1	\xB0cN\xB0bM\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 10	\xB0cN\xB0bh\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 11	\xB0cN\xB0bk\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 12	\xB0cN\xB0bn\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 2	\xB0cN\xB0bP\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 3	\xB0cN\xB0bS\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 4	\xB0cN\xB0bV\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 5	\xB0cN\xB0bY\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 6	\xB0cN\xB0b\ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 7	\xB0cN\xB0b_ \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 8	\xB0cN\xB0bb\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source Group 9	\xB0cN\xB0be\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 1 Source LR	\xB0cN\xB0b&\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 1	\xBFcN\xBFb)\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 10	\xBFcN\xBFbD\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 11	\xBFcN\xBFbG\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 12	\xBFcN\xBFbJ\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 2	\xBFcN\xBFb, \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 3	\xBFcN\xBFb/\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 4	\xBFcN\xBFb2\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 5	\xBFcN\xBFb5\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel	\xBFcN\xBFb8\xBF\x06\x00\xBF&\x00

Global Scripter Module Communication Sheet

16 Source AUX 6	
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 7	\xBFcN\xBFb; \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 8	\xBFcN\xBFb> \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source AUX 9	\xBFcN\xBFbA \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 1	\xBFcN\xBFbM \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 10	\xBFcN\xBFbh \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 11	\xBFcN\xBFbk \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 12	\xBFcN\xBFbn \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 2	\xBFcN\xBFbP \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 3	\xBFcN\xBFbS \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 4	\xBFcN\xBFbV \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 5	\xBFcN\xBFbY \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 6	\xBFcN\xBFb\ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 7	\xBFcN\xBFb_ \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 8	\xBFcN\xBFbb \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source Group 9	\xBFcN\xBFbe \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Matrix 3 MIDI Channel 16 Source LR	\xBFcN\xBFb& \xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 1	\xB0c0\xB0b\x01 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 10	\xB0c0\xB0b\x0A \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 11	\xB0c0\xB0b\x0B \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 12	\xB0c0\xB0b\x0C \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 2	\xB0c0\xB0b\x02 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 3	\xB0c0\xB0b\x03 \xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 4	\xB0c0\xB0b\x04 \xB0\x06\x00\xB0&\x00

Global Scripter Module Communication Sheet

Level Control -90 Destination Output MIDI Channel 1 Source AUX 5	\xB0c0\xB0b\x05\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 6	\xB0c0\xB0b\x06\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 7	\xB0c0\xB0b\x07\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 8	\xB0c0\xB0b\x08\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source AUX 9	\xB0c0\xB0b\x09\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source FX 1 Send	\xB0c0\xB0b\x0D\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source FX 2 Send	\xB0c0\xB0b\x0E\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source FX 3 Send	\xB0c0\xB0b\x0F\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source FX 4 Send	\xB0c0\xB0b\x10\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source LR	\xB0c0\xB0b\x00\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source Matrix 1	\xB0c0\xB0b\x11\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source Matrix 2	\xB0c0\xB0b\x12\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 1 Source Matrix 3	\xB0c0\xB0b\x13\xB0\x06\x00\xB0&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 1	\xBFc0\xBFb\x01\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 10	\xBFc0\xBFb\x0A\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 11	\xBFc0\xBFb\x0B\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 12	\xBFc0\xBFb\x0C\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 2	\xBFc0\xBFb\x02\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 3	\xBFc0\xBFb\x03\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 4	\xBFc0\xBFb\x04\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 5	\xBFc0\xBFb\x05\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 6	\xBFc0\xBFb\x06\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source AUX 7	\xBFc0\xBFb\x07\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel	\xBFc0\xBFb\x08\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

16 Source AUX 8	
Level Control -90 Destination Output MIDI Channel 16 Source AUX 9	\xBFc0\xBFb\x09\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source FX 1 Send	\xBFc0\xBFb\x0D\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source FX 2 Send	\xBFc0\xBFb\x0E\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source FX 3 Send	\xBFc0\xBFb\x0F\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source FX 4 Send	\xBFc0\xBFb\x10\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source LR	\xBFc0\xBFb\x00\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source Matrix 1	\xBFc0\xBFb\x11\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source Matrix 2	\xBFc0\xBFb\x12\xBF\x06\x00\xBF&\x00
Level Control -90 Destination Output MIDI Channel 16 Source Matrix 3	\xBFc0\xBFb\x13\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 1 Source AUX 1	\xB0c\x00\xB0bE\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 10	\xB0c\x00\xB0bN\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 11	\xB0c\x00\xB0bO\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 12	\xB0c\x00\xB0bP\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 2	\xB0c\x00\xB0bF\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 3	\xB0c\x00\xB0bG\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 4	\xB0c\x00\xB0bH\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 5	\xB0c\x00\xB0bI\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 6	\xB0c\x00\xB0bJ\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 7	\xB0c\x00\xB0bK\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 8	\xB0c\x00\xB0bL\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source AUX 9	\xB0c\x00\xB0bM\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 1	\xB0c\x02\xB0b\x00\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 2	\xB0c\x02\xB0b\x01\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 3	\xB0c\x02\xB0b\x02\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 4	\xB0c\x02\xB0b\x03\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 5	\xB0c\x02\xB0b\x04\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 6	\xB0c\x02\xB0b\x05\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 7	\xB0c\x02\xB0b\x06\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source DCA 8	\xB0c\x02\xB0b\x07\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 1 Return	\xB0c\x00\xB0b<\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 1 Send	\xB0c\x00\xB0bQ\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 2 Return	\xB0c\x00\xB0b=\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 2 Send	\xB0c\x00\xB0bR\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 3 Return	\xB0c\x00\xB0b>\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 3 Send	\xB0c\x00\xB0bS\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Mute Control Off MIDI Channel 1 Source FX 4 Return	\xB0c\x00\xB0b?\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 4 Send	\xB0c\x00\xB0bT\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 5 Return	\xB0c\x00\xB0b@\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 6 Return	\xB0c\x00\xB0bA\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 7 Return	\xB0c\x00\xB0bB\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source FX 8 Return	\xB0c\x00\xB0bC\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 1	\xB0c\x00\xB0b0\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 10	\xB0c\x00\xB0b9\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 11	\xB0c\x00\xB0b:\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 12	\xB0c\x00\xB0b;\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 2	\xB0c\x00\xB0b1\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 3	\xB0c\x00\xB0b2\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 4	\xB0c\x00\xB0b3\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 5	\xB0c\x00\xB0b4\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 6	\xB0c\x00\xB0b5\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 7	\xB0c\x00\xB0b6\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 8	\xB0c\x00\xB0b7\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Group 9	\xB0c\x00\xB0b8\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 1	\xB0c\x00\xB0b\x00\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 10	\xB0c\x00\xB0b\x09\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 11	\xB0c\x00\xB0b\x0A\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 12	\xB0c\x00\xB0b\x0B\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 13	\xB0c\x00\xB0b\x0C\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 14	\xB0c\x00\xB0b\x0D\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 15	\xB0c\x00\xB0b\x0E\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 16	\xB0c\x00\xB0b\x0F\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 17	\xB0c\x00\xB0b\x10\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 18	\xB0c\x00\xB0b\x11\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 19	\xB0c\x00\xB0b\x12\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 2	\xB0c\x00\xB0b\x01\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 20	\xB0c\x00\xB0b\x13\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 21	\xB0c\x00\xB0b\x14\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 22	\xB0c\x00\xB0b\x15\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 23	\xB0c\x00\xB0b\x16\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 24	\xB0c\x00\xB0b\x17\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 25	\xB0c\x00\xB0b\x18\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 26	\xB0c\x00\xB0b\x19\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 27	\xB0c\x00\xB0b\x1A\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 28	\xB0c\x00\xB0b\x1B\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 29	\xB0c\x00\xB0b\x1C\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 3	\xB0c\x00\xB0b\x02\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 30	\xB0c\x00\xB0b\x1D\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 31	\xB0c\x00\xB0b\x1E\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 32	\xB0c\x00\xB0b\x1F\xB0\x06\x00\xB0&\x00

Global Scriptor Module Communication Sheet

Mute Control Off MIDI Channel 1 Source Input 33	\xB0c\x00\xB0b \xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 34	\xB0c\x00\xB0b!\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 35	\xB0c\x00\xB0b"\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 36	\xB0c\x00\xB0b#\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 37	\xB0c\x00\xB0b\$\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 38	\xB0c\x00\xB0b%\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 39	\xB0c\x00\xB0b&\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 4	\xB0c\x00\xB0b\x03\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 40	\xB0c\x00\xB0b'\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 41	\xB0c\x00\xB0b(\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 42	\xB0c\x00\xB0b)\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 43	\xB0c\x00\xB0b*\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 44	\xB0c\x00\xB0b+\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 45	\xB0c\x00\xB0b,\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 46	\xB0c\x00\xB0b-\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 47	\xB0c\x00\xB0b.\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 48	\xB0c\x00\xB0b/\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 5	\xB0c\x00\xB0b\x04\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 6	\xB0c\x00\xB0b\x05\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 7	\xB0c\x00\xB0b\x06\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 8	\xB0c\x00\xB0b\x07\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Input 9	\xB0c\x00\xB0b\x08\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source LR	\xB0c\x00\xB0bD\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 1	\xB0c\x04\xB0b\x00\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 2	\xB0c\x04\xB0b\x01\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 3	\xB0c\x04\xB0b\x02\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 4	\xB0c\x04\xB0b\x03\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 5	\xB0c\x04\xB0b\x04\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 6	\xB0c\x04\xB0b\x05\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 7	\xB0c\x04\xB0b\x06\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Master Group 8	\xB0c\x04\xB0b\x07\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Matrix 1	\xB0c\x00\xB0bU\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Matrix 2	\xB0c\x00\xB0bV\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 1 Source Matrix 3	\xB0c\x00\xB0bW\xB0\x06\x00\xB0&\x00
Mute Control Off MIDI Channel 16 Source AUX 1	\xBFc\x00\xBFbE\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 10	\xBFc\x00\xBFbN\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 11	\xBFc\x00\xBFbO\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Mute Control Off MIDI Channel 16 Source AUX 12	\xBFc\x00\xBFbP\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 2	\xBFc\x00\xBFbF\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 3	\xBFc\x00\xBFbG\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 4	\xBFc\x00\xBFbH\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 5	\xBFc\x00\xBFbI\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 6	\xBFc\x00\xBFbJ\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 7	\xBFc\x00\xBFbK\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 8	\xBFc\x00\xBFbL\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source AUX 9	\xBFc\x00\xBFbM\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 1	\xBFc\x02\xBFb\x00\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 2	\xBFc\x02\xBFb\x01\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 3	\xBFc\x02\xBFb\x02\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 4	\xBFc\x02\xBFb\x03\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 5	\xBFc\x02\xBFb\x04\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 6	\xBFc\x02\xBFb\x05\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 7	\xBFc\x02\xBFb\x06\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source DCA 8	\xBFc\x02\xBFb\x07\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 1 Return	\xBFc\x00\xBFb<\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 1 Send	\xBFc\x00\xBFbQ\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 2 Return	\xBFc\x00\xBFb=\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 2 Send	\xBFc\x00\xBFbR\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 3 Return	\xBFc\x00\xBFb>\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 3 Send	\xBFc\x00\xBFbS\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 4 Return	\xBFc\x00\xBFb?\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 4 Send	\xBFc\x00\xBFbT\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 5 Return	\xBFc\x00\xBFb@\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 6 Return	\xBFc\x00\xBFbA\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 7 Return	\xBFc\x00\xBFbB\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source FX 8 Return	\xBFc\x00\xBFbC\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 1	\xBFc\x00\xBFb0\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 10	\xBFc\x00\xBFb9\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 11	\xBFc\x00\xBFb:\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 12	\xBFc\x00\xBFb;\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 2	\xBFc\x00\xBFb1\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 3	\xBFc\x00\xBFb2\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 4	\xBFc\x00\xBFb3\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 5	\xBFc\x00\xBFb4\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Mute Control Off MIDI Channel 16 Source Group 6	\xBFc\x00\xBFb5\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 7	\xBFc\x00\xBFb6\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 8	\xBFc\x00\xBFb7\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Group 9	\xBFc\x00\xBFb8\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 1	\xBFc\x00\xBFb\x00\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 10	\xBFc\x00\xBFb\x09\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 11	\xBFc\x00\xBFb\x0A\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 12	\xBFc\x00\xBFb\x0B\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 13	\xBFc\x00\xBFb\x0C\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 14	\xBFc\x00\xBFb\x0D\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 15	\xBFc\x00\xBFb\x0E\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 16	\xBFc\x00\xBFb\x0F\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 17	\xBFc\x00\xBFb\x10\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 18	\xBFc\x00\xBFb\x11\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 19	\xBFc\x00\xBFb\x12\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 2	\xBFc\x00\xBFb\x01\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 20	\xBFc\x00\xBFb\x13\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 21	\xBFc\x00\xBFb\x14\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 22	\xBFc\x00\xBFb\x15\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 23	\xBFc\x00\xBFb\x16\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 24	\xBFc\x00\xBFb\x17\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 25	\xBFc\x00\xBFb\x18\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 26	\xBFc\x00\xBFb\x19\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 27	\xBFc\x00\xBFb\x1A\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 28	\xBFc\x00\xBFb\x1B\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 29	\xBFc\x00\xBFb\x1C\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 3	\xBFc\x00\xBFb\x02\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 30	\xBFc\x00\xBFb\x1D\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 31	\xBFc\x00\xBFb\x1E\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 32	\xBFc\x00\xBFb\x1F\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 33	\xBFc\x00\xBFb \xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 34	\xBFc\x00\xBFb!\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 35	\xBFc\x00\xBFb"\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 36	\xBFc\x00\xBFb#\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 37	\xBFc\x00\xBFb\$\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 38	\xBFc\x00\xBFb%\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 39	\xBFc\x00\xBFb&\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 4	\xBFc\x00\xBFb\x03\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 40	\xBFc\x00\xBFb'\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 41	\xBFc\x00\xBFb(\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 42	\xBFc\x00\xBFb)\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 43	\xBFc\x00\xBFb*\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 44	\xBFc\x00\xBFb+\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 45	\xBFc\x00\xBFb,\xBF\x06\x00\xBF&\x00

Global Scriptor Module Communication Sheet

Mute Control Off MIDI Channel 16 Source Input 46	\xBFc\x00\xBFb-\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 47	\xBFc\x00\xBFb.\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 48	\xBFc\x00\xBFb/\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 5	\xBFc\x00\xBFb\x04\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 6	\xBFc\x00\xBFb\x05\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 7	\xBFc\x00\xBFb\x06\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 8	\xBFc\x00\xBFb\x07\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Input 9	\xBFc\x00\xBFb\x08\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source LR	\xBFc\x00\xBFbD\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 1	\xBFc\x04\xBFb\x00\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 2	\xBFc\x04\xBFb\x01\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 3	\xBFc\x04\xBFb\x02\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 4	\xBFc\x04\xBFb\x03\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 5	\xBFc\x04\xBFb\x04\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 6	\xBFc\x04\xBFb\x05\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 7	\xBFc\x04\xBFb\x06\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Master Group 8	\xBFc\x04\xBFb\x07\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Matrix 1	\xBFc\x00\xBFbU\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Matrix 2	\xBFc\x00\xBFbV\xBF\x06\x00\xBF&\x00
Mute Control Off MIDI Channel 16 Source Matrix 3	\xBFc\x00\xBFbW\xBF\x06\x00\xBF&\x00
Mute Control On MIDI Channel 1 Source AUX 1	\xB0c\x00\xB0bE\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 10	\xB0c\x00\xB0bN\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 11	\xB0c\x00\xB0bO\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 12	\xB0c\x00\xB0bP\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 2	\xB0c\x00\xB0bF\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 3	\xB0c\x00\xB0bG\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 4	\xB0c\x00\xB0bH\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 5	\xB0c\x00\xB0bI\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 6	\xB0c\x00\xB0bJ\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 7	\xB0c\x00\xB0bK\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 8	\xB0c\x00\xB0bL\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source AUX 9	\xB0c\x00\xB0bM\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 1	\xB0c\x02\xB0b\x00\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 2	\xB0c\x02\xB0b\x01\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 3	\xB0c\x02\xB0b\x02\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 4	\xB0c\x02\xB0b\x03\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 5	\xB0c\x02\xB0b\x04\xB0\x06\x00\xB0&\x01

Global Scriptor Module Communication Sheet

Mute Control On MIDI Channel 1 Source DCA 6	\xB0c\x02\xB0b\x05\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 7	\xB0c\x02\xB0b\x06\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source DCA 8	\xB0c\x02\xB0b\x07\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 1 Return	\xB0c\x00\xB0b<\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 1 Send	\xB0c\x00\xB0bQ\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 2 Return	\xB0c\x00\xB0b=\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 2 Send	\xB0c\x00\xB0bR\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 3 Return	\xB0c\x00\xB0b>\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 3 Send	\xB0c\x00\xB0bS\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 4 Return	\xB0c\x00\xB0b?\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 4 Send	\xB0c\x00\xB0bT\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 5 Return	\xB0c\x00\xB0b@\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 6 Return	\xB0c\x00\xB0bA\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 7 Return	\xB0c\x00\xB0bB\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source FX 8 Return	\xB0c\x00\xB0bC\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 1	\xB0c\x00\xB0b0\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 10	\xB0c\x00\xB0b9\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 11	\xB0c\x00\xB0b:\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 12	\xB0c\x00\xB0b;\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 2	\xB0c\x00\xB0b1\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 3	\xB0c\x00\xB0b2\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 4	\xB0c\x00\xB0b3\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 5	\xB0c\x00\xB0b4\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 6	\xB0c\x00\xB0b5\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 7	\xB0c\x00\xB0b6\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 8	\xB0c\x00\xB0b7\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Group 9	\xB0c\x00\xB0b8\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 1	\xB0c\x00\xB0b\x00\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 10	\xB0c\x00\xB0b\x09\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 11	\xB0c\x00\xB0b\x0A\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 12	\xB0c\x00\xB0b\x0B\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 13	\xB0c\x00\xB0b\x0C\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 14	\xB0c\x00\xB0b\x0D\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 15	\xB0c\x00\xB0b\x0E\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 16	\xB0c\x00\xB0b\x0F\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 17	\xB0c\x00\xB0b\x10\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 18	\xB0c\x00\xB0b\x11\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 19	\xB0c\x00\xB0b\x12\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 2	\xB0c\x00\xB0b\x01\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 20	\xB0c\x00\xB0b\x13\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 21	\xB0c\x00\xB0b\x14\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 22	\xB0c\x00\xB0b\x15\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 23	\xB0c\x00\xB0b\x16\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 24	\xB0c\x00\xB0b\x17\xB0\x06\x00\xB0&\x01

Global Scriptor Module Communication Sheet

Mute Control On MIDI Channel 1 Source Input 25	\xB0c\x00\xB0b\x18\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 26	\xB0c\x00\xB0b\x19\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 27	\xB0c\x00\xB0b\x1A\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 28	\xB0c\x00\xB0b\x1B\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 29	\xB0c\x00\xB0b\x1C\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 3	\xB0c\x00\xB0b\x02\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 30	\xB0c\x00\xB0b\x1D\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 31	\xB0c\x00\xB0b\x1E\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 32	\xB0c\x00\xB0b\x1F\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 33	\xB0c\x00\xB0b \xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 34	\xB0c\x00\xB0b!\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 35	\xB0c\x00\xB0b"\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 36	\xB0c\x00\xB0b#\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 37	\xB0c\x00\xB0b\$\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 38	\xB0c\x00\xB0b%\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 39	\xB0c\x00\xB0b&\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 4	\xB0c\x00\xB0b\x03\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 40	\xB0c\x00\xB0b'\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 41	\xB0c\x00\xB0b(\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 42	\xB0c\x00\xB0b)\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 43	\xB0c\x00\xB0b*\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 44	\xB0c\x00\xB0b+\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 45	\xB0c\x00\xB0b,\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 46	\xB0c\x00\xB0b-\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 47	\xB0c\x00\xB0b.\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 48	\xB0c\x00\xB0b/\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 5	\xB0c\x00\xB0b\x04\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 6	\xB0c\x00\xB0b\x05\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 7	\xB0c\x00\xB0b\x06\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 8	\xB0c\x00\xB0b\x07\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Input 9	\xB0c\x00\xB0b\x08\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source LR	\xB0c\x00\xB0bD\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 1	\xB0c\x04\xB0b\x00\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 2	\xB0c\x04\xB0b\x01\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 3	\xB0c\x04\xB0b\x02\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 4	\xB0c\x04\xB0b\x03\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 5	\xB0c\x04\xB0b\x04\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master Group 6	\xB0c\x04\xB0b\x05\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Master	\xB0c\x04\xB0b\x06\xB0\x06\x00\xB0&\x01

Global Scriptor Module Communication Sheet

Group 7	
Mute Control On MIDI Channel 1 Source Master	\xB0c\x04\xB0b\x07\xB0\x06\x00\xB0&\x01
Group 8	
Mute Control On MIDI Channel 1 Source Matrix 1	\xB0c\x00\xB0bU\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Matrix 2	\xB0c\x00\xB0bV\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 1 Source Matrix 3	\xB0c\x00\xB0bW\xB0\x06\x00\xB0&\x01
Mute Control On MIDI Channel 16 Source AUX 1	\xBFc\x00\xBFbE\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 10	\xBFc\x00\xBFbN\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 11	\xBFc\x00\xBFbO\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 12	\xBFc\x00\xBFbP\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 2	\xBFc\x00\xBFbF\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 3	\xBFc\x00\xBFbG\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 4	\xBFc\x00\xBFbH\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 5	\xBFc\x00\xBFbI\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 6	\xBFc\x00\xBFbJ\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 7	\xBFc\x00\xBFbK\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 8	\xBFc\x00\xBFbL\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source AUX 9	\xBFc\x00\xBFbM\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 1	\xBFc\x02\xBFb\x00\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 2	\xBFc\x02\xBFb\x01\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 3	\xBFc\x02\xBFb\x02\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 4	\xBFc\x02\xBFb\x03\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 5	\xBFc\x02\xBFb\x04\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 6	\xBFc\x02\xBFb\x05\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 7	\xBFc\x02\xBFb\x06\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source DCA 8	\xBFc\x02\xBFb\x07\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 1 Return	\xBFc\x00\xBFb<\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 1 Send	\xBFc\x00\xBFbQ\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 2 Return	\xBFc\x00\xBFb=\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 2 Send	\xBFc\x00\xBFbR\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 3 Return	\xBFc\x00\xBFb>\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 3 Send	\xBFc\x00\xBFbS\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 4 Return	\xBFc\x00\xBFb?\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 4 Send	\xBFc\x00\xBFbT\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 5 Return	\xBFc\x00\xBFb@\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 6 Return	\xBFc\x00\xBFbA\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 7 Return	\xBFc\x00\xBFbB\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source FX 8	\xBFc\x00\xBFbC\xBF\x06\x00\xBF&\x01

Global Scripter Module Communication Sheet

Return	
Mute Control On MIDI Channel 16 Source Group 1	\xBFc\x00\xBFb0\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 10	\xBFc\x00\xBFb9\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 11	\xBFc\x00\xBFb:\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 12	\xBFc\x00\xBFb;\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 2	\xBFc\x00\xBFb1\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 3	\xBFc\x00\xBFb2\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 4	\xBFc\x00\xBFb3\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 5	\xBFc\x00\xBFb4\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 6	\xBFc\x00\xBFb5\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 7	\xBFc\x00\xBFb6\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 8	\xBFc\x00\xBFb7\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Group 9	\xBFc\x00\xBFb8\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 1	\xBFc\x00\xBFb\x00\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 10	\xBFc\x00\xBFb\x09\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 11	\xBFc\x00\xBFb\x0A\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 12	\xBFc\x00\xBFb\x0B\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 13	\xBFc\x00\xBFb\x0C\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 14	\xBFc\x00\xBFb\x0D\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 15	\xBFc\x00\xBFb\x0E\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 16	\xBFc\x00\xBFb\x0F\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 17	\xBFc\x00\xBFb\x10\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 18	\xBFc\x00\xBFb\x11\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 19	\xBFc\x00\xBFb\x12\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 2	\xBFc\x00\xBFb\x01\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 20	\xBFc\x00\xBFb\x13\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 21	\xBFc\x00\xBFb\x14\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 22	\xBFc\x00\xBFb\x15\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 23	\xBFc\x00\xBFb\x16\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 24	\xBFc\x00\xBFb\x17\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 25	\xBFc\x00\xBFb\x18\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 26	\xBFc\x00\xBFb\x19\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 27	\xBFc\x00\xBFb\x1A\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 28	\xBFc\x00\xBFb\x1B\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 29	\xBFc\x00\xBFb\x1C\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 3	\xBFc\x00\xBFb\x02\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 30	\xBFc\x00\xBFb\x1D\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 31	\xBFc\x00\xBFb\x1E\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 32	\xBFc\x00\xBFb\x1F\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 33	\xBFc\x00\xBFb \xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 34	\xBFc\x00\xBFb!\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 35	\xBFc\x00\xBFb"\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 36	\xBFc\x00\xBFb#\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 37	\xBFc\x00\xBFb\$\xBF\x06\x00\xBF&\x01

Global Scriptor Module Communication Sheet

Mute Control On MIDI Channel 16 Source Input 38	\xBFc\x00\xBFb%\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 39	\xBFc\x00\xBFb&\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 4	\xBFc\x00\xBFb\x03\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 40	\xBFc\x00\xBFb'\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 41	\xBFc\x00\xBFb(\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 42	\xBFc\x00\xBFb)\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 43	\xBFc\x00\xBFb*\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 44	\xBFc\x00\xBFb+\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 45	\xBFc\x00\xBFb,\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 46	\xBFc\x00\xBFb-\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 47	\xBFc\x00\xBFb.\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 48	\xBFc\x00\xBFb/\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 5	\xBFc\x00\xBFb\x04\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 6	\xBFc\x00\xBFb\x05\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 7	\xBFc\x00\xBFb\x06\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 8	\xBFc\x00\xBFb\x07\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Input 9	\xBFc\x00\xBFb\x08\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source LR	\xBFc\x00\xBFbD\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 1	\xBFc\x04\xBFb\x00\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 2	\xBFc\x04\xBFb\x01\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 3	\xBFc\x04\xBFb\x02\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 4	\xBFc\x04\xBFb\x03\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 5	\xBFc\x04\xBFb\x04\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 6	\xBFc\x04\xBFb\x05\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 7	\xBFc\x04\xBFb\x06\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Master Group 8	\xBFc\x04\xBFb\x07\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Matrix 1	\xBFc\x00\xBFbU\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Matrix 2	\xBFc\x00\xBFbV\xBF\x06\x00\xBF&\x01
Mute Control On MIDI Channel 16 Source Matrix 3	\xBFc\x00\xBFbW\xBF\x06\x00\xBF&\x01
Scene Recall 1 MIDI Channel 1	\xB0\x00\x00\xC0\x00
Scene Recall 1 MIDI Channel 16	\xBF\x00\x00\xC0\x00
Scene Recall 300 MIDI Channel 1	\xB0\x00\x02\xC0+
Scene Recall 300 MIDI Channel 16	\xBF\x00\x02\xC0+