

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Audio Processor
Manufacturer: Allen and Heath
Firmware Version: N/A
Model(s): iLive IDR16, iLive IDR64, iLive IDR32, iLive IDR48

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.04.0001-b002	2.3.1

Version History

Module Version	Date	Notes
1_0_2_0	1/6/2020	Initial Version

Module Notes

- Status is not supported.

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 51325, Model='iLive IDR16')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value
FaderLevel	0 to 127 in steps of 1
Qualifier Key	Qualifier Value
'Input'	'1' – '64'
Qualifier Key	Qualifier Value
'MIDI Channel'	'1' – '16'
# FaderLevel example InterfaceName.Set('FaderLevel', 127, {'Input': '1', 'MIDI Channel': '1'})	
Command	Value
MuteControl	'On' 'Off'
Qualifier Key	Qualifier Value
'Input'	'1' – '64'
Qualifier Key	Qualifier Value
'MIDI Channel'	'1' – '16'
# MuteControl example InterfaceName.Set('MuteControl', 'On', {'Input': '1', 'MIDI Channel': '1'})	
Command	Value
SceneRecall	'1' – '250'
Qualifier Key	Qualifier Value
'MIDI Channel'	'1' – '16'
# SceneRecall example InterfaceName.Set('SceneRecall', '1', {'MIDI Channel': '1'})	

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Default Port:	51325
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Fader Level 0 Input 1 MIDI Channel 1	\xB0c b\x17\x06\x00
Fader Level 0 Input 1 MIDI Channel 16	\xBFc b\x17\x06\x00
Fader Level 0 Input 16 MIDI Channel 1	\xB0c/b\x17\x06\x00
Fader Level 0 Input 16 MIDI Channel 16	\xBFc/b\x17\x06\x00
Fader Level 0 Input 32 MIDI Channel 1	\xB0c?b\x17\x06\x00
Fader Level 0 Input 32 MIDI Channel 16	\xBFc?b\x17\x06\x00
Fader Level 0 Input 48 MIDI Channel 1	\xB0c0b\x17\x06\x00
Fader Level 0 Input 48 MIDI Channel 16	\xBFc0b\x17\x06\x00
Fader Level 0 Input 64 MIDI Channel 1	\xB0c_b\x17\x06\x00
Fader Level 0 Input 64 MIDI Channel 16	\xBFc_b\x17\x06\x00
Fader Level 127 Input 1 MIDI Channel 1	\xB0c b\x17\x06\x7F
Fader Level 127 Input 1 MIDI Channel 16	\xBFc b\x17\x06\x7F
Fader Level 127 Input 16 MIDI Channel 1	\xB0c/b\x17\x06\x7F
Fader Level 127 Input 16 MIDI Channel 16	\xBFc/b\x17\x06\x7F
Fader Level 127 Input 32 MIDI Channel 1	\xB0c?b\x17\x06\x7F
Fader Level 127 Input 32 MIDI Channel 16	\xBFc?b\x17\x06\x7F
Fader Level 127 Input 48 MIDI Channel 1	\xB0c0b\x17\x06\x7F
Fader Level 127 Input 48 MIDI Channel 16	\xBFc0b\x17\x06\x7F
Fader Level 127 Input 64 MIDI Channel 1	\xB0c_b\x17\x06\x7F
Fader Level 127 Input 64 MIDI Channel 16	\xBFc_b\x17\x06\x7F
Mute Control Off Input 1 MIDI Channel 1	\x90 ? \x00
Mute Control Off Input 1 MIDI Channel 16	\x9F ? \x00
Mute Control Off Input 16 MIDI Channel 1	\x90/?/\x00
Mute Control Off Input 16 MIDI Channel 16	\x9F/?/\x00
Mute Control Off Input 32 MIDI Channel 1	\x90??? \x00
Mute Control Off Input 32 MIDI Channel 16	\x9F??? \x00
Mute Control Off Input 48 MIDI Channel 1	\x900?0\x00
Mute Control Off Input 48 MIDI Channel 16	\x9F0?0\x00
Mute Control Off Input 64 MIDI Channel 1	\x90_?_ \x00
Mute Control Off Input 64 MIDI Channel 16	\x9F_?_ \x00
Mute Control On Input 1 MIDI Channel 1	\x90 \x7F \x00
Mute Control On Input 1 MIDI Channel 16	\x9F \x7F \x00
Mute Control On Input 16 MIDI Channel 1	\x90/\x7F/\x00
Mute Control On Input 16 MIDI Channel 16	\x9F/\x7F/\x00
Mute Control On Input 32 MIDI Channel 1	\x90?\x7F?\x00
Mute Control On Input 32 MIDI Channel 16	\x9F?\x7F?\x00
Mute Control On Input 48 MIDI Channel 1	\x900\x7F0\x00
Mute Control On Input 48 MIDI Channel 16	\x9F0\x7F0\x00
Mute Control On Input 64 MIDI Channel 1	\x90_\x7F_\x00
Mute Control On Input 64 MIDI Channel 16	\x9F_\x7F_\x00
Scene Recall 1 MIDI Channel 1	\xB0\x00\x00\xC0\x00
Scene Recall 1 MIDI Channel 16	\xBF\x00\x00\xCF\x00

Global Scripter Module Communication Sheet

Scene Recall 250 MIDI Channel 1	\xB0\x00\x01\xC0\xF9
Scene Recall 250 MIDI Channel 16	\xBF\x00\x01\xCF\xF9

