

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Media Player
Manufacturer: Alcorn McBride
Firmware Version: 1.28
Model(s): DVM8400

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.03.0000-b006	2.01.0001-b001	1.1.1

Version History

Module Version	Date	Notes
1_0_0_0	11/3/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- DeviceID needs to match the ID on the Media Player. Default DeviceID is 1. DeviceID set to 'All' will set the module to be unidirectional. DeviceID value can be 'All' or '0' to '126'
Example: InterfaceName.DeviceID = '1'

Control Commands, States, and Qualifiers:

AudioMute	'On'	'Off'	
Colorspace	'YPbPr'	'RGsB'	
FileTransport	'Search'	'Play File'	'Loop File'
	'Play Next'	'Loop Next'	
['File']	0 – 99999		
OutputFormat	'1080i29'	'720p59'	'480p'
	'480i'	'1080i25'	'720p50'
	'576p'	'576i'	
RelayOutput	'On'	'Off'	'Auto'
['Relay Type']	'Play'	'Fault'	
Transport	'Stop'	'Loop'	'Still'
	'Pause'	'Play'	
VideoMute	'On'	'Off'	

Status Available:

Colorspace	'YPbPr'	'RGsB'	
ConnectionStatus	'Connected'	'Disconnected'	
DeviceStatus	'Playing'	'Stopped'	'Error'
	'Stilled'	'Paused'	
OutputFormat	'1080i29'	'720p59'	'480p'
	'480i'	'1080i25'	'720p50'
	'576p'	'576i'	

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:

Serial communication:

Port Type: RS-232

Parity: None


Baud Rate: 9600

Stop Bits: One


Data Bits: 8

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND



General Notes:

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	2638
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

AudioMute Off	1@1AD\r
AudioMute On	1@0AD\r
Colorspace RGsB	1@0VC\r
Colorspace YPbPr	1@1VC\r
OutputFormat 1080i25	1@1080i25VO\r
OutputFormat 1080i29	1@1080i29VO\r
OutputFormat 480i	1@480iVO\r
OutputFormat 480p	1@480pVO\r
OutputFormat 576i	1@576iVO\r
OutputFormat 576p	1@576pVO\r
OutputFormat 720p50	1@720p50VO\r
OutputFormat 720p59	1@720p59VO\r
RelayOutput Relay Type Fault Auto	1@XFRL\r
RelayOutput Relay Type Fault Off	1@0FRL\r
RelayOutput Relay Type Fault On	1@1FRL\r
RelayOutput Relay Type Play Auto	1@XPRL\r
RelayOutput Relay Type Play Off	1@0PRL\r
RelayOutput Relay Type Play On	1@1PRL\r
Transport Loop	1@LP\r
Transport Pause	1@PA\r
Transport Play	1@PL\r
Transport Still	1@ST\r
Transport Stop	1@RJ\r
VideoMute Off	1@1VD\r
VideoMute On	1@0VD\r

Appendix B. Query Commands

Colorspace	1@VC\r
DeviceStatus	1@?P\r
OutputFormat	1@VO\r