

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Media Player
Manufacturer: Autonomic
Firmware Version: N/A
Model(s): MMS-5A

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.06.0000-b010	2.01.0002-b005	1.4.0

Version History

Module Version	Date	Notes
1_0_1_0	7/20/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5

Control Commands, States, and Qualifiers:

BrowseFilter	None		
['Type']	'Artist'	'Album'	'Genre'
	'Playlist'	'Song'	'Search'
	'Radio Source'	'Radio Genre'	'Disable Filter'
	'Disable Radio Filter'		
BrowseListNavigation	'Up' 'Down'		
['List Type']	'Albums'	'Artists'	'Genres'
	'Now Playing'	'Playlists'	'Songs'
	'Radio Sources'	'Radio Stations'	'Radio Genres'
['Step']	'1' – '10'		
BrowseListUpdate ¹	'Albums'	'Artists'	'Genres'
	'Now Playing'	'Playlists'	'Songs'
	'Radio Sources'	'Radio Stations'	'Radio Genres'
ClearNowPlayingQueue	None		
MCSInstanceListNavigation	'Up' 'Down'		
['Step']	'1' – '10'		
MCSInstanceListUpdate ²	None		
MenuNavigation	'Home'	'Up'	'Down'
	'Left'	'Right'	'Select'
PlayMedia	'Album'	'Artist'	'Genre'
	'Playlist'	'Song'	'Radio Station'
['Position']	'1' – '10'		
['Queue']	'True'	'False'	
Repeat	'On'	'Off'	
SetMCSInstance	'1' – '10'		
Shuffle	'On'	'Off'	
Transport	'Play'	'Pause'	'Stop'
	'Fast Forward'	'Rewind'	'Next'
	'Previous'		
Volume	'Up'	'Down'	

¹ Must be set before any other Browse List command calls² Must be set before any other MCS Instance command calls

Status Available:

BrowseList	'String'		
['List Type']	'Albums'	'Artists'	'Genres'
	'Now Playing'	'Playlists'	'Songs'
	'Radio Sources'	'Radio Stations'	'Radio Genres'
['Position']	'1' – '10'		
ConnectionStatus ¹	'Connected' 'Disconnected'		
CurrentAlbum ¹	'String'		
CurrentArtist ¹	'String'		
CurrentInstanceStatus ¹	'String'		
CurrentSongTitle ¹	'String'		
CurrentTrack ¹	'String'		
CurrentTrackTime ¹	Seconds		
MCSInstanceList ¹	'String'		
['Position']	'1' – '10'		
Repeat ¹	'On' 'Off'		
Shuffle ¹	'On' 'Off'		
Transport ¹	'Play'	'Pause'	'Stop'
	'Fast Forward'	'Rewind'	'Next'
	'Previous'		
VolumeLevelStatus ¹	0 to 50 in steps of 1		

¹ Only one update call is necessary for all commands. SubscribeStatus is required for all commands to get current status.

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type: Ethernet

Default Port: 5004

Logon Credentials Supported: No

Multi-Connection Capabilities: Yes

Port Changeability: Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands

Browse Filter None Type Album	SetMusicFilter Album="None"\x0D\x0A
Browse Filter None Type Artist	SetMusicFilter Artist="None"\x0D\x0A
Browse Filter None Type Disable Filter	SetMusicFilter Clear\x0D\x0A
Browse Filter None Type Disable Radio Filter	SetRadioFilter Clear\x0D\x0A
Browse Filter None Type Genre	SetMusicFilter Genre="None"\x0D\x0A
Browse Filter None Type Playlist	SetMusicFilter Playlist="None"\x0D\x0A
Browse Filter None Type Radio Genre	SetRadioFilter Genre="None"\x0D\x0A
Browse Filter None Type Radio Source	SetRadioFilter Source="None"\x0D\x0A
Browse Filter None Type Search	SetMusicFilter Search="None"\x0D\x0A
Browse Filter None Type Song	SetMusicFilter Title="None"\x0D\x0A
Clear Now Playing Queue None	ClearNowPlaying\x0D\x0A
MCS Instance List Update None	BrowseInstances\x0D\x0A
Menu Navigation Down	SendKeys Down\x0D\x0A
Menu Navigation Home	SendKeys Home\x0D\x0A
Menu Navigation Left	SendKeys Left\x0D\x0A
Menu Navigation Right	SendKeys Right\x0D\x0A
Menu Navigation Select	SendKeys Select\x0D\x0A
Menu Navigation Up	SendKeys Up\x0D\x0A
Repeat Off	Repeat false\x0D\x0A
Repeat On	Repeat true\x0D\x0A
Shuffle Off	Shuffle false\x0D\x0A
Shuffle On	Shuffle true\x0D\x0A
Transport Fast Forward	FastForward\x0D\x0A
Transport Next	SkipNext\x0D\x0A
Transport Pause	Pause\x0D\x0A
Transport Play	Play\x0D\x0A
Transport Previous	SkipPrevious\x0D\x0A
Transport Rewind	Rewind\x0D\x0A
Transport Stop	Stop\x0D\x0A
Volume Down	VolumeDown\x0D\x0A
Volume Up	VolumeUp\x0D\x0A

Appendix B. Query Commands

*Transport query response provides data for all commands that support status.

Transport	GetStatus\x0D\x0A
-----------	-------------------