

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Touch Display
 Manufacturer: Arthur Holm
 Firmware Version: N/A
 Model(s): Dynamic3Reverse

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.05.0000-b007	2.01.0002-b005	1.3.0

Version History

Module Version	Date	Notes
1_0_0_0	5/26/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- DeviceID variable must be set accordingly. Default value is '1'. Device ID ranges from '1' – '30' and 'Broadcast'. Status is unavailable when the Device ID is set to 'Broadcast'. Example: InterfaceName.DeviceID = '1'
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

AutoConfigVGA	None	
ButtonLock	'On'	'Off'
Input	'VGA'	'DVI'
Power	'On'	'Off'
ScreenControl	'Up'	'Down'

Status Available:

ButtonLock ¹	'On'	'Off'
ConnectionStatus	'Connected'	'Disconnected'
DeviceStatus ¹	'Normal'	'System Failure'
Input ¹	'VGA'	'DVI'
Power ¹	'On'	'Off'

¹ These statuses use the same query.

Cable and Adapter Requirements:

Captive Screw to RJ45

Notes for the Device:

Serial communication:

Port Type: RS-422

Baud Rate: 38400


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
Tx- (Tx)	→	2	Tx-
Rx- (Rx)	←	6	Rx-
GND	→	8	GND
Tx+ (RTS)	→	1	Tx+
Rx+ (CTS)	←	3	Rx+



General Notes:

Appendix A. Set Commands

Auto Config VGA None	\xFA\x01\x05\x00\x00
Button Lock Off	\xFA\x01\x04\x00\x00
Button Lock On	\xFA\x01\x04\x01\x00
Input DVI	\xFA\x01\x03\x00\x00
Input VGA	\xFA\x01\x03\x01\x00
Power Off	\xFA\x01\x02\x00\x00
Power On	\xFA\x01\x02\x01\x00
Screen Control Down	\xFA\x01\x01\x00\x00
Screen Control Up	\xFA\x01\x01\x01\x00

Appendix B. Query Commands

Button Lock	\xFA\x01\x14\x00\x00
Device Status	\xFA\x01\x14\x00\x00
Input	\xFA\x01\x14\x00\x00
Power	\xFA\x01\x14\x00\x00