

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Lighting Control
Manufacturer: Artistic Licence
Firmware Version: N/A
Model(s): Art-Net 3

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_1_0	1/9/2017	Initial Version

Module Notes

- Physical variable must be set accordingly. Default value is 1. Physical ranges from 0 to 255. Example:
InterfaceName.Physical = 1
- Universe variable must be set accordingly. Default value is 1. Universe ranges from 0 to 255. Example:
InterfaceName.Universe = 1
- Network variable must be set accordingly. Default value is 1. Network ranges from 0 to 127. Example:
InterfaceName.Network = 1

Control Commands, States, and Qualifiers:

DMX512Data	0 to 255 in steps of 1
['Slot']	1 – 512

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Device Listen Port:	6454
Device Reply Port:	6454
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Undetermined

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Art-Net™ Designed by and Copyright Artistic License Holdings Ltd.

[illegible]

