

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Receiver
Manufacturer: Atlona
Firmware Version: N/A
Model(s): AT-HDVS-150-RX

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	12/20/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

AspectRatio	'Full' '4:3'	'16:9' 'Keep'	'16:10'
AudioMute	'On'	'Off'	
AutoImage ¹	None		
AutoSwitch	'On'	'Off'	
Input ²	'HDMI 1'	'HDMI 2'	'VGA'
InputResolution	'800x600' '1280x800' '1920x1200'	'1024x768' '1366x768'	'1280x720' '1920x1080'
OutputResolution	'1024x768' '1366x768' '1680x1050' '720p29.97' '720p59.94' '1080i59.94' '1080p24' '1080p30' '1080p60'	'1280x800' '1400x1050' '1920x1200' '720p30' '720p60' '1080i60' '1080p25' '1080p50' 'Native'	'1280x1024' '1600x1200' '720p35' '720p50' '1080i50' '1080p23.98' '1080p29.97' '1080p59.94'
Power	'On'	'Off'	

¹ This command only works in combination with VGA input.

² This command will send an Input selection command to a TX version of this device.

Status Available:

AspectRatio	'Full' '4:3'	'16:9' 'Keep'	'16:10'
AudioMute	'On'	'Off'	
AutoSwitch	'On'	'Off'	
ConnectionStatus	'Connected'	'Disconnected'	
Input	'HDMI 1'	'HDMI 2'	'VGA'
InputResolution	'800x600' '1280x800' '1920x1200'	'1024x768' '1366x768'	'1280x720' '1920x1080'
OutputResolution	'1024x768' '1366x768' '1680x1050' '720p29.97' '720p59.94' '1080i59.94' '1080p24' '1080p30' '1080p60'	'1280x800' '1400x1050' '1920x1200' '720p30' '720p60' '1080i60' '1080p25' '1080p50' 'Native'	'1280x1024' '1600x1200' '720p35' '720p50' '1080i50' '1080p23.98' '1080p29.97' '1080p59.94'
Power	'On'	'Off'	

Cable and Adapter Requirements:

Captive Screw to Captive Screw

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Signal
TxD		TxD
RxD		RxD
GND		GND



General Notes:

Appendix A. Set Commands

Aspect Ratio 16:10	WP_Aspect[16:10]\$\\x0D
Aspect Ratio 16:9	WP_Aspect[16:9]\$\\x0D
Aspect Ratio 4:3	WP_Aspect[4:3]\$\\x0D
Aspect Ratio Full	WP_Aspect[Full]\$\\x0D
Aspect Ratio Keep	WP_Aspect[Keep]\$\\x0D
Audio Mute Off	WP_AudioEn[Off]\$\\x0D
Audio Mute On	WP_AudioEn[On]\$\\x0D
Auto Image None	WP_VgaAuto[Go]\$\\x0D
Auto Switch Off	WP_AutoSwitch[Off]\$\\x0D
Auto Switch On	WP_AutoSwitch[On]\$\\x0D
Input HDMI 1	WP_Input[Hdmi1]\$\\x0D
Input HDMI 2	WP_Input[Hdmi2]\$\\x0D
Input Resolution 1024x768	WP_InputPrefer[1]\$\\x0D
Input Resolution 1280x720	WP_InputPrefer[2]\$\\x0D
Input Resolution 1280x800	WP_InputPrefer[3]\$\\x0D
Input Resolution 1366x768	WP_InputPrefer[4]\$\\x0D
Input Resolution 1920x1080	WP_InputPrefer[5]\$\\x0D
Input Resolution 1920x1200	WP_InputPrefer[6]\$\\x0D
Input Resolution 800x600	WP_InputPrefer[0]\$\\x0D
Input VGA	WP_Input[Vga]\$\\x0D
Output Resolution 1024x768	WP_Output[0]\$\\x0D
Output Resolution 1080i50	WP_Output[14]\$\\x0D
Output Resolution 1080i59.94	WP_Output[15]\$\\x0D
Output Resolution 1080i60	WP_Output[16]\$\\x0D
Output Resolution 1080p23.98	WP_Output[17]\$\\x0D
Output Resolution 1080p24	WP_Output[18]\$\\x0D
Output Resolution 1080p25	WP_Output[19]\$\\x0D
Output Resolution 1080p29.97	WP_Output[20]\$\\x0D
Output Resolution 1080p30	WP_Output[21]\$\\x0D
Output Resolution 1080p50	WP_Output[22]\$\\x0D
Output Resolution 1080p59.94	WP_Output[23]\$\\x0D
Output Resolution 1080p60	WP_Output[24]\$\\x0D
Output Resolution 1280x1024	WP_Output[2]\$\\x0D
Output Resolution 1280x800	WP_Output[1]\$\\x0D
Output Resolution 1366x768	WP_Output[3]\$\\x0D
Output Resolution 1400x1050	WP_Output[4]\$\\x0D
Output Resolution 1600x1200	WP_Output[5]\$\\x0D
Output Resolution 1680x1050	WP_Output[6]\$\\x0D
Output Resolution 1920x1200	WP_Output[7]\$\\x0D
Output Resolution 720p29.97	WP_Output[9]\$\\x0D
Output Resolution 720p30	WP_Output[10]\$\\x0D
Output Resolution 720p35	WP_Output[8]\$\\x0D
Output Resolution 720p50	WP_Output[11]\$\\x0D
Output Resolution 720p59.94	WP_Output[12]\$\\x0D
Output Resolution 720p60	WP_Output[13]\$\\x0D

Output Resolution Native	WP_Output[25]\$\x0D
Power Off	WP_Display[Off]\$\x0D
Power On	WP_Display[On]\$\x0D

Appendix B. Query Commands

Aspect Ratio None	WP_Aspect[?]\$\x0D
Audio Mute None	WP_AudioEn[?]\$\x0D
Auto Switch None	WP_AutoSwitch[?]\$\x0D
Input None	WP_Input[?]\$\x0D
Input Resolution None	WP_InputPrefer[?]\$\x0D
Output Resolution None	WP_Output[?]\$\x0D
Power None	WP_Display[?]\$\x0D