

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Controller
Manufacturer: Aviosys
Firmware Version: N/A
Model(s): IP Power 8258-T-SP-TP, IP Power 9522 Pro, IP Power 9258S

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
2.08.0002-b002	1.4.2

Version History

Module Version	Date	Notes
1_0_2_0	7/11/2018	Initial Version

Module Notes

- If login credentials are required, devicePassword and deviceUsername must be set accordingly. devicePassword and deviceUsername default values are 12345678 and admin respectively. Example:
InterfaceName.devicePassword = 'extron'

Supported Classes and Examples

HTTPClass

```
InterfaceName = ModuleName.HTTPClass('192.168.254.254', 80, 'admin', 'password', Model='IP Power 8258-T-SP-TP')
```

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command Power	Value 'On'	Value 'Off'
Qualifier Key 'Port'	Qualifier Value '1' – '4'	
# Power example InterfaceName.Set('Power', 'On', {'Port': '1'})		

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scripter ethernet interface

Port Type:	Ethernet
Default Port:	80
Logon Credentials Supported:	Yes
Default Username:	admin
Default Password:	12345678
Multi-Connection Capabilities:	Undetermined
Port Changeability:	No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device