

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Audio Processor
Manufacturer: Bose
Firmware Version: N/A
Model(s): ControlSpace EX-440C

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.09.0000-b009	2.4.2

Version History

Module Version	Date	Notes
1_0_0_0	6/9/2020	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- for AMPLink module commands to work properly, the channels must be labeled “Ch 1” to “Ch 4”.

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='ControlSpace EX-440C')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='ControlSpace EX-440C')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 10055, Model='ControlSpace EX-440C')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value		Value
AECNEnable	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '8'		
# AECNEnable example InterfaceName.Set('AECNEnable', 'On', {'Name': 'String', 'Index 1': '1'})			
Command	Value		Value
AECEnable	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '8'		
# AECEnable example InterfaceName.Set('AECEnable', 'On', {'Name': 'String', 'Index 1': '1'})			
Command	Value		Value
AECInternalMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '8'		
# AECInternalMute example InterfaceName.Set('AECInternalMute', 'On', {'Name': 'String', 'Index 1': '1'})			
Command	Value		Value
AECNLPControl	'Light'	'Medium'	'Strong'
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '8'		
# AECNLPControl example InterfaceName.Set('AECNLPControl', 'Light', {'Name': 'String', 'Index 1': '1'})			
Command	Value		
AECNRLevel	0 to 24 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '8'		
# AECNRLevel example InterfaceName.Set('AECNRLevel', 24, {'Name': 'String', 'Index 1': '1'})			
Command	Value		
AMMGainSharingAttack	0.5 to 100 in steps of 0.5		
Qualifier Key	Qualifier Value		
'Name'	'String'		

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

# AMMGainSharingAttack example InterfaceName.Set('AMMGainSharingAttack', 100, {'Name': 'String'})		
Command	Value	Value
AMMGainSharingBypass	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '32'	
# AMMGainSharingBypass example InterfaceName.Set('AMMGainSharingBypass', 'On', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AMMGainSharingDecay	5 to 50000 in steps of 5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# AMMGainSharingDecay example InterfaceName.Set('AMMGainSharingDecay', 50000, {'Name': 'String'})		
Command	Value	
AMMGainSharingGain	-60.5 to 12 in steps of 0.5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'0' – '32'	
# AMMGainSharingGain example InterfaceName.Set('AMMGainSharingGain', 12, {'Name': 'String', 'Index 1': '0'})		
Command	Value	
AMMGainSharingHold	0 to 1000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# AMMGainSharingHold example InterfaceName.Set('AMMGainSharingHold', 1000, {'Name': 'String'})		
Command	Value	Value
AMMGainSharingMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'0' – '32'	
# AMMGainSharingMute example InterfaceName.Set('AMMGainSharingMute', 'On', {'Name': 'String', 'Index 1': '0'})		
Command	Value	
AMMGainSharingPriority	'1' – '5'	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '32'	
# AMMGainSharingPriority example InterfaceName.Set('AMMGainSharingPriority', '1', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AMMGainSharingRMSave rage	1 to 500 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	Qualifier Value
'Type'	'Input'	'Output'

Global Scripter Module Communication Sheet

Revision: 6/9/2020

# AMMGainSharingRMSAverage example InterfaceName.Set('AMMGainSharingRMSAverage', 500, {'Name': 'String', 'Type': 'Input'})	
Command AMMGainSharingSlope	Value 0.01 to 2 in steps of 0.01
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGainSharingSlope example InterfaceName.Set('AMMGainSharingSlope', 2, {'Name': 'String'})	
Command AMMGatedAttack	Value 0.5 to 500 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedAttack example InterfaceName.Set('AMMGatedAttack', 500, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedDecay	Value 1 to 50000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedDecay example InterfaceName.Set('AMMGatedDecay', 50000, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedDuckingDepth	Value -60 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedDuckingDepth example InterfaceName.Set('AMMGatedDuckingDepth', 0, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
# AMMGatedGain example InterfaceName.Set('AMMGatedGain', 12, {'Name': 'String', 'Index 1': '0'})	
Command AMMGatedGateDepth	Value -70 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedGateDepth example InterfaceName.Set('AMMGatedGateDepth', 0, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedHighPass	Value 20 to 20000 in steps of 0.1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key	Qualifier Value

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

'Index 1'	'1' – '32'
# AMMGatedHighPass example InterfaceName.Set('AMMGatedHighPass', 20000, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedHold	Value 1 to 50000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedHold example InterfaceName.Set('AMMGatedHold', 50000, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedLowPass	Value 20 to 20000 in steps of 0.1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedLowPass example InterfaceName.Set('AMMGatedLowPass', 20000, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedMute	Value 'On' 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
# AMMGatedMute example InterfaceName.Set('AMMGatedMute', 'On', {'Name': 'String', 'Index 1': '0'})	
Command AMMGatedPriority	Value '1' – '5'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedPriority example InterfaceName.Set('AMMGatedPriority', '1', {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedRMSAvg	Value 1 to 1000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedRMSAvg example InterfaceName.Set('AMMGatedRMSAvg', 1000, {'Name': 'String', 'Index 1': '1'})	
Command AMMGatedThreshold	Value -80 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGatedThreshold example InterfaceName.Set('AMMGatedThreshold', 0, {'Name': 'String', 'Index 1': '1'})	
Command AMPLinkLevel	Value -60.5 to 12 in steps of 0.5

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Channel'	Qualifier Value '1' – '4'		
# AMPLinkLevel example InterfaceName.Set('AMPLinkLevel', 12, {'Channel': '1'})			
Command AMPLinkMute	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value '1' – '4'		
# AMPLinkMute example InterfaceName.Set('AMPLinkMute', 'On', {'Channel': '1'})			
Command AMPLinkPolarity	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value '1' – '4'		
# AMPLinkPolarity example InterfaceName.Set('AMPLinkPolarity', 'On', {'Channel': '1'})			
Command ArrayEQAdvanced	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQAdvanced example InterfaceName.Set('ArrayEQAdvanced', 'On', {'Name': 'String'})			
Command ArrayEQCenterFrequency	Value 100 to 4000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQCenterFrequency example InterfaceName.Set('ArrayEQCenterFrequency', 4000, {'Name': 'String'})			
Command ArrayEQTilt	Value 0.1 to 10 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQTilt example InterfaceName.Set('ArrayEQTilt', 10, {'Name': 'String'})			
Command ArrayEQVerticalAngle	Value 20 to 100 in steps of 5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQVerticalAngle example InterfaceName.Set('ArrayEQVerticalAngle', 100, {'Name': 'String'})			
Command CompressorLimiterInputDetect	Value 'Left'	Value 'Right'	Value 'Mix'
	'Sidechain'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterInputDetect example InterfaceName.Set('CompressorLimiterInputDetect', 'Left', {'Name': 'String'})			
Command CompressorLimiterRatio	Value 1 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRatio example InterfaceName.Set('CompressorLimiterRatio', 20, {'Name': 'String'})			

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Command CompressorLimiterRelease	Value 5 to 1000 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRelease example InterfaceName.Set('CompressorLimiterRelease', 1000, {'Name': 'String'})			
Command CrossoverFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid HPF'	Qualifier Value 'Mid LPF'
# CrossoverFilter example InterfaceName.Set('CrossoverFilter', 'Butterworth 6dB/oct', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command CrossoverFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid HPF'	Qualifier Value 'Mid LPF'
# CrossoverFrequency example InterfaceName.Set('CrossoverFrequency', 20000, {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command CrossoverMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid'	
# CrossoverMute example InterfaceName.Set('CrossoverMute', 'On', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command CrossoverPolarity	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid'	

# CrossoverPolarity example InterfaceName.Set('CrossoverPolarity', 'On', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})	
Command CRRAdvancedLevel	Value -60.5 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Input'	Qualifier Value '1' – '51'
Qualifier Key 'Output'	Qualifier Value '1' – '51'
# CRRAdvancedLevel example InterfaceName.Set('CRRAdvancedLevel', 0, {'Name': 'String', 'Input': '1', 'Output': '1'})	
Command CRRAdvancedState	Value 'On' Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Input'	Qualifier Value '1' – '51'
Qualifier Key 'Output'	Qualifier Value '1' – '51'
# CRRAdvancedState example InterfaceName.Set('CRRAdvancedState', 'On', {'Name': 'String', 'Input': '1', 'Output': '1'})	
Command DelayBypass	Value 'On' Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Output'	Qualifier Value '1' – '8'
# DelayBypass example InterfaceName.Set('DelayBypass', 'On', {'Name': 'String', 'Output': '1'})	
Command DelayTime	Value 0 to 48000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Output'	Qualifier Value '1' – '8'
# DelayTime example InterfaceName.Set('DelayTime', 48000, {'Name': 'String', 'Output': '1'})	
Command DuckerDecay	Value 5 to 50000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
# DuckerDecay example InterfaceName.Set('DuckerDecay', 50000, {'Name': 'String'})	
Command DuckerHold	Value 0 to 1000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
# DuckerHold example InterfaceName.Set('DuckerHold', 1000, {'Name': 'String'})	
Command DuckerRange	Value -60 to 0 in steps of 0.1

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Name'	Qualifier Value 'String'
# DuckerRange example InterfaceName.Set('DuckerRange', 0, {'Name': 'String'})	
Command Gain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
# Gain example InterfaceName.Set('Gain', 12, {'Name': 'String'})	
Command GainMute	Value 'On' 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
# GainMute example InterfaceName.Set('GainMute', 'On', {'Name': 'String'})	
Command GateDecay	Value 5 to 50000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
# GateDecay example InterfaceName.Set('GateDecay', 50000, {'Name': 'String'})	
Command GateDetector	Value Value Value 'Left' 'Right' 'Mix' 'Sidechain'
Qualifier Key 'Name'	Qualifier Value 'String'
# GateDetector example InterfaceName.Set('GateDetector', 'Left', {'Name': 'String'})	
Command GateHold	Value 0 to 1000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
# GateHold example InterfaceName.Set('GateHold', 1000, {'Name': 'String'})	
Command GateRange	Value -70 to 0 in steps of 0.1
Qualifier Key 'Name'	Qualifier Value 'String'
# GateRange example InterfaceName.Set('GateRange', 0, {'Name': 'String'})	
Command GPOMode	Value Value 'On' 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Pin'	Qualifier Value '1' – '5'
# GPOMode example InterfaceName.Set('GPOMode', 'On', {'Name': 'String', 'Pin': '1'})	
Command GraphicEQLevel	Value -15 to 15 in steps of 0.1
Qualifier Key 'Name'	Qualifier Value 'String'

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Frequency'	Qualifier Value '20Hz' '40Hz' '80Hz' '160Hz' '315Hz' '630Hz' '1.25kHz' '2.5kHz' '5kHz' '10kHz' '20kHz'	Qualifier Value '25Hz' '50Hz' '100Hz' '200Hz' '400Hz' '800Hz' '1.6kHz' '3.15kHz' '6.3kHz' '12.5kHz'	Qualifier Value '31.5Hz' '63Hz' '125Hz' '250Hz' '500Hz' '1kHz' '2kHz' '4kHz' '8kHz' '16kHz'
# GraphicEQLevel example InterfaceName.Set('GraphicEQLevel', 15, {'Name': 'String', 'Frequency': '20Hz'})			
Command GroupLevel	Value -60 to 12 in steps of 0.5		
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
# GroupLevel example InterfaceName.Set('GroupLevel', 12, {'Group': '1'})			
Command GroupMute	Value 'On'	Value 'Off'	
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
# GroupMute example InterfaceName.Set('GroupMute', 'On', {'Group': '1'})			
Command MatrixMixerLevel	Value -60.5 to 0 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Output'	Qualifier Value '1' – '32'		
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'		
# MatrixMixerLevel example InterfaceName.Set('MatrixMixerLevel', 0, {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'})			
Command MatrixMixerState	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Output'	Qualifier Value '1' – '32'		
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'		
# MatrixMixerState example InterfaceName.Set('MatrixMixerState', 'On', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'})			

Global Scripter Module Communication Sheet

Command	Value		
ParameterRecall	'1' – '255'		
# ParameterRecall example InterfaceName.Set('ParameterRecall', '1')			
Command	Value		
ParametricEQFrequency	20 to 20000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Band'	'1' – '16'		
# ParametricEQFrequency example InterfaceName.Set('ParametricEQFrequency', 20000, {'Name': 'String', 'Band': '1'})			
Command	Value		
ParametricEQGain	-20 to 20 in steps of 0.1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Band'	'1' – '16'		
# ParametricEQGain example InterfaceName.Set('ParametricEQGain', 20, {'Name': 'String', 'Band': '1'})			
Command	Value		
ParametricEQQ	0.1 to 14 in steps of 0.001		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Band'	'1' – '16'		
# ParametricEQQ example InterfaceName.Set('ParametricEQQ', 14, {'Name': 'String', 'Band': '1'})			
Command			
ParametricEQSlope			
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Band'	'1' – '16'		
# ParametricEQSlope example InterfaceName.Set('ParametricEQSlope', , {'Name': 'String', 'Band': '1'})			
Command	Value	Value	Value
ParametricEQType	'PEQ'	'High Shelf'	'Low Shelf'
	'Low Pass'	'High Pass'	'Notch'
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Band'	'1' – '16'		
# ParametricEQType example InterfaceName.Set('ParametricEQType', 'PEQ', {'Name': 'String', 'Band': '1'})			
Command	Value	Value	Value
PeakRMSInputDetect	'Left'	'Right'	'Mix'
	'Sidechain'		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# PeakRMSInputDetect example InterfaceName.Set('PeakRMSInputDetect', 'Left', {'Name': 'String'})			
Command	Value		

Global Scripter Module Communication Sheet

Revision: 6/9/2020

PeakRMSRMS	500 to 10000 in steps of 100		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Function'	Qualifier Value 'Attack'	Qualifier Value 'Release'	
# PeakRMSRMS example InterfaceName.Set('PeakRMSRMS', 10000, {'Name': 'String', 'Function': 'Attack'})			
Command PSTNAction	Value 'Make Call'	Value 'End Call'	Value 'Answer Call'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Dial String'	Qualifier Value 'String'	Qualifier Value None	
# PSTNAction example InterfaceName.Set('PSTNAction', 'Make Call', {'Name': 'String', 'Dial String': 'String'})			
Command PSTNDialKey	Value '0' – '9' '!'	Value '#'	Value '*'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNDialKey example InterfaceName.Set('PSTNDialKey', '0', {'Name': 'String'})			
Command PSTNHook	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNHook example InterfaceName.Set('PSTNHook', 'On', {'Name': 'String'})			
Command PSTNLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNLevel example InterfaceName.Set('PSTNLevel', 12, {'Module': 'Input', 'Name': 'String'})			
Command PSTNMute	Value 'On'	Value 'Off'	
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNMute example InterfaceName.Set('PSTNMute', 'On', {'Module': 'Input', 'Name': 'String'})			
Command RouterInputSelect	Value '0' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Output'	Qualifier Value '1' – '32'		
# RouterInputSelect example InterfaceName.Set('RouterInputSelect', '0', {'Name': 'String', 'Output': '1'})			
Command	Value		

Global Scripter Module Communication Sheet

SignalGeneratorGain	-60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Wave'	Qualifier Value 'Sine' 'Sweep'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorGain example InterfaceName.Set('SignalGeneratorGain', 12, {'Name': 'String', 'Wave': 'Sine'})			
Command SignalGeneratorMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Wave'	Qualifier Value 'Sine'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorMute example InterfaceName.Set('SignalGeneratorMute', 'On', {'Name': 'String', 'Wave': 'Sine'})			
Command SourceSelect	Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SourceSelect example InterfaceName.Set('SourceSelect', '1', {'Name': 'String'})			
Command SpeakerParametricAlignDelay	Value 0 to 480 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricAlignDelay example InterfaceName.Set('SpeakerParametricAlignDelay', 480, {'Name': 'String'})			
Command SpeakerParametricBypass	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricBypass example InterfaceName.Set('SpeakerParametricBypass', 'On', {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricEQBandBypass	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandBypass example InterfaceName.Set('SpeakerParametricEQBandBypass', 'On', {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandFilter	Value 'PEQ' 'Notch'	Value 'High Shelf'	Value 'Low Shelf'
Qualifier Key 'Name'	Qualifier Value 'String'		

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFilter example InterfaceName.Set('SpeakerParametricEQBandFilter', 'PEQ', {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFrequency example InterfaceName.Set('SpeakerParametricEQBandFrequency', 20000, {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandGain	Value -20 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandGain example InterfaceName.Set('SpeakerParametricEQBandGain', 20, {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandQ	Value 0.1 to 10 in steps of 0.001		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandQ example InterfaceName.Set('SpeakerParametricEQBandQ', 10, {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFilter example InterfaceName.Set('SpeakerParametricFilter', 'Butterworth 6dB/oct', {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	

Global Scripter Module Communication Sheet

# SpeakerParametricFrequency example InterfaceName.Set('SpeakerParametricFrequency', 20000, {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricGain	Value -15 to 15 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricGain example InterfaceName.Set('SpeakerParametricGain', 15, {'Name': 'String'})			
Command StandardMixerLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'		
# StandardMixerLevel example InterfaceName.Set('StandardMixerLevel', 12, {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'})			
Command StandardMixerMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'		
# StandardMixerMute example InterfaceName.Set('StandardMixerMute', 'On', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'})			
Command StandardMixerRouting	Value 'Route'	Value 'Unroute'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key 'Output'	Qualifier Value '1' – '32'		
# StandardMixerRouting example InterfaceName.Set('StandardMixerRouting', 'Route', {'Name': 'String', 'Input': '1', 'Output': '1'})			
Command ToneControlGain	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Low'	Qualifier Value 'Mid'	Qualifier Value 'High'
# ToneControlGain example InterfaceName.Set('ToneControlGain', 15, {'Name': 'String', 'Type': 'Low'})			
Command USBLLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'
# USBLevel example InterfaceName.Set('USBLevel', 12, {'Name': 'String', 'Channel': 'Left'})		
Command USBMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'
# USBMute example InterfaceName.Set('USBMute', 'On', {'Name': 'String', 'Channel': 'Left'})		
Command VoIPAction	Value 'Make Call' 'Transfer Call'	Value 'End Call' 'Answer Call'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Dial String'	Qualifier Value 'String'	Qualifier Value None
# VoIPAction example InterfaceName.Set('VoIPAction', 'Make Call', {'Name': 'String', 'Dial String': 'String'})		
Command VoIPDialKey	Value '0' – '9'	Value '#' '*'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPDialKey example InterfaceName.Set('VoIPDialKey', '0', {'Name': 'String'})		
Command VoIPLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPLevel example InterfaceName.Set('VoIPLevel', 12, {'Name': 'String'})		
Command VoIPMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPMute example InterfaceName.Set('VoIPMute', 'On', {'Name': 'String'})		

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
```

FeedbackHandler will be called when any qualifier gets a new status.

Command	Value	Value
AECCNEnable	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '8'	
# AECCNEnable example InterfaceName.Update('AECCNEnable', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECCNEnable', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECCNEnable', None, FeedbackHandler)		
Command	Value	Value
AECEnable	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '8'	
# AECEnable example InterfaceName.Update('AECEnable', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECEnable', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECEnable', None, FeedbackHandler)		
Command	Value	Value
AECInternalMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '8'	
# AECInternalMute example InterfaceName.Update('AECInternalMute', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECInternalMute', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECInternalMute', None, FeedbackHandler)		
Command	Value	Value
AECNLPControl	'Light'	'Medium'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '8'	
# AECNLPControl example InterfaceName.Update('AECNLPControl', {'Name': 'String', 'Index 1': '1'})		

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Value = InterfaceName.ReadStatus('AECNLPControl', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECNLPControl', None, FeedbackHandler)	
Command AECNRLevel	Value 0 to 24 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'
# AECNRLevel example InterfaceName.Update('AECNRLevel', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECNRLevel', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECNRLevel', None, FeedbackHandler)	
Command AECReference	Value '1' – '4'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'
# AECReference example InterfaceName.Update('AECReference', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECReference', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECReference', None, FeedbackHandler)	
Command AMMGainSharingAttack	Value 0.5 to 100 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGainSharingAttack example InterfaceName.Update('AMMGainSharingAttack', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingAttack', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingAttack', None, FeedbackHandler)	
Command AMMGainSharingBypass	Value 'On' 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
# AMMGainSharingBypass example InterfaceName.Update('AMMGainSharingBypass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGainSharingBypass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGainSharingBypass', None, FeedbackHandler)	
Command AMMGainSharingDecay	Value 5 to 50000 in steps of 5
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGainSharingDecay example InterfaceName.Update('AMMGainSharingDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingDecay', None, FeedbackHandler)	
Command AMMGainSharingGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'

<pre># AMMGainSharingGain example InterfaceName.Update('AMMGainSharingGain', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGainSharingGain', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGainSharingGain', None, FeedbackHandler)</pre>		
Command	Value	
AMMGainSharingHold	0 to 1000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
<pre># AMMGainSharingHold example InterfaceName.Update('AMMGainSharingHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingHold', None, FeedbackHandler)</pre>		
Command	Value	Value
AMMGainSharingMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'0' – '32'	
<pre># AMMGainSharingMute example InterfaceName.Update('AMMGainSharingMute', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGainSharingMute', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGainSharingMute', None, FeedbackHandler)</pre>		
Command	Value	
AMMGainSharingPriority	'1' – '5'	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '32'	
<pre># AMMGainSharingPriority example InterfaceName.Update('AMMGainSharingPriority', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGainSharingPriority', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGainSharingPriority', None, FeedbackHandler)</pre>		
Command	Value	
AMMGainSharingRMSAverage	1 to 500 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	Qualifier Value
'Type'	'Input'	'Output'
<pre># AMMGainSharingRMSAverage example InterfaceName.Update('AMMGainSharingRMSAverage', {'Name': 'String', 'Type': 'Input'}) Value = InterfaceName.ReadStatus('AMMGainSharingRMSAverage', {'Name': 'String', 'Type': 'Input'}) InterfaceName.SubscribeStatus('AMMGainSharingRMSAverage', None, FeedbackHandler)</pre>		
Command	Value	
AMMGainSharingSlope	0.01 to 2 in steps of 0.01	
Qualifier Key	Qualifier Value	
'Name'	'String'	
<pre># AMMGainSharingSlope example InterfaceName.Update('AMMGainSharingSlope', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingSlope', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingSlope', None, FeedbackHandler)</pre>		
Command	Value	
AMMGatedAttack	0.5 to 500 in steps of 0.5	

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
<pre># AMMGatedAttack example InterfaceName.Update('AMMGatedAttack', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedAttack', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedAttack', None, FeedbackHandler)</pre>	
Command AMMGatedDecay	Value 1 to 50000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
<pre># AMMGatedDecay example InterfaceName.Update('AMMGatedDecay', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedDecay', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedDecay', None, FeedbackHandler)</pre>	
Command AMMGatedDuckingDepth	Value -60 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
<pre># AMMGatedDuckingDepth example InterfaceName.Update('AMMGatedDuckingDepth', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedDuckingDepth', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedDuckingDepth', None, FeedbackHandler)</pre>	
Command AMMGatedGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
<pre># AMMGatedGain example InterfaceName.Update('AMMGatedGain', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGatedGain', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGatedGain', None, FeedbackHandler)</pre>	
Command AMMGatedGateDepth	Value -70 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
<pre># AMMGatedGateDepth example InterfaceName.Update('AMMGatedGateDepth', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedGateDepth', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedGateDepth', None, FeedbackHandler)</pre>	
Command AMMGatedHighPass	Value 20 to 20000 in steps of 0.1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'

Global Scripter Module Communication Sheet

Revision: 6/9/2020

<pre># AMMGatedHighPass example InterfaceName.Update('AMMGatedHighPass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedHighPass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedHighPass', None, FeedbackHandler)</pre>	
Command	Value
AMMGatedHold	1 to 50000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '32'
<pre># AMMGatedHold example InterfaceName.Update('AMMGatedHold', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedHold', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedHold', None, FeedbackHandler)</pre>	
Command	Value
AMMGatedLowPass	20 to 20000 in steps of 0.1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '32'
<pre># AMMGatedLowPass example InterfaceName.Update('AMMGatedLowPass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedLowPass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedLowPass', None, FeedbackHandler)</pre>	
Command	Value
AMMGatedMute	'On' 'Off'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'0' – '32'
<pre># AMMGatedMute example InterfaceName.Update('AMMGatedMute', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGatedMute', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGatedMute', None, FeedbackHandler)</pre>	
Command	Value
AMMGatedPriority	'1' – '5'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '32'
<pre># AMMGatedPriority example InterfaceName.Update('AMMGatedPriority', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedPriority', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedPriority', None, FeedbackHandler)</pre>	
Command	Value
AMMGatedRMSAvg	1 to 1000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '32'
<pre># AMMGatedRMSAvg example InterfaceName.Update('AMMGatedRMSAvg', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedRMSAvg', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedRMSAvg', None, FeedbackHandler)</pre>	
Command	Value

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

AMMGatedThreshold	-80 to 0 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
# AMMGatedThreshold example InterfaceName.Update('AMMGatedThreshold', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedThreshold', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedThreshold', None, FeedbackHandler)		
Command AMPLinkLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Channel'	Qualifier Value '1' – '4'	
# AMPLinkLevel example InterfaceName.Update('AMPLinkLevel', {'Channel': '1'}) Value = InterfaceName.ReadStatus('AMPLinkLevel', {'Channel': '1'}) InterfaceName.SubscribeStatus('AMPLinkLevel', None, FeedbackHandler)		
Command AMPLinkMute	Value 'On'	Value 'Off'
Qualifier Key 'Channel'	Qualifier Value '1' – '4'	
# AMPLinkMute example InterfaceName.Update('AMPLinkMute', {'Channel': '1'}) Value = InterfaceName.ReadStatus('AMPLinkMute', {'Channel': '1'}) InterfaceName.SubscribeStatus('AMPLinkMute', None, FeedbackHandler)		
Command AMPLinkPolarity	Value 'On'	Value 'Off'
Qualifier Key 'Channel'	Qualifier Value '1' – '4'	
# AMPLinkPolarity example InterfaceName.Update('AMPLinkPolarity', {'Channel': '1'}) Value = InterfaceName.ReadStatus('AMPLinkPolarity', {'Channel': '1'}) InterfaceName.SubscribeStatus('AMPLinkPolarity', None, FeedbackHandler)		
Command ArrayEQAdvanced	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQAdvanced example InterfaceName.Update('ArrayEQAdvanced', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQAdvanced', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQAdvanced', None, FeedbackHandler)		
Command ArrayEQCenterFrequency	Value 100 to 4000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQCenterFrequency example InterfaceName.Update('ArrayEQCenterFrequency', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQCenterFrequency', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQCenterFrequency', None, FeedbackHandler)		
Command ArrayEQTilt	Value 0.1 to 10 in steps of 0.1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQTilt example InterfaceName.Update('ArrayEQTilt', {'Name': 'String'})		

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Value = InterfaceName.ReadStatus('ArrayEQTilt', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQTilt', None, FeedbackHandler)			
Command ArrayEQVerticalAngle	Value 20 to 100 in steps of 5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQVerticalAngle example InterfaceName.Update('ArrayEQVerticalAngle', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQVerticalAngle', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQVerticalAngle', None, FeedbackHandler)			
Command CompressorLimiterInputDetect	Value 'Left'	Value 'Right'	Value 'Mix'
	'Sidechain'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterInputDetect example InterfaceName.Update('CompressorLimiterInputDetect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterInputDetect', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterInputDetect', None, FeedbackHandler)			
Command CompressorLimiterRatio	Value 1 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRatio example InterfaceName.Update('CompressorLimiterRatio', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterRatio', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterRatio', None, FeedbackHandler)			
Command CompressorLimiterRelease	Value 5 to 1000 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRelease example InterfaceName.Update('CompressorLimiterRelease', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterRelease', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterRelease', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command CrossoverFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid HPF'	Qualifier Value 'Mid LPF'

# CrossoverFilter example InterfaceName.Update('CrossoverFilter', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverFilter', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverFilter', None, FeedbackHandler)			
Command	Value		
CrossoverFrequency	20 to 20000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Type'	'Low/High'	'Mid HPF'	'Mid LPF'
# CrossoverFrequency example InterfaceName.Update('CrossoverFrequency', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverFrequency', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverFrequency', None, FeedbackHandler)			
Command	Value	Value	
CrossoverMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverMute example InterfaceName.Update('CrossoverMute', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverMute', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverMute', None, FeedbackHandler)			
Command	Value	Value	
CrossoverPolarity	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverPolarity example InterfaceName.Update('CrossoverPolarity', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverPolarity', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverPolarity', None, FeedbackHandler)			
Command	Value		
CRRAdvancedLevel	-60.5 to 0 in steps of 0.5		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Input'	'1' – '51'		
Qualifier Key	Qualifier Value		
'Output'	'1' – '51'		

Global Scripter Module Communication Sheet

Revision: 6/9/2020

<pre># CRRAdvancedLevel example InterfaceName.Update('CRRAdvancedLevel', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('CRRAdvancedLevel', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('CRRAdvancedLevel', None, FeedbackHandler)</pre>	
Command	Value
CRRAdvancedState	'On' 'Off'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Input'	'1' – '51'
Qualifier Key	Qualifier Value
'Output'	'1' – '51'
<pre># CRRAdvancedState example InterfaceName.Update('CRRAdvancedState', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('CRRAdvancedState', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('CRRAdvancedState', None, FeedbackHandler)</pre>	
Command	Value
DelayBypass	'On' 'Off'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Output'	'1' – '8'
<pre># DelayBypass example InterfaceName.Update('DelayBypass', {'Name': 'String', 'Output': '1'}) Value = InterfaceName.ReadStatus('DelayBypass', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('DelayBypass', None, FeedbackHandler)</pre>	
Command	Value
DelayTime	0 to 48000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Output'	'1' – '8'
<pre># DelayTime example InterfaceName.Update('DelayTime', {'Name': 'String', 'Output': '1'}) Value = InterfaceName.ReadStatus('DelayTime', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('DelayTime', None, FeedbackHandler)</pre>	
Command	Value
DuckerDecay	5 to 50000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
<pre># DuckerDecay example InterfaceName.Update('DuckerDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerDecay', None, FeedbackHandler)</pre>	
Command	Value
DuckerHold	0 to 1000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
<pre># DuckerHold example InterfaceName.Update('DuckerHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerHold', None, FeedbackHandler)</pre>	
Command	Value

Global Scripter Module Communication Sheet

Revision: 6/9/2020

DuckerRange	-60 to 0 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# DuckerRange example InterfaceName.Update('DuckerRange', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerRange', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerRange', None, FeedbackHandler)			
Command Gain	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# Gain example InterfaceName.Update('Gain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('Gain', {'Name': 'String'}) InterfaceName.SubscribeStatus('Gain', None, FeedbackHandler)			
Command GainMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# GainMute example InterfaceName.Update('GainMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GainMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('GainMute', None, FeedbackHandler)			
Command GateDecay	Value 5 to 50000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateDecay example InterfaceName.Update('GateDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateDecay', None, FeedbackHandler)			
Command GateDetector	Value 'Left' 'Sidechain'	Value 'Right'	Value 'Mix'
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateDetector example InterfaceName.Update('GateDetector', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateDetector', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateDetector', None, FeedbackHandler)			
Command GateHold	Value 0 to 1000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateHold example InterfaceName.Update('GateHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateHold', None, FeedbackHandler)			
Command GateRange	Value -70 to 0 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateRange example InterfaceName.Update('GateRange', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateRange', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateRange', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Command GPOMode	Value 'On' 'Off'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Pin'	Qualifier Value '1' – '5'		
<pre># GPOMode example InterfaceName.Update('GPOMode', {'Name': 'String', 'Pin': '1'}) Value = InterfaceName.ReadStatus('GPOMode', {'Name': 'String', 'Pin': '1'}) InterfaceName.SubscribeStatus('GPOMode', None, FeedbackHandler)</pre>			
Command GraphicEQLevel	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Frequency'	Qualifier Value '20Hz' '40Hz' '80Hz' '160Hz' '315Hz' '630Hz' '1.25kHz' '2.5kHz' '5kHz' '10kHz' '20kHz'	Qualifier Value '25Hz' '50Hz' '100Hz' '200Hz' '400Hz' '800Hz' '1.6kHz' '3.15kHz' '6.3kHz' '12.5kHz'	Qualifier Value '31.5Hz' '63Hz' '125Hz' '250Hz' '500Hz' '1kHz' '2kHz' '4kHz' '8kHz' '16kHz'
<pre># GraphicEQLevel example InterfaceName.Update('GraphicEQLevel', {'Name': 'String', 'Frequency': '20Hz'}) Value = InterfaceName.ReadStatus('GraphicEQLevel', {'Name': 'String', 'Frequency': '20Hz'}) InterfaceName.SubscribeStatus('GraphicEQLevel', None, FeedbackHandler)</pre>			
Command GroupLevel	Value -60 to 12 in steps of 0.5		
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
<pre># GroupLevel example InterfaceName.Update('GroupLevel', {'Group': '1'}) Value = InterfaceName.ReadStatus('GroupLevel', {'Group': '1'}) InterfaceName.SubscribeStatus('GroupLevel', None, FeedbackHandler)</pre>			
Command GroupMute	Value 'On' 'Off'		
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
<pre># GroupMute example InterfaceName.Update('GroupMute', {'Group': '1'}) Value = InterfaceName.ReadStatus('GroupMute', {'Group': '1'}) InterfaceName.SubscribeStatus('GroupMute', None, FeedbackHandler)</pre>			
Command MatrixMixerLevel	Value -60.5 to 0 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Input'	Qualifier Value '1' – '32'		
Qualifier Key	Qualifier Value		

Global Scripter Module Communication Sheet

'Output'	'1' – '32'
Qualifier Key	Qualifier Value
'Matrix Size'	'1' – '32'
<pre># MatrixMixerLevel example InterfaceName.Update('MatrixMixerLevel', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) Value = InterfaceName.ReadStatus('MatrixMixerLevel', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) InterfaceName.SubscribeStatus('MatrixMixerLevel', None, FeedbackHandler)</pre>	
Command	Value
MatrixMixerState	'On' 'Off'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Input'	'1' – '32'
Qualifier Key	Qualifier Value
'Output'	'1' – '32'
Qualifier Key	Qualifier Value
'Matrix Size'	'1' – '32'
<pre># MatrixMixerState example InterfaceName.Update('MatrixMixerState', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) Value = InterfaceName.ReadStatus('MatrixMixerState', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) InterfaceName.SubscribeStatus('MatrixMixerState', None, FeedbackHandler)</pre>	
Command	Value
ParameterRecall	'1' – '255' 'None'
<pre># ParameterRecall example InterfaceName.Update('ParameterRecall') Value = InterfaceName.ReadStatus('ParameterRecall') InterfaceName.SubscribeStatus('ParameterRecall', None, FeedbackHandler)</pre>	
Command	Value
ParametricEQFrequency	20 to 20000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Band'	'1' – '16'
<pre># ParametricEQFrequency example InterfaceName.Update('ParametricEQFrequency', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQFrequency', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQFrequency', None, FeedbackHandler)</pre>	
Command	Value
ParametricEQGain	-20 to 20 in steps of 0.1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Band'	'1' – '16'
<pre># ParametricEQGain example InterfaceName.Update('ParametricEQGain', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQGain', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQGain', None, FeedbackHandler)</pre>	
Command	Value
ParametricEQQ	0.1 to 14 in steps of 0.001
Qualifier Key	Qualifier Value
'Name'	'String'

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQQ example InterfaceName.Update('ParametricEQQ', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQQ', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQQ', None, FeedbackHandler)			
Command ParametricEQSlope			
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQSlope example InterfaceName.Update('ParametricEQSlope', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQSlope', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQSlope', None, FeedbackHandler)			
Command ParametricEQType	Value 'PEQ' 'Low Pass'	Value 'High Shelf' 'High Pass'	Value 'Low Shelf' 'Notch'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQType example InterfaceName.Update('ParametricEQType', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQType', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQType', None, FeedbackHandler)			
Command PeakRMSInputDetect	Value 'Left' 'Sidechain'	Value 'Right'	Value 'Mix'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PeakRMSInputDetect example InterfaceName.Update('PeakRMSInputDetect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PeakRMSInputDetect', {'Name': 'String'}) InterfaceName.SubscribeStatus('PeakRMSInputDetect', None, FeedbackHandler)			
Command PeakRMSRMS	Value 500 to 10000 in steps of 100		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Function'	Qualifier Value 'Attack'	Qualifier Value 'Release'	
# PeakRMSRMS example InterfaceName.Update('PeakRMSRMS', {'Name': 'String', 'Function': 'Attack'}) Value = InterfaceName.ReadStatus('PeakRMSRMS', {'Name': 'String', 'Function': 'Attack'}) InterfaceName.SubscribeStatus('PeakRMSRMS', None, FeedbackHandler)			
Command PSTNCallActive	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNCallActive example InterfaceName.Update('PSTNCallActive', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNCallActive', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNCallActive', None, FeedbackHandler)			
Command	Value	Value	Value

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

PSTNCallStatus	'Hangup'			'Incoming'	'Active'
	'Error'				
Qualifier Key 'Name'	Qualifier Value 'String'				
# PSTNCallStatus example InterfaceName.Update('PSTNCallStatus', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNCallStatus', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNCallStatus', None, FeedbackHandler)					
Command PSTNCallerID	Value 'String'				
Qualifier Key 'Name'	Qualifier Value 'String'				
Qualifier Key 'Type'	Qualifier Value 'Date'	Qualifier Value 'Time'	Qualifier Value 'Number'		
	'Name'				
# PSTNCallerID example InterfaceName.Update('PSTNCallerID', {'Name': 'String', 'Type': 'Date'}) Value = InterfaceName.ReadStatus('PSTNCallerID', {'Name': 'String', 'Type': 'Date'}) InterfaceName.SubscribeStatus('PSTNCallerID', None, FeedbackHandler)					
Command PSTNHook	Value 'On'	Value 'Off'			
Qualifier Key 'Name'	Qualifier Value 'String'				
# PSTNHook example InterfaceName.Update('PSTNHook', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNHook', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNHook', None, FeedbackHandler)					
Command PSTNLevel	Value -60.5 to 12 in steps of 0.5				
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'			
Qualifier Key 'Name'	Qualifier Value 'String'				
# PSTNLevel example InterfaceName.Update('PSTNLevel', {'Module': 'Input', 'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNLevel', {'Module': 'Input', 'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNLevel', None, FeedbackHandler)					
Command PSTNMute	Value 'On'	Value 'Off'			
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'			
Qualifier Key 'Name'	Qualifier Value 'String'				
# PSTNMute example InterfaceName.Update('PSTNMute', {'Module': 'Input', 'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNMute', {'Module': 'Input', 'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNMute', None, FeedbackHandler)					
Command RouterInputSelect	Value '0' – '32'				
Qualifier Key 'Name'	Qualifier Value 'String'				
Qualifier Key 'Output'	Qualifier Value '1' – '32'				
# RouterInputSelect example InterfaceName.Update('RouterInputSelect', {'Name': 'String', 'Output': '1'})					

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Value = InterfaceName.ReadStatus('RouterInputSelect', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('RouterInputSelect', None, FeedbackHandler)			
Command SignalGeneratorGain	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Wave'	Qualifier Value 'Sine' 'Sweep'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorGain example InterfaceName.Update('SignalGeneratorGain', {'Name': 'String', 'Wave': 'Sine'}) Value = InterfaceName.ReadStatus('SignalGeneratorGain', {'Name': 'String', 'Wave': 'Sine'}) InterfaceName.SubscribeStatus('SignalGeneratorGain', None, FeedbackHandler)			
Command SignalGeneratorMute	Value 'On'		Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Wave'	Qualifier Value 'Sine'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorMute example InterfaceName.Update('SignalGeneratorMute', {'Name': 'String', 'Wave': 'Sine'}) Value = InterfaceName.ReadStatus('SignalGeneratorMute', {'Name': 'String', 'Wave': 'Sine'}) InterfaceName.SubscribeStatus('SignalGeneratorMute', None, FeedbackHandler)			
Command SourceSelect	Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SourceSelect example InterfaceName.Update('SourceSelect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SourceSelect', {'Name': 'String'}) InterfaceName.SubscribeStatus('SourceSelect', None, FeedbackHandler)			
Command SpeakerParametricAlignDelay	Value 0 to 480 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricAlignDelay example InterfaceName.Update('SpeakerParametricAlignDelay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SpeakerParametricAlignDelay', {'Name': 'String'}) InterfaceName.SubscribeStatus('SpeakerParametricAlignDelay', None, FeedbackHandler)			
Command SpeakerParametricBypass	Value 'On'		Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricBypass example InterfaceName.Update('SpeakerParametricBypass', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricBypass', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricBypass', None, FeedbackHandler)			
Command SpeakerParametricEQBandBypass	Value 'On'		Value 'Off'
Qualifier Key	Qualifier Value		

Global Scripter Module Communication Sheet

Revision: 6/9/2020

'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '9'
<pre># SpeakerParametricEQBandBypass example InterfaceName.Update('SpeakerParametricEQBandBypass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandBypass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandBypass', None, FeedbackHandler)</pre>	
Command	Value
SpeakerParametricEQBandFilter	Value
	Value
	'PEQ'
	'High Shelf'
	'Low Shelf'
	'Notch'
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '9'
<pre># SpeakerParametricEQBandFilter example InterfaceName.Update('SpeakerParametricEQBandFilter', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandFilter', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandFilter', None, FeedbackHandler)</pre>	
Command	Value
SpeakerParametricEQBandFrequency	20 to 20000 in steps of 1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '9'
<pre># SpeakerParametricEQBandFrequency example InterfaceName.Update('SpeakerParametricEQBandFrequency', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandFrequency', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandFrequency', None, FeedbackHandler)</pre>	
Command	Value
SpeakerParametricEQBandGain	-20 to 20 in steps of 0.1
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '9'
<pre># SpeakerParametricEQBandGain example InterfaceName.Update('SpeakerParametricEQBandGain', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandGain', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandGain', None, FeedbackHandler)</pre>	
Command	Value
SpeakerParametricEQBandQ	0.1 to 10 in steps of 0.001
Qualifier Key	Qualifier Value
'Name'	'String'
Qualifier Key	Qualifier Value
'Index 1'	'1' – '9'
<pre># SpeakerParametricEQBandQ example InterfaceName.Update('SpeakerParametricEQBandQ', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandQ', {'Name': 'String', 'Index 1': '1'})</pre>	

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

'1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandQ', None, FeedbackHandler)			
Command SpeakerParametricFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFilter example InterfaceName.Update('SpeakerParametricFilter', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricFilter', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricFilter', None, FeedbackHandler)			
Command SpeakerParametricFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFrequency example InterfaceName.Update('SpeakerParametricFrequency', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricFrequency', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricFrequency', None, FeedbackHandler)			
Command SpeakerParametricGain	Value -15 to 15 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricGain example InterfaceName.Update('SpeakerParametricGain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SpeakerParametricGain', {'Name': 'String'}) InterfaceName.SubscribeStatus('SpeakerParametricGain', None, FeedbackHandler)			
Command StandardMixerLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'		
# StandardMixerLevel example InterfaceName.Update('StandardMixerLevel', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) Value = InterfaceName.ReadStatus('StandardMixerLevel', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) InterfaceName.SubscribeStatus('StandardMixerLevel', None, FeedbackHandler)			
Command StandardMixerMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'	
# StandardMixerMute example InterfaceName.Update('StandardMixerMute', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) Value = InterfaceName.ReadStatus('StandardMixerMute', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) InterfaceName.SubscribeStatus('StandardMixerMute', None, FeedbackHandler)		
Command StandardMixerRouting	Value 'Route'	Value 'Unroute'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
# StandardMixerRouting example InterfaceName.Update('StandardMixerRouting', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('StandardMixerRouting', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('StandardMixerRouting', None, FeedbackHandler)		
Command ToneControlGain	Value -15 to 15 in steps of 0.1	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Type'	Qualifier Value 'Low'	Qualifier Value 'Mid'
		Qualifier Value 'High'
# ToneControlGain example InterfaceName.Update('ToneControlGain', {'Name': 'String', 'Type': 'Low'}) Value = InterfaceName.ReadStatus('ToneControlGain', {'Name': 'String', 'Type': 'Low'}) InterfaceName.SubscribeStatus('ToneControlGain', None, FeedbackHandler)		
Command USBLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'
# USBLevel example InterfaceName.Update('USBLevel', {'Name': 'String', 'Channel': 'Left'}) Value = InterfaceName.ReadStatus('USBLevel', {'Name': 'String', 'Channel': 'Left'}) InterfaceName.SubscribeStatus('USBLevel', None, FeedbackHandler)		
Command USBMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'
# USBMute example InterfaceName.Update('USBMute', {'Name': 'String', 'Channel': 'Left'}) Value = InterfaceName.ReadStatus('USBMute', {'Name': 'String', 'Channel': 'Left'}) InterfaceName.SubscribeStatus('USBMute', None, FeedbackHandler)		
Command VoIPCallActive	Value 'On'	Value 'Off'

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPCallActive example InterfaceName.Update('VoIPCallActive', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPCallActive', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPCallActive', None, FeedbackHandler)			
Command VoIPCallStatus	Value 'Incoming' 'Active'	Value 'Dialing' 'Hangup'	Value 'Ringback' 'Hold State Peer'
Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPCallStatus example InterfaceName.Update('VoIPCallStatus', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPCallStatus', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPCallStatus', None, FeedbackHandler)			
Command VoIPCallerID	Value 'String'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Name'	Qualifier Value 'Hostname'	
# VoIPCallerID example InterfaceName.Update('VoIPCallerID', {'Name': 'String', 'Type': 'Name'}) Value = InterfaceName.ReadStatus('VoIPCallerID', {'Name': 'String', 'Type': 'Name'}) InterfaceName.SubscribeStatus('VoIPCallerID', None, FeedbackHandler)			
Command VoIPLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPLevel example InterfaceName.Update('VoIPLevel', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPLevel', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPLevel', None, FeedbackHandler)			
Command VoIPMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPMute example InterfaceName.Update('VoIPMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPMute', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to Captive Screw RS-232 Serial Cable


Notes for the Device

Serial communication


Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Signal
TxD		TxD
RxD		RxD
GND		GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type:	Ethernet
Default Port:	10055
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

This model support port changeability, and you must enable **Enable Serial over IP** within the device's properties. This can be accessed by right clicking the device block in the Project View tab within the Bose ControlSpace Designer software.

Appendix A. Set Commands

AEC CN Enable Off Name testString Index 1 1	SA"testString">1>8=F\x0D
AEC CN Enable Off Name testString Index 1 8	SA"testString">8>8=F\x0D
AEC CN Enable On Name testString Index 1 1	SA"testString">1>8=0\x0D
AEC CN Enable On Name testString Index 1 8	SA"testString">8>8=0\x0D
AEC Enable Off Name testString Index 1 1	SA"testString">1>6=F\x0D
AEC Enable Off Name testString Index 1 8	SA"testString">8>6=F\x0D
AEC Enable On Name testString Index 1 1	SA"testString">1>6=0\x0D
AEC Enable On Name testString Index 1 8	SA"testString">8>6=0\x0D
AEC Internal Mute Off Name testString Index 1 1	SA"testString">1>5=F\x0D
AEC Internal Mute Off Name testString Index 1 8	SA"testString">8>5=F\x0D
AEC Internal Mute On Name testString Index 1 1	SA"testString">1>5=0\x0D
AEC Internal Mute On Name testString Index 1 8	SA"testString">8>5=0\x0D
AEC NLP Control Light Name testString Index 1 1	SA"testString">1>7=1\x0D
AEC NLP Control Light Name testString Index 1 8	SA"testString">8>7=1\x0D
AEC NLP Control Medium Name testString Index 1 1	SA"testString">1>7=2\x0D
AEC NLP Control Medium Name testString Index 1 8	SA"testString">8>7=2\x0D
AEC NLP Control Strong Name testString Index 1 1	SA"testString">1>7=3\x0D
AEC NLP Control Strong Name testString Index 1 8	SA"testString">8>7=3\x0D
AEC NR Level 0 Name testString Index 1 1	SA"testString">1>9=0\x0D
AEC NR Level 0 Name testString Index 1 8	SA"testString">8>9=0\x0D
AEC NR Level 24 Name testString Index 1 1	SA"testString">1>9=24\x0D
AEC NR Level 24 Name testString Index 1 8	SA"testString">8>9=24\x0D
AMM Gain Sharing Attack 0 Name testString	SA"testString">0>4=0.0\x0D
AMM Gain Sharing Attack 100 Name testString	SA"testString">0>4=100.0\x0D
AMM Gain Sharing Bypass Off Name testString Index 1 1	SA"testString">1>4=F\x0D
AMM Gain Sharing Bypass Off Name testString Index 1 32	SA"testString">32>4=F\x0D
AMM Gain Sharing Bypass On Name testString Index 1 1	SA"testString">1>4=0\x0D
AMM Gain Sharing Bypass On Name testString Index 1 32	SA"testString">32>4=0\x0D
AMM Gain Sharing Decay 5 Name testString	SA"testString">0>6=5\x0D
AMM Gain Sharing Decay 50000 Name testString	SA"testString">0>6=50000\x0D
AMM Gain Sharing Gain 12 Name testString Index 1 0	SA"testString">0>1=12.0\x0D
AMM Gain Sharing Gain 12 Name testString Index 1 32	SA"testString">32>1=12.0\x0D
AMM Gain Sharing Gain -60 Name testString Index 1 0	SA"testString">0>1=-60.0\x0D
AMM Gain Sharing Gain -60 Name testString Index 1 32	SA"testString">32>1=-60.0\x0D
AMM Gain Sharing Hold 0 Name testString	SA"testString">0>5=0\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

AMM Gain Sharing Hold 1000 Name testString	SA"testString">0>5=1000\x0D
AMM Gain Sharing Mute Off Name testString Index 1 0	SA"testString">0>2=F\x0D
AMM Gain Sharing Mute Off Name testString Index 1 32	SA"testString">32>2=F\x0D
AMM Gain Sharing Mute On Name testString Index 1 0	SA"testString">0>2=0\x0D
AMM Gain Sharing Mute On Name testString Index 1 32	SA"testString">32>2=0\x0D
AMM Gain Sharing Priority 1 Name testString Index 1 1	SA"testString">1>3=1\x0D
AMM Gain Sharing Priority 1 Name testString Index 1 32	SA"testString">32>3=1\x0D
AMM Gain Sharing Priority 5 Name testString Index 1 1	SA"testString">1>3=5\x0D
AMM Gain Sharing Priority 5 Name testString Index 1 32	SA"testString">32>3=5\x0D
AMM Gain Sharing RMS Average 1 Name testString Type Input	SA"testString">0>7=1\x0D
AMM Gain Sharing RMS Average 1 Name testString Type Output	SA"testString">0>8=1\x0D
AMM Gain Sharing RMS Average 500 Name testString Type Input	SA"testString">0>7=500\x0D
AMM Gain Sharing RMS Average 500 Name testString Type Output	SA"testString">0>8=500\x0D
AMM Gain Sharing Slope 0 Name testString	SA"testString">0>3=0.00\x0D
AMM Gain Sharing Slope 2 Name testString	SA"testString">0>3=2.00\x0D
AMM Gated Attack 0 Name testString Index 1 1	SA"testString">1>14=0.0\x0D
AMM Gated Attack 0 Name testString Index 1 32	SA"testString">32>14=0.0\x0D
AMM Gated Attack 500 Name testString Index 1 1	SA"testString">1>14=500.0\x0D
AMM Gated Attack 500 Name testString Index 1 32	SA"testString">32>14=500.0\x0D
AMM Gated Decay 1 Name testString Index 1 1	SA"testString">1>16=1\x0D
AMM Gated Decay 1 Name testString Index 1 32	SA"testString">32>16=1\x0D
AMM Gated Decay 50000 Name testString Index 1 1	SA"testString">1>16=50000\x0D
AMM Gated Decay 50000 Name testString Index 1 32	SA"testString">32>16=50000\x0D
AMM Gated Ducking Depth 0 Name testString Index 1 1	SA"testString">1>12=0.0\x0D
AMM Gated Ducking Depth 0 Name testString Index 1 32	SA"testString">32>12=0.0\x0D
AMM Gated Ducking Depth -60 Name testString Index 1 1	SA"testString">1>12=-60.0\x0D
AMM Gated Ducking Depth -60 Name testString Index 1 32	SA"testString">32>12=-60.0\x0D
AMM Gated Gain 12 Name testString Index 1 0	SA"testString">0>1=12.0\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

AMM Gated Gain 12 Name testString Index 1 32	SA"testString">32>2=12.0\0D
AMM Gated Gain -60 Name testString Index 1 0	SA"testString">0>1=-60.0\0D
AMM Gated Gain -60 Name testString Index 1 32	SA"testString">32>2=-60.0\0D
AMM Gated Gate Depth 0 Name testString Index 1 1	SA"testString">1>13=0.0\0D
AMM Gated Gate Depth 0 Name testString Index 1 32	SA"testString">32>13=0.0\0D
AMM Gated Gate Depth -70 Name testString Index 1 1	SA"testString">1>13=-70.0\0D
AMM Gated Gate Depth -70 Name testString Index 1 32	SA"testString">32>13=-70.0\0D
AMM Gated High Pass 20 Name testString Index 1 1	SA"testString">1>10=20.0\0D
AMM Gated High Pass 20 Name testString Index 1 32	SA"testString">32>10=20.0\0D
AMM Gated High Pass 20000 Name testString Index 1 1	SA"testString">1>10=20000.0\0D
AMM Gated High Pass 20000 Name testString Index 1 32	SA"testString">32>10=20000.0\0D
AMM Gated Hold 1 Name testString Index 1 1	SA"testString">1>15=1\0D
AMM Gated Hold 1 Name testString Index 1 32	SA"testString">32>15=1\0D
AMM Gated Hold 50000 Name testString Index 1 1	SA"testString">1>15=50000\0D
AMM Gated Hold 50000 Name testString Index 1 32	SA"testString">32>15=50000\0D
AMM Gated Low Pass 20 Name testString Index 1 1	SA"testString">1>9=20.0\0D
AMM Gated Low Pass 20 Name testString Index 1 32	SA"testString">32>9=20.0\0D
AMM Gated Low Pass 20000 Name testString Index 1 1	SA"testString">1>9=20000.0\0D
AMM Gated Low Pass 20000 Name testString Index 1 32	SA"testString">32>9=20000.0\0D
AMM Gated Mute Off Name testString Index 1 0	SA"testString">0>2=F\0D
AMM Gated Mute Off Name testString Index 1 32	SA"testString">32>3=F\0D
AMM Gated Mute On Name testString Index 1 0	SA"testString">0>2=0\0D
AMM Gated Mute On Name testString Index 1 32	SA"testString">32>3=0\0D
AMM Gated Priority 1 Name testString Index 1 1	SA"testString">1>1=1\0D
AMM Gated Priority 1 Name testString Index 1 32	SA"testString">32>1=1\0D
AMM Gated Priority 5 Name testString Index 1 1	SA"testString">1>1=5\0D
AMM Gated Priority 5 Name testString Index 1 32	SA"testString">32>1=5\0D
AMM Gated RMS Avg 1 Name testString Index 1 1	SA"testString">1>11=1\0D
AMM Gated RMS Avg 1 Name testString Index 1 32	SA"testString">32>11=1\0D
AMM Gated RMS Avg 1000 Name testString Index 1 1	SA"testString">1>11=1000\0D
AMM Gated RMS Avg 1000 Name testString Index 1 32	SA"testString">32>11=1000\0D
AMM Gated Threshold 0 Name testString Index 1 1	SA"testString">1>5=0.0\0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

AMM Gated Threshold 0 Name testString Index 1 32	SA"testString">32>5=0.0\x0D
AMM Gated Threshold -80 Name testString Index 1 1	SA"testString">1>5=-80.0\x0D
AMM Gated Threshold -80 Name testString Index 1 32	SA"testString">32>5=-80.0\x0D
AMPLink Level 12 Channel 1	SA"AMPLink-Ch 1">1=12.0\x0D
AMPLink Level 12 Channel 4	SA"AMPLink-Ch 4">1=12.0\x0D
AMPLink Level -60 Channel 1	SA"AMPLink-Ch 1">1=-60.0\x0D
AMPLink Level -60 Channel 4	SA"AMPLink-Ch 4">1=-60.0\x0D
AMPLink Mute Off Channel 1	SA"AMPLink-Ch 1">2=F\x0D
AMPLink Mute Off Channel 4	SA"AMPLink-Ch 4">2=F\x0D
AMPLink Mute On Channel 1	SA"AMPLink-Ch 1">2=0\x0D
AMPLink Mute On Channel 4	SA"AMPLink-Ch 4">2=0\x0D
AMPLink Polarity Off Channel 1	SA"AMPLink-Ch 1">3=F\x0D
AMPLink Polarity Off Channel 4	SA"AMPLink-Ch 4">3=F\x0D
AMPLink Polarity On Channel 1	SA"AMPLink-Ch 1">3=0\x0D
AMPLink Polarity On Channel 4	SA"AMPLink-Ch 4">3=0\x0D
Array EQ Advanced Off Name testString	SA"testString">1>6=F\x0D
Array EQ Advanced On Name testString	SA"testString">1>6=0\x0D
Array EQ Center Frequency 100 Name testString	SA"testString">1>1=100\x0D
Array EQ Center Frequency 4000 Name testString	SA"testString">1>1=4000\x0D
Array EQ Tilt 0 Name testString	SA"testString">1>2=0.0\x0D
Array EQ Tilt 10 Name testString	SA"testString">1>2=10.0\x0D
Array EQ Vertical Angle 100 Name testString	SA"testString">1>8=100\x0D
Array EQ Vertical Angle 20 Name testString	SA"testString">1>8=20\x0D
Compressor/Limiter Input Detect Left Name testString	SA"testString">1=L\x0D
Compressor/Limiter Input Detect Mix Name testString	SA"testString">1=M\x0D
Compressor/Limiter Input Detect Right Name testString	SA"testString">1=R\x0D
Compressor/Limiter Input Detect Sidechain Name testString	SA"testString">1=S\x0D
Compressor/Limiter Ratio 1 Name testString	SA"testString">3=1.0\x0D
Compressor/Limiter Ratio 20 Name testString	SA"testString">3=20.0\x0D
Compressor/Limiter Release 1000 Name testString	SA"testString">5=1000.0\x0D
Compressor/Limiter Release 5 Name testString	SA"testString">5=5.0\x0D
Crossover Filter Bessel 12dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Bes12\x0D
Crossover Filter Bessel 12dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Bes12\x0D

Global Scripter Module Communication Sheet

Crossover Filter Bessel 12dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Bes12\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Bes18\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Bes18\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Bes24\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Bes24\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Bes36\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Bes36\x0D
Crossover Filter Bessel 48dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Bes48\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Crossover Filter Bessel 48dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Bes48\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But12\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But12\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But18\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But18\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But24\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But24\x0D
Crossover Filter Butterworth 36dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But36\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Crossover Filter Butterworth 36dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But36\x0D
Crossover Filter Butterworth 36dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But36\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But48\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But48\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=But6\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=But6\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Lin12\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Lin24\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Lin24\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Lin36\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 1 Type Low/High	SA"testString">1>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 1 Type Mid HPF	SA"testString">1>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 1 Type Mid LPF	SA"testString">1>3=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 4 Type Low/High	SA"testString">4>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 4 Type Mid HPF	SA"testString">4>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Name testString Index 1 4 Type Mid LPF	SA"testString">4>3=Lin48\x0D
Crossover Frequency 20 Name testString Index 1 1 Type Low/High	SA"testString">1>2=20\x0D
Crossover Frequency 20 Name testString Index 1 1 Type Mid HPF	SA"testString">1>2=20\x0D
Crossover Frequency 20 Name testString Index 1 1 Type Mid LPF	SA"testString">1>4=20\x0D
Crossover Frequency 20 Name testString Index 1 4 Type Low/High	SA"testString">4>2=20\x0D
Crossover Frequency 20 Name testString Index 1 4 Type Mid HPF	SA"testString">4>2=20\x0D
Crossover Frequency 20 Name testString Index 1 4 Type Mid LPF	SA"testString">4>4=20\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Crossover Frequency 20000 Name testString Index 1 1 Type Low/High	SA"testString">1>2=20000\x0D
Crossover Frequency 20000 Name testString Index 1 1 Type Mid HPF	SA"testString">1>2=20000\x0D
Crossover Frequency 20000 Name testString Index 1 1 Type Mid LPF	SA"testString">1>4=20000\x0D
Crossover Frequency 20000 Name testString Index 1 4 Type Low/High	SA"testString">4>2=20000\x0D
Crossover Frequency 20000 Name testString Index 1 4 Type Mid HPF	SA"testString">4>2=20000\x0D
Crossover Frequency 20000 Name testString Index 1 4 Type Mid LPF	SA"testString">4>4=20000\x0D
Crossover Mute Off Name testString Index 1 1 Type Low/High	SA"testString">1>5=F\x0D
Crossover Mute Off Name testString Index 1 1 Type Mid	SA"testString">1>7=F\x0D
Crossover Mute Off Name testString Index 1 4 Type Low/High	SA"testString">4>5=F\x0D
Crossover Mute Off Name testString Index 1 4 Type Mid	SA"testString">4>7=F\x0D
Crossover Mute On Name testString Index 1 1 Type Low/High	SA"testString">1>5=0\x0D
Crossover Mute On Name testString Index 1 1 Type Mid	SA"testString">1>7=0\x0D
Crossover Mute On Name testString Index 1 4 Type Low/High	SA"testString">4>5=0\x0D
Crossover Mute On Name testString Index 1 4 Type Mid	SA"testString">4>7=0\x0D
Crossover Polarity Off Name testString Index 1 1 Type Low/High	SA"testString">1>4=F\x0D
Crossover Polarity Off Name testString Index 1 1 Type Mid	SA"testString">1>6=F\x0D
Crossover Polarity Off Name testString Index 1 4 Type Low/High	SA"testString">4>4=F\x0D
Crossover Polarity Off Name testString Index 1 4 Type Mid	SA"testString">4>6=F\x0D
Crossover Polarity On Name testString Index 1 1 Type Low/High	SA"testString">1>4=0\x0D
Crossover Polarity On Name testString Index 1 1 Type Mid	SA"testString">1>6=0\x0D
Crossover Polarity On Name testString Index 1 4 Type Low/High	SA"testString">4>4=0\x0D
Crossover Polarity On Name testString Index 1 4 Type Mid	SA"testString">4>6=0\x0D
CRR Advanced Level 0 Name testString Input 1 Output 1	SA"testString">6>(1,1)=0.0\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

CRR Advanced Level 0 Name testString Input 1 Output 51	SA"testString">6>(1,51)=0.0\x0D
CRR Advanced Level 0 Name testString Input 51 Output 1	SA"testString">6>(51,1)=0.0\x0D
CRR Advanced Level 0 Name testString Input 51 Output 51	SA"testString">6>(51,51)=0.0\x0D
CRR Advanced Level -60 Name testString Input 1 Output 1	SA"testString">6>(1,1)=-60.0\x0D
CRR Advanced Level -60 Name testString Input 1 Output 51	SA"testString">6>(1,51)=-60.0\x0D
CRR Advanced Level -60 Name testString Input 51 Output 1	SA"testString">6>(51,1)=-60.0\x0D
CRR Advanced Level -60 Name testString Input 51 Output 51	SA"testString">6>(51,51)=-60.0\x0D
CRR Advanced State Off Name testString Input 1 Output 1	SA"testString">5>(1,1)=F\x0D
CRR Advanced State Off Name testString Input 1 Output 51	SA"testString">5>(1,51)=F\x0D
CRR Advanced State Off Name testString Input 51 Output 1	SA"testString">5>(51,1)=F\x0D
CRR Advanced State Off Name testString Input 51 Output 51	SA"testString">5>(51,51)=F\x0D
CRR Advanced State On Name testString Input 1 Output 1	SA"testString">5>(1,1)=0\x0D
CRR Advanced State On Name testString Input 1 Output 51	SA"testString">5>(1,51)=0\x0D
CRR Advanced State On Name testString Input 51 Output 1	SA"testString">5>(51,1)=0\x0D
CRR Advanced State On Name testString Input 51 Output 51	SA"testString">5>(51,51)=0\x0D
Delay Bypass Off Name testString Output 1	SA"testString">1>2=F\x0D
Delay Bypass Off Name testString Output 8	SA"testString">8>2=F\x0D
Delay Bypass On Name testString Output 1	SA"testString">1>2=0\x0D
Delay Bypass On Name testString Output 8	SA"testString">8>2=0\x0D
Delay Time 0 Name testString Output 1	SA"testString">1>1=0\x0D
Delay Time 0 Name testString Output 8	SA"testString">8>1=0\x0D
Delay Time 48000 Name testString Output 1	SA"testString">1>1=48000\x0D
Delay Time 48000 Name testString Output 8	SA"testString">8>1=48000\x0D
Ducker Decay 5 Name testString	SA"testString">6=5\x0D
Ducker Decay 50000 Name testString	SA"testString">6=50000\x0D
Ducker Hold 0 Name testString	SA"testString">5=0\x0D
Ducker Hold 1000 Name testString	SA"testString">5=1000\x0D
Ducker Range 0 Name testString	SA"testString">3=0.0\x0D
Ducker Range -60 Name testString	SA"testString">3=-60.0\x0D
Gain 12 Name testString	SA"testString">1=12.0\x0D
Gain -60 Name testString	SA"testString">1=-60.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Gain Mute Off Name testString	SA"testString">2=F\x0D
Gain Mute On Name testString	SA"testString">2=0\x0D
Gate Decay 5 Name testString	SA"testString">6=5\x0D
Gate Decay 50000 Name testString	SA"testString">6=50000\x0D
Gate Detector Left Name testString	SA"testString">1=L\x0D
Gate Detector Mix Name testString	SA"testString">1=M\x0D
Gate Detector Right Name testString	SA"testString">1=R\x0D
Gate Detector Sidechain Name testString	SA"testString">1=S\x0D
Gate Hold 0 Name testString	SA"testString">5=0\x0D
Gate Hold 1000 Name testString	SA"testString">5=1000\x0D
Gate Range 0 Name testString	SA"testString">3=0.0\x0D
Gate Range -70 Name testString	SA"testString">3=-70.0\x0D
GPO Mode Off Name testString Pin 1	SA"testString">1=F\x0D
GPO Mode Off Name testString Pin 5	SA"testString">5=F\x0D
GPO Mode On Name testString Pin 1	SA"testString">1=0\x0D
GPO Mode On Name testString Pin 5	SA"testString">5=0\x0D
Graphic EQ Level 15 Name testString Frequency 1.25kHz	SA"testString">19=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1.25kHz	SA"testString">19=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 1.6kHz	SA"testString">20=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1.6kHz	SA"testString">20=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 100Hz	SA"testString">8=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 100Hz	SA"testString">8=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 10kHz	SA"testString">28=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 10kHz	SA"testString">28=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 12.5kHz	SA"testString">29=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 12.5kHz	SA"testString">29=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 125Hz	SA"testString">9=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 125Hz	SA"testString">9=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 160Hz	SA"testString">10=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 160Hz	SA"testString">10=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 16kHz	SA"testString">30=15.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Graphic EQ Level -15 Name testString Frequency 16kHz	SA"testString">30=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 1kHz	SA"testString">18=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1kHz	SA"testString">18=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 2.5kHz	SA"testString">22=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 2.5kHz	SA"testString">22=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 200Hz	SA"testString">11=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 200Hz	SA"testString">11=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 20Hz	SA"testString">1=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 20Hz	SA"testString">1=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 20kHz	SA"testString">31=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 20kHz	SA"testString">31=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 250Hz	SA"testString">12=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 250Hz	SA"testString">12=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 25Hz	SA"testString">2=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 25Hz	SA"testString">2=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 2kHz	SA"testString">21=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 2kHz	SA"testString">21=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 3.15kHz	SA"testString">23=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 3.15kHz	SA"testString">23=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 31.5Hz	SA"testString">3=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 31.5Hz	SA"testString">3=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 315Hz	SA"testString">13=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 315Hz	SA"testString">13=-15.0\x0D

Global Scriptor Module Communication Sheet

Graphic EQ Level 15 Name testString Frequency 400Hz	SA"testString">14=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 400Hz	SA"testString">14=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 40Hz	SA"testString">4=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 40Hz	SA"testString">4=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 4kHz	SA"testString">24=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 4kHz	SA"testString">24=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 500Hz	SA"testString">15=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 500Hz	SA"testString">15=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 50Hz	SA"testString">5=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 50Hz	SA"testString">5=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 5kHz	SA"testString">25=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 5kHz	SA"testString">25=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 6.3kHz	SA"testString">26=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 6.3kHz	SA"testString">26=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 630Hz	SA"testString">16=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 630Hz	SA"testString">16=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 63Hz	SA"testString">6=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 63Hz	SA"testString">6=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 800Hz	SA"testString">17=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 800Hz	SA"testString">17=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 80Hz	SA"testString">7=15.0\X0D
Graphic EQ Level -15 Name testString Frequency 80Hz	SA"testString">7=-15.0\X0D
Graphic EQ Level 15 Name testString Frequency 8kHz	SA"testString">27=15.0\X0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Graphic EQ Level -15 Name testString Frequency 8kHz	SA"testString">27=-15.0\x0D
Group Level 12 Group 1	SG 1,90\x0D
Group Level 12 Group 64	SG 40,90\x0D
Group Level -60 Group 1	SG 1,0\x0D
Group Level -60 Group 64	SG 40,0\x0D
Group Mute Off Group 1	SN 1,U\x0D
Group Mute Off Group 64	SN 40,U\x0D
Group Mute On Group 1	SN 1,M\x0D
Group Mute On Group 64	SN 40,M\x0D
Matrix Mixer Level 0 Name testString Input 1 Output 1 Matrix Size 1	SA"testString">2>1=0.0\x0D
Matrix Mixer Level 0 Name testString Input 1 Output 1 Matrix Size 32	SA"testString">2>1=0.0\x0D
Matrix Mixer Level 0 Name testString Input 1 Output 32 Matrix Size 1	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Name testString Input 1 Output 32 Matrix Size 32	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Name testString Input 32 Output 1 Matrix Size 1	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Name testString Input 32 Output 1 Matrix Size 32	SA"testString">2>993=0.0\x0D
Matrix Mixer Level 0 Name testString Input 32 Output 32 Matrix Size 1	SA"testString">2>63=0.0\x0D
Matrix Mixer Level 0 Name testString Input 32 Output 32 Matrix Size 32	SA"testString">2>1024=0.0\x0D
Matrix Mixer Level -60 Name testString Input 1 Output 1 Matrix Size 1	SA"testString">2>1=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 1 Output 1 Matrix Size 32	SA"testString">2>1=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 1 Output 32 Matrix Size 1	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 1 Output 32 Matrix Size 32	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 32 Output 1 Matrix Size 1	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 32 Output 1 Matrix Size 32	SA"testString">2>993=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 32 Output 32 Matrix Size 1	SA"testString">2>63=-60.0\x0D
Matrix Mixer Level -60 Name testString Input 32 Output 32 Matrix Size 32	SA"testString">2>1024=-60.0\x0D
Matrix Mixer State Off Name testString Input 1 Output 1 Matrix Size 1	SA"testString">1>1=F\x0D
Matrix Mixer State Off Name testString Input 1 Output 1 Matrix Size 32	SA"testString">1>1=F\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Matrix Mixer State Off Name testString Input 1 Output 32 Matrix Size 1	SA"testString">1>32=F\x0D
Matrix Mixer State Off Name testString Input 1 Output 32 Matrix Size 32	SA"testString">1>32=F\x0D
Matrix Mixer State Off Name testString Input 32 Output 1 Matrix Size 1	SA"testString">1>32=F\x0D
Matrix Mixer State Off Name testString Input 32 Output 1 Matrix Size 32	SA"testString">1>993=F\x0D
Matrix Mixer State Off Name testString Input 32 Output 32 Matrix Size 1	SA"testString">1>63=F\x0D
Matrix Mixer State Off Name testString Input 32 Output 32 Matrix Size 32	SA"testString">1>1024=F\x0D
Matrix Mixer State On Name testString Input 1 Output 1 Matrix Size 1	SA"testString">1>1=0\x0D
Matrix Mixer State On Name testString Input 1 Output 1 Matrix Size 32	SA"testString">1>1=0\x0D
Matrix Mixer State On Name testString Input 1 Output 32 Matrix Size 1	SA"testString">1>32=0\x0D
Matrix Mixer State On Name testString Input 1 Output 32 Matrix Size 32	SA"testString">1>32=0\x0D
Matrix Mixer State On Name testString Input 32 Output 1 Matrix Size 1	SA"testString">1>32=0\x0D
Matrix Mixer State On Name testString Input 32 Output 1 Matrix Size 32	SA"testString">1>993=0\x0D
Matrix Mixer State On Name testString Input 32 Output 32 Matrix Size 1	SA"testString">1>63=0\x0D
Matrix Mixer State On Name testString Input 32 Output 32 Matrix Size 32	SA"testString">1>1024=0\x0D
Parameter Recall 1	SS 1\x0D
Parameter Recall 255	SS ff\x0D
Parametric EQ Frequency 20 Name testString Band 1	SA"testString">1>1=20\x0D
Parametric EQ Frequency 20 Name testString Band 16	SA"testString">16>1=20\x0D
Parametric EQ Frequency 20000 Name testString Band 1	SA"testString">1>1=20000\x0D
Parametric EQ Frequency 20000 Name testString Band 16	SA"testString">16>1=20000\x0D
Parametric EQ Gain 20 Name testString Band 1	SA"testString">1>3=20.0\x0D
Parametric EQ Gain -20 Name testString Band 1	SA"testString">1>3=-20.0\x0D
Parametric EQ Gain 20 Name testString Band 16	SA"testString">16>3=20.0\x0D
Parametric EQ Gain -20 Name testString Band 16	SA"testString">16>3=-20.0\x0D
Parametric EQ Q 0 Name testString Band 1	SA"testString">1>2=0.000\x0D
Parametric EQ Q 0 Name testString Band 16	SA"testString">16>2=0.000\x0D
Parametric EQ Q 14 Name testString Band 1	SA"testString">1>2=14.000\x0D
Parametric EQ Q 14 Name testString Band 16	SA"testString">16>2=14.000\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Parametric EQ Slope -12 Name testString Band 1	SA"testString">1>4=-12\x0D
Parametric EQ Slope -12 Name testString Band 16	SA"testString">16>4=-12\x0D
Parametric EQ Slope -6 Name testString Band 1	SA"testString">1>4=-6\x0D
Parametric EQ Slope -6 Name testString Band 16	SA"testString">16>4=-6\x0D
Parametric EQ Type High Pass Name testString Band 1	SA"testString">1>5=LC\x0D
Parametric EQ Type High Pass Name testString Band 16	SA"testString">16>5=LC\x0D
Parametric EQ Type High Shelf Name testString Band 1	SA"testString">1>5=HS\x0D
Parametric EQ Type High Shelf Name testString Band 16	SA"testString">16>5=HS\x0D
Parametric EQ Type Low Pass Name testString Band 1	SA"testString">1>5=HC\x0D
Parametric EQ Type Low Pass Name testString Band 16	SA"testString">16>5=HC\x0D
Parametric EQ Type Low Shelf Name testString Band 1	SA"testString">1>5=LS\x0D
Parametric EQ Type Low Shelf Name testString Band 16	SA"testString">16>5=LS\x0D
Parametric EQ Type Notch Name testString Band 1	SA"testString">1>5=N\x0D
Parametric EQ Type Notch Name testString Band 16	SA"testString">16>5=N\x0D
Parametric EQ Type PEQ Name testString Band 1	SA"testString">1>5=B\x0D
Parametric EQ Type PEQ Name testString Band 16	SA"testString">16>5=B\x0D
Peak/RMS Input Detect Left Name testString	SA"testString">1=L\x0D
Peak/RMS Input Detect Mix Name testString	SA"testString">1=M\x0D
Peak/RMS Input Detect Right Name testString	SA"testString">1=R\x0D
Peak/RMS Input Detect Sidechain Name testString	SA"testString">1=S\x0D
Peak/RMS RMS 10000 Name testString Function Attack	SA"testString">8=10000\x0D
Peak/RMS RMS 10000 Name testString Function Release	SA"testString">9=10000\x0D
Peak/RMS RMS 500 Name testString Function Attack	SA"testString">8=500\x0D
Peak/RMS RMS 500 Name testString Function Release	SA"testString">9=500\x0D
PSTN Action Answer Call Name testString	MA"testString">4\x0D
PSTN Action End Call Name testString	MA"testString">3\x0D
PSTN Action Make Call Name testString	MA"testString">2="TEST"\x0D
PSTN Dial Key ! Name testString	MA"testString">1="!"\x0D
PSTN Dial Key # Name testString	MA"testString">1="#"\x0D
PSTN Dial Key * Name testString	MA"testString">1="*\x0D
PSTN Dial Key 0 Name testString	MA"testString">1="0"\x0D
PSTN Dial Key 9 Name testString	MA"testString">1="9"\x0D
PSTN Hook Off Name testString	SA"testString">0>9=F\x0D
PSTN Hook On Name testString	SA"testString">0>9=O\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

PSTN Level 12 Module Input Name testString	SA"testString">1>1=12.0\x0D
PSTN Level 12 Module Output Name testString	SA"testString">1=12.0\x0D
PSTN Level -60 Module Input Name testString	SA"testString">1>1=-60.0\x0D
PSTN Level -60 Module Output Name testString	SA"testString">1=-60.0\x0D
PSTN Mute Off Module Input Name testString	SA"testString">1>2=F\x0D
PSTN Mute Off Module Output Name testString	SA"testString">2=F\x0D
PSTN Mute On Module Input Name testString	SA"testString">1>2=0\x0D
PSTN Mute On Module Output Name testString	SA"testString">2=0\x0D
Router Input Select 0 Name testString Output 1	SA"testString">1=0\x0D
Router Input Select 0 Name testString Output 32	SA"testString">32=0\x0D
Router Input Select 32 Name testString Output 1	SA"testString">1=32\x0D
Router Input Select 32 Name testString Output 32	SA"testString">32=32\x0D
Signal Generator Gain 12 Name testString Wave Pink	SA"testString">3>1=12.0\x0D
Signal Generator Gain 12 Name testString Wave Sine	SA"testString">1>2=12.0\x0D
Signal Generator Gain 12 Name testString Wave Sweep	SA"testString">4>1=12.0\x0D
Signal Generator Gain 12 Name testString Wave White	SA"testString">2>1=12.0\x0D
Signal Generator Gain -60 Name testString Wave Pink	SA"testString">3>1=-60.0\x0D
Signal Generator Gain -60 Name testString Wave Sine	SA"testString">1>2=-60.0\x0D
Signal Generator Gain -60 Name testString Wave Sweep	SA"testString">4>1=-60.0\x0D
Signal Generator Gain -60 Name testString Wave White	SA"testString">2>1=-60.0\x0D
Signal Generator Mute Off Name testString Wave Pink	SA"testString">3>2=F\x0D
Signal Generator Mute Off Name testString Wave Sine	SA"testString">1>3=F\x0D
Signal Generator Mute Off Name testString Wave White	SA"testString">2>2=F\x0D
Signal Generator Mute On Name testString Wave Pink	SA"testString">3>2=0\x0D
Signal Generator Mute On Name testString Wave Sine	SA"testString">1>3=0\x0D
Signal Generator Mute On Name testString Wave White	SA"testString">2>2=0\x0D
Source Select 1 Name testString	SA"testString">1=1\x0D
Source Select 32 Name testString	SA"testString">1=32\x0D
Speaker Parametric Align Delay 0 Name testString	SA"testString">0>4=0\x0D
Speaker Parametric Align Delay 480 Name testString	SA"testString">0>4=480\x0D

Global Scripter Module Communication Sheet

Speaker Parametric Bypass Off Name testString Type High	SA"testString">0>10=F\x0D
Speaker Parametric Bypass Off Name testString Type Low	SA"testString">0>9=F\x0D
Speaker Parametric Bypass On Name testString Type High	SA"testString">0>10=0\x0D
Speaker Parametric Bypass On Name testString Type Low	SA"testString">0>9=0\x0D
Speaker Parametric EQ Band Bypass Off Name testString Index 1 1	SA"testString">1>6=F\x0D
Speaker Parametric EQ Band Bypass Off Name testString Index 1 9	SA"testString">9>6=F\x0D
Speaker Parametric EQ Band Bypass On Name testString Index 1 1	SA"testString">1>6=0\x0D
Speaker Parametric EQ Band Bypass On Name testString Index 1 9	SA"testString">9>6=0\x0D
Speaker Parametric EQ Band Filter High Shelf Name testString Index 1 1	SA"testString">1>5=HS\x0D
Speaker Parametric EQ Band Filter High Shelf Name testString Index 1 9	SA"testString">9>5=HS\x0D
Speaker Parametric EQ Band Filter Low Shelf Name testString Index 1 1	SA"testString">1>5=LS\x0D
Speaker Parametric EQ Band Filter Low Shelf Name testString Index 1 9	SA"testString">9>5=LS\x0D
Speaker Parametric EQ Band Filter Notch Name testString Index 1 1	SA"testString">1>5=N\x0D
Speaker Parametric EQ Band Filter Notch Name testString Index 1 9	SA"testString">9>5=N\x0D
Speaker Parametric EQ Band Filter PEQ Name testString Index 1 1	SA"testString">1>5=B\x0D
Speaker Parametric EQ Band Filter PEQ Name testString Index 1 9	SA"testString">9>5=B\x0D
Speaker Parametric EQ Band Frequency 20 Name testString Index 1 1	SA"testString">1>1=20\x0D
Speaker Parametric EQ Band Frequency 20 Name testString Index 1 9	SA"testString">9>1=20\x0D
Speaker Parametric EQ Band Frequency 20000 Name testString Index 1 1	SA"testString">1>1=20000\x0D
Speaker Parametric EQ Band Frequency 20000 Name testString Index 1 9	SA"testString">9>1=20000\x0D
Speaker Parametric EQ Band Gain 20 Name testString Index 1 1	SA"testString">1>3=20.0\x0D
Speaker Parametric EQ Band Gain -20 Name testString Index 1 1	SA"testString">1>3=-20.0\x0D
Speaker Parametric EQ Band Gain 20 Name testString Index 1 9	SA"testString">9>3=20.0\x0D

Global Scripter Module Communication Sheet

Speaker Parametric EQ Band Gain -20 Name testString Index 1 9	SA"testString">9>3=-20.0\x0D
Speaker Parametric EQ Band Q 0 Name testString Index 1 1	SA"testString">1>2=0.000\x0D
Speaker Parametric EQ Band Q 0 Name testString Index 1 9	SA"testString">9>2=0.000\x0D
Speaker Parametric EQ Band Q 10 Name testString Index 1 1	SA"testString">1>2=10.000\x0D
Speaker Parametric EQ Band Q 10 Name testString Index 1 9	SA"testString">9>2=10.000\x0D
Speaker Parametric Filter Bessel 12dB/oct Name testString Type High	SA"testString">0>5=Bes12\x0D
Speaker Parametric Filter Bessel 12dB/oct Name testString Type Low	SA"testString">0>7=Bes12\x0D
Speaker Parametric Filter Bessel 18dB/oct Name testString Type High	SA"testString">0>5=Bes18\x0D
Speaker Parametric Filter Bessel 18dB/oct Name testString Type Low	SA"testString">0>7=Bes18\x0D
Speaker Parametric Filter Bessel 24dB/oct Name testString Type High	SA"testString">0>5=Bes24\x0D
Speaker Parametric Filter Bessel 24dB/oct Name testString Type Low	SA"testString">0>7=Bes24\x0D
Speaker Parametric Filter Bessel 36dB/oct Name testString Type High	SA"testString">0>5=Bes36\x0D
Speaker Parametric Filter Bessel 36dB/oct Name testString Type Low	SA"testString">0>7=Bes36\x0D
Speaker Parametric Filter Bessel 48dB/oct Name testString Type High	SA"testString">0>5=Bes48\x0D
Speaker Parametric Filter Bessel 48dB/oct Name testString Type Low	SA"testString">0>7=Bes48\x0D
Speaker Parametric Filter Butterworth 12dB/oct Name testString Type High	SA"testString">0>5=But12\x0D
Speaker Parametric Filter Butterworth 12dB/oct Name testString Type Low	SA"testString">0>7=But12\x0D
Speaker Parametric Filter Butterworth 18dB/oct Name testString Type High	SA"testString">0>5=But18\x0D
Speaker Parametric Filter Butterworth 18dB/oct Name testString Type Low	SA"testString">0>7=But18\x0D
Speaker Parametric Filter Butterworth 24dB/oct Name testString Type High	SA"testString">0>5=But24\x0D
Speaker Parametric Filter Butterworth 24dB/oct Name testString Type Low	SA"testString">0>7=But24\x0D
Speaker Parametric Filter Butterworth 36dB/oct Name testString Type High	SA"testString">0>5=But36\x0D
Speaker Parametric Filter Butterworth 36dB/oct Name testString Type Low	SA"testString">0>7=But36\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Speaker Parametric Filter Butterworth 48dB/oct Name testString Type High	SA"testString">0>5=But48\x0D
Speaker Parametric Filter Butterworth 48dB/oct Name testString Type Low	SA"testString">0>7=But48\x0D
Speaker Parametric Filter Butterworth 6dB/oct Name testString Type High	SA"testString">0>5=But6\x0D
Speaker Parametric Filter Butterworth 6dB/oct Name testString Type Low	SA"testString">0>7=But6\x0D
Speaker Parametric Filter Linkwitz-Reily 12dB/oct Name testString Type High	SA"testString">0>5=Lin12\x0D
Speaker Parametric Filter Linkwitz-Reily 12dB/oct Name testString Type Low	SA"testString">0>7=Lin12\x0D
Speaker Parametric Filter Linkwitz-Reily 24dB/oct Name testString Type High	SA"testString">0>5=Lin24\x0D
Speaker Parametric Filter Linkwitz-Reily 24dB/oct Name testString Type Low	SA"testString">0>7=Lin24\x0D
Speaker Parametric Filter Linkwitz-Reily 36dB/oct Name testString Type High	SA"testString">0>5=Lin36\x0D
Speaker Parametric Filter Linkwitz-Reily 36dB/oct Name testString Type Low	SA"testString">0>7=Lin36\x0D
Speaker Parametric Filter Linkwitz-Reily 48dB/oct Name testString Type High	SA"testString">0>5=Lin48\x0D
Speaker Parametric Filter Linkwitz-Reily 48dB/oct Name testString Type Low	SA"testString">0>7=Lin48\x0D
Speaker Parametric Frequency 20 Name testString Type High	SA"testString">0>6=20\x0D
Speaker Parametric Frequency 20 Name testString Type Low	SA"testString">0>8=20\x0D
Speaker Parametric Frequency 20000 Name testString Type High	SA"testString">0>6=20000\x0D
Speaker Parametric Frequency 20000 Name testString Type Low	SA"testString">0>8=20000\x0D
Speaker Parametric Gain 15 Name testString	SA"testString">0>3=15.0\x0D
Speaker Parametric Gain -15 Name testString	SA"testString">0>3=-15.0\x0D
Standard Mixer Level 12 Name testString Index 1 Input Index 2 1	SA"testString">1>1=12.0\x0D
Standard Mixer Level 12 Name testString Index 1 Input Index 2 32	SA"testString">1>63=12.0\x0D
Standard Mixer Level 12 Name testString Index 1 Output Index 2 1	SA"testString">2>1=12.0\x0D
Standard Mixer Level 12 Name testString Index 1 Output Index 2 32	SA"testString">2>63=12.0\x0D
Standard Mixer Level -60 Name testString Index 1 Input Index 2 1	SA"testString">1>1=-60.0\x0D
Standard Mixer Level -60 Name testString Index 1 Input Index 2 32	SA"testString">1>63=-60.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Standard Mixer Level -60 Name testString Index 1 Output Index 2 1	SA"testString">2>1=-60.0\x0D
Standard Mixer Level -60 Name testString Index 1 Output Index 2 32	SA"testString">2>63=-60.0\x0D
Standard Mixer Mute Off Name testString Index 1 Input Index 2 1	SA"testString">1>2=F\x0D
Standard Mixer Mute Off Name testString Index 1 Input Index 2 32	SA"testString">1>64=F\x0D
Standard Mixer Mute Off Name testString Index 1 Output Index 2 1	SA"testString">2>2=F\x0D
Standard Mixer Mute Off Name testString Index 1 Output Index 2 32	SA"testString">2>64=F\x0D
Standard Mixer Mute On Name testString Index 1 Input Index 2 1	SA"testString">1>2=0\x0D
Standard Mixer Mute On Name testString Index 1 Input Index 2 32	SA"testString">1>64=0\x0D
Standard Mixer Mute On Name testString Index 1 Output Index 2 1	SA"testString">2>2=0\x0D
Standard Mixer Mute On Name testString Index 1 Output Index 2 32	SA"testString">2>64=0\x0D
Standard Mixer Routing Route Name testString Input 1 Output 1	SA"testString">4>(1,1)=0\x0D
Standard Mixer Routing Route Name testString Input 1 Output 32	SA"testString">4>(1,32)=0\x0D
Standard Mixer Routing Route Name testString Input 32 Output 1	SA"testString">4>(32,1)=0\x0D
Standard Mixer Routing Route Name testString Input 32 Output 32	SA"testString">4>(32,32)=0\x0D
Standard Mixer Routing Unroute Name testString Input 1 Output 1	SA"testString">4>(1,1)=F\x0D
Standard Mixer Routing Unroute Name testString Input 1 Output 32	SA"testString">4>(1,32)=F\x0D
Standard Mixer Routing Unroute Name testString Input 32 Output 1	SA"testString">4>(32,1)=F\x0D
Standard Mixer Routing Unroute Name testString Input 32 Output 32	SA"testString">4>(32,32)=F\x0D
Tone Control Gain 15 Name testString Type High	SA"testString">5=15.0\x0D
Tone Control Gain -15 Name testString Type High	SA"testString">5=-15.0\x0D
Tone Control Gain 15 Name testString Type Low	SA"testString">1=15.0\x0D
Tone Control Gain -15 Name testString Type Low	SA"testString">1=-15.0\x0D
Tone Control Gain 15 Name testString Type Mid	SA"testString">3=15.0\x0D
Tone Control Gain -15 Name testString Type Mid	SA"testString">3=-15.0\x0D
USB Level 12 Name testString Channel Left	SA"testString">1>1=12.0\x0D
USB Level 12 Name testString Channel Right	SA"testString">2>1=12.0\x0D
USB Level -60 Name testString Channel Left	SA"testString">1>1=-60.0\x0D
USB Level -60 Name testString Channel Right	SA"testString">2>1=-60.0\x0D

Global Scriptor Module Communication Sheet

USB Mute Off Name testString Channel Left	SA"testString">1>2=F\x0D
USB Mute Off Name testString Channel Right	SA"testString">2>2=F\x0D
USB Mute On Name testString Channel Left	SA"testString">1>2=0\x0D
USB Mute On Name testString Channel Right	SA"testString">2>2=0\x0D
VoIP Action Answer Call Name testString	MA"testString">4\x0D
VoIP Action End Call Name testString	MA"testString">3\x0D
VoIP Action Make Call Name testString	MA"testString">2="TEST"\x0D
VoIP Action Transfer Call Name testString	MA"testString">5="TEST"\x0D
VoIP Dial Key # Name testString	MA"testString">1=#\x0D
VoIP Dial Key * Name testString	MA"testString">1=*\x0D
VoIP Dial Key 0 Name testString	MA"testString">1=0\x0D
VoIP Dial Key 9 Name testString	MA"testString">1=9\x0D
VoIP Level 12 Name testString	SA"testString">1>1=12.0\x0D
VoIP Level -60 Name testString	SA"testString">1>1=-60.0\x0D
VoIP Mute Off Name testString	SA"testString">1>2=F\x0D
VoIP Mute On Name testString	SA"testString">1>2=0\x0D

Appendix B. Update Commands

AEC CN Enable Name testString Index 1 1	GA"testString">1>8\x0D
AEC CN Enable Name testString Index 1 8	GA"testString">8>8\x0D
AEC Enable Name testString Index 1 1	GA"testString">1>6\x0D
AEC Enable Name testString Index 1 8	GA"testString">8>6\x0D
AEC Internal Mute Name testString Index 1 1	GA"testString">1>5\x0D
AEC Internal Mute Name testString Index 1 8	GA"testString">8>5\x0D
AEC NLP Control Name testString Index 1 1	GA"testString">1>7\x0D
AEC NLP Control Name testString Index 1 8	GA"testString">8>7\x0D
AMM Gain Sharing Attack Name testString	GA"testString">0>4\x0D
AMM Gain Sharing Bypass Name testString Index 1 1	GA"testString">1>4\x0D
AMM Gain Sharing Bypass Name testString Index 1 32	GA"testString">32>4\x0D
AMM Gain Sharing Decay Name testString	GA"testString">0>6\x0D
AMM Gain Sharing Gain Name testString Index 1 0	GA"testString">0>1\x0D
AMM Gain Sharing Gain Name testString Index 1 32	GA"testString">32>1\x0D
AMM Gain Sharing Hold Name testString	GA"testString">0>5\x0D
AMM Gain Sharing Mute Name testString Index 1 0	GA"testString">0>2\x0D
AMM Gain Sharing Mute Name testString Index 1 32	GA"testString">32>2\x0D
AMM Gain Sharing Priority Name testString Index 1 1	GA"testString">1>3\x0D
AMM Gain Sharing Priority Name testString Index 1 32	GA"testString">32>3\x0D
AMM Gain Sharing RMS Average Name testString Type Input	GA"testString">0>7\x0D
AMM Gain Sharing RMS Average Name testString Type Output	GA"testString">0>8\x0D
AMM Gain Sharing Slope Name testString	GA"testString">0>3\x0D
AMM Gated Attack Name testString Index 1 1	GA"testString">1>14\x0D
AMM Gated Attack Name testString Index 1 32	GA"testString">32>14\x0D
AMM Gated Decay Name testString Index 1 1	GA"testString">1>16\x0D
AMM Gated Decay Name testString Index 1 32	GA"testString">32>16\x0D
AMM Gated Ducking Depth Name testString Index 1 1	GA"testString">1>12\x0D
AMM Gated Ducking Depth Name testString Index 1 32	GA"testString">32>12\x0D
AMM Gated Gain Name testString Index 1 0	GA"testString">0>1\x0D
AMM Gated Gain Name testString Index 1 32	GA"testString">32>2\x0D
AMM Gated Gate Depth Name testString Index 1 1	GA"testString">1>13\x0D
AMM Gated Gate Depth Name testString Index 1 32	GA"testString">32>13\x0D
AMM Gated High Pass Name testString Index 1 1	GA"testString">1>10\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

AMM Gated High Pass Name testString Index 1 32	GA"testString">32>10\x0D
AMM Gated Hold Name testString Index 1 1	GA"testString">1>15\x0D
AMM Gated Hold Name testString Index 1 32	GA"testString">32>15\x0D
AMM Gated Low Pass Name testString Index 1 1	GA"testString">1>9\x0D
AMM Gated Low Pass Name testString Index 1 32	GA"testString">32>9\x0D
AMM Gated Mute Name testString Index 1 0	GA"testString">0>2\x0D
AMM Gated Mute Name testString Index 1 32	GA"testString">32>3\x0D
AMM Gated Priority Name testString Index 1 1	GA"testString">1>1\x0D
AMM Gated Priority Name testString Index 1 32	GA"testString">32>1\x0D
AMM Gated RMS Avg Name testString Index 1 1	GA"testString">1>11\x0D
AMM Gated RMS Avg Name testString Index 1 32	GA"testString">32>11\x0D
AMM Gated Threshold Name testString Index 1 1	GA"testString">1>5\x0D
AMM Gated Threshold Name testString Index 1 32	GA"testString">32>5\x0D
AMPLink Level Channel 1	GA"AMPLink-Ch 1">1\x0D
AMPLink Level Channel 4	GA"AMPLink-Ch 4">1\x0D
AMPLink Mute Channel 1	GA"AMPLink-Ch 1">2\x0D
AMPLink Mute Channel 4	GA"AMPLink-Ch 4">2\x0D
AMPLink Polarity Channel 1	GA"AMPLink-Ch 1">3\x0D
AMPLink Polarity Channel 4	GA"AMPLink-Ch 4">3\x0D
Array EQ Advanced Name testString	GA"testString">1>6\x0D
Array EQ Center Frequency Name testString	GA"testString">1>1\x0D
Array EQ Tilt Name testString	GA"testString">1>2\x0D
Array EQ Vertical Angle Name testString	GA"testString">1>8\x0D
Compressor/Limiter Input Detect Name testString	GA"testString">1\x0D
Compressor/Limiter Ratio Name testString	GA"testString">3\x0D
Compressor/Limiter Release Name testString	GA"testString">5\x0D
Crossover Filter Name testString Index 1 1 Type Low/High	GA"testString">1>1\x0D
Crossover Filter Name testString Index 1 1 Type Mid HPF	GA"testString">1>1\x0D
Crossover Filter Name testString Index 1 1 Type Mid LPF	GA"testString">1>3\x0D
Crossover Filter Name testString Index 1 4 Type Low/High	GA"testString">4>1\x0D
Crossover Filter Name testString Index 1 4 Type Mid HPF	GA"testString">4>1\x0D
Crossover Filter Name testString Index 1 4 Type Mid LPF	GA"testString">4>3\x0D
Crossover Frequency Name testString Index 1 1 Type Low/High	GA"testString">1>2\x0D
Crossover Frequency Name testString Index 1 1 Type Mid HPF	GA"testString">1>2\x0D
Crossover Frequency Name testString Index 1 1 Type Mid LPF	GA"testString">1>4\x0D

Global Scripter Module Communication Sheet

Revision: 6/9/2020

Crossover Frequency Name testString Index 1 4 Type Low/High	GA"testString">4>2\x0D
Crossover Frequency Name testString Index 1 4 Type Mid HPF	GA"testString">4>2\x0D
Crossover Frequency Name testString Index 1 4 Type Mid LPF	GA"testString">4>4\x0D
Crossover Mute Name testString Index 1 1 Type Low/High	GA"testString">1>5\x0D
Crossover Mute Name testString Index 1 1 Type Mid	GA"testString">1>7\x0D
Crossover Mute Name testString Index 1 4 Type Low/High	GA"testString">4>5\x0D
Crossover Mute Name testString Index 1 4 Type Mid	GA"testString">4>7\x0D
Crossover Polarity Name testString Index 1 1 Type Low/High	GA"testString">1>4\x0D
Crossover Polarity Name testString Index 1 1 Type Mid	GA"testString">1>6\x0D
Crossover Polarity Name testString Index 1 4 Type Low/High	GA"testString">4>4\x0D
Crossover Polarity Name testString Index 1 4 Type Mid	GA"testString">4>6\x0D
CRR Advanced Level Name testString Input 1 Output 1	GA"testString">6>(1,1)\x0D
CRR Advanced Level Name testString Input 1 Output 51	GA"testString">6>(1,51)\x0D
CRR Advanced Level Name testString Input 51 Output 1	GA"testString">6>(51,1)\x0D
CRR Advanced Level Name testString Input 51 Output 51	GA"testString">6>(51,51)\x0D
CRR Advanced State Name testString Input 1 Output 1	GA"testString">5>(1,1)\x0D
CRR Advanced State Name testString Input 1 Output 51	GA"testString">5>(1,51)\x0D
CRR Advanced State Name testString Input 51 Output 1	GA"testString">5>(51,1)\x0D
CRR Advanced State Name testString Input 51 Output 51	GA"testString">5>(51,51)\x0D
Delay Bypass Name testString Output 1	GA"testString">1>2\x0D
Delay Bypass Name testString Output 8	GA"testString">8>2\x0D
Delay Time Name testString Output 1	GA"testString">1>1\x0D
Delay Time Name testString Output 8	GA"testString">8>1\x0D
Ducker Decay Name testString	GA"testString">6\x0D
Ducker Hold Name testString	GA"testString">5\x0D
Ducker Range Name testString	GA"testString">3\x0D
Gain Mute Name testString	GA"testString">2\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Gain Name testString	GA"testString">1\x0D
Gate Decay Name testString	GA"testString">6\x0D
Gate Detector Name testString	GA"testString">1\x0D
Gate Hold Name testString	GA"testString">5\x0D
Gate Range Name testString	GA"testString">3\x0D
GPO Mode Name testString Pin 1	GA"testString">1\x0D
GPO Mode Name testString Pin 5	GA"testString">5\x0D
Graphic EQ Level Name testString Frequency 1.25kHz	GA"testString">19\x0D
Graphic EQ Level Name testString Frequency 1.6kHz	GA"testString">20\x0D
Graphic EQ Level Name testString Frequency 100Hz	GA"testString">8\x0D
Graphic EQ Level Name testString Frequency 10kHz	GA"testString">28\x0D
Graphic EQ Level Name testString Frequency 12.5kHz	GA"testString">29\x0D
Graphic EQ Level Name testString Frequency 125Hz	GA"testString">9\x0D
Graphic EQ Level Name testString Frequency 160Hz	GA"testString">10\x0D
Graphic EQ Level Name testString Frequency 16kHz	GA"testString">30\x0D
Graphic EQ Level Name testString Frequency 1kHz	GA"testString">18\x0D
Graphic EQ Level Name testString Frequency 2.5kHz	GA"testString">22\x0D
Graphic EQ Level Name testString Frequency 200Hz	GA"testString">11\x0D
Graphic EQ Level Name testString Frequency 20Hz	GA"testString">1\x0D
Graphic EQ Level Name testString Frequency 20kHz	GA"testString">31\x0D
Graphic EQ Level Name testString Frequency 250Hz	GA"testString">12\x0D
Graphic EQ Level Name testString Frequency 25Hz	GA"testString">2\x0D
Graphic EQ Level Name testString Frequency 2kHz	GA"testString">21\x0D
Graphic EQ Level Name testString Frequency 3.15kHz	GA"testString">23\x0D
Graphic EQ Level Name testString Frequency 31.5Hz	GA"testString">3\x0D
Graphic EQ Level Name testString Frequency 315Hz	GA"testString">13\x0D
Graphic EQ Level Name testString Frequency 400Hz	GA"testString">14\x0D
Graphic EQ Level Name testString Frequency 40Hz	GA"testString">4\x0D
Graphic EQ Level Name testString Frequency 4kHz	GA"testString">24\x0D
Graphic EQ Level Name testString Frequency 500Hz	GA"testString">15\x0D
Graphic EQ Level Name testString Frequency 50Hz	GA"testString">5\x0D
Graphic EQ Level Name testString Frequency 5kHz	GA"testString">25\x0D
Graphic EQ Level Name testString Frequency 6.3kHz	GA"testString">26\x0D
Graphic EQ Level Name testString Frequency 630Hz	GA"testString">16\x0D
Graphic EQ Level Name testString Frequency 63Hz	GA"testString">6\x0D
Graphic EQ Level Name testString Frequency 800Hz	GA"testString">17\x0D
Graphic EQ Level Name testString Frequency 80Hz	GA"testString">7\x0D
Graphic EQ Level Name testString Frequency 8kHz	GA"testString">27\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Group Level Group 1	GG 1\x0D
Group Level Group 64	GG 40\x0D
Group Mute Group 1	GN 1\x0D
Group Mute Group 64	GN 40\x0D
Matrix Mixer Level Name testString Input 1 Output 1 Matrix Size 1	GA"testString">2>1\x0D
Matrix Mixer Level Name testString Input 1 Output 1 Matrix Size 32	GA"testString">2>1\x0D
Matrix Mixer Level Name testString Input 1 Output 32 Matrix Size 1	GA"testString">2>32\x0D
Matrix Mixer Level Name testString Input 1 Output 32 Matrix Size 32	GA"testString">2>32\x0D
Matrix Mixer Level Name testString Input 32 Output 1 Matrix Size 1	GA"testString">2>32\x0D
Matrix Mixer Level Name testString Input 32 Output 1 Matrix Size 32	GA"testString">2>993\x0D
Matrix Mixer Level Name testString Input 32 Output 32 Matrix Size 1	GA"testString">2>63\x0D
Matrix Mixer Level Name testString Input 32 Output 32 Matrix Size 32	GA"testString">2>1024\x0D
Matrix Mixer State Name testString Input 1 Output 1 Matrix Size 1	GA"testString">1>1\x0D
Matrix Mixer State Name testString Input 1 Output 1 Matrix Size 32	GA"testString">1>1\x0D
Matrix Mixer State Name testString Input 1 Output 32 Matrix Size 1	GA"testString">1>32\x0D
Matrix Mixer State Name testString Input 1 Output 32 Matrix Size 32	GA"testString">1>32\x0D
Matrix Mixer State Name testString Input 32 Output 1 Matrix Size 1	GA"testString">1>32\x0D
Matrix Mixer State Name testString Input 32 Output 1 Matrix Size 32	GA"testString">1>993\x0D
Matrix Mixer State Name testString Input 32 Output 32 Matrix Size 1	GA"testString">1>63\x0D
Matrix Mixer State Name testString Input 32 Output 32 Matrix Size 32	GA"testString">1>1024\x0D
Parameter Recall	GS\x0D
Parametric EQ Frequency Name testString Band 1	GA"testString">1>1\x0D
Parametric EQ Frequency Name testString Band 16	GA"testString">16>1\x0D
Parametric EQ Gain Name testString Band 1	GA"testString">1>3\x0D
Parametric EQ Gain Name testString Band 16	GA"testString">16>3\x0D
Parametric EQ Q Name testString Band 1	GA"testString">1>2\x0D
Parametric EQ Q Name testString Band 16	GA"testString">16>2\x0D
Parametric EQ Slope Name testString Band 1	GA"testString">1>4\x0D
Parametric EQ Slope Name testString Band 16	GA"testString">16>4\x0D
Parametric EQ Type Name testString Band 1	GA"testString">1>5\x0D

Global Scriptor Module Communication Sheet

Revision: 6/9/2020

Parametric EQ Type Name testString Band 16	GA"testString">16>5\x0D
Peak/RMS Input Detect Name testString	GA"testString">1\x0D
Peak/RMS RMS Name testString Function Attack	GA"testString">8\x0D
Peak/RMS RMS Name testString Function Release	GA"testString">9\x0D
PSTN Call Active Name testString	GA"testString">0>8\x0D
PSTN Call Status Name testString	GA"testString">0>1\x0D
PSTN Caller ID Name testString Type Date	GA"testString">0>2\x0D
PSTN Caller ID Name testString Type Name	GA"testString">0>2\x0D
PSTN Caller ID Name testString Type Number	GA"testString">0>2\x0D
PSTN Caller ID Name testString Type Time	GA"testString">0>2\x0D
PSTN Hook Name testString	GA"testString">0>9\x0D
PSTN Level Module Input Name testString	GA"testString">1>1\x0D
PSTN Level Module Output Name testString	GA"testString">1\x0D
PSTN Mute Module Input Name testString	GA"testString">1>2\x0D
PSTN Mute Module Output Name testString	GA"testString">2\x0D
Router Input Select Name testString Output 1	GA"testString">1\x0D
Router Input Select Name testString Output 32	GA"testString">32\x0D
Signal Generator Gain Name testString Wave Pink	GA"testString">3>1\x0D
Signal Generator Gain Name testString Wave Sine	GA"testString">1>2\x0D
Signal Generator Gain Name testString Wave Sweep	GA"testString">4>1\x0D
Signal Generator Gain Name testString Wave White	GA"testString">2>1\x0D
Signal Generator Mute Name testString Wave Pink	GA"testString">3>2\x0D
Signal Generator Mute Name testString Wave Sine	GA"testString">1>3\x0D
Signal Generator Mute Name testString Wave White	GA"testString">2>2\x0D
Source Select Name testString	GA"testString">1\x0D
Speaker Parametric Align Delay Name testString	GA"testString">0>4\x0D
Speaker Parametric Bypass Name testString Type High	GA"testString">0>10\x0D
Speaker Parametric Bypass Name testString Type Low	GA"testString">0>9\x0D
Speaker Parametric EQ Band Bypass Name testString Index 1 1	GA"testString">1>6\x0D
Speaker Parametric EQ Band Bypass Name testString Index 1 9	GA"testString">9>6\x0D
Speaker Parametric EQ Band Filter Name testString Index 1 1	GA"testString">1>5\x0D
Speaker Parametric EQ Band Filter Name testString Index 1 9	GA"testString">9>5\x0D
Speaker Parametric EQ Band Frequency Name testString Index 1 1	GA"testString">1>1\x0D
Speaker Parametric EQ Band Frequency Name testString Index 1 9	GA"testString">9>1\x0D
Speaker Parametric EQ Band Gain Name testString Index 1 1	GA"testString">1>3\x0D

Global Scripter Module Communication Sheet

Speaker Parametric EQ Band Gain Name testString Index 1 9	GA"testString">9>3\x0D
Speaker Parametric EQ Band Q Name testString Index 1 1	GA"testString">1>2\x0D
Speaker Parametric EQ Band Q Name testString Index 1 9	GA"testString">9>2\x0D
Speaker Parametric Filter Name testString Type High	GA"testString">0>5\x0D
Speaker Parametric Filter Name testString Type Low	GA"testString">0>7\x0D
Speaker Parametric Frequency Name testString Type High	GA"testString">0>6\x0D
Speaker Parametric Frequency Name testString Type Low	GA"testString">0>8\x0D
Speaker Parametric Gain Name testString	GA"testString">0>3\x0D
Standard Mixer Level Name testString Index 1 Input Index 2 1	GA"testString">1>1\x0D
Standard Mixer Level Name testString Index 1 Input Index 2 32	GA"testString">1>63\x0D
Standard Mixer Level Name testString Index 1 Output Index 2 1	GA"testString">2>1\x0D
Standard Mixer Level Name testString Index 1 Output Index 2 32	GA"testString">2>63\x0D
Standard Mixer Mute Name testString Index 1 Input Index 2 1	GA"testString">1>2\x0D
Standard Mixer Mute Name testString Index 1 Input Index 2 32	GA"testString">1>64\x0D
Standard Mixer Mute Name testString Index 1 Output Index 2 1	GA"testString">2>2\x0D
Standard Mixer Mute Name testString Index 1 Output Index 2 32	GA"testString">2>64\x0D
Standard Mixer Routing Name testString Input 1 Output 1	GA"testString">4>(1,1)\x0D
Standard Mixer Routing Name testString Input 1 Output 32	GA"testString">4>(1,32)\x0D
Standard Mixer Routing Name testString Input 32 Output 1	GA"testString">4>(32,1)\x0D
Standard Mixer Routing Name testString Input 32 Output 32	GA"testString">4>(32,32)\x0D
Tone Control Gain Name testString Type High	GA"testString">5\x0D
Tone Control Gain Name testString Type Low	GA"testString">1\x0D
Tone Control Gain Name testString Type Mid	GA"testString">3\x0D
USB Level Name testString Channel Left	GA"testString">1>1\x0D
USB Level Name testString Channel Right	GA"testString">2>1\x0D
USB Mute Name testString Channel Left	GA"testString">1>2\x0D
USB Mute Name testString Channel Right	GA"testString">2>2\x0D

Global Scripter Module Communication Sheet

VoIP Call Active Name testString	GA"testString">0>6\x0D
VoIP Call Status Name testString	GA"testString">0>1\x0D
VoIP Caller ID Name testString Type Hostname	GA"testString">0>2\x0D
VoIP Caller ID Name testString Type Name	GA"testString">0>2\x0D
VoIP Level Name testString	GA"testString">1>1\x0D
VoIP Mute Name testString	GA"testString">1>2\x0D