

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Audio Processor
 Manufacturer: Bose
 Firmware Version: v3.210
 Model(s): ControlSpace ESP-880, ControlSpace ESP-00 Series II, ControlSpace ESP-1240, ControlSpace ESP-1600, ControlSpace ESP-4120, ControlSpace EX-1280C, PowerMatch PM4250N, PowerMatch PM4500N, PowerMatch PM8250N, PowerMatch PM8500N, ControlSpace ESP-1240AD, ControlSpace ESP-880AD

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.09.0000-b003	2.4.2

Version History

Module Version	Date	Notes
1_5_3_0	6/10/2020	Added commands for ControlSpace EX-1280C: - Room Combine Layout - Standard Room Combiner Main Input Gain - Standard Room Combiner Main Input Mute - Standard Room Combiner Main Output Gain - Standard Room Combiner Main Output Mute
1_5_2_0	5/27/2020	Added CRR Advanced Level and CRR Advanced State commands for ControlSpace EX-1280C. Added GPO Mode command for ControlSpace EX-1280C. Added model ControlSpace ESP-880AD. AEC NR Level - Minimum Value: 32dB → 24dB AMM Gated Gate Depth - Step Size: 0.5dB → 0.1dB (ESP models)

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

		AMM Gated Low Pass - Minimum Value: 1000Hz → 300Hz (ESP models) AMM Gated Threshold - Minimum Value: -80dB → -60dB (ESP Models) Array EQ Center Frequency - Range: 220 – 700Hz → 100 – 4000Hz Array EQ Tilt - Minimum Value: 0.0dB → 0.1dB Attack - Removed command Bypass - Removed command Compressor/Limiter Release - Minimum Value: 1ms → 5ms Crossover Filter - Fixed typo in Linkwitz-Reilly values Ducker Range - Minimum Value -70dB → -60dB - Step Size: 0.5dB → 0.1dB - Unit: dBFS → dB Gain - Removed command (PowerMatch models) - Added to Gain Module group Gain Mute - Removed command (PowerMatch models) - Added to Gain Module group - Removed Toggle value Gate Range - Step Size: 0.5dB → 0.1dB - Unit: dBFS → dB Group Mute - Removed Toggle value Level - Removed command Mute - Removed command Parametric EQ Q - Maximum Value: 10.0 → 14.42 - Step Size: 0.1 → 0.001 Parametric EQ Slope - Removed 0 value Parametric EQ Type: - Renamed - Band → PEQ
--	--	---

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

		○ High Cut → Low Pass ○ Low Cut → High Pass Polarity • Removed command PSTN commands • Renamed PTSN portion of command name to PSTN Source Select • Added 17 – 32 values Speaker Parametric EQ Band Filter: • Renamed Band/PEQ to PEQ Speaker Parametric EQ Band Frequency • Minimum Value: 200Hz → 20Hz Speaker Parametric EQ Band Q • Step Size: 0. 1 → 0.001 Speaker Parametric Filter • Fixed typo in Linkwitz-Reilly values Standard Mixer Level • Changed Index 2 parameter to states from number • Maximum Index 2 Value: 100 → 32 Standard Mixer Mute • Changed Index 2 parameter to states from number • Maximum Index 2 Value: 100 → 32 Standard Mixer Routing • Change Input and Output parameter to states from number • Maximum Input and Output Value: 100 → 32 Threshold • Removed command VoIP Level • Removed Module parameter VoIP Mute • Removed Module parameter
1_4_2	6/4/2019	Fixed VoIP Dial Key. Added model ControlSpace ESP-1240AD.
1_4_0_0	3/8/2019	ControlSpace EX-1280C model: • Added commands: ○ AECCNEnable ○ AECEnable ○ AECInternalMute ○ AECNLPControl ○ AECNRLevel ○ AECReference • Fixed command strings for the following commands: ○ AMMGatedDecay ○ AMMGatedDuckingDepth ○ AMMGatedGateDepth

		○ AMMGatedHold ○ AMMGatedLowPass ○ AMMGatedMute ○ AMMGatedRMSAvg ○ AMMGatedThreshold • Fixed status strings for the following commands: ○ PTSNLevel ○ PTSNMute ○ USBLevel ○ USBMute ○ VoIPLevel ○ VoIPMute • Fixed issue where status failed to update: ○ PTSNCallerID ○ VoIPCallerID • Fixed issue where command strings did not send out: ○ PTSNDialKey ○ PTSNHook ○ VoIPDialKey • Bypass ○ Fixed AGC and Array EQ state command strings ○ Added Index 1 parameter • Threshold ○ Removed AGC state • VoIP Caller ID ○ Removed extra quotation mark and angle bracket that was shown in status ControlSpace ESP-1240 model: • AMM Gated Decay ○ Reduced maximum Index 1 parameter from 32 to 8 ○ Increased minimum value from 1 to 5 ControlSpace ESP-1600 model: • Removed Fault Status command ControlSpace ESP-00, ControlSpace ESP-00 Series II, and ControlSpace 88 models: • Removed unsupported commands: ○ AMMGainSharingAttack ○ AMMGainSharingBypass ○ AMMGainSharingDecay ○ AMMGainSharingGain ○ AMMGainSharingHold ○ AMMGainSharingMute ○ AMMGainSharingPriority
--	--	--

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

		○ AMMGainSharingRMS Average ○ AMMGainSharingSlope • Reduced baud rate from 115,200 to 38,400 for serial control • Removed port changeability for ethernet control ControlSpace ESP-880, ControlSpace ESP-1240, ControlSpace ESP-4120, ControlSpace ESP-1600, and ControlSpace EX-1280C models: • Delay Time ○ Reduced maximum value from 144,00 to 48,000 PowerMatch models: • Removed the following commands: ○ Level • Mute ○ Removed Output and ESPLink from the Module parameter ○ Added AMP Output to the Module parameter • Removed port changeability for ethernet control Removed unnecessary Module parameter from the following commands: • Attack • Polarity • USB Level • USB Mute Tone Control Gain • Reduced interval step from 1 to 0.1 Added Supported Commands and Supported Value Discrepancies table.
1_3_1	12/27/2018	Updated Firmware version on communication sheet.
1_2_0_0	7/6/2018	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- Please refer to the Supported Commands table on the next page to determine what commands and statuses are supported by your device.
- Some commands differ depending on the configured model. Please refer to the Supported Values Discrepancies tables to see how some commands differ.

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='ControlSpace ESP-880')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='ControlSpace ESP-880')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 10055, Model='ControlSpace ESP-880')</code>

Supported Commands

Command	ControlSpace ESP-88	ControlSpace ESP-00, ControlSpace ESP-00 Series II	ControlSpace ESP-880, ControlSpace ESP-880AD, ControlSpace ESP-1240, ControlSpace ESP-1240AD, ControlSpace ESP-1600, ControlSpace ESP-4120	ControlSpace EX-1280C	PowerMatch Models
AEC CN Enable				•	
AEC Enable				•	
AEC Internal Mute				•	
AEC NLP Control				•	
AEC NR Level				•	
AEC Reference				•	
AMM Gain Sharing Attack			•	•	
AMM Gain Sharing Bypass			•	•	
AMM Gain Sharing Decay			•	•	
AMM Gain Sharing Gain			•	•	
AMM Gain Sharing Hold			•	•	
AMM Gain Sharing Mute			•	•	
AMM Gain Sharing Priority			•	•	
AMM Gain Sharing RMS Average			•	•	
AMM Gain Sharing Slope			•	•	
AMM Gated Attack	•	•	•	•	
AMM Gated Decay	•	•	•	•	
AMM Gated Detection	•	•	•		
AMM Gated Ducking Depth	•	•	•	•	
AMM Gated Gain	•	•	•	•	
AMM Gated Gate Depth	•	•	•	•	
AMM Gated High Pass	•	•	•	•	
AMM Gated Hold	•	•	•	•	
AMM Gated Low Pass	•	•	•	•	
AMM Gated Mute	•	•	•	•	

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated NOM	•	•	•		
AMM Gated Priority	•	•	•	•	
AMM Gated Push To Talk	•	•	•		
AMM Gated RMS Avg	•	•	•	•	
AMM Gated Threshold	•	•	•	•	
Array EQ Advanced	•	•	•	•	
Array EQ Center Frequency	•	•	•	•	
Array EQ Tilt	•	•	•	•	
Array EQ Vertical Angle				•	
Clear FaultAlarms					•
Compressor/Limiter Input Detect	•	•	•	•	
Compressor/Limiter Ratio	•	•	•	•	
Compressor/Limiter Release	•	•	•	•	
Connection Status	•	•	•	•	•
Crossover Filter	•	•	•	•	
Crossover Frequency	•	•	•	•	
Crossover Mute	•	•	•	•	
Crossover Polarity	•	•	•	•	
CRR Advanced Level				•	
CRR Advanced State				•	
Delay Bypass	•	•	•	•	
Delay Time	•	•	•	•	
Ducker Decay	•	•	•	•	
Ducker Hold	•	•	•	•	
Ducker Range	•	•	•	•	
Fault Status					•
Gain	•	•	•	•	
Gain Mute	•	•	•	•	
Gate Decay	•	•	•	•	
Gate Detector	•	•	•	•	
Gate Hold	•	•	•	•	
Gate Range	•	•	•	•	
GPO Mode				•	
Graphic EQ Level	•	•	•	•	
Group Level	•	•	•	•	•
Group Mute	•	•	•	•	•
Matrix Mixer Level	•	•	•	•	
Matrix Mixer State	•	•	•	•	
Parameter Recall	•	•	•	•	•
Parametric EQ Frequency	•	•	•	•	
Parametric EQ Gain	•	•	•	•	
Parametric EQ Q	•	•	•	•	

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Parametric EQ Slope	•	•	•	•	
Parametric EQ Type	•	•	•	•	
Peak/RMS Input Detect	•	•	•	•	
Peak/RMS RMS	•	•	•	•	
PTSN Action				•	
PTSN Call Active				•	
PTSN Call Status				•	
PTSN Caller ID				•	
PTSN Dial Key				•	
PTSN Dial String				•	
PTSN Hook				•	
PTSN Level				•	
PTSN Mute				•	
Room Combine Layout				•	
Router Input Select	•	•	•	•	
Signal Generator Gain	•	•	•	•	
Signal Generator Mute	•	•	•	•	
Source Select	•	•	•	•	
Speaker Parametric Align Delay	•	•	•	•	
Speaker Parametric Bypass	•	•	•	•	
Speaker Parametric EQ Band Bypass	•	•	•	•	
Speaker Parametric EQ Band Filter	•	•	•	•	
Speaker Parametric EQ Band Frequency	•	•	•	•	
Speaker Parametric EQ Band Gain	•	•	•	•	
Speaker Parametric EQ Band Q	•	•	•	•	
Speaker Parametric Filter	•	•	•	•	
Speaker Parametric Frequency	•	•	•	•	
Speaker Parametric Gain	•	•	•	•	
Standard Mixer Level	•	•	•	•	
Standard Mixer Mute	•	•	•	•	
Standard Mixer Routing	•	•	•	•	
Standard Room Combiner Main Input Gain				•	
Standard Room Combiner Main Input Mute				•	

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Standard Room Combiner Main Output Gain				•	
Standard Room Combiner Main Output Mute				•	
Surround Input Level		•			
Surround Input Output Format		•			
Surround Input Room Type		•			
Surround Input Source		•			
Tone Control Gain	•	•	•	•	
USB Level				•	
USB Mute				•	
User Defined Command	•	•	•	•	•
User Defined String	•	•	•	•	•
VoIP Action				•	
VoIP Call Active				•	
VoIP Call Status				•	
VoIP Caller ID				•	
VoIP Dial Key				•	
VoIP Dial String				•	
VoIP Level				•	
VoIP Mute				•	

Supported Value Discrepancies

While two different models may support the same command, the available parameters or values may differ. The tables below show how some parameters and values differ for such applicable commands. If a parameter or value field is left blank for any given model, then the parameter or value is not supported by that model. Note that this table does not indicate commands that are supported by a model.

Table 1

Command	ESP Models	ControlSpace EX-1280C	PowerMatch Models
AMM Gated Attack			
Index 1	1 – 8	1 – 32	
Value	0.5 to 100 in steps of 0.5 ms	0.5 to 500 in steps of 0.5 ms	
AMM Gated Decay			
Index 1	1 – 8	1 – 32	
Value	5 to 50000 in steps of 1 ms	1 to 50000 in steps of 1 ms	
AMM Gated Ducking Depth			
Index 1	1 – 8	1 – 32	
AMM Gated Gain			
Index 1	0 – 8	0 – 32	
Value	-60.5 to 0 in steps of 0.5 dB	-60.5 to 12 in steps of 0.5 dB	
AMM Gated Gate Depth			
Index 1	1 – 8	1 – 32	
Value	-70 to 0 in steps of 0.1 dB	-70 to 0 in steps of 0.5 dB	
AMM Gated High Pass			
Index 1	1 – 8	1 – 32	
Value	20 to 1000 in steps of 1 Hz	20 to 20000 in steps of 0.1 Hz	
AMM Gated Hold			
Index 1	1 – 8	1 – 32	
AMM Gated Low Pass			
Index 1	1 – 8	1 – 32	
Value	300 to 20000 in steps of 1 Hz	20 to 20000 in steps of 0.1 Hz	
AMM Gated Mute			
Index 1	0 – 8	0 – 32	
AMM Gated Priority			
Index 1	1 – 8	1 – 32	
Value	On, Off	1 – 5	
AMM Gated RMS Avg			
Index 1	1 – 8	1 – 32	
Value	1 to 500 in steps of 1 ms	1 to 1000 in steps of 1 ms	
AMM Gated Threshold			
Index 1	1 – 8	1 – 32	
Value	-60 to 0 in steps of 0.5 dB	-80 to 0 in steps of 0.5 dB	
Group Level			
Value	-60 to 12 in steps of 0.5 dB	-60 to 12 in steps of 0.5 dB	-60 to 0 in steps

	of 0.5 dB
--	-----------

Table 2

Command	ControlSpace ESP-00, ControlSpace ESP-00 Series II, ControlSpace ESP-88	ControlSpace ESP-880, ControlSpace ESP-880AD, ControlSpace ESP-1240, ControlSpace ESP-1240AD, ControlSpace ESP-1600 ControlSpace ESP-4120, ControlSpace EX-1280C
Delay Time		
Value	0 to 144000 in steps of 1 Samples	0 to 48000 in steps of 1 Samples

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	
AECNEnable	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '12'	
# AECNEnable example InterfaceName.Set('AECNEnable', 'On', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AECEnable	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '12'	
# AECEnable example InterfaceName.Set('AECEnable', 'On', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AECInternalMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '12'	
# AECInternalMute example InterfaceName.Set('AECInternalMute', 'On', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AECNLPControl	'Light'	'Medium'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '12'	
# AECNLPControl example InterfaceName.Set('AECNLPControl', 'Light', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AECNRLevel	0 to 24 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '12'	
# AECNRLevel example InterfaceName.Set('AECNRLevel', 24, {'Name': 'String', 'Index 1': '1'})		

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command	Value	
AMMGainSharingAttack	0.5 to 100 in steps of 0.5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# AMMGainSharingAttack example InterfaceName.Set('AMMGainSharingAttack', 100, {'Name': 'String'})		
Command	Value	Value
AMMGainSharingBypass	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '32'	
# AMMGainSharingBypass example InterfaceName.Set('AMMGainSharingBypass', 'On', {'Name': 'String', 'Index 1': '1'})		
Command	Value	
AMMGainSharingDecay	5 to 50000 in steps of 5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# AMMGainSharingDecay example InterfaceName.Set('AMMGainSharingDecay', 50000, {'Name': 'String'})		
Command	Value	
AMMGainSharingGain	-60.5 to 12 in steps of 0.5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'0' – '32'	
# AMMGainSharingGain example InterfaceName.Set('AMMGainSharingGain', 12, {'Name': 'String', 'Index 1': '0'})		
Command	Value	
AMMGainSharingHold	0 to 1000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# AMMGainSharingHold example InterfaceName.Set('AMMGainSharingHold', 1000, {'Name': 'String'})		
Command	Value	Value
AMMGainSharingMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'0' – '32'	
# AMMGainSharingMute example InterfaceName.Set('AMMGainSharingMute', 'On', {'Name': 'String', 'Index 1': '0'})		
Command	Value	
AMMGainSharingPriority	'1' – '5'	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Index 1'	'1' – '32'	
# AMMGainSharingPriority example InterfaceName.Set('AMMGainSharingPriority', '1', {'Name': 'String', 'Index 1': '1'})		

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command AMMGainSharingRMSAverage	Value 1 to 500 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Input'	Qualifier Value 'Output'	
# AMMGainSharingRMSAverage example InterfaceName.Set('AMMGainSharingRMSAverage', 500, {'Name': 'String', 'Type': 'Input'})			
Command AMMGainSharingSlope	Value 0.01 to 2 in steps of 0.01		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGainSharingSlope example InterfaceName.Set('AMMGainSharingSlope', 2, {'Name': 'String'})			
Command AMMGatedAttack	Value 0.5 to 500 in steps of 0.5		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedAttack example InterfaceName.Set('AMMGatedAttack', 500, {'Index 1': '1', 'Name': 'String'})			
Command AMMGatedDecay	Value 5 to 50000 in steps of 1		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedDecay example InterfaceName.Set('AMMGatedDecay', 50000, {'Index 1': '1', 'Name': 'String'})			
Command AMMGatedDetection	Value 'Threshold' 'Bypass'	Value 'LastOn'	Value 'PushToTalk'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'		
# AMMGatedDetection example InterfaceName.Set('AMMGatedDetection', 'Threshold', {'Name': 'String', 'Index 1': '1'})			
Command AMMGatedDuckingDepth	Value -60 to 0 in steps of 0.5		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedDuckingDepth example InterfaceName.Set('AMMGatedDuckingDepth', 0, {'Index 1': '1', 'Name': 'String'})			

Command AMMGatedGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedGain example InterfaceName.Set('AMMGatedGain', 12, {'Index 1': '0', 'Name': 'String'})	
Command AMMGatedGateDepth	Value -70 to 0 in steps of 0.1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedGateDepth example InterfaceName.Set('AMMGatedGateDepth', 0, {'Index 1': '1', 'Name': 'String'})	
Command AMMGatedHighPass	Value 20 to 1000 in steps of 1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedHighPass example InterfaceName.Set('AMMGatedHighPass', 1000, {'Index 1': '1', 'Name': 'String'})	
Command AMMGatedHold	Value 1 to 50000 in steps of 1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedHold example InterfaceName.Set('AMMGatedHold', 50000, {'Index 1': '1', 'Name': 'String'})	
Command AMMGatedLowPass	Value 300 to 20000 in steps of 1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedLowPass example InterfaceName.Set('AMMGatedLowPass', 20000, {'Index 1': '1', 'Name': 'String'})	
Command AMMGatedMute	Value 'On' 'Off'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
# AMMGatedMute example InterfaceName.Set('AMMGatedMute', 'On', {'Index 1': '0', 'Name': 'String'})	

Global Scriptor Module Communication Sheet

Command AMMGatedNOM	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedNOM example InterfaceName.Set('AMMGatedNOM', 'On', {'Name': 'String'})		
Command AMMGatedPriority	Value '1' – '5'	Value 'On'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedPriority example InterfaceName.Set('AMMGatedPriority', '1', {'Index 1': '1', 'Name': 'String'})		
Command AMMGatedPushToTalk	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'	
# AMMGatedPushToTalk example InterfaceName.Set('AMMGatedPushToTalk', 'On', {'Name': 'String', 'Index 1': '1'})		
Command AMMGatedRMSAvg	Value 1 to 1000 in steps of 1	
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedRMSAvg example InterfaceName.Set('AMMGatedRMSAvg', 1000, {'Index 1': '1', 'Name': 'String'})		
Command AMMGatedThreshold	Value -80 to 0 in steps of 0.5	
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedThreshold example InterfaceName.Set('AMMGatedThreshold', 0, {'Index 1': '1', 'Name': 'String'})		
Command ArrayEQAdvanced	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQAdvanced example InterfaceName.Set('ArrayEQAdvanced', 'On', {'Name': 'String'})		
Command ArrayEQCenterFrequency	Value 100 to 4000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQCenterFrequency example InterfaceName.Set('ArrayEQCenterFrequency', 4000, {'Name': 'String'})		

Command ArrayEQTilt	Value 0.1 to 10 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQTilt example InterfaceName.Set('ArrayEQTilt', 10, {'Name': 'String'})			
Command ArrayEQVerticalAngle	Value 20 to 100 in steps of 5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# ArrayEQVerticalAngle example InterfaceName.Set('ArrayEQVerticalAngle', 100, {'Name': 'String'})			
Command ClearFaultAlarms	Value None		
# ClearFaultAlarms example InterfaceName.Set('ClearFaultAlarms', None)			
Command CompressorLimiterInputDetect	Value 'Left'	Value 'Right'	Value 'Mix'
	'Sidechain'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterInputDetect example InterfaceName.Set('CompressorLimiterInputDetect', 'Left', {'Name': 'String'})			
Command CompressorLimiterRatio	Value 1 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRatio example InterfaceName.Set('CompressorLimiterRatio', 20, {'Name': 'String'})			
Command CompressorLimiterRelease	Value 5 to 1000 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRelease example InterfaceName.Set('CompressorLimiterRelease', 1000, {'Name': 'String'})			
Command CrossoverFilter	Value 'Butterworth 6dB/oct'	Value 'Butterworth 12dB/oct'	Value 'Butterworth 18dB/oct'
	'Butterworth 24dB/oct'	'Butterworth 36dB/oct'	'Butterworth 48dB/oct'
	'Bessel 12dB/oct'	'Bessel 18dB/oct'	'Bessel 24dB/oct'
	'Bessel 36dB/oct'	'Bessel 48dB/oct'	'Linkwitz-Reily 12dB/oct'
	'Linkwitz-Reily 24dB/oct'	'Linkwitz-Reily 36dB/oct'	'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid HPF'	Qualifier Value 'Mid LPF'
# CrossoverFilter example InterfaceName.Set('CrossoverFilter', 'Butterworth 6dB/oct', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			

Command	Value		
CrossoverFrequency	20 to 20000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Type'	'Low/High'	'Mid HPF'	'Mid LPF'
# CrossoverFrequency example InterfaceName.Set('CrossoverFrequency', 20000, {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command	Value		Value
CrossoverMute	'On'		'Off'
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverMute example InterfaceName.Set('CrossoverMute', 'On', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command	Value		Value
CrossoverPolarity	'On'		'Off'
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverPolarity example InterfaceName.Set('CrossoverPolarity', 'On', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'})			
Command	Value		
CRRAdvancedLevel	-60.5 to 0 in steps of 0.5		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Input'	'1' – '51'		
Qualifier Key	Qualifier Value		
'Output'	'1' – '67'		
# CRRAdvancedLevel example InterfaceName.Set('CRRAdvancedLevel', 0, {'Name': 'String', 'Input': '1', 'Output': '1'})			
Command	Value		Value
CRRAdvancedState	'On'		'Off'
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Input'	'1' – '51'		
Qualifier Key	Qualifier Value		
'Output'	'1' – '67'		
# CRRAdvancedState example InterfaceName.Set('CRRAdvancedState', 'On', {'Name': 'String', 'Input': '1', 'Output': '1'})			

Command	Value	
DelayBypass	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Output'	'1' – '8'	
# DelayBypass example InterfaceName.Set('DelayBypass', 'On', {'Name': 'String', 'Output': '1'})		
Command	Value	
DelayTime	0 to 48000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
Qualifier Key	Qualifier Value	
'Output'	'1' – '8'	
# DelayTime example InterfaceName.Set('DelayTime', 48000, {'Name': 'String', 'Output': '1'})		
Command	Value	
DuckerDecay	5 to 50000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# DuckerDecay example InterfaceName.Set('DuckerDecay', 50000, {'Name': 'String'})		
Command	Value	
DuckerHold	0 to 1000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# DuckerHold example InterfaceName.Set('DuckerHold', 1000, {'Name': 'String'})		
Command	Value	
DuckerRange	-60 to 0 in steps of 0.1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# DuckerRange example InterfaceName.Set('DuckerRange', 0, {'Name': 'String'})		
Command	Value	
Gain	-60.5 to 12 in steps of 0.5	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# Gain example InterfaceName.Set('Gain', 12, {'Name': 'String'})		
Command	Value	Value
GainMute	'On'	'Off'
Qualifier Key	Qualifier Value	
'Name'	'String'	
# GainMute example InterfaceName.Set('GainMute', 'On', {'Name': 'String'})		
Command	Value	
GateDecay	5 to 50000 in steps of 1	
Qualifier Key	Qualifier Value	
'Name'	'String'	
# GateDecay example InterfaceName.Set('GateDecay', 50000, {'Name': 'String'})		

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Command GateDetector	Value 'Left' 'Right' 'Mix' 'Sidechain'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateDetector example InterfaceName.Set('GateDetector', 'Left', {'Name': 'String'})			
Command GateHold	Value 0 to 1000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateHold example InterfaceName.Set('GateHold', 1000, {'Name': 'String'})			
Command GateRange	Value -70 to 0 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateRange example InterfaceName.Set('GateRange', 0, {'Name': 'String'})			
Command GPOMode	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Pin'	Qualifier Value '1' – '5'		
# GPOMode example InterfaceName.Set('GPOMode', 'On', {'Name': 'String', 'Pin': '1'})			
Command GraphicEQLevel	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Frequency'	Qualifier Value '20Hz' '40Hz' '80Hz' '160Hz' '315Hz' '630Hz' '1.25kHz' '2.5kHz' '5kHz' '10kHz' '20kHz'	Qualifier Value '25Hz' '50Hz' '100Hz' '200Hz' '400Hz' '800Hz' '1.6kHz' '3.15kHz' '6.3kHz' '12.5kHz'	Qualifier Value '31.5Hz' '63Hz' '125Hz' '250Hz' '500Hz' '1kHz' '2kHz' '4kHz' '8kHz' '16kHz'
# GraphicEQLevel example InterfaceName.Set('GraphicEQLevel', 15, {'Name': 'String', 'Frequency': '20Hz'})			
Command GroupLevel	Value -60 to 12 in steps of 0.5		
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
# GroupLevel example InterfaceName.Set('GroupLevel', 12, {'Group': '1'})			

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command GroupMute	Value 'On'	Value 'Off'
Qualifier Key 'Group'	Qualifier Value '1' – '64'	
# GroupMute example InterfaceName.Set('GroupMute', 'On', {'Group': '1'})		
Command MatrixMixerLevel	Value -60.5 to 0 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'	
# MatrixMixerLevel example InterfaceName.Set('MatrixMixerLevel', 0, {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'})		
Command MatrixMixerState	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'	
# MatrixMixerState example InterfaceName.Set('MatrixMixerState', 'On', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'})		
Command ParameterRecall	Value '1' – '255'	
# ParameterRecall example InterfaceName.Set('ParameterRecall', '1')		
Command ParametricEQFrequency	Value 20 to 20000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Band'	Qualifier Value '1' – '16'	
# ParametricEQFrequency example InterfaceName.Set('ParametricEQFrequency', 20000, {'Name': 'String', 'Band': '1'})		
Command ParametricEQGain	Value -20 to 20 in steps of 0.1	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Band'	Qualifier Value '1' – '16'	
# ParametricEQGain example InterfaceName.Set('ParametricEQGain', 20, {'Name': 'String', 'Band': '1'})		

Command ParametricEQQ	Value 0.1 to 14 in steps of 0.001		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQQ example InterfaceName.Set('ParametricEQQ', 14, {'Name': 'String', 'Band': '1'})			
Command ParametricEQSlope			
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQSlope example InterfaceName.Set('ParametricEQSlope', , {'Name': 'String', 'Band': '1'})			
Command ParametricEQType	Value 'PEQ' 'Low Pass'	Value 'High Shelf' 'High Pass'	Value 'Low Shelf' 'Notch'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQType example InterfaceName.Set('ParametricEQType', 'PEQ', {'Name': 'String', 'Band': '1'})			
Command PeakRMSInputDetect	Value 'Left' 'Sidechain'	Value 'Right'	Value 'Mix'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PeakRMSInputDetect example InterfaceName.Set('PeakRMSInputDetect', 'Left', {'Name': 'String'})			
Command PeakRMSRMS	Value 500 to 10000 in steps of 100		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Function'	Qualifier Value 'Attack'	Qualifier Value 'Release'	
# PeakRMSRMS example InterfaceName.Set('PeakRMSRMS', 10000, {'Name': 'String', 'Function': 'Attack'})			
Command PSTNAction	Value 'Make Call'	Value 'End Call'	Value 'Answer Call'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNAction example InterfaceName.Set('PSTNAction', 'Make Call', {'Name': 'String'})			
Command PSTNDialKey	Value '0' – '9' '!'	Value '#'	Value '*'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNDialKey example InterfaceName.Set('PSTNDialKey', '0', {'Name': 'String'})			

Global Scriptor Module Communication Sheet

Command PSTNHook	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# PSTNHook example InterfaceName.Set('PSTNHook', 'On', {'Name': 'String'})		
Command PSTNLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Name'	Qualifier Value 'String'	
# PSTNLevel example InterfaceName.Set('PSTNLevel', 12, {'Module': 'Input', 'Name': 'String'})		
Command PSTNMute	Value 'On'	Value 'Off'
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Name'	Qualifier Value 'String'	
# PSTNMute example InterfaceName.Set('PSTNMute', 'On', {'Module': 'Input', 'Name': 'String'})		
Command RoomCombineLayout	Value 'Join'	Value 'Split'
Qualifier Key 'Group'	Value '1' – '6'	
Qualifier Key 'Room 1'	Value '1' – '6'	
Qualifier Key 'Room 2'	Value '1' – '6'	
# RoomCombineLayout example InterfaceName.Set('RoomCombineLayout', 'Join', {'Group': '1', 'Room 1': '3', 'Room 2': '6'})		
Command RouterInputSelect	Value '0' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
# RouterInputSelect example InterfaceName.Set('RouterInputSelect', '0', {'Name': 'String', 'Output': '1'})		
Command SignalGeneratorGain	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Wave'	Qualifier Value 'Sine'	Qualifier Value 'White'
	'Sweep'	Qualifier Value 'Pink'
# SignalGeneratorGain example InterfaceName.Set('SignalGeneratorGain', 12, {'Name': 'String', 'Wave': 'Sine'})		
Command SignalGeneratorMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Qualifier Key 'Wave'	Qualifier Value 'Sine'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorMute example InterfaceName.Set('SignalGeneratorMute', 'On', {'Name': 'String', 'Wave': 'Sine'})			
Command SourceSelect	Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SourceSelect example InterfaceName.Set('SourceSelect', '1', {'Name': 'String'})			
Command SpeakerParametricAlignDelay	Value 0 to 480 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricAlignDelay example InterfaceName.Set('SpeakerParametricAlignDelay', 480, {'Name': 'String'})			
Command SpeakerParametricBypass	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricBypass example InterfaceName.Set('SpeakerParametricBypass', 'On', {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricEQBandBypass	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandBypass example InterfaceName.Set('SpeakerParametricEQBandBypass', 'On', {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandFilter	Value 'PEQ' 'Notch'	Value 'High Shelf'	Value 'Low Shelf'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFilter example InterfaceName.Set('SpeakerParametricEQBandFilter', 'PEQ', {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFrequency example InterfaceName.Set('SpeakerParametricEQBandFrequency', 20000, {'Name': 'String', 'Index 1':			

'1'}})			
Command SpeakerParametricEQBandGain	Value -20 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandGain example InterfaceName.Set('SpeakerParametricEQBandGain', 20, {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricEQBandQ	Value 0.1 to 10 in steps of 0.001		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandQ example InterfaceName.Set('SpeakerParametricEQBandQ', 10, {'Name': 'String', 'Index 1': '1'})			
Command SpeakerParametricFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFilter example InterfaceName.Set('SpeakerParametricFilter', 'Butterworth 6dB/oct', {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFrequency example InterfaceName.Set('SpeakerParametricFrequency', 20000, {'Name': 'String', 'Type': 'High'})			
Command SpeakerParametricGain	Value -15 to 15 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricGain example InterfaceName.Set('SpeakerParametricGain', 15, {'Name': 'String'})			

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command StandardMixerLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'	
# StandardMixerLevel example InterfaceName.Set('StandardMixerLevel', 12, {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'})		
Command StandardMixerMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'	
# StandardMixerMute example InterfaceName.Set('StandardMixerMute', 'On', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'})		
Command StandardMixerRouting	Value 'Route'	Value 'Unroute'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
# StandardMixerRouting example InterfaceName.Set('StandardMixerRouting', 'Route', {'Name': 'String', 'Input': '1', 'Output': '1'})		
Command StandardRoomCombinerMainInputGain	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# StandardRoomCombinerMainInputGain example InterfaceName.Set('StandardRoomCombinerMainInputGain', 12, {'Name': 'String'})		
Command StandardRoomCombinerMainInputMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# StandardRoomCombinerMainInputMute example InterfaceName.Set('StandardRoomCombinerMainInputMute', 'On', {'Name': 'String'})		

Command StandardRoomCombinerMainOutputGain	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# StandardRoomCombinerMainOutputGain example InterfaceName.Set('StandardRoomCombinerMainOutputGain', 12, {'Name': 'String'})			
Command StandardRoomCombinerMainOutputMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# StandardRoomCombinerMainOutputMute example InterfaceName.Set('StandardRoomCombinerMainOutputMute', 'On', {'Name': 'String'})			
Command SurroundInputLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Level'	Qualifier Value 'Left Front' 'Right Surround' 'Back Surround Left'	Qualifier Value 'Right Front' 'Center' 'Back Surround Right'	Qualifier Value 'Left Surround' 'LFE (Sub)'
# SurroundInputLevel example InterfaceName.Set('SurroundInputLevel', 12, {'Name': 'String', 'Level': 'Left Front'})			
Command SurroundInputSource	Value 'Optical'	Value 'Coaxial'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# SurroundInputSource example InterfaceName.Set('SurroundInputSource', 'Optical', {'Name': 'String'})			
Command ToneControlGain	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Low'	Qualifier Value 'Mid'	Qualifier Value 'High'
# ToneControlGain example InterfaceName.Set('ToneControlGain', 15, {'Name': 'String', 'Type': 'Low'})			
Command USBLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'	
# USBLevel example InterfaceName.Set('USBLevel', 12, {'Name': 'String', 'Channel': 'Left'})			

Global Scripter Module Communication Sheet

Command USBMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'
# USBMute example InterfaceName.Set('USBMute', 'On', {'Name': 'String', 'Channel': 'Left'})		
Command VoIPAction	Value 'Make Call' 'Transfer Call'	Value 'End Call' 'Answer Call'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPAction example InterfaceName.Set('VoIPAction', 'Make Call', {'Name': 'String'})		
Command VoIPDialKey	Value '0' – '9'	Value '#' '*'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPDialKey example InterfaceName.Set('VoIPDialKey', '0', {'Name': 'String'})		
Command VoIPLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPLevel example InterfaceName.Set('VoIPLevel', 12, {'Name': 'String'})		
Command VoIPMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPMute example InterfaceName.Set('VoIPMute', 'On', {'Name': 'String'})		

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AECCNEnable	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'	
# AECCNEnable example InterfaceName.Update('AECCNEnable', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECCNEnable', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECCNEnable', None, FeedbackHandler)		
Command AECEnable	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'	
# AECEnable example InterfaceName.Update('AECEnable', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECEnable', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECEnable', None, FeedbackHandler)		
Command AECInternalMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'	
# AECInternalMute example InterfaceName.Update('AECInternalMute', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECInternalMute', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECInternalMute', None, FeedbackHandler)		

Command AECNLPControl	Value 'Light'	Value 'Medium'	Value 'Strong'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'		
# AECNLPControl example InterfaceName.Update('AECNLPControl', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECNLPControl', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECNLPControl', None, FeedbackHandler)			
Command AECNRLevel	Value 0 to 24 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'		
# AECNRLevel example InterfaceName.Update('AECNRLevel', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECNRLevel', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECNRLevel', None, FeedbackHandler)			
Command AECReference	Value '1' – '4'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '12'		
# AECReference example InterfaceName.Update('AECReference', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AECReference', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AECReference', None, FeedbackHandler)			
Command AMMGainSharingAttack	Value 0.5 to 100 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGainSharingAttack example InterfaceName.Update('AMMGainSharingAttack', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingAttack', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingAttack', None, FeedbackHandler)			
Command AMMGainSharingBypass	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
# AMMGainSharingBypass example InterfaceName.Update('AMMGainSharingBypass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGainSharingBypass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGainSharingBypass', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command AMMGainSharingDecay	Value 5 to 50000 in steps of 5
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGainSharingDecay example InterfaceName.Update('AMMGainSharingDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingDecay', None, FeedbackHandler)</pre>	
Command AMMGainSharingGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
<pre># AMMGainSharingGain example InterfaceName.Update('AMMGainSharingGain', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGainSharingGain', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGainSharingGain', None, FeedbackHandler)</pre>	
Command AMMGainSharingHold	Value 0 to 1000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGainSharingHold example InterfaceName.Update('AMMGainSharingHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingHold', None, FeedbackHandler)</pre>	
Command AMMGainSharingMute	Value 'On' 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
<pre># AMMGainSharingMute example InterfaceName.Update('AMMGainSharingMute', {'Name': 'String', 'Index 1': '0'}) Value = InterfaceName.ReadStatus('AMMGainSharingMute', {'Name': 'String', 'Index 1': '0'}) InterfaceName.SubscribeStatus('AMMGainSharingMute', None, FeedbackHandler)</pre>	
Command AMMGainSharingPriority	Value '1' – '5'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
<pre># AMMGainSharingPriority example InterfaceName.Update('AMMGainSharingPriority', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGainSharingPriority', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGainSharingPriority', None, FeedbackHandler)</pre>	

Command AMMGainSharingRMSAverage	Value 1 to 500 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Input'	Qualifier Value 'Output'	
# AMMGainSharingRMSAverage example InterfaceName.Update('AMMGainSharingRMSAverage', {'Name': 'String', 'Type': 'Input'}) Value = InterfaceName.ReadStatus('AMMGainSharingRMSAverage', {'Name': 'String', 'Type': 'Input'}) InterfaceName.SubscribeStatus('AMMGainSharingRMSAverage', None, FeedbackHandler)			
Command AMMGainSharingSlope	Value 0.01 to 2 in steps of 0.01		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGainSharingSlope example InterfaceName.Update('AMMGainSharingSlope', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGainSharingSlope', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGainSharingSlope', None, FeedbackHandler)			
Command AMMGatedAttack	Value 0.5 to 500 in steps of 0.5		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedAttack example InterfaceName.Update('AMMGatedAttack', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedAttack', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedAttack', None, FeedbackHandler)			
Command AMMGatedDecay	Value 5 to 50000 in steps of 1		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedDecay example InterfaceName.Update('AMMGatedDecay', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedDecay', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedDecay', None, FeedbackHandler)			
Command AMMGatedDetection	Value 'Threshold' 'Bypass'	Value 'LastOn'	Value 'PushToTalk'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'		
# AMMGatedDetection example InterfaceName.Update('AMMGatedDetection', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedDetection', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedDetection', None, FeedbackHandler)			

Command AMMGatedDuckingDepth	Value -60 to 0 in steps of 0.5
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGatedDuckingDepth example InterfaceName.Update('AMMGatedDuckingDepth', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedDuckingDepth', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedDuckingDepth', None, FeedbackHandler)</pre>	
Command AMMGatedGain	Value -60.5 to 12 in steps of 0.5
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGatedGain example InterfaceName.Update('AMMGatedGain', {'Index 1': '0', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedGain', {'Index 1': '0', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedGain', None, FeedbackHandler)</pre>	
Command AMMGatedGateDepth	Value -70 to 0 in steps of 0.1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGatedGateDepth example InterfaceName.Update('AMMGatedGateDepth', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedGateDepth', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedGateDepth', None, FeedbackHandler)</pre>	
Command AMMGatedHighPass	Value 20 to 1000 in steps of 1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGatedHighPass example InterfaceName.Update('AMMGatedHighPass', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedHighPass', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedHighPass', None, FeedbackHandler)</pre>	
Command AMMGatedHold	Value 1 to 50000 in steps of 1
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'
Qualifier Key 'Name'	Qualifier Value 'String'
<pre># AMMGatedHold example InterfaceName.Update('AMMGatedHold', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedHold', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedHold', None, FeedbackHandler)</pre>	

Global Scriptor Module Communication Sheet

Command AMMGatedLowPass	Value 300 to 20000 in steps of 1		
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedLowPass example InterfaceName.Update('AMMGatedLowPass', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedLowPass', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedLowPass', None, FeedbackHandler)			
Command AMMGatedMute	Value 'On'	Value 'Off'	
Qualifier Key 'Index 1'	Qualifier Value '0' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedMute example InterfaceName.Update('AMMGatedMute', {'Index 1': '0', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedMute', {'Index 1': '0', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedMute', None, FeedbackHandler)			
Command AMMGatedNOM	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedNOM example InterfaceName.Update('AMMGatedNOM', {'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedNOM', {'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedNOM', None, FeedbackHandler)			
Command AMMGatedPriority	Value '1' – '5'	Value 'On'	Value 'Off'
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# AMMGatedPriority example InterfaceName.Update('AMMGatedPriority', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedPriority', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedPriority', None, FeedbackHandler)			
Command AMMGatedPushToTalk	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '8'		
# AMMGatedPushToTalk example InterfaceName.Update('AMMGatedPushToTalk', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('AMMGatedPushToTalk', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('AMMGatedPushToTalk', None, FeedbackHandler)			

Command AMMGatedRMSAvg	Value 1 to 1000 in steps of 1	
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedRMSAvg example InterfaceName.Update('AMMGatedRMSAvg', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedRMSAvg', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedRMSAvg', None, FeedbackHandler)		
Command AMMGatedThreshold	Value -80 to 0 in steps of 0.5	
Qualifier Key 'Index 1'	Qualifier Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# AMMGatedThreshold example InterfaceName.Update('AMMGatedThreshold', {'Index 1': '1', 'Name': 'String'}) Value = InterfaceName.ReadStatus('AMMGatedThreshold', {'Index 1': '1', 'Name': 'String'}) InterfaceName.SubscribeStatus('AMMGatedThreshold', None, FeedbackHandler)		
Command ArrayEQAdvanced	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQAdvanced example InterfaceName.Update('ArrayEQAdvanced', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQAdvanced', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQAdvanced', None, FeedbackHandler)		
Command ArrayEQCenterFrequency	Value 100 to 4000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQCenterFrequency example InterfaceName.Update('ArrayEQCenterFrequency', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQCenterFrequency', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQCenterFrequency', None, FeedbackHandler)		
Command ArrayEQTilt	Value 0.1 to 10 in steps of 0.1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQTilt example InterfaceName.Update('ArrayEQTilt', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQTilt', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQTilt', None, FeedbackHandler)		
Command ArrayEQVerticalAngle	Value 20 to 100 in steps of 5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# ArrayEQVerticalAngle example InterfaceName.Update('ArrayEQVerticalAngle', {'Name': 'String'}) Value = InterfaceName.ReadStatus('ArrayEQVerticalAngle', {'Name': 'String'}) InterfaceName.SubscribeStatus('ArrayEQVerticalAngle', None, FeedbackHandler)		

Command CompressorLimiterInputDetect	Value 'Left'	Value 'Right'	Value 'Mix'
	'Sidechain'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterInputDetect example InterfaceName.Update('CompressorLimiterInputDetect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterInputDetect', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterInputDetect', None, FeedbackHandler)			
Command CompressorLimiterRatio	Value 1 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRatio example InterfaceName.Update('CompressorLimiterRatio', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterRatio', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterRatio', None, FeedbackHandler)			
Command CompressorLimiterRelease	Value 5 to 1000 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# CompressorLimiterRelease example InterfaceName.Update('CompressorLimiterRelease', {'Name': 'String'}) Value = InterfaceName.ReadStatus('CompressorLimiterRelease', {'Name': 'String'}) InterfaceName.SubscribeStatus('CompressorLimiterRelease', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command CrossoverFilter	Value 'Butterworth 6dB/oct'	Value 'Butterworth 12dB/oct'	Value 'Butterworth 18dB/oct'
	'Butterworth 24dB/oct'	'Butterworth 36dB/oct'	'Butterworth 48dB/oct'
	'Bessel 12dB/oct'	'Bessel 18dB/oct'	'Bessel 24dB/oct'
	'Bessel 36dB/oct'	'Bessel 48dB/oct'	'Linkwitz-Reily 12dB/oct'
	'Linkwitz-Reily 24dB/oct'	'Linkwitz-Reily 36dB/oct'	'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '4'		
Qualifier Key 'Type'	Qualifier Value 'Low/High'	Qualifier Value 'Mid HPF'	Qualifier Value 'Mid LPF'
# CrossoverFilter example InterfaceName.Update('CrossoverFilter', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverFilter', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverFilter', None, FeedbackHandler)			

Command	Value		
CrossoverFrequency	20 to 20000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	Qualifier Value
'Type'	'Low/High'	'Mid HPF'	'Mid LPF'
# CrossoverFrequency example InterfaceName.Update('CrossoverFrequency', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverFrequency', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverFrequency', None, FeedbackHandler)			
Command	Value		Value
CrossoverMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverMute example InterfaceName.Update('CrossoverMute', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverMute', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverMute', None, FeedbackHandler)			
Command	Value		Value
CrossoverPolarity	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Index 1'	'1' – '4'		
Qualifier Key	Qualifier Value	Qualifier Value	
'Type'	'Low/High'	'Mid'	
# CrossoverPolarity example InterfaceName.Update('CrossoverPolarity', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) Value = InterfaceName.ReadStatus('CrossoverPolarity', {'Name': 'String', 'Index 1': '1', 'Type': 'Low/High'}) InterfaceName.SubscribeStatus('CrossoverPolarity', None, FeedbackHandler)			
Command	Value		
CRRAdvancedLevel	-60.5 to 0 in steps of 0.5		
Qualifier Key	Qualifier Value		
'Name'	'String'		
Qualifier Key	Qualifier Value		
'Input'	'1' – '51'		
Qualifier Key	Qualifier Value		
'Output'	'1' – '67'		
# CRRAdvancedLevel example InterfaceName.Update('CRRAdvancedLevel', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('CRRAdvancedLevel', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('CRRAdvancedLevel', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Command CRRAdvancedState	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '51'	
Qualifier Key 'Output'	Qualifier Value '1' – '67'	
# CRRAdvancedState example InterfaceName.Update('CRRAdvancedState', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('CRRAdvancedState', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('CRRAdvancedState', None, FeedbackHandler)		
Command DelayBypass	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Output'	Qualifier Value '1' – '8'	
# DelayBypass example InterfaceName.Update('DelayBypass', {'Name': 'String', 'Output': '1'}) Value = InterfaceName.ReadStatus('DelayBypass', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('DelayBypass', None, FeedbackHandler)		
Command DelayTime	Value 0 to 48000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Output'	Qualifier Value '1' – '8'	
# DelayTime example InterfaceName.Update('DelayTime', {'Name': 'String', 'Output': '1'}) Value = InterfaceName.ReadStatus('DelayTime', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('DelayTime', None, FeedbackHandler)		
Command DuckerDecay	Value 5 to 50000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# DuckerDecay example InterfaceName.Update('DuckerDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerDecay', None, FeedbackHandler)		
Command DuckerHold	Value 0 to 1000 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# DuckerHold example InterfaceName.Update('DuckerHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerHold', None, FeedbackHandler)		

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Command	Value		
DuckerRange	-60 to 0 in steps of 0.1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# DuckerRange example InterfaceName.Update('DuckerRange', {'Name': 'String'}) Value = InterfaceName.ReadStatus('DuckerRange', {'Name': 'String'}) InterfaceName.SubscribeStatus('DuckerRange', None, FeedbackHandler)			
Command	Value	Value	
FaultStatus	'Fault'	'No Fault'	
# FaultStatus example InterfaceName.Update('FaultStatus') Value = InterfaceName.ReadStatus('FaultStatus') InterfaceName.SubscribeStatus('FaultStatus', None, FeedbackHandler)			
Command	Value		
Gain	-60.5 to 12 in steps of 0.5		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# Gain example InterfaceName.Update('Gain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('Gain', {'Name': 'String'}) InterfaceName.SubscribeStatus('Gain', None, FeedbackHandler)			
Command	Value	Value	
GainMute	'On'	'Off'	
Qualifier Key	Qualifier Value		
'Name'	'String'		
# GainMute example InterfaceName.Update('GainMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GainMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('GainMute', None, FeedbackHandler)			
Command	Value		
GateDecay	5 to 50000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# GateDecay example InterfaceName.Update('GateDecay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateDecay', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateDecay', None, FeedbackHandler)			
Command	Value	Value	Value
GateDetector	'Left'	'Right'	'Mix'
	'Sidechain'		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# GateDetector example InterfaceName.Update('GateDetector', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateDetector', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateDetector', None, FeedbackHandler)			
Command	Value		
GateHold	0 to 1000 in steps of 1		
Qualifier Key	Qualifier Value		
'Name'	'String'		
# GateHold example InterfaceName.Update('GateHold', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateHold', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateHold', None, FeedbackHandler)			

Command GateRange	Value -70 to 0 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
# GateRange example InterfaceName.Update('GateRange', {'Name': 'String'}) Value = InterfaceName.ReadStatus('GateRange', {'Name': 'String'}) InterfaceName.SubscribeStatus('GateRange', None, FeedbackHandler)			
Command GPOMode	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Pin'	Qualifier Value '1' – '5'		
# GPOMode example InterfaceName.Update('GPOMode', {'Name': 'String', 'Pin': '1'}) Value = InterfaceName.ReadStatus('GPOMode', {'Name': 'String', 'Pin': '1'}) InterfaceName.SubscribeStatus('GPOMode', None, FeedbackHandler)			
Command GraphicEQLevel	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Frequency'	Qualifier Value '20Hz' '40Hz' '80Hz' '160Hz' '315Hz' '630Hz' '1.25kHz' '2.5kHz' '5kHz' '10kHz' '20kHz'	Qualifier Value '25Hz' '50Hz' '100Hz' '200Hz' '400Hz' '800Hz' '1.6kHz' '3.15kHz' '6.3kHz' '12.5kHz'	Qualifier Value '31.5Hz' '63Hz' '125Hz' '250Hz' '500Hz' '1kHz' '2kHz' '4kHz' '8kHz' '16kHz'
# GraphicEQLevel example InterfaceName.Update('GraphicEQLevel', {'Name': 'String', 'Frequency': '20Hz'}) Value = InterfaceName.ReadStatus('GraphicEQLevel', {'Name': 'String', 'Frequency': '20Hz'}) InterfaceName.SubscribeStatus('GraphicEQLevel', None, FeedbackHandler)			
Command GroupLevel	Value -60 to 12 in steps of 0.5		
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
# GroupLevel example InterfaceName.Update('GroupLevel', {'Group': '1'}) Value = InterfaceName.ReadStatus('GroupLevel', {'Group': '1'}) InterfaceName.SubscribeStatus('GroupLevel', None, FeedbackHandler)			
Command GroupMute	Value 'On'	Value 'Off'	
Qualifier Key 'Group'	Qualifier Value '1' – '64'		
# GroupMute example InterfaceName.Update('GroupMute', {'Group': '1'}) Value = InterfaceName.ReadStatus('GroupMute', {'Group': '1'}) InterfaceName.SubscribeStatus('GroupMute', None, FeedbackHandler)			

Command MatrixMixerLevel	Value -60.5 to 0 in steps of 0.5
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Input'	Qualifier Value '1' – '32'
Qualifier Key 'Output'	Qualifier Value '1' – '32'
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'
<pre># MatrixMixerLevel example InterfaceName.Update('MatrixMixerLevel', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) Value = InterfaceName.ReadStatus('MatrixMixerLevel', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) InterfaceName.SubscribeStatus('MatrixMixerLevel', None, FeedbackHandler)</pre>	
Command MatrixMixerState	Value 'On' Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Input'	Qualifier Value '1' – '32'
Qualifier Key 'Output'	Qualifier Value '1' – '32'
Qualifier Key 'Matrix Size'	Qualifier Value '1' – '32'
<pre># MatrixMixerState example InterfaceName.Update('MatrixMixerState', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) Value = InterfaceName.ReadStatus('MatrixMixerState', {'Name': 'String', 'Input': '1', 'Output': '1', 'Matrix Size': '1'}) InterfaceName.SubscribeStatus('MatrixMixerState', None, FeedbackHandler)</pre>	
Command ParameterRecall	Value '1' – '255' Value 'None'
<pre># ParameterRecall example InterfaceName.Update('ParameterRecall') Value = InterfaceName.ReadStatus('ParameterRecall') InterfaceName.SubscribeStatus('ParameterRecall', None, FeedbackHandler)</pre>	
Command ParametricEQFrequency	Value 20 to 20000 in steps of 1
Qualifier Key 'Name'	Qualifier Value 'String'
Qualifier Key 'Band'	Qualifier Value '1' – '16'
<pre># ParametricEQFrequency example InterfaceName.Update('ParametricEQFrequency', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQFrequency', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQFrequency', None, FeedbackHandler)</pre>	

Command ParametricEQGain	Value -20 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQGain example InterfaceName.Update('ParametricEQGain', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQGain', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQGain', None, FeedbackHandler)			
Command ParametricEQQ	Value 0.1 to 14 in steps of 0.001		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQQ example InterfaceName.Update('ParametricEQQ', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQQ', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQQ', None, FeedbackHandler)			
Command ParametricEQSlope			
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQSlope example InterfaceName.Update('ParametricEQSlope', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQSlope', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQSlope', None, FeedbackHandler)			
Command ParametricEQType	Value 'PEQ' 'Low Pass'	Value 'High Shelf' 'High Pass'	Value 'Low Shelf' 'Notch'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Band'	Qualifier Value '1' – '16'		
# ParametricEQType example InterfaceName.Update('ParametricEQType', {'Name': 'String', 'Band': '1'}) Value = InterfaceName.ReadStatus('ParametricEQType', {'Name': 'String', 'Band': '1'}) InterfaceName.SubscribeStatus('ParametricEQType', None, FeedbackHandler)			
Command PeakRMSInputDetect	Value 'Left' 'Sidechain'	Value 'Right'	Value 'Mix'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PeakRMSInputDetect example InterfaceName.Update('PeakRMSInputDetect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PeakRMSInputDetect', {'Name': 'String'}) InterfaceName.SubscribeStatus('PeakRMSInputDetect', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Command PeakRMSRMS	Value 500 to 10000 in steps of 100		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Function'	Qualifier Value 'Attack'	Qualifier Value 'Release'	
# PeakRMSRMS example InterfaceName.Update('PeakRMSRMS', {'Name': 'String', 'Function': 'Attack'}) Value = InterfaceName.ReadStatus('PeakRMSRMS', {'Name': 'String', 'Function': 'Attack'}) InterfaceName.SubscribeStatus('PeakRMSRMS', None, FeedbackHandler)			
Command PSTNCallActive	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNCallActive example InterfaceName.Update('PSTNCallActive', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNCallActive', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNCallActive', None, FeedbackHandler)			
Command PSTNCallStatus	Value 'Hangup' 'Error'	Value 'Incoming'	Value 'Active'
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNCallStatus example InterfaceName.Update('PSTNCallStatus', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNCallStatus', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNCallStatus', None, FeedbackHandler)			
Command PSTNCallerID	Value 'String'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Date' 'Name'	Qualifier Value 'Time'	Qualifier Value 'Number'
# PSTNCallerID example InterfaceName.Update('PSTNCallerID', {'Name': 'String', 'Type': 'Date'}) Value = InterfaceName.ReadStatus('PSTNCallerID', {'Name': 'String', 'Type': 'Date'}) InterfaceName.SubscribeStatus('PSTNCallerID', None, FeedbackHandler)			
Command PSTNHook	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNHook example InterfaceName.Update('PSTNHook', {'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNHook', {'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNHook', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command PSTNLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNLevel example InterfaceName.Update('PSTNLevel', {'Module': 'Input', 'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNLevel', {'Module': 'Input', 'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNLevel', None, FeedbackHandler)			
Command PSTNMute	Value 'On'	Value 'Off'	
Qualifier Key 'Module'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# PSTNMute example InterfaceName.Update('PSTNMute', {'Module': 'Input', 'Name': 'String'}) Value = InterfaceName.ReadStatus('PSTNMute', {'Module': 'Input', 'Name': 'String'}) InterfaceName.SubscribeStatus('PSTNMute', None, FeedbackHandler)			
Command RoomCombineLayout	Value 'Join'	Value 'Split'	
Qualifier Key 'Group'	Qualifier Value '1' – '6'		
Qualifier Key 'Room 1'	Qualifier Value '1' – '6'		
Qualifier Key 'Room 2'	Qualifier Value '1' – '6'		
# RoomCombineLayout example InterfaceName.Update('RoomCombineLayout', {'Group': '1', 'Room 1': '3', 'Room 2': '6'}) Value = InterfaceName.ReadStatus('RoomCombineLayout', {'Group': '1', 'Room 1': '3', 'Room 2': '6'}) InterfaceName.SubscribeStatus('RoomCombineLayout', None, FeedbackHandler)			
Command RouterInputSelect	Value '0' – '32'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Output'	Qualifier Value '1' – '32'		
# RouterInputSelect example InterfaceName.Update('RouterInputSelect', {'Name': 'String', 'Output': '1'}) Value = InterfaceName.ReadStatus('RouterInputSelect', {'Name': 'String', 'Output': '1'}) InterfaceName.SubscribeStatus('RouterInputSelect', None, FeedbackHandler)			
Command SignalGeneratorGain	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Wave'	Qualifier Value 'Sine' 'Sweep'	Qualifier Value 'White'	Qualifier Value 'Pink'
# SignalGeneratorGain example InterfaceName.Update('SignalGeneratorGain', {'Name': 'String', 'Wave': 'Sine'}) Value = InterfaceName.ReadStatus('SignalGeneratorGain', {'Name': 'String', 'Wave': 'Sine'}) InterfaceName.SubscribeStatus('SignalGeneratorGain', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command SignalGeneratorMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Wave'	Qualifier Value 'Sine'	Qualifier Value 'White' Qualifier Value 'Pink'
# SignalGeneratorMute example InterfaceName.Update('SignalGeneratorMute', {'Name': 'String', 'Wave': 'Sine'}) Value = InterfaceName.ReadStatus('SignalGeneratorMute', {'Name': 'String', 'Wave': 'Sine'}) InterfaceName.SubscribeStatus('SignalGeneratorMute', None, FeedbackHandler)		
Command SourceSelect	Value '1' – '32'	
Qualifier Key 'Name'	Qualifier Value 'String'	
# SourceSelect example InterfaceName.Update('SourceSelect', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SourceSelect', {'Name': 'String'}) InterfaceName.SubscribeStatus('SourceSelect', None, FeedbackHandler)		
Command SpeakerParametricAlignDelay	Value 0 to 480 in steps of 1	
Qualifier Key 'Name'	Qualifier Value 'String'	
# SpeakerParametricAlignDelay example InterfaceName.Update('SpeakerParametricAlignDelay', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SpeakerParametricAlignDelay', {'Name': 'String'}) InterfaceName.SubscribeStatus('SpeakerParametricAlignDelay', None, FeedbackHandler)		
Command SpeakerParametricBypass	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'
# SpeakerParametricBypass example InterfaceName.Update('SpeakerParametricBypass', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricBypass', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricBypass', None, FeedbackHandler)		
Command SpeakerParametricEQBandBypass	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'	
# SpeakerParametricEQBandBypass example InterfaceName.Update('SpeakerParametricEQBandBypass', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandBypass', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandBypass', None, FeedbackHandler)		

Command SpeakerParametricEQBandFilter	Value 'PEQ'	Value 'High Shelf'	Value 'Low Shelf'
	'Notch'		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFilter example InterfaceName.Update('SpeakerParametricEQBandFilter', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandFilter', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandFilter', None, FeedbackHandler)			
Command SpeakerParametricEQBandFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandFrequency example InterfaceName.Update('SpeakerParametricEQBandFrequency', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandFrequency', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandFrequency', None, FeedbackHandler)			
Command SpeakerParametricEQBandGain	Value -20 to 20 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandGain example InterfaceName.Update('SpeakerParametricEQBandGain', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandGain', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandGain', None, FeedbackHandler)			
Command SpeakerParametricEQBandQ	Value 0.1 to 10 in steps of 0.001		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value '1' – '9'		
# SpeakerParametricEQBandQ example InterfaceName.Update('SpeakerParametricEQBandQ', {'Name': 'String', 'Index 1': '1'}) Value = InterfaceName.ReadStatus('SpeakerParametricEQBandQ', {'Name': 'String', 'Index 1': '1'}) InterfaceName.SubscribeStatus('SpeakerParametricEQBandQ', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command SpeakerParametricFilter	Value 'Butterworth 6dB/oct' 'Butterworth 24dB/oct' 'Bessel 12dB/oct' 'Bessel 36dB/oct' 'Linkwitz-Reily 24dB/oct'	Value 'Butterworth 12dB/oct' 'Butterworth 36dB/oct' 'Bessel 18dB/oct' 'Bessel 48dB/oct' 'Linkwitz-Reily 36dB/oct'	Value 'Butterworth 18dB/oct' 'Butterworth 48dB/oct' 'Bessel 24dB/oct' 'Linkwitz-Reily 12dB/oct' 'Linkwitz-Reily 48dB/oct'
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFilter example InterfaceName.Update('SpeakerParametricFilter', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricFilter', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricFilter', None, FeedbackHandler)			
Command SpeakerParametricFrequency	Value 20 to 20000 in steps of 1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'High'	Qualifier Value 'Low'	
# SpeakerParametricFrequency example InterfaceName.Update('SpeakerParametricFrequency', {'Name': 'String', 'Type': 'High'}) Value = InterfaceName.ReadStatus('SpeakerParametricFrequency', {'Name': 'String', 'Type': 'High'}) InterfaceName.SubscribeStatus('SpeakerParametricFrequency', None, FeedbackHandler)			
Command SpeakerParametricGain	Value -15 to 15 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
# SpeakerParametricGain example InterfaceName.Update('SpeakerParametricGain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SpeakerParametricGain', {'Name': 'String'}) InterfaceName.SubscribeStatus('SpeakerParametricGain', None, FeedbackHandler)			
Command StandardMixerLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'	
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'		
# StandardMixerLevel example InterfaceName.Update('StandardMixerLevel', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) Value = InterfaceName.ReadStatus('StandardMixerLevel', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) InterfaceName.SubscribeStatus('StandardMixerLevel', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Command StandardMixerMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Index 1'	Qualifier Value 'Input'	Qualifier Value 'Output'
Qualifier Key 'Index 2'	Qualifier Value '1' – '32'	
# StandardMixerMute example InterfaceName.Update('StandardMixerMute', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) Value = InterfaceName.ReadStatus('StandardMixerMute', {'Name': 'String', 'Index 1': 'Input', 'Index 2': '1'}) InterfaceName.SubscribeStatus('StandardMixerMute', None, FeedbackHandler)		
Command StandardMixerRouting	Value 'Route'	Value 'Unroute'
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Input'	Qualifier Value '1' – '32'	
Qualifier Key 'Output'	Qualifier Value '1' – '32'	
# StandardMixerRouting example InterfaceName.Update('StandardMixerRouting', {'Name': 'String', 'Input': '1', 'Output': '1'}) Value = InterfaceName.ReadStatus('StandardMixerRouting', {'Name': 'String', 'Input': '1', 'Output': '1'}) InterfaceName.SubscribeStatus('StandardMixerRouting', None, FeedbackHandler)		
Command StandardRoomCombiner MainInputGain	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# StandardRoomCombinerMainInputGain example InterfaceName.Update('StandardRoomCombinerMainInputGain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('StandardRoomCombinerMainInputGain', {'Name': 'String'}) InterfaceName.SubscribeStatus('StandardRoomCombinerMainInputGain', None, FeedbackHandler)		
Command StandardRoomCombiner MainInputMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# StandardRoomCombinerMainInputMute example InterfaceName.Update('StandardRoomCombinerMainInputMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('StandardRoomCombinerMainInputMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('StandardRoomCombinerMainInputMute', None, FeedbackHandler)		
Command StandardRoomCombiner MainOutputGain	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# StandardRoomCombinerMainOutputGain example InterfaceName.Update('StandardRoomCombinerMainOutputGain', {'Name': 'String'}) Value = InterfaceName.ReadStatus('StandardRoomCombinerMainOutputGain', {'Name': 'String'}) InterfaceName.SubscribeStatus('StandardRoomCombinerMainOutputGain', None, FeedbackHandler)		

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Command StandardRoomCombinerMainOutputMute	Value 'On' 'Off'		
Qualifier Key 'Name'	Qualifier Value 'String'		
# StandardRoomCombinerMainOutputMute example InterfaceName.Update('StandardRoomCombinerMainOutputMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('StandardRoomCombinerMainOutputMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('StandardRoomCombinerMainOutputMute', None, FeedbackHandler)			
Command SurroundInputLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Level'	Qualifier Value 'Left Front' 'Right Surround' 'Back Surround Left'	Qualifier Value 'Right Front' 'Center' 'Back Surround Right'	Qualifier Value 'Left Surround' 'LFE (Sub)'
# SurroundInputLevel example InterfaceName.Update('SurroundInputLevel', {'Name': 'String', 'Level': 'Left Front'}) Value = InterfaceName.ReadStatus('SurroundInputLevel', {'Name': 'String', 'Level': 'Left Front'}) InterfaceName.SubscribeStatus('SurroundInputLevel', None, FeedbackHandler)			
Command SurroundInputOutputFormat	Value 'No Signal' 'DTS 5.1' 'Dolby1.0' 'DTS2.0' 'DTS4.0'	Value 'PCM' 'DTS 5.1 Discrete' 'Dolby2.0' 'DTS2.1' 'DTS5.0'	Value 'Dolby5.1' 'DTS 5.1 Matrix' 'DTS1.0' 'DTS3.0'
Qualifier Key 'Name'	Qualifier Value 'String'		
# SurroundInputOutputFormat example InterfaceName.Update('SurroundInputOutputFormat', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SurroundInputOutputFormat', {'Name': 'String'}) InterfaceName.SubscribeStatus('SurroundInputOutputFormat', None, FeedbackHandler)			
Command SurroundInputRoomType	Value 'Small'	Value 'Large'	Value 'None'
Qualifier Key 'Name'	Qualifier Value 'String'		
# SurroundInputRoomType example InterfaceName.Update('SurroundInputRoomType', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SurroundInputRoomType', {'Name': 'String'}) InterfaceName.SubscribeStatus('SurroundInputRoomType', None, FeedbackHandler)			
Command SurroundInputSource	Value 'Optical'	Value 'Coaxial'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# SurroundInputSource example InterfaceName.Update('SurroundInputSource', {'Name': 'String'}) Value = InterfaceName.ReadStatus('SurroundInputSource', {'Name': 'String'}) InterfaceName.SubscribeStatus('SurroundInputSource', None, FeedbackHandler)			

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Command ToneControlGain	Value -15 to 15 in steps of 0.1		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'Low'	Qualifier Value 'Mid'	Qualifier Value 'High'
# ToneControlGain example InterfaceName.Update('ToneControlGain', {'Name': 'String', 'Type': 'Low'}) Value = InterfaceName.ReadStatus('ToneControlGain', {'Name': 'String', 'Type': 'Low'}) InterfaceName.SubscribeStatus('ToneControlGain', None, FeedbackHandler)			
Command USBLevel	Value -60.5 to 12 in steps of 0.5		
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'	
# USBLevel example InterfaceName.Update('USBLevel', {'Name': 'String', 'Channel': 'Left'}) Value = InterfaceName.ReadStatus('USBLevel', {'Name': 'String', 'Channel': 'Left'}) InterfaceName.SubscribeStatus('USBLevel', None, FeedbackHandler)			
Command USBMute	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
Qualifier Key 'Channel'	Qualifier Value 'Left'	Qualifier Value 'Right'	
# USBMute example InterfaceName.Update('USBMute', {'Name': 'String', 'Channel': 'Left'}) Value = InterfaceName.ReadStatus('USBMute', {'Name': 'String', 'Channel': 'Left'}) InterfaceName.SubscribeStatus('USBMute', None, FeedbackHandler)			
Command VoIPCallActive	Value 'On'	Value 'Off'	
Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPCallActive example InterfaceName.Update('VoIPCallActive', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPCallActive', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPCallActive', None, FeedbackHandler)			
Command VoIPCallStatus	Value 'Incoming' 'Active'	Value 'Dialing' 'Hangup'	Value 'Ringback' 'Hold State Peer'
Qualifier Key 'Name'	Qualifier Value 'String'		
# VoIPCallStatus example InterfaceName.Update('VoIPCallStatus', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPCallStatus', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPCallStatus', None, FeedbackHandler)			

Global Scripter Module Communication Sheet

Command VoIPCallerID	Value 'String'	
Qualifier Key 'Name'	Qualifier Value 'String'	
Qualifier Key 'Type'	Qualifier Value 'Name'	Qualifier Value 'Hostname'
# VoIPCallerID example InterfaceName.Update('VoIPCallerID', {'Name': 'String', 'Type': 'Name'}) Value = InterfaceName.ReadStatus('VoIPCallerID', {'Name': 'String', 'Type': 'Name'}) InterfaceName.SubscribeStatus('VoIPCallerID', None, FeedbackHandler)		
Command VoIPLevel	Value -60.5 to 12 in steps of 0.5	
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPLevel example InterfaceName.Update('VoIPLevel', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPLevel', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPLevel', None, FeedbackHandler)		
Command VoIPMute	Value 'On'	Value 'Off'
Qualifier Key 'Name'	Qualifier Value 'String'	
# VoIPMute example InterfaceName.Update('VoIPMute', {'Name': 'String'}) Value = InterfaceName.ReadStatus('VoIPMute', {'Name': 'String'}) InterfaceName.SubscribeStatus('VoIPMute', None, FeedbackHandler)		

Cable and Adapter Requirements

Captive Screw to Female DB9 RS-232 Serial Cable (ESP models)

Captive Screw to Captive Screw RS-232 Serial Cable (EX-1280C model)

Notes for the Device

The ControlSpace ESP-00, ControlSpace ESP-00 Series II, and ControlSpace ESP-88 support a default baud rate of 38400. All other models that support serial control support a default baud rate of 115200. Serial control is not available for the PowerMatch models.

Serial communication

Port Type: RS-232

Baud Rate: 115200

Data Bits: 8


Parity: None

Stop Bits: One

Flow Control: None

Pin Assignments Diagram


ESP models:




Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



EX-1280C model:



Signal	Main Cable	Signal
TxD	↔	TxD
RxD	↔	RxD
GND	→	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet

Default Port: 10055

Logon Credentials Supported: No

Multi-Connection Capabilities: Yes

Port Changeability: Yes

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

The ControlSpace ESP-00, ControlSpace ESP-00 Series II, ControlSpace ESP-88, and all PowerMatch models do not support port changeability. All other ESP and EX models support port changeability, and you must enable **Enable Serial over IP** within the device's properties. This can be accessed by right clicking the device block in the Project View tab within the Bose ControlSpace Designer software.

Appendix A. Set Commands

AEC CN Enable Off Index 1 1 Name testString	SA"testString">1>8=F\x0D
AEC CN Enable Off Index 1 12 Name testString	SA"testString">12>8=F\x0D
AEC CN Enable On Index 1 1 Name testString	SA"testString">1>8=0\x0D
AEC CN Enable On Index 1 12 Name testString	SA"testString">12>8=0\x0D
AEC Enable Off Index 1 1 Name testString	SA"testString">1>6=F\x0D
AEC Enable Off Index 1 12 Name testString	SA"testString">12>6=F\x0D
AEC Enable On Index 1 1 Name testString	SA"testString">1>6=0\x0D
AEC Enable On Index 1 12 Name testString	SA"testString">12>6=0\x0D
AEC Internal Mute Off Index 1 1 Name testString	SA"testString">1>5=F\x0D
AEC Internal Mute Off Index 1 12 Name testString	SA"testString">12>5=F\x0D
AEC Internal Mute On Index 1 1 Name testString	SA"testString">1>5=0\x0D
AEC Internal Mute On Index 1 12 Name testString	SA"testString">12>5=0\x0D
AEC NLP Control Light Index 1 1 Name testString	SA"testString">1>7=1\x0D
AEC NLP Control Light Index 1 12 Name testString	SA"testString">12>7=1\x0D
AEC NLP Control Medium Index 1 1 Name testString	SA"testString">1>7=2\x0D
AEC NLP Control Medium Index 1 12 Name testString	SA"testString">12>7=2\x0D
AEC NLP Control Strong Index 1 1 Name testString	SA"testString">1>7=3\x0D
AEC NLP Control Strong Index 1 12 Name testString	SA"testString">12>7=3\x0D
AEC NR Level 0 Index 1 1 Name testString	SA"testString">1>9=0\x0D
AEC NR Level 0 Index 1 12 Name testString	SA"testString">12>9=0\x0D
AEC NR Level 24 Index 1 1 Name testString	SA"testString">1>9=24\x0D
AEC NR Level 24 Index 1 12 Name testString	SA"testString">12>9=24\x0D
AMM Gain Sharing Attack 0 Name testString	SA"testString">0>4=0.0\x0D
AMM Gain Sharing Attack 100 Name testString	SA"testString">0>4=100.0\x0D
AMM Gain Sharing Bypass Off Index 1 1 Name testString	SA"testString">1>4=F\x0D
AMM Gain Sharing Bypass Off Index 1 32 Name testString	SA"testString">32>4=F\x0D
AMM Gain Sharing Bypass On Index 1 1 Name testString	SA"testString">1>4=0\x0D
AMM Gain Sharing Bypass On Index 1 32 Name testString	SA"testString">32>4=0\x0D
AMM Gain Sharing Decay 5 Name testString	SA"testString">0>6=5\x0D
AMM Gain Sharing Decay 50000 Name testString	SA"testString">0>6=50000\x0D
AMM Gain Sharing Gain 12 Index 1 0 Name testString	SA"testString">0>1=12.0\x0D
AMM Gain Sharing Gain 12 Index 1 32 Name testString	SA"testString">32>1=12.0\x0D
AMM Gain Sharing Gain -60 Index 1 0 Name testString	SA"testString">0>1=-60.0\x0D
AMM Gain Sharing Gain -60 Index 1 32 Name testString	SA"testString">32>1=-60.0\x0D
AMM Gain Sharing Hold 0 Name testString	SA"testString">0>5=0\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

AMM Gain Sharing Hold 1000 Name testString	SA"testString">0>5=1000\x0D
AMM Gain Sharing Mute Off Index 1 0 Name testString	SA"testString">0>2=F\x0D
AMM Gain Sharing Mute Off Index 1 32 Name testString	SA"testString">32>2=F\x0D
AMM Gain Sharing Mute On Index 1 0 Name testString	SA"testString">0>2=0\x0D
AMM Gain Sharing Mute On Index 1 32 Name testString	SA"testString">32>2=0\x0D
AMM Gain Sharing Priority 1 Index 1 1 Name testString	SA"testString">1>3=1\x0D
AMM Gain Sharing Priority 1 Index 1 32 Name testString	SA"testString">32>3=1\x0D
AMM Gain Sharing Priority 5 Index 1 1 Name testString	SA"testString">1>3=5\x0D
AMM Gain Sharing Priority 5 Index 1 32 Name testString	SA"testString">32>3=5\x0D
AMM Gain Sharing RMS Average 1 Type Input Name testString	SA"testString">0>7=1\x0D
AMM Gain Sharing RMS Average 1 Type Output Name testString	SA"testString">0>8=1\x0D
AMM Gain Sharing RMS Average 500 Type Input Name testString	SA"testString">0>7=500\x0D
AMM Gain Sharing RMS Average 500 Type Output Name testString	SA"testString">0>8=500\x0D
AMM Gain Sharing Slope 0 Name testString	SA"testString">0>3=0.00\x0D
AMM Gain Sharing Slope 2 Name testString	SA"testString">0>3=2.00\x0D
AMM Gated Attack 0 Index 1 1 Name testString	SA"testString">1>14=0.0\x0D
AMM Gated Attack 0 Index 1 32 Name testString	SA"testString">32>14=0.0\x0D
AMM Gated Attack 0 Index 1 8 Name testString	SA"testString">8>14=0.0\x0D
AMM Gated Attack 100 Index 1 1 Name testString	SA"testString">1>14=100.0\x0D
AMM Gated Attack 100 Index 1 8 Name testString	SA"testString">8>14=100.0\x0D
AMM Gated Attack 500 Index 1 1 Name testString	SA"testString">1>14=500.0\x0D
AMM Gated Attack 500 Index 1 32 Name testString	SA"testString">32>14=500.0\x0D
AMM Gated Decay 1 Index 1 1 Name testString	SA"testString">1>8=1\x0D
AMM Gated Decay 1 Index 1 1 Name testString	SA"testString">1>16=1\x0D
AMM Gated Decay 1 Index 1 32 Name testString	SA"testString">32>8=1\x0D
AMM Gated Decay 1 Index 1 32 Name testString	SA"testString">32>16=1\x0D
AMM Gated Decay 5 Index 1 1 Name testString	SA"testString">1>8=5\x0D
AMM Gated Decay 5 Index 1 1 Name testString	SA"testString">1>16=5\x0D
AMM Gated Decay 5 Index 1 8 Name testString	SA"testString">8>8=5\x0D
AMM Gated Decay 5 Index 1 8 Name testString	SA"testString">8>16=5\x0D
AMM Gated Decay 50000 Index 1 1 Name testString	SA"testString">1>8=50000\x0D
AMM Gated Decay 50000 Index 1 1 Name testString	SA"testString">1>16=50000\x0D
AMM Gated Decay 50000 Index 1 32 Name testString	SA"testString">32>8=50000\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated Decay 50000 Index 1 32 Name testString	SA"testString">32>16=50000\x0D
AMM Gated Decay 50000 Index 1 8 Name testString	SA"testString">8>8=50000\x0D
AMM Gated Decay 50000 Index 1 8 Name testString	SA"testString">8>16=50000\x0D
AMM Gated Detection Bypass Index 1 1 Name testString	SA"testString">1>3=4\x0D
AMM Gated Detection Bypass Index 1 8 Name testString	SA"testString">8>3=4\x0D
AMM Gated Detection LastOn Index 1 1 Name testString	SA"testString">1>3=2\x0D
AMM Gated Detection LastOn Index 1 8 Name testString	SA"testString">8>3=2\x0D
AMM Gated Detection PushToTalk Index 1 1 Name testString	SA"testString">1>3=3\x0D
AMM Gated Detection PushToTalk Index 1 8 Name testString	SA"testString">8>3=3\x0D
AMM Gated Detection Threshold Index 1 1 Name testString	SA"testString">1>3=1\x0D
AMM Gated Detection Threshold Index 1 8 Name testString	SA"testString">8>3=1\x0D
AMM Gated Ducking Depth 0 Index 1 1 Name testString	SA"testString">1>7=0.0\x0D
AMM Gated Ducking Depth 0 Index 1 1 Name testString	SA"testString">1>12=0.0\x0D
AMM Gated Ducking Depth 0 Index 1 32 Name testString	SA"testString">32>7=0.0\x0D
AMM Gated Ducking Depth 0 Index 1 32 Name testString	SA"testString">32>12=0.0\x0D
AMM Gated Ducking Depth 0 Index 1 8 Name testString	SA"testString">8>7=0.0\x0D
AMM Gated Ducking Depth 0 Index 1 8 Name testString	SA"testString">8>12=0.0\x0D
AMM Gated Ducking Depth -60 Index 1 1 Name testString	SA"testString">1>7=-60.0\x0D
AMM Gated Ducking Depth -60 Index 1 1 Name testString	SA"testString">1>12=-60.0\x0D
AMM Gated Ducking Depth -60 Index 1 32 Name testString	SA"testString">32>7=-60.0\x0D
AMM Gated Ducking Depth -60 Index 1 32 Name testString	SA"testString">32>12=-60.0\x0D
AMM Gated Ducking Depth -60 Index 1 8 Name testString	SA"testString">8>7=-60.0\x0D
AMM Gated Ducking Depth -60 Index 1 8 Name testString	SA"testString">8>12=-60.0\x0D
AMM Gated Gain 0 Index 1 0 Name testString	SA"testString">0>1=0.0\x0D
AMM Gated Gain 0 Index 1 8 Name testString	SA"testString">8>2=0.0\x0D
AMM Gated Gain 12 Index 1 0 Name testString	SA"testString">0>1=12.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated Gain 12 Index 1 32 Name testString	SA"testString">32>2=12.0\x0D
AMM Gated Gain -60 Index 1 0 Name testString	SA"testString">0>1=-60.0\x0D
AMM Gated Gain -60 Index 1 32 Name testString	SA"testString">32>2=-60.0\x0D
AMM Gated Gain -60 Index 1 8 Name testString	SA"testString">8>2=-60.0\x0D
AMM Gated Gate Depth 0 Index 1 1 Name testString	SA"testString">1>5=0.0\x0D
AMM Gated Gate Depth 0 Index 1 1 Name testString	SA"testString">1>13=0.0\x0D
AMM Gated Gate Depth 0 Index 1 32 Name testString	SA"testString">32>5=0.0\x0D
AMM Gated Gate Depth 0 Index 1 32 Name testString	SA"testString">32>13=0.0\x0D
AMM Gated Gate Depth 0 Index 1 8 Name testString	SA"testString">8>5=0.0\x0D
AMM Gated Gate Depth 0 Index 1 8 Name testString	SA"testString">8>13=0.0\x0D
AMM Gated Gate Depth -70 Index 1 1 Name testString	SA"testString">1>5=-70.0\x0D
AMM Gated Gate Depth -70 Index 1 1 Name testString	SA"testString">1>13=-70.0\x0D
AMM Gated Gate Depth -70 Index 1 32 Name testString	SA"testString">32>5=-70.0\x0D
AMM Gated Gate Depth -70 Index 1 32 Name testString	SA"testString">32>13=-70.0\x0D
AMM Gated Gate Depth -70 Index 1 8 Name testString	SA"testString">8>5=-70.0\x0D
AMM Gated Gate Depth -70 Index 1 8 Name testString	SA"testString">8>13=-70.0\x0D
AMM Gated High Pass 1000 Index 1 1 Name testString	SA"testString">1>10=1000\x0D
AMM Gated High Pass 1000 Index 1 1 Name testString	SA"testString">1>10=1000.0\x0D
AMM Gated High Pass 1000 Index 1 8 Name testString	SA"testString">8>10=1000\x0D
AMM Gated High Pass 1000 Index 1 8 Name testString	SA"testString">8>10=1000.0\x0D
AMM Gated High Pass 20 Index 1 1 Name testString	SA"testString">1>10=20\x0D
AMM Gated High Pass 20 Index 1 1 Name testString	SA"testString">1>10=20.0\x0D
AMM Gated High Pass 20 Index 1 32 Name testString	SA"testString">32>10=20\x0D
AMM Gated High Pass 20 Index 1 32 Name testString	SA"testString">32>10=20.0\x0D
AMM Gated High Pass 20 Index 1 8 Name testString	SA"testString">8>10=20\x0D
AMM Gated High Pass 20 Index 1 8 Name testString	SA"testString">8>10=20.0\x0D
AMM Gated High Pass 20000 Index 1 1 Name testString	SA"testString">1>10=20000\x0D
AMM Gated High Pass 20000 Index 1 1 Name testString	SA"testString">1>10=20000.0\x0D
AMM Gated High Pass 20000 Index 1 32 Name testString	SA"testString">32>10=20000\x0D
AMM Gated High Pass 20000 Index 1 32 Name testString	SA"testString">32>10=20000.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated Hold 1 Index 1 1 Name testString	SA"testString">1>6=1\x0D
AMM Gated Hold 1 Index 1 1 Name testString	SA"testString">1>15=1\x0D
AMM Gated Hold 1 Index 1 32 Name testString	SA"testString">32>6=1\x0D
AMM Gated Hold 1 Index 1 32 Name testString	SA"testString">32>15=1\x0D
AMM Gated Hold 1 Index 1 8 Name testString	SA"testString">8>6=1\x0D
AMM Gated Hold 1 Index 1 8 Name testString	SA"testString">8>15=1\x0D
AMM Gated Hold 50000 Index 1 1 Name testString	SA"testString">1>6=50000\x0D
AMM Gated Hold 50000 Index 1 1 Name testString	SA"testString">1>15=50000\x0D
AMM Gated Hold 50000 Index 1 32 Name testString	SA"testString">32>6=50000\x0D
AMM Gated Hold 50000 Index 1 32 Name testString	SA"testString">32>15=50000\x0D
AMM Gated Hold 50000 Index 1 8 Name testString	SA"testString">8>6=50000\x0D
AMM Gated Hold 50000 Index 1 8 Name testString	SA"testString">8>15=50000\x0D
AMM Gated Low Pass 20 Index 1 1 Name testString	SA"testString">1>11=20\x0D
AMM Gated Low Pass 20 Index 1 1 Name testString	SA"testString">1>9=20.0\x0D
AMM Gated Low Pass 20 Index 1 32 Name testString	SA"testString">32>11=20\x0D
AMM Gated Low Pass 20 Index 1 32 Name testString	SA"testString">32>9=20.0\x0D
AMM Gated Low Pass 20000 Index 1 1 Name testString	SA"testString">1>11=20000\x0D
AMM Gated Low Pass 20000 Index 1 1 Name testString	SA"testString">1>9=20000.0\x0D
AMM Gated Low Pass 20000 Index 1 32 Name testString	SA"testString">32>11=20000\x0D
AMM Gated Low Pass 20000 Index 1 32 Name testString	SA"testString">32>9=20000.0\x0D
AMM Gated Low Pass 20000 Index 1 8 Name testString	SA"testString">8>11=20000\x0D
AMM Gated Low Pass 20000 Index 1 8 Name testString	SA"testString">8>9=20000.0\x0D
AMM Gated Low Pass 300 Index 1 1 Name testString	SA"testString">1>11=300\x0D
AMM Gated Low Pass 300 Index 1 1 Name testString	SA"testString">1>9=300.0\x0D
AMM Gated Low Pass 300 Index 1 8 Name testString	SA"testString">8>11=300\x0D
AMM Gated Low Pass 300 Index 1 8 Name testString	SA"testString">8>9=300.0\x0D
AMM Gated Mute Off Index 1 0 Name testString	SA"testString">0>3=F\x0D
AMM Gated Mute Off Index 1 0 Name testString	SA"testString">0>2=F\x0D
AMM Gated Mute Off Index 1 32 Name testString	SA"testString">32>16=F\x0D
AMM Gated Mute Off Index 1 32 Name testString	SA"testString">32>3=F\x0D
AMM Gated Mute Off Index 1 8 Name testString	SA"testString">8>16=F\x0D
AMM Gated Mute Off Index 1 8 Name testString	SA"testString">8>3=F\x0D
AMM Gated Mute On Index 1 0 Name testString	SA"testString">0>3=0\x0D
AMM Gated Mute On Index 1 0 Name testString	SA"testString">0>2=0\x0D
AMM Gated Mute On Index 1 32 Name testString	SA"testString">32>16=0\x0D
AMM Gated Mute On Index 1 32 Name testString	SA"testString">32>3=0\x0D
AMM Gated Mute On Index 1 8 Name testString	SA"testString">8>16=0\x0D
AMM Gated Mute On Index 1 8 Name testString	SA"testString">8>3=0\x0D
AMM Gated NOM Off Name testString	SA"testString">0>2=F\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated NOM On Name testString	SA"testString">0>2=0\x0D
AMM Gated Priority 1 Index 1 1 Name testString	SA"testString">1>1=1\x0D
AMM Gated Priority 1 Index 1 32 Name testString	SA"testString">32>1=1\x0D
AMM Gated Priority 5 Index 1 1 Name testString	SA"testString">1>1=5\x0D
AMM Gated Priority 5 Index 1 32 Name testString	SA"testString">32>1=5\x0D
AMM Gated Priority Off Index 1 1 Name testString	SA"testString">1>1=F\x0D
AMM Gated Priority Off Index 1 8 Name testString	SA"testString">8>1=F\x0D
AMM Gated Priority On Index 1 1 Name testString	SA"testString">1>1=0\x0D
AMM Gated Priority On Index 1 8 Name testString	SA"testString">8>1=0\x0D
AMM Gated Push To Talk Off Index 1 1 Name testString	SA"testString">1>15=F\x0D
AMM Gated Push To Talk Off Index 1 8 Name testString	SA"testString">8>15=F\x0D
AMM Gated Push To Talk On Index 1 1 Name testString	SA"testString">1>15=0\x0D
AMM Gated Push To Talk On Index 1 8 Name testString	SA"testString">8>15=0\x0D
AMM Gated RMS Avg 1 Index 1 1 Name testString	SA"testString">1>12=1\x0D
AMM Gated RMS Avg 1 Index 1 1 Name testString	SA"testString">1>11=1\x0D
AMM Gated RMS Avg 1 Index 1 32 Name testString	SA"testString">32>12=1\x0D
AMM Gated RMS Avg 1 Index 1 32 Name testString	SA"testString">32>11=1\x0D
AMM Gated RMS Avg 1 Index 1 8 Name testString	SA"testString">8>12=1\x0D
AMM Gated RMS Avg 1 Index 1 8 Name testString	SA"testString">8>11=1\x0D
AMM Gated RMS Avg 1000 Index 1 1 Name testString	SA"testString">1>12=1000\x0D
AMM Gated RMS Avg 1000 Index 1 1 Name testString	SA"testString">1>11=1000\x0D
AMM Gated RMS Avg 1000 Index 1 32 Name testString	SA"testString">32>12=1000\x0D
AMM Gated RMS Avg 1000 Index 1 32 Name testString	SA"testString">32>11=1000\x0D
AMM Gated RMS Avg 500 Index 1 1 Name testString	SA"testString">1>12=500\x0D
AMM Gated RMS Avg 500 Index 1 1 Name testString	SA"testString">1>11=500\x0D
AMM Gated RMS Avg 500 Index 1 8 Name testString	SA"testString">8>12=500\x0D
AMM Gated RMS Avg 500 Index 1 8 Name testString	SA"testString">8>11=500\x0D
AMM Gated Threshold 0 Index 1 1 Name testString	SA"testString">1>4=0.0\x0D
AMM Gated Threshold 0 Index 1 1 Name testString	SA"testString">1>5=0.0\x0D
AMM Gated Threshold 0 Index 1 32 Name testString	SA"testString">32>4=0.0\x0D
AMM Gated Threshold 0 Index 1 32 Name testString	SA"testString">32>5=0.0\x0D
AMM Gated Threshold 0 Index 1 8 Name testString	SA"testString">8>4=0.0\x0D
AMM Gated Threshold 0 Index 1 8 Name testString	SA"testString">8>5=0.0\x0D
AMM Gated Threshold -60 Index 1 1 Name testString	SA"testString">1>4=-60.0\x0D
AMM Gated Threshold -60 Index 1 1 Name testString	SA"testString">1>5=-60.0\x0D
AMM Gated Threshold -60 Index 1 8 Name testString	SA"testString">8>4=-60.0\x0D
AMM Gated Threshold -60 Index 1 8 Name testString	SA"testString">8>5=-60.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated Threshold -80 Index 1 1 Name testString	SA"testString">1>4=-80.0\x0D
AMM Gated Threshold -80 Index 1 1 Name testString	SA"testString">1>5=-80.0\x0D
AMM Gated Threshold -80 Index 1 32 Name testString	SA"testString">32>4=-80.0\x0D
AMM Gated Threshold -80 Index 1 32 Name testString	SA"testString">32>5=-80.0\x0D
Array EQ Advanced Off Name testString	SA"testString">1>6=F\x0D
Array EQ Advanced On Name testString	SA"testString">1>6=0\x0D
Array EQ Center Frequency 100 Name testString	SA"testString">1>1=100\x0D
Array EQ Center Frequency 4000 Name testString	SA"testString">1>1=4000\x0D
Array EQ Tilt 0 Name testString	SA"testString">1>2=0.0\x0D
Array EQ Tilt 10 Name testString	SA"testString">1>2=10.0\x0D
Array EQ Vertical Angle 100 Name testString	SA"testString">1>8=100\x0D
Array EQ Vertical Angle 20 Name testString	SA"testString">1>8=20\x0D
Compressor/Limiter Input Detect Left Name testString	SA"testString">1=L\x0D
Compressor/Limiter Input Detect Mix Name testString	SA"testString">1=M\x0D
Compressor/Limiter Input Detect Right Name testString	SA"testString">1=R\x0D
Compressor/Limiter Input Detect Sidechain Name testString	SA"testString">1=S\x0D
Compressor/Limiter Ratio 1 Name testString	SA"testString">3=1.0\x0D
Compressor/Limiter Ratio 20 Name testString	SA"testString">3=20.0\x0D
Compressor/Limiter Release 1000 Name testString	SA"testString">5=1000.0\x0D
Compressor/Limiter Release 5 Name testString	SA"testString">5=5.0\x0D
Crossover Filter Bessel 12dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Bes12\x0D
Crossover Filter Bessel 12dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Bes12\x0D
Crossover Filter Bessel 12dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Bes12\x0D
Crossover Filter Bessel 18dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Bes18\x0D
Crossover Filter Bessel 18dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Bes18\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Crossover Filter Bessel 18dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Bes18\x0D
Crossover Filter Bessel 18dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Bes18\x0D
Crossover Filter Bessel 24dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Bes24\x0D
Crossover Filter Bessel 24dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Bes24\x0D
Crossover Filter Bessel 24dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Bes24\x0D
Crossover Filter Bessel 36dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Bes36\x0D
Crossover Filter Bessel 36dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Bes36\x0D
Crossover Filter Bessel 36dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Bes36\x0D
Crossover Filter Bessel 48dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Bes48\x0D
Crossover Filter Bessel 48dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Bes48\x0D
Crossover Filter Bessel 48dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Bes48\x0D
Crossover Filter Butterworth 12dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But12\x0D
Crossover Filter Butterworth 12dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But12\x0D

Global Scripter Module Communication Sheet

Index 1 4 Name testString	
Crossover Filter Butterworth 12dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But12\x0D
Crossover Filter Butterworth 12dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But12\x0D
Crossover Filter Butterworth 18dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But18\x0D
Crossover Filter Butterworth 18dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But18\x0D
Crossover Filter Butterworth 18dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But18\x0D
Crossover Filter Butterworth 24dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But24\x0D
Crossover Filter Butterworth 24dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But24\x0D
Crossover Filter Butterworth 24dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But24\x0D
Crossover Filter Butterworth 36dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But36\x0D
Crossover Filter Butterworth 36dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But36\x0D
Crossover Filter Butterworth 36dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But36\x0D
Crossover Filter Butterworth 48dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But48\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Crossover Filter Butterworth 48dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But48\x0D
Crossover Filter Butterworth 48dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But48\x0D
Crossover Filter Butterworth 48dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But48\x0D
Crossover Filter Butterworth 6dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=But6\x0D
Crossover Filter Butterworth 6dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=But6\x0D
Crossover Filter Butterworth 6dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=But6\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Lin12\x0D
Crossover Filter Linkwitz-Reily 12dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Lin12\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Lin24\x0D
Crossover Filter Linkwitz-Reily 24dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Lin24\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Type Mid	SA"testString">1>1=Lin36\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

HPF Index 1 1 Name testString	
Crossover Filter Linkwitz-Reily 36dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Lin36\x0D
Crossover Filter Linkwitz-Reily 36dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Lin36\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Low/High Index 1 1 Name testString	SA"testString">1>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Low/High Index 1 4 Name testString	SA"testString">4>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Mid HPF Index 1 1 Name testString	SA"testString">1>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Mid HPF Index 1 4 Name testString	SA"testString">4>1=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Mid LPF Index 1 1 Name testString	SA"testString">1>3=Lin48\x0D
Crossover Filter Linkwitz-Reily 48dB/oct Type Mid LPF Index 1 4 Name testString	SA"testString">4>3=Lin48\x0D
Crossover Frequency 20 Type Low/High Index 1 1 Name testString	SA"testString">1>2=20\x0D
Crossover Frequency 20 Type Low/High Index 1 4 Name testString	SA"testString">4>2=20\x0D
Crossover Frequency 20 Type Mid HPF Index 1 1 Name testString	SA"testString">1>2=20\x0D
Crossover Frequency 20 Type Mid HPF Index 1 4 Name testString	SA"testString">4>2=20\x0D
Crossover Frequency 20 Type Mid LPF Index 1 1 Name testString	SA"testString">1>4=20\x0D
Crossover Frequency 20 Type Mid LPF Index 1 4 Name testString	SA"testString">4>4=20\x0D
Crossover Frequency 20000 Type Low/High Index 1 1 Name testString	SA"testString">1>2=20000\x0D
Crossover Frequency 20000 Type Low/High Index 1 4 Name testString	SA"testString">4>2=20000\x0D
Crossover Frequency 20000 Type Mid HPF Index 1 1 Name testString	SA"testString">1>2=20000\x0D
Crossover Frequency 20000 Type Mid HPF Index 1 4 Name testString	SA"testString">4>2=20000\x0D
Crossover Frequency 20000 Type Mid LPF Index 1 1 Name testString	SA"testString">1>4=20000\x0D
Crossover Frequency 20000 Type Mid LPF Index 1 4 Name testString	SA"testString">4>4=20000\x0D
Crossover Mute Off Type Low/High Index 1 1 Name testString	SA"testString">1>5=F\x0D
Crossover Mute Off Type Low/High Index 1 4 Name testString	SA"testString">4>5=F\x0D

Global Scripter Module Communication Sheet

Crossover Mute Off Type Mid Index 1 1 Name testString	SA"testString">1>7=F\x0D
Crossover Mute Off Type Mid Index 1 4 Name testString	SA"testString">4>7=F\x0D
Crossover Mute On Type Low/High Index 1 1 Name testString	SA"testString">1>5=0\x0D
Crossover Mute On Type Low/High Index 1 4 Name testString	SA"testString">4>5=0\x0D
Crossover Mute On Type Mid Index 1 1 Name testString	SA"testString">1>7=0\x0D
Crossover Mute On Type Mid Index 1 4 Name testString	SA"testString">4>7=0\x0D
Crossover Polarity Off Type Low/High Index 1 1 Name testString	SA"testString">1>4=F\x0D
Crossover Polarity Off Type Low/High Index 1 4 Name testString	SA"testString">4>4=F\x0D
Crossover Polarity Off Type Mid Index 1 1 Name testString	SA"testString">1>6=F\x0D
Crossover Polarity Off Type Mid Index 1 4 Name testString	SA"testString">4>6=F\x0D
Crossover Polarity On Type Low/High Index 1 1 Name testString	SA"testString">1>4=0\x0D
Crossover Polarity On Type Low/High Index 1 4 Name testString	SA"testString">4>4=0\x0D
Crossover Polarity On Type Mid Index 1 1 Name testString	SA"testString">1>6=0\x0D
Crossover Polarity On Type Mid Index 1 4 Name testString	SA"testString">4>6=0\x0D
CRR Advanced Level 0 Input 1 Name testString Output 1	SA"testString">6>(1,1)=0.0\x0D
CRR Advanced Level 0 Input 1 Name testString Output 67	SA"testString">6>(1,67)=0.0\x0D
CRR Advanced Level 0 Input 51 Name testString Output 1	SA"testString">6>(51,1)=0.0\x0D
CRR Advanced Level 0 Input 51 Name testString Output 67	SA"testString">6>(51,67)=0.0\x0D
CRR Advanced Level -60 Input 1 Name testString Output 1	SA"testString">6>(1,1)=-60.0\x0D
CRR Advanced Level -60 Input 1 Name testString Output 67	SA"testString">6>(1,67)=-60.0\x0D
CRR Advanced Level -60 Input 51 Name testString Output 1	SA"testString">6>(51,1)=-60.0\x0D
CRR Advanced Level -60 Input 51 Name testString Output 67	SA"testString">6>(51,67)=-60.0\x0D
CRR Advanced State Off Input 1 Name testString Output 1	SA"testString">5>(1,1)=F\x0D
CRR Advanced State Off Input 1 Name testString	SA"testString">5>(1,67)=F\x0D

Global Scriptor Module Communication Sheet

Output 67	
CRR Advanced State Off Input 51 Name testString Output 1	SA"testString">5>(51,1)=F\x0D
CRR Advanced State Off Input 51 Name testString Output 67	SA"testString">5>(51,67)=F\x0D
CRR Advanced State On Input 1 Name testString Output 1	SA"testString">5>(1,1)=0\x0D
CRR Advanced State On Input 1 Name testString Output 67	SA"testString">5>(1,67)=0\x0D
CRR Advanced State On Input 51 Name testString Output 1	SA"testString">5>(51,1)=0\x0D
CRR Advanced State On Input 51 Name testString Output 67	SA"testString">5>(51,67)=0\x0D
Delay Bypass Off Name testString Output 1	SA"testString">1>2=F\x0D
Delay Bypass Off Name testString Output 8	SA"testString">8>2=F\x0D
Delay Bypass On Name testString Output 1	SA"testString">1>2=0\x0D
Delay Bypass On Name testString Output 8	SA"testString">8>2=0\x0D
Delay Time 0 Name testString Output 1	SA"testString">1>1=0\x0D
Delay Time 0 Name testString Output 8	SA"testString">8>1=0\x0D
Delay Time 144000 Name testString Output 1	SA"testString">1>1=144000\x0D
Delay Time 144000 Name testString Output 8	SA"testString">8>1=144000\x0D
Delay Time 48000 Name testString Output 1	SA"testString">1>1=48000\x0D
Delay Time 48000 Name testString Output 8	SA"testString">8>1=48000\x0D
Ducker Decay 5 Name testString	SA"testString">6=5\x0D
Ducker Decay 50000 Name testString	SA"testString">6=50000\x0D
Ducker Hold 0 Name testString	SA"testString">5=0\x0D
Ducker Hold 1000 Name testString	SA"testString">5=1000\x0D
Ducker Range 0 Name testString	SA"testString">3=0.0\x0D
Ducker Range -60 Name testString	SA"testString">3=-60.0\x0D
Gain 12 Name testString	SA"testString">1=12.0\x0D
Gain -60 Name testString	SA"testString">1=-60.0\x0D
Gain Mute Off Name testString	SA"testString">2=F\x0D
Gain Mute On Name testString	SA"testString">2=0\x0D
Gate Decay 5 Name testString	SA"testString">6=5\x0D
Gate Decay 50000 Name testString	SA"testString">6=50000\x0D
Gate Detector Left Name testString	SA"testString">1=L\x0D
Gate Detector Mix Name testString	SA"testString">1=M\x0D
Gate Detector Right Name testString	SA"testString">1=R\x0D
Gate Detector Sidechain Name testString	SA"testString">1=S\x0D
Gate Hold 0 Name testString	SA"testString">5=0\x0D
Gate Hold 1000 Name testString	SA"testString">5=1000\x0D
Gate Range 0 Name testString	SA"testString">3=0.0\x0D
Gate Range -70 Name testString	SA"testString">3=-70.0\x0D
GPO Mode Off Name testString Pin 1	SA"testString">1=F\x0D
GPO Mode Off Name testString Pin 5	SA"testString">5=F\x0D

Global Scriptor Module Communication Sheet

GPO Mode On Name testString Pin 1	SA"testString">1=0\x0D
GPO Mode On Name testString Pin 5	SA"testString">5=0\x0D
Graphic EQ Level 15 Name testString Frequency 1.25kHz	SA"testString">19=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1.25kHz	SA"testString">19=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 1.6kHz	SA"testString">20=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1.6kHz	SA"testString">20=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 100Hz	SA"testString">8=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 100Hz	SA"testString">8=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 10kHz	SA"testString">28=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 10kHz	SA"testString">28=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 12.5kHz	SA"testString">29=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 12.5kHz	SA"testString">29=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 125Hz	SA"testString">9=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 125Hz	SA"testString">9=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 160Hz	SA"testString">10=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 160Hz	SA"testString">10=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 16kHz	SA"testString">30=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 16kHz	SA"testString">30=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 1kHz	SA"testString">18=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 1kHz	SA"testString">18=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 2.5kHz	SA"testString">22=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 2.5kHz	SA"testString">22=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 200Hz	SA"testString">11=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 200Hz	SA"testString">11=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 20Hz	SA"testString">1=15.0\x0D
Graphic EQ Level -15 Name testString Frequency	SA"testString">1=-15.0\x0D

Global Scriptor Module Communication Sheet

20Hz	
Graphic EQ Level 15 Name testString Frequency 20kHz	SA"testString">31=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 20kHz	SA"testString">31=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 250Hz	SA"testString">12=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 250Hz	SA"testString">12=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 25Hz	SA"testString">2=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 25Hz	SA"testString">2=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 2kHz	SA"testString">21=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 2kHz	SA"testString">21=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 3.15kHz	SA"testString">23=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 3.15kHz	SA"testString">23=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 31.5Hz	SA"testString">3=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 31.5Hz	SA"testString">3=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 315Hz	SA"testString">13=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 315Hz	SA"testString">13=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 400Hz	SA"testString">14=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 400Hz	SA"testString">14=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 40Hz	SA"testString">4=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 40Hz	SA"testString">4=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 4kHz	SA"testString">24=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 4kHz	SA"testString">24=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 500Hz	SA"testString">15=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 500Hz	SA"testString">15=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 50Hz	SA"testString">5=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 50Hz	SA"testString">5=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 5kHz	SA"testString">25=15.0\x0D
Graphic EQ Level -15 Name testString Frequency	SA"testString">25=-15.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

5kHz	
Graphic EQ Level 15 Name testString Frequency 6.3kHz	SA"testString">26=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 6.3kHz	SA"testString">26=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 630Hz	SA"testString">16=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 630Hz	SA"testString">16=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 63Hz	SA"testString">6=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 63Hz	SA"testString">6=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 800Hz	SA"testString">17=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 800Hz	SA"testString">17=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 80Hz	SA"testString">7=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 80Hz	SA"testString">7=-15.0\x0D
Graphic EQ Level 15 Name testString Frequency 8kHz	SA"testString">27=15.0\x0D
Graphic EQ Level -15 Name testString Frequency 8kHz	SA"testString">27=-15.0\x0D
Group Level 0 Group 1	SG 1,78\x0D
Group Level 0 Group 64	SG 40,78\x0D
Group Level 12 Group 1	SG 1,90\x0D
Group Level 12 Group 64	SG 40,90\x0D
Group Level -60 Group 1	SG 1,0\x0D
Group Level -60 Group 64	SG 40,0\x0D
Group Mute Off Group 1	SN 1,U\x0D
Group Mute Off Group 64	SN 40,U\x0D
Group Mute On Group 1	SN 1,M\x0D
Group Mute On Group 64	SN 40,M\x0D
Matrix Mixer Level 0 Input 1 Name testString Matrix Size 1 Output 1	SA"testString">2>1=0.0\x0D
Matrix Mixer Level 0 Input 1 Name testString Matrix Size 1 Output 32	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Input 1 Name testString Matrix Size 32 Output 1	SA"testString">2>1=0.0\x0D
Matrix Mixer Level 0 Input 1 Name testString Matrix Size 32 Output 32	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Input 32 Name testString Matrix Size 1 Output 1	SA"testString">2>32=0.0\x0D
Matrix Mixer Level 0 Input 32 Name testString Matrix Size 1 Output 32	SA"testString">2>63=0.0\x0D
Matrix Mixer Level 0 Input 32 Name testString Matrix Size 32 Output 1	SA"testString">2>993=0.0\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Matrix Mixer Level 0 Input 32 Name testString Matrix Size 32 Output 32	SA"testString">2>1024=0.0\x0D
Matrix Mixer Level -60 Input 1 Name testString Matrix Size 1 Output 1	SA"testString">2>1=-60.0\x0D
Matrix Mixer Level -60 Input 1 Name testString Matrix Size 1 Output 32	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Input 1 Name testString Matrix Size 32 Output 1	SA"testString">2>1=-60.0\x0D
Matrix Mixer Level -60 Input 1 Name testString Matrix Size 32 Output 32	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Input 32 Name testString Matrix Size 1 Output 1	SA"testString">2>32=-60.0\x0D
Matrix Mixer Level -60 Input 32 Name testString Matrix Size 1 Output 32	SA"testString">2>63=-60.0\x0D
Matrix Mixer Level -60 Input 32 Name testString Matrix Size 32 Output 1	SA"testString">2>993=-60.0\x0D
Matrix Mixer Level -60 Input 32 Name testString Matrix Size 32 Output 32	SA"testString">2>1024=-60.0\x0D
Matrix Mixer State Off Input 1 Name testString Matrix Size 1 Output 1	SA"testString">1>1=F\x0D
Matrix Mixer State Off Input 1 Name testString Matrix Size 1 Output 32	SA"testString">1>32=F\x0D
Matrix Mixer State Off Input 1 Name testString Matrix Size 32 Output 1	SA"testString">1>1=F\x0D
Matrix Mixer State Off Input 1 Name testString Matrix Size 32 Output 32	SA"testString">1>32=F\x0D
Matrix Mixer State Off Input 32 Name testString Matrix Size 1 Output 1	SA"testString">1>32=F\x0D
Matrix Mixer State Off Input 32 Name testString Matrix Size 1 Output 32	SA"testString">1>63=F\x0D
Matrix Mixer State Off Input 32 Name testString Matrix Size 32 Output 1	SA"testString">1>993=F\x0D
Matrix Mixer State Off Input 32 Name testString Matrix Size 32 Output 32	SA"testString">1>1024=F\x0D
Matrix Mixer State On Input 1 Name testString Matrix Size 1 Output 1	SA"testString">1>1=0\x0D
Matrix Mixer State On Input 1 Name testString Matrix Size 1 Output 32	SA"testString">1>32=0\x0D
Matrix Mixer State On Input 1 Name testString Matrix Size 32 Output 1	SA"testString">1>1=0\x0D
Matrix Mixer State On Input 1 Name testString Matrix Size 32 Output 32	SA"testString">1>32=0\x0D
Matrix Mixer State On Input 32 Name testString Matrix Size 1 Output 1	SA"testString">1>32=0\x0D
Matrix Mixer State On Input 32 Name testString Matrix Size 1 Output 32	SA"testString">1>63=0\x0D
Matrix Mixer State On Input 32 Name testString	SA"testString">1>993=0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Matrix Size 32 Output 1	
Matrix Mixer State On Input 32 Name testString	SA"testString">1>1024=0\x0D
Matrix Size 32 Output 32	
Parameter Recall 1	SS 1\x0D
Parameter Recall 255	SS ff\x0D
Parametric EQ Frequency 20 Name testString Band 1	SA"testString">1>1=20\x0D
Parametric EQ Frequency 20 Name testString Band 16	SA"testString">16>1=20\x0D
Parametric EQ Frequency 20000 Name testString Band 1	SA"testString">1>1=20000\x0D
Parametric EQ Frequency 20000 Name testString Band 16	SA"testString">16>1=20000\x0D
Parametric EQ Gain 20 Name testString Band 1	SA"testString">1>3=20.0\x0D
Parametric EQ Gain -20 Name testString Band 1	SA"testString">1>3=-20.0\x0D
Parametric EQ Gain 20 Name testString Band 16	SA"testString">16>3=20.0\x0D
Parametric EQ Gain -20 Name testString Band 16	SA"testString">16>3=-20.0\x0D
Parametric EQ Q 0 Name testString Band 1	SA"testString">1>2=0.000\x0D
Parametric EQ Q 0 Name testString Band 16	SA"testString">16>2=0.000\x0D
Parametric EQ Q 14 Name testString Band 1	SA"testString">1>2=14.000\x0D
Parametric EQ Q 14 Name testString Band 16	SA"testString">16>2=14.000\x0D
Parametric EQ Slope -12 Name testString Band 1	SA"testString">1>4=-12\x0D
Parametric EQ Slope -12 Name testString Band 16	SA"testString">16>4=-12\x0D
Parametric EQ Slope -6 Name testString Band 1	SA"testString">1>4=-6\x0D
Parametric EQ Slope -6 Name testString Band 16	SA"testString">16>4=-6\x0D
Parametric EQ Type High Pass Name testString Band 1	SA"testString">1>5=LC\x0D
Parametric EQ Type High Pass Name testString Band 16	SA"testString">16>5=LC\x0D
Parametric EQ Type High Shelf Name testString Band 1	SA"testString">1>5=HS\x0D
Parametric EQ Type High Shelf Name testString Band 16	SA"testString">16>5=HS\x0D
Parametric EQ Type Low Pass Name testString Band 1	SA"testString">1>5=HC\x0D
Parametric EQ Type Low Pass Name testString Band 16	SA"testString">16>5=HC\x0D
Parametric EQ Type Low Shelf Name testString Band 1	SA"testString">1>5=LS\x0D
Parametric EQ Type Low Shelf Name testString Band 16	SA"testString">16>5=LS\x0D
Parametric EQ Type Notch Name testString Band 1	SA"testString">1>5=N\x0D
Parametric EQ Type Notch Name testString Band 16	SA"testString">16>5=N\x0D
Parametric EQ Type PEQ Name testString Band 1	SA"testString">1>5=B\x0D
Parametric EQ Type PEQ Name testString Band 16	SA"testString">16>5=B\x0D
Peak/RMS Input Detect Left Name testString	SA"testString">1=L\x0D
Peak/RMS Input Detect Mix Name testString	SA"testString">1=M\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Peak/RMS Input Detect Right Name testString	SA"testString">1=R\x0D
Peak/RMS Input Detect Sidechain Name testString	SA"testString">1=S\x0D
Peak/RMS RMS 10000 Name testString Function Attack	SA"testString">8=10000\x0D
Peak/RMS RMS 10000 Name testString Function Release	SA"testString">9=10000\x0D
Peak/RMS RMS 500 Name testString Function Attack	SA"testString">8=500\x0D
Peak/RMS RMS 500 Name testString Function Release	SA"testString">9=500\x0D
PSTN Hook Off Name testString	SA"testString">0>9=F\x0D
PSTN Hook On Name testString	SA"testString">0>9=O\x0D
PSTN Level 12 Name testString Module Input	SA"testString">1>1=12.0\x0D
PSTN Level 12 Name testString Module Output	SA"testString">1=12.0\x0D
PSTN Level -60 Name testString Module Input	SA"testString">1>1=-60.0\x0D
PSTN Level -60 Name testString Module Output	SA"testString">1=-60.0\x0D
PSTN Mute Off Name testString Module Input	SA"testString">1>2=F\x0D
PSTN Mute Off Name testString Module Output	SA"testString">2=F\x0D
PSTN Mute On Name testString Module Input	SA"testString">1>2=O\x0D
PSTN Mute On Name testString Module Output	SA"testString">2=O\x0D
Router Input Select 0 Name testString Output 1	SA"testString">1=0\x0D
Router Input Select 0 Name testString Output 32	SA"testString">32=0\x0D
Router Input Select 32 Name testString Output 1	SA"testString">1=32\x0D
Router Input Select 32 Name testString Output 32	SA"testString">32=32\x0D
Signal Generator Gain 12 Wave Pink Name testString	SA"testString">3>1=12.0\x0D
Signal Generator Gain 12 Wave Sine Name testString	SA"testString">1>2=12.0\x0D
Signal Generator Gain 12 Wave Sweep Name testString	SA"testString">4>1=12.0\x0D
Signal Generator Gain 12 Wave White Name testString	SA"testString">2>1=12.0\x0D
Signal Generator Gain -60 Wave Pink Name testString	SA"testString">3>1=-60.0\x0D
Signal Generator Gain -60 Wave Sine Name testString	SA"testString">1>2=-60.0\x0D
Signal Generator Gain -60 Wave Sweep Name testString	SA"testString">4>1=-60.0\x0D
Signal Generator Gain -60 Wave White Name testString	SA"testString">2>1=-60.0\x0D
Signal Generator Mute Off Wave Pink Name testString	SA"testString">3>2=F\x0D
Signal Generator Mute Off Wave Sine Name testString	SA"testString">1>3=F\x0D
Signal Generator Mute Off Wave White Name testString	SA"testString">2>2=F\x0D
Signal Generator Mute On Wave Pink Name testString	SA"testString">3>2=O\x0D
Signal Generator Mute On Wave Sine Name testString	SA"testString">1>3=O\x0D

Global Scriptor Module Communication Sheet

testString	
Signal Generator Mute On Wave White Name testString	SA"testString">2>2=0\x0D
Source Select 1 Name testString	SA"testString">1=1\x0D
Source Select 32 Name testString	SA"testString">1=32\x0D
Speaker Parametric Align Delay 0 Name testString	SA"testString">0>4=0\x0D
Speaker Parametric Align Delay 480 Name testString	SA"testString">0>4=480\x0D
Speaker Parametric Bypass Off Type High Name testString	SA"testString">0>10=F\x0D
Speaker Parametric Bypass Off Type Low Name testString	SA"testString">0>9=F\x0D
Speaker Parametric Bypass On Type High Name testString	SA"testString">0>10=0\x0D
Speaker Parametric Bypass On Type Low Name testString	SA"testString">0>9=0\x0D
Speaker Parametric EQ Band Bypass Off Index 1 1 Name testString	SA"testString">1>6=F\x0D
Speaker Parametric EQ Band Bypass Off Index 1 9 Name testString	SA"testString">9>6=F\x0D
Speaker Parametric EQ Band Bypass On Index 1 1 Name testString	SA"testString">1>6=0\x0D
Speaker Parametric EQ Band Bypass On Index 1 9 Name testString	SA"testString">9>6=0\x0D
Speaker Parametric EQ Band Filter High Shelf Index 1 1 Name testString	SA"testString">1>5=HS\x0D
Speaker Parametric EQ Band Filter High Shelf Index 1 9 Name testString	SA"testString">9>5=HS\x0D
Speaker Parametric EQ Band Filter Low Shelf Index 1 1 Name testString	SA"testString">1>5=LS\x0D
Speaker Parametric EQ Band Filter Low Shelf Index 1 9 Name testString	SA"testString">9>5=LS\x0D
Speaker Parametric EQ Band Filter Notch Index 1 1 Name testString	SA"testString">1>5=N\x0D
Speaker Parametric EQ Band Filter Notch Index 1 9 Name testString	SA"testString">9>5=N\x0D
Speaker Parametric EQ Band Filter PEQ Index 1 1 Name testString	SA"testString">1>5=B\x0D
Speaker Parametric EQ Band Filter PEQ Index 1 9 Name testString	SA"testString">9>5=B\x0D
Speaker Parametric EQ Band Frequency 20 Index 1 1 Name testString	SA"testString">1>1=20\x0D
Speaker Parametric EQ Band Frequency 20 Index 1 9 Name testString	SA"testString">9>1=20\x0D
Speaker Parametric EQ Band Frequency 20000 Index 1 1 Name testString	SA"testString">1>1=20000\x0D
Speaker Parametric EQ Band Frequency 20000 Index 1 9 Name testString	SA"testString">9>1=20000\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Speaker Parametric EQ Band Gain 20 Index 1 1 Name testString	SA"testString">1>3=20.0\x0D
Speaker Parametric EQ Band Gain -20 Index 1 1 Name testString	SA"testString">1>3=-20.0\x0D
Speaker Parametric EQ Band Gain 20 Index 1 9 Name testString	SA"testString">9>3=20.0\x0D
Speaker Parametric EQ Band Gain -20 Index 1 9 Name testString	SA"testString">9>3=-20.0\x0D
Speaker Parametric EQ Band Q 0 Index 1 1 Name testString	SA"testString">1>2=0.000\x0D
Speaker Parametric EQ Band Q 0 Index 1 9 Name testString	SA"testString">9>2=0.000\x0D
Speaker Parametric EQ Band Q 10 Index 1 1 Name testString	SA"testString">1>2=10.000\x0D
Speaker Parametric EQ Band Q 10 Index 1 9 Name testString	SA"testString">9>2=10.000\x0D
Speaker Parametric Filter Bessel 12dB/oct Type High Name testString	SA"testString">0>5=Bes12\x0D
Speaker Parametric Filter Bessel 12dB/oct Type Low Name testString	SA"testString">0>7=Bes12\x0D
Speaker Parametric Filter Bessel 18dB/oct Type High Name testString	SA"testString">0>5=Bes18\x0D
Speaker Parametric Filter Bessel 18dB/oct Type Low Name testString	SA"testString">0>7=Bes18\x0D
Speaker Parametric Filter Bessel 24dB/oct Type High Name testString	SA"testString">0>5=Bes24\x0D
Speaker Parametric Filter Bessel 24dB/oct Type Low Name testString	SA"testString">0>7=Bes24\x0D
Speaker Parametric Filter Bessel 36dB/oct Type High Name testString	SA"testString">0>5=Bes36\x0D
Speaker Parametric Filter Bessel 36dB/oct Type Low Name testString	SA"testString">0>7=Bes36\x0D
Speaker Parametric Filter Bessel 48dB/oct Type High Name testString	SA"testString">0>5=Bes48\x0D
Speaker Parametric Filter Bessel 48dB/oct Type Low Name testString	SA"testString">0>7=Bes48\x0D
Speaker Parametric Filter Butterworth 12dB/oct Type High Name testString	SA"testString">0>5=But12\x0D
Speaker Parametric Filter Butterworth 12dB/oct Type Low Name testString	SA"testString">0>7=But12\x0D
Speaker Parametric Filter Butterworth 18dB/oct Type High Name testString	SA"testString">0>5=But18\x0D
Speaker Parametric Filter Butterworth 18dB/oct Type Low Name testString	SA"testString">0>7=But18\x0D
Speaker Parametric Filter Butterworth 24dB/oct Type High Name testString	SA"testString">0>5=But24\x0D
Speaker Parametric Filter Butterworth 24dB/oct	SA"testString">0>7=But24\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Type Low Name testString	
Speaker Parametric Filter Butterworth 36dB/oct Type High Name testString	SA"testString">0>5=But36\x0D
Speaker Parametric Filter Butterworth 36dB/oct Type Low Name testString	SA"testString">0>7=But36\x0D
Speaker Parametric Filter Butterworth 48dB/oct Type High Name testString	SA"testString">0>5=But48\x0D
Speaker Parametric Filter Butterworth 48dB/oct Type Low Name testString	SA"testString">0>7=But48\x0D
Speaker Parametric Filter Butterworth 6dB/oct Type High Name testString	SA"testString">0>5=But6\x0D
Speaker Parametric Filter Butterworth 6dB/oct Type Low Name testString	SA"testString">0>7=But6\x0D
Speaker Parametric Filter Linkwitz-Reily 12dB/oct Type High Name testString	SA"testString">0>5=Lin12\x0D
Speaker Parametric Filter Linkwitz-Reily 12dB/oct Type Low Name testString	SA"testString">0>7=Lin12\x0D
Speaker Parametric Filter Linkwitz-Reily 24dB/oct Type High Name testString	SA"testString">0>5=Lin24\x0D
Speaker Parametric Filter Linkwitz-Reily 24dB/oct Type Low Name testString	SA"testString">0>7=Lin24\x0D
Speaker Parametric Filter Linkwitz-Reily 36dB/oct Type High Name testString	SA"testString">0>5=Lin36\x0D
Speaker Parametric Filter Linkwitz-Reily 36dB/oct Type Low Name testString	SA"testString">0>7=Lin36\x0D
Speaker Parametric Filter Linkwitz-Reily 48dB/oct Type High Name testString	SA"testString">0>5=Lin48\x0D
Speaker Parametric Filter Linkwitz-Reily 48dB/oct Type Low Name testString	SA"testString">0>7=Lin48\x0D
Speaker Parametric Frequency 20 Type High Name testString	SA"testString">0>6=20\x0D
Speaker Parametric Frequency 20 Type Low Name testString	SA"testString">0>8=20\x0D
Speaker Parametric Frequency 20000 Type High Name testString	SA"testString">0>6=20000\x0D
Speaker Parametric Frequency 20000 Type Low Name testString	SA"testString">0>8=20000\x0D
Speaker Parametric Gain 15 Name testString	SA"testString">0>3=15.0\x0D
Speaker Parametric Gain -15 Name testString	SA"testString">0>3=-15.0\x0D
Standard Mixer Level 12 Index 1 Input Name testString Index 2 1	SA"testString">1>1=12.0\x0D
Standard Mixer Level 12 Index 1 Input Name testString Index 2 32	SA"testString">1>63=12.0\x0D
Standard Mixer Level 12 Index 1 Output Name testString Index 2 1	SA"testString">2>1=12.0\x0D
Standard Mixer Level 12 Index 1 Output Name testString Index 2 32	SA"testString">2>63=12.0\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Standard Mixer Level -60 Index 1 Input Name testString Index 2 1	SA"testString">1>1=-60.0\x0D
Standard Mixer Level -60 Index 1 Input Name testString Index 2 32	SA"testString">1>63=-60.0\x0D
Standard Mixer Level -60 Index 1 Output Name testString Index 2 1	SA"testString">2>1=-60.0\x0D
Standard Mixer Level -60 Index 1 Output Name testString Index 2 32	SA"testString">2>63=-60.0\x0D
Standard Mixer Mute Off Index 1 Input Name testString Index 2 1	SA"testString">1>2=F\x0D
Standard Mixer Mute Off Index 1 Input Name testString Index 2 32	SA"testString">1>64=F\x0D
Standard Mixer Mute Off Index 1 Output Name testString Index 2 1	SA"testString">2>2=F\x0D
Standard Mixer Mute Off Index 1 Output Name testString Index 2 32	SA"testString">2>64=F\x0D
Standard Mixer Mute On Index 1 Input Name testString Index 2 1	SA"testString">1>2=0\x0D
Standard Mixer Mute On Index 1 Input Name testString Index 2 32	SA"testString">1>64=0\x0D
Standard Mixer Mute On Index 1 Output Name testString Index 2 1	SA"testString">2>2=0\x0D
Standard Mixer Mute On Index 1 Output Name testString Index 2 32	SA"testString">2>64=0\x0D
Standard Mixer Routing Route Input 1 Name testString Output 1	SA"testString">4>(1,1)=0\x0D
Standard Mixer Routing Route Input 1 Name testString Output 32	SA"testString">4>(1,32)=0\x0D
Standard Mixer Routing Route Input 32 Name testString Output 1	SA"testString">4>(32,1)=0\x0D
Standard Mixer Routing Route Input 32 Name testString Output 32	SA"testString">4>(32,32)=0\x0D
Standard Mixer Routing Unroute Input 1 Name testString Output 1	SA"testString">4>(1,1)=F\x0D
Standard Mixer Routing Unroute Input 1 Name testString Output 32	SA"testString">4>(1,32)=F\x0D
Standard Mixer Routing Unroute Input 32 Name testString Output 1	SA"testString">4>(32,1)=F\x0D
Standard Mixer Routing Unroute Input 32 Name testString Output 32	SA"testString">4>(32,32)=F\x0D
Surround Input Level 12 Name testString Level Back Surround Left	SA"testString">10=12.0\x0D
Surround Input Level 12 Name testString Level Back Surround Right	SA"testString">11=12.0\x0D
Surround Input Level 12 Name testString Level Center	SA"testString">8=12.0\x0D
Surround Input Level 12 Name testString Level Left	SA"testString">4=12.0\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Front	
Surround Input Level 12 Name testString Level Left Surround	SA"testString">6=12.0\x0D
Surround Input Level 12 Name testString Level LFE (Sub)	SA"testString">9=12.0\x0D
Surround Input Level 12 Name testString Level Right Front	SA"testString">5=12.0\x0D
Surround Input Level 12 Name testString Level Right Surround	SA"testString">7=12.0\x0D
Surround Input Level -60 Name testString Level Back Surround Left	SA"testString">10=-60.0\x0D
Surround Input Level -60 Name testString Level Back Surround Right	SA"testString">11=-60.0\x0D
Surround Input Level -60 Name testString Level Center	SA"testString">8=-60.0\x0D
Surround Input Level -60 Name testString Level Left Front	SA"testString">4=-60.0\x0D
Surround Input Level -60 Name testString Level Left Surround	SA"testString">6=-60.0\x0D
Surround Input Level -60 Name testString Level LFE (Sub)	SA"testString">9=-60.0\x0D
Surround Input Level -60 Name testString Level Right Front	SA"testString">5=-60.0\x0D
Surround Input Level -60 Name testString Level Right Surround	SA"testString">7=-60.0\x0D
Surround Input Source Coaxial Name testString	SA"testString">1=C\x0D
Surround Input Source Optical Name testString	SA"testString">1=0\x0D
Tone Control Gain 15 Type High Name testString	SA"testString">5=15.0\x0D
Tone Control Gain -15 Type High Name testString	SA"testString">5=-15.0\x0D
Tone Control Gain 15 Type Low Name testString	SA"testString">1=15.0\x0D
Tone Control Gain -15 Type Low Name testString	SA"testString">1=-15.0\x0D
Tone Control Gain 15 Type Mid Name testString	SA"testString">3=15.0\x0D
Tone Control Gain -15 Type Mid Name testString	SA"testString">3=-15.0\x0D
USB Level 12 Name testString Channel Left	SA"testString">1>1=12.0\x0D
USB Level 12 Name testString Channel Right	SA"testString">2>1=12.0\x0D
USB Level -60 Name testString Channel Left	SA"testString">1>1=-60.0\x0D
USB Level -60 Name testString Channel Right	SA"testString">2>1=-60.0\x0D
USB Mute Off Name testString Channel Left	SA"testString">1>2=F\x0D
USB Mute Off Name testString Channel Right	SA"testString">2>2=F\x0D
USB Mute On Name testString Channel Left	SA"testString">1>2=0\x0D
USB Mute On Name testString Channel Right	SA"testString">2>2=0\x0D
VoIP Level 12 Name testString	SA"testString">1>1=12.0\x0D
VoIP Level -60 Name testString	SA"testString">1>1=-60.0\x0D
VoIP Mute Off Name testString	SA"testString">1>2=F\x0D
VoIP Mute On Name testString	SA"testString">1>2=0\x0D

Appendix B. Update Commands

AEC CN Enable Index 1 1 Name testString	GA"testString">1>8\x0D
AEC CN Enable Index 1 12 Name testString	GA"testString">12>8\x0D
AEC Enable Index 1 1 Name testString	GA"testString">1>6\x0D
AEC Enable Index 1 12 Name testString	GA"testString">12>6\x0D
AEC Internal Mute Index 1 1 Name testString	GA"testString">1>5\x0D
AEC Internal Mute Index 1 12 Name testString	GA"testString">12>5\x0D
AEC NLP Control Index 1 1 Name testString	GA"testString">1>7\x0D
AEC NLP Control Index 1 12 Name testString	GA"testString">12>7\x0D
AEC NR Level Index 1 1 Name testString	GA"testString">1>9\x0D
AEC NR Level Index 1 12 Name testString	GA"testString">12>9\x0D
AEC Reference Index 1 1 Name testString	GA"testString">1>10\x0D
AEC Reference Index 1 12 Name testString	GA"testString">12>10\x0D
AMM Gain Sharing Attack Name testString	GA"testString">0>4\x0D
AMM Gain Sharing Bypass Index 1 1 Name testString	GA"testString">1>4\x0D
AMM Gain Sharing Bypass Index 1 32 Name testString	GA"testString">32>4\x0D
AMM Gain Sharing Decay Name testString	GA"testString">0>6\x0D
AMM Gain Sharing Gain Index 1 0 Name testString	GA"testString">0>1\x0D
AMM Gain Sharing Gain Index 1 32 Name testString	GA"testString">32>1\x0D
AMM Gain Sharing Hold Name testString	GA"testString">0>5\x0D
AMM Gain Sharing Mute Index 1 0 Name testString	GA"testString">0>2\x0D
AMM Gain Sharing Mute Index 1 32 Name testString	GA"testString">32>2\x0D
AMM Gain Sharing Priority Index 1 1 Name testString	GA"testString">1>3\x0D
AMM Gain Sharing Priority Index 1 32 Name testString	GA"testString">32>3\x0D
AMM Gain Sharing RMS Average Type Input Name testString	GA"testString">0>7\x0D
AMM Gain Sharing RMS Average Type Output Name testString	GA"testString">0>8\x0D
AMM Gain Sharing Slope Name testString	GA"testString">0>3\x0D
AMM Gated Attack Index 1 1 Name testString	GA"testString">1>14\x0D
AMM Gated Attack Index 1 32 Name testString	GA"testString">32>14\x0D
AMM Gated Attack Index 1 8 Name testString	GA"testString">8>14\x0D
AMM Gated Decay Index 1 1 Name testString	GA"testString">1>8\x0D
AMM Gated Decay Index 1 1 Name testString	GA"testString">1>16\x0D
AMM Gated Decay Index 1 32 Name testString	GA"testString">32>16\x0D
AMM Gated Decay Index 1 8 Name testString	GA"testString">8>8\x0D
AMM Gated Decay Index 1 8 Name testString	GA"testString">8>16\x0D
AMM Gated Detection Index 1 1 Name testString	GA"testString">1>3\x0D
AMM Gated Detection Index 1 8 Name testString	GA"testString">8>3\x0D
AMM Gated Ducking Depth Index 1 1 Name testString	GA"testString">1>7\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

AMM Gated Ducking Depth Index 1 1 Name testString	GA"testString">1>12\x0D
AMM Gated Ducking Depth Index 1 32 Name testString	GA"testString">32>12\x0D
AMM Gated Ducking Depth Index 1 8 Name testString	GA"testString">8>7\x0D
AMM Gated Ducking Depth Index 1 8 Name testString	GA"testString">8>12\x0D
AMM Gated Gain Index 1 0 Name testString	GA"testString">0>1\x0D
AMM Gated Gain Index 1 32 Name testString	GA"testString">32>2\x0D
AMM Gated Gain Index 1 8 Name testString	GA"testString">8>2\x0D
AMM Gated Gate Depth Index 1 1 Name testString	GA"testString">1>5\x0D
AMM Gated Gate Depth Index 1 1 Name testString	GA"testString">1>13\x0D
AMM Gated Gate Depth Index 1 32 Name testString	GA"testString">32>13\x0D
AMM Gated Gate Depth Index 1 8 Name testString	GA"testString">8>5\x0D
AMM Gated Gate Depth Index 1 8 Name testString	GA"testString">8>13\x0D
AMM Gated High Pass Index 1 1 Name testString	GA"testString">1>10\x0D
AMM Gated High Pass Index 1 32 Name testString	GA"testString">32>10\x0D
AMM Gated High Pass Index 1 8 Name testString	GA"testString">8>10\x0D
AMM Gated Hold Index 1 1 Name testString	GA"testString">1>6\x0D
AMM Gated Hold Index 1 1 Name testString	GA"testString">1>15\x0D
AMM Gated Hold Index 1 32 Name testString	GA"testString">32>15\x0D
AMM Gated Hold Index 1 8 Name testString	GA"testString">8>6\x0D
AMM Gated Hold Index 1 8 Name testString	GA"testString">8>15\x0D
AMM Gated Low Pass Index 1 1 Name testString	GA"testString">1>11\x0D
AMM Gated Low Pass Index 1 1 Name testString	GA"testString">1>9\x0D
AMM Gated Low Pass Index 1 32 Name testString	GA"testString">32>9\x0D
AMM Gated Low Pass Index 1 8 Name testString	GA"testString">8>11\x0D
AMM Gated Low Pass Index 1 8 Name testString	GA"testString">8>9\x0D
AMM Gated Mute Index 1 0 Name testString	GA"testString">0>3\x0D
AMM Gated Mute Index 1 0 Name testString	GA"testString">0>2\x0D
AMM Gated Mute Index 1 32 Name testString	GA"testString">32>3\x0D
AMM Gated Mute Index 1 8 Name testString	GA"testString">8>16\x0D
AMM Gated Mute Index 1 8 Name testString	GA"testString">8>3\x0D
AMM Gated NOM Name testString	GA"testString">0>2\x0D
AMM Gated Priority Index 1 1 Name testString	GA"testString">1>1\x0D
AMM Gated Priority Index 1 32 Name testString	GA"testString">32>1\x0D
AMM Gated Priority Index 1 8 Name testString	GA"testString">8>1\x0D
AMM Gated Push To Talk Index 1 1 Name testString	GA"testString">1>15\x0D
AMM Gated Push To Talk Index 1 8 Name testString	GA"testString">8>15\x0D
AMM Gated RMS Avg Index 1 1 Name testString	GA"testString">1>12\x0D
AMM Gated RMS Avg Index 1 1 Name testString	GA"testString">1>11\x0D
AMM Gated RMS Avg Index 1 32 Name testString	GA"testString">32>11\x0D
AMM Gated RMS Avg Index 1 8 Name testString	GA"testString">8>12\x0D
AMM Gated RMS Avg Index 1 8 Name testString	GA"testString">8>11\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

AMM Gated Threshold Index 1 1 Name testString	GA"testString">1>4\x0D
AMM Gated Threshold Index 1 1 Name testString	GA"testString">1>5\x0D
AMM Gated Threshold Index 1 32 Name testString	GA"testString">32>5\x0D
AMM Gated Threshold Index 1 8 Name testString	GA"testString">8>4\x0D
AMM Gated Threshold Index 1 8 Name testString	GA"testString">8>5\x0D
Array EQ Advanced Name testString	GA"testString">1>6\x0D
Array EQ Center Frequency Name testString	GA"testString">1>1\x0D
Array EQ Tilt Name testString	GA"testString">1>2\x0D
Array EQ Vertical Angle Name testString	GA"testString">1>8\x0D
Compressor/Limiter Input Detect Name testString	GA"testString">1\x0D
Compressor/Limiter Ratio Name testString	GA"testString">3\x0D
Compressor/Limiter Release Name testString	GA"testString">5\x0D
Crossover Filter Type Low/High Index 1 1 Name testString	GA"testString">1>1\x0D
Crossover Filter Type Low/High Index 1 4 Name testString	GA"testString">4>1\x0D
Crossover Filter Type Mid HPF Index 1 1 Name testString	GA"testString">1>1\x0D
Crossover Filter Type Mid HPF Index 1 4 Name testString	GA"testString">4>1\x0D
Crossover Filter Type Mid LPF Index 1 1 Name testString	GA"testString">1>3\x0D
Crossover Filter Type Mid LPF Index 1 4 Name testString	GA"testString">4>3\x0D
Crossover Frequency Type Low/High Index 1 1 Name testString	GA"testString">1>2\x0D
Crossover Frequency Type Low/High Index 1 4 Name testString	GA"testString">4>2\x0D
Crossover Frequency Type Mid HPF Index 1 1 Name testString	GA"testString">1>2\x0D
Crossover Frequency Type Mid HPF Index 1 4 Name testString	GA"testString">4>2\x0D
Crossover Frequency Type Mid LPF Index 1 1 Name testString	GA"testString">1>4\x0D
Crossover Frequency Type Mid LPF Index 1 4 Name testString	GA"testString">4>4\x0D
Crossover Mute Type Low/High Index 1 1 Name testString	GA"testString">1>5\x0D
Crossover Mute Type Low/High Index 1 4 Name testString	GA"testString">4>5\x0D
Crossover Mute Type Mid Index 1 1 Name testString	GA"testString">1>7\x0D
Crossover Mute Type Mid Index 1 4 Name testString	GA"testString">4>7\x0D
Crossover Polarity Type Low/High Index 1 1 Name testString	GA"testString">1>4\x0D
Crossover Polarity Type Low/High Index 1 4 Name testString	GA"testString">4>4\x0D

Global Scriptor Module Communication Sheet

Crossover Polarity Type Mid Index 1 1 Name testString	GA"testString">1>6\x0D
Crossover Polarity Type Mid Index 1 4 Name testString	GA"testString">4>6\x0D
CRR Advanced Level Input 1 Name testString Output 1	GA"testString">6>(1,1)\x0D
CRR Advanced Level Input 1 Name testString Output 67	GA"testString">6>(1,67)\x0D
CRR Advanced Level Input 51 Name testString Output 1	GA"testString">6>(51,1)\x0D
CRR Advanced Level Input 51 Name testString Output 67	GA"testString">6>(51,67)\x0D
CRR Advanced State Input 1 Name testString Output 1	GA"testString">5>(1,1)\x0D
CRR Advanced State Input 1 Name testString Output 67	GA"testString">5>(1,67)\x0D
CRR Advanced State Input 51 Name testString Output 1	GA"testString">5>(51,1)\x0D
CRR Advanced State Input 51 Name testString Output 67	GA"testString">5>(51,67)\x0D
Delay Bypass Name testString Output 1	GA"testString">1>2\x0D
Delay Bypass Name testString Output 8	GA"testString">8>2\x0D
Delay Time Name testString Output 1	GA"testString">1>1\x0D
Delay Time Name testString Output 8	GA"testString">8>1\x0D
Ducker Decay Name testString	GA"testString">6\x0D
Ducker Hold Name testString	GA"testString">5\x0D
Ducker Range Name testString	GA"testString">3\x0D
Fault Status	GF\x0D
Gain Mute Name testString	GA"testString">2\x0D
Gain Name testString	GA"testString">1\x0D
Gate Decay Name testString	GA"testString">6\x0D
Gate Detector Name testString	GA"testString">1\x0D
Gate Hold Name testString	GA"testString">5\x0D
Gate Range Name testString	GA"testString">3\x0D
GPO Mode Name testString Pin 1	GA"testString">1\x0D
GPO Mode Name testString Pin 5	GA"testString">5\x0D
Graphic EQ Level Name testString Frequency 1.25kHz	GA"testString">19\x0D
Graphic EQ Level Name testString Frequency 1.6kHz	GA"testString">20\x0D
Graphic EQ Level Name testString Frequency 100Hz	GA"testString">8\x0D
Graphic EQ Level Name testString Frequency 10kHz	GA"testString">28\x0D
Graphic EQ Level Name testString Frequency 12.5kHz	GA"testString">29\x0D
Graphic EQ Level Name testString Frequency 125Hz	GA"testString">9\x0D
Graphic EQ Level Name testString Frequency 160Hz	GA"testString">10\x0D
Graphic EQ Level Name testString Frequency 16kHz	GA"testString">30\x0D
Graphic EQ Level Name testString Frequency 1kHz	GA"testString">18\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Graphic EQ Level Name testString Frequency 2.5kHz	GA"testString">22\x0D
Graphic EQ Level Name testString Frequency 200Hz	GA"testString">11\x0D
Graphic EQ Level Name testString Frequency 20Hz	GA"testString">1\x0D
Graphic EQ Level Name testString Frequency 20kHz	GA"testString">31\x0D
Graphic EQ Level Name testString Frequency 250Hz	GA"testString">12\x0D
Graphic EQ Level Name testString Frequency 25Hz	GA"testString">2\x0D
Graphic EQ Level Name testString Frequency 2kHz	GA"testString">21\x0D
Graphic EQ Level Name testString Frequency 3.15kHz	GA"testString">23\x0D
Graphic EQ Level Name testString Frequency 31.5Hz	GA"testString">3\x0D
Graphic EQ Level Name testString Frequency 315Hz	GA"testString">13\x0D
Graphic EQ Level Name testString Frequency 400Hz	GA"testString">14\x0D
Graphic EQ Level Name testString Frequency 40Hz	GA"testString">4\x0D
Graphic EQ Level Name testString Frequency 4kHz	GA"testString">24\x0D
Graphic EQ Level Name testString Frequency 500Hz	GA"testString">15\x0D
Graphic EQ Level Name testString Frequency 50Hz	GA"testString">5\x0D
Graphic EQ Level Name testString Frequency 5kHz	GA"testString">25\x0D
Graphic EQ Level Name testString Frequency 6.3kHz	GA"testString">26\x0D
Graphic EQ Level Name testString Frequency 630Hz	GA"testString">16\x0D
Graphic EQ Level Name testString Frequency 63Hz	GA"testString">6\x0D
Graphic EQ Level Name testString Frequency 800Hz	GA"testString">17\x0D
Graphic EQ Level Name testString Frequency 80Hz	GA"testString">7\x0D
Graphic EQ Level Name testString Frequency 8kHz	GA"testString">27\x0D
Group Level Group 1	GG 1\x0D
Group Level Group 64	GG 40\x0D
Group Mute Group 1	GN 1\x0D
Group Mute Group 64	GN 40\x0D
Matrix Mixer Level Input 1 Name testString Matrix Size 1 Output 1	GA"testString">2>1\x0D
Matrix Mixer Level Input 1 Name testString Matrix Size 1 Output 32	GA"testString">2>32\x0D
Matrix Mixer Level Input 1 Name testString Matrix Size 32 Output 1	GA"testString">2>1\x0D
Matrix Mixer Level Input 1 Name testString Matrix Size 32 Output 32	GA"testString">2>32\x0D
Matrix Mixer Level Input 32 Name testString Matrix Size 1 Output 1	GA"testString">2>32\x0D
Matrix Mixer Level Input 32 Name testString Matrix Size 1 Output 32	GA"testString">2>63\x0D
Matrix Mixer Level Input 32 Name testString Matrix Size 32 Output 1	GA"testString">2>993\x0D
Matrix Mixer Level Input 32 Name testString Matrix Size 32 Output 32	GA"testString">2>1024\x0D
Matrix Mixer State Input 1 Name testString Matrix Size 1 Output 1	GA"testString">1>1\x0D
Matrix Mixer State Input 1 Name testString Matrix	GA"testString">1>32\x0D

Global Scriptor Module Communication Sheet

Revision: 6/10/2020

Size 1 Output 32	
Matrix Mixer State Input 1 Name testString Matrix Size 32 Output 1	GA"testString">1>1\x0D
Matrix Mixer State Input 1 Name testString Matrix Size 32 Output 32	GA"testString">1>32\x0D
Matrix Mixer State Input 32 Name testString Matrix Size 1 Output 1	GA"testString">1>32\x0D
Matrix Mixer State Input 32 Name testString Matrix Size 1 Output 32	GA"testString">1>63\x0D
Matrix Mixer State Input 32 Name testString Matrix Size 32 Output 1	GA"testString">1>993\x0D
Matrix Mixer State Input 32 Name testString Matrix Size 32 Output 32	GA"testString">1>1024\x0D
Parameter Recall	GS\x0D
Parametric EQ Frequency Name testString Band 1	GA"testString">1>1\x0D
Parametric EQ Frequency Name testString Band 16	GA"testString">16>1\x0D
Parametric EQ Gain Name testString Band 1	GA"testString">1>3\x0D
Parametric EQ Gain Name testString Band 16	GA"testString">16>3\x0D
Parametric EQ Q Name testString Band 1	GA"testString">1>2\x0D
Parametric EQ Q Name testString Band 16	GA"testString">16>2\x0D
Parametric EQ Slope Name testString Band 1	GA"testString">1>4\x0D
Parametric EQ Slope Name testString Band 16	GA"testString">16>4\x0D
Parametric EQ Type Name testString Band 1	GA"testString">1>5\x0D
Parametric EQ Type Name testString Band 16	GA"testString">16>5\x0D
Peak/RMS Input Detect Name testString	GA"testString">1\x0D
Peak/RMS RMS Name testString Function Attack	GA"testString">8\x0D
Peak/RMS RMS Name testString Function Release	GA"testString">9\x0D
PSTN Call Active Name testString	GA"testString">0>8\x0D
PSTN Call Status Name testString	GA"testString">0>1\x0D
PSTN Caller ID Type Date Name testString	GA"testString">0>2\x0D
PSTN Caller ID Type Name Name testString	GA"testString">0>2\x0D
PSTN Caller ID Type Number Name testString	GA"testString">0>2\x0D
PSTN Caller ID Type Time Name testString	GA"testString">0>2\x0D
PSTN Hook Name testString	GA"testString">0>9\x0D
PSTN Level Name testString Module Input	GA"testString">1>1\x0D
PSTN Level Name testString Module Output	GA"testString">1\x0D
PSTN Mute Name testString Module Input	GA"testString">1>2\x0D
PSTN Mute Name testString Module Output	GA"testString">2\x0D
Router Input Select Name testString Output 1	GA"testString">1\x0D
Router Input Select Name testString Output 32	GA"testString">32\x0D
Signal Generator Gain Wave Pink Name testString	GA"testString">3>1\x0D
Signal Generator Gain Wave Sine Name testString	GA"testString">1>2\x0D
Signal Generator Gain Wave Sweep Name testString	GA"testString">4>1\x0D
Signal Generator Gain Wave White Name testString	GA"testString">2>1\x0D
Signal Generator Mute Wave Pink Name testString	GA"testString">3>2\x0D

Global Scriptor Module Communication Sheet

Signal Generator Mute Wave Sine Name testString	GA"testString">1>3\x0D
Signal Generator Mute Wave White Name testString	GA"testString">2>2\x0D
Source Select Name testString	GA"testString">1\x0D
Speaker Parametric Align Delay Name testString	GA"testString">0>4\x0D
Speaker Parametric Bypass Type High Name testString	GA"testString">0>10\x0D
Speaker Parametric Bypass Type Low Name testString	GA"testString">0>9\x0D
Speaker Parametric EQ Band Bypass Index 1 1 Name testString	GA"testString">1>6\x0D
Speaker Parametric EQ Band Bypass Index 1 9 Name testString	GA"testString">9>6\x0D
Speaker Parametric EQ Band Filter Index 1 1 Name testString	GA"testString">1>5\x0D
Speaker Parametric EQ Band Filter Index 1 9 Name testString	GA"testString">9>5\x0D
Speaker Parametric EQ Band Frequency Index 1 1 Name testString	GA"testString">1>1\x0D
Speaker Parametric EQ Band Frequency Index 1 9 Name testString	GA"testString">9>1\x0D
Speaker Parametric EQ Band Gain Index 1 1 Name testString	GA"testString">1>3\x0D
Speaker Parametric EQ Band Gain Index 1 9 Name testString	GA"testString">9>3\x0D
Speaker Parametric EQ Band Q Index 1 1 Name testString	GA"testString">1>2\x0D
Speaker Parametric EQ Band Q Index 1 9 Name testString	GA"testString">9>2\x0D
Speaker Parametric Filter Type High Name testString	GA"testString">0>5\x0D
Speaker Parametric Filter Type Low Name testString	GA"testString">0>7\x0D
Speaker Parametric Frequency Type High Name testString	GA"testString">0>6\x0D
Speaker Parametric Frequency Type Low Name testString	GA"testString">0>8\x0D
Speaker Parametric Gain Name testString	GA"testString">0>3\x0D
Standard Mixer Level Index 1 Input Name testString Index 2 1	GA"testString">1>1\x0D
Standard Mixer Level Index 1 Input Name testString Index 2 32	GA"testString">1>63\x0D
Standard Mixer Level Index 1 Output Name testString Index 2 1	GA"testString">2>1\x0D
Standard Mixer Level Index 1 Output Name testString Index 2 32	GA"testString">2>63\x0D
Standard Mixer Mute Index 1 Input Name testString Index 2 1	GA"testString">1>2\x0D
Standard Mixer Mute Index 1 Input Name testString	GA"testString">1>64\x0D

Global Scripter Module Communication Sheet

Revision: 6/10/2020

Index 2 32	
Standard Mixer Mute Index 1 Output Name testString Index 2 1	GA"testString">2>2\x0D
Standard Mixer Mute Index 1 Output Name testString Index 2 32	GA"testString">2>64\x0D
Standard Mixer Routing Input 1 Name testString Output 1	GA"testString">4>(1,1)\x0D
Standard Mixer Routing Input 1 Name testString Output 32	GA"testString">4>(1,32)\x0D
Standard Mixer Routing Input 32 Name testString Output 1	GA"testString">4>(32,1)\x0D
Standard Mixer Routing Input 32 Name testString Output 32	GA"testString">4>(32,32)\x0D
Surround Input Level Name testString Level Back Surround Left	GA"testString">10\x0D
Surround Input Level Name testString Level Back Surround Right	GA"testString">11\x0D
Surround Input Level Name testString Level Center	GA"testString">8\x0D
Surround Input Level Name testString Level Left Front	GA"testString">4\x0D
Surround Input Level Name testString Level Left Surround	GA"testString">6\x0D
Surround Input Level Name testString Level LFE (Sub)	GA"testString">9\x0D
Surround Input Level Name testString Level Right Front	GA"testString">5\x0D
Surround Input Level Name testString Level Right Surround	GA"testString">7\x0D
Surround Input Output Format Name testString	GA"testString">2\x0D
Surround Input Room Type Name testString	GA"testString">3\x0D
Surround Input Source Name testString	GA"testString">1\x0D
Tone Control Gain Type High Name testString	GA"testString">5\x0D
Tone Control Gain Type Low Name testString	GA"testString">1\x0D
Tone Control Gain Type Mid Name testString	GA"testString">3\x0D
USB Level Name testString Channel Left	GA"testString">1>1\x0D
USB Level Name testString Channel Right	GA"testString">2>1\x0D
USB Mute Name testString Channel Left	GA"testString">1>2\x0D
USB Mute Name testString Channel Right	GA"testString">2>2\x0D
VoIP Call Active Name testString	GA"testString">0>6\x0D
VoIP Call Status Name testString	GA"testString">0>1\x0D
VoIP Caller ID Type Hostname Name testString	GA"testString">0>2\x0D
VoIP Caller ID Type Name Name testString	GA"testString">0>2\x0D
VoIP Level Name testString	GA"testString">1>1\x0D
VoIP Mute Name testString	GA"testString">1>2\x0D