

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Camera
Manufacturer: Bosch
Firmware Version: N/A
Model(s): HD Conference Dome

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/23/2017	Initial Version

Module Notes

- For Ethernet support using HTTP protocol, HTTPClass must be used. Example: InterfaceName = ModuleName.HTTPClass ('192.168.254.254', 'admin', 'password', Model = 'ModelName')

Control Commands, States, and Qualifiers:

Pan	'Left'	'Right'
['Speed']	1 – 15	
Preset	'1' – '99'	
['Action']	'Save'	'Recall'
StopControl	None	
Tilt	'Up'	'Down'
['Speed']	1 – 15	
Zoom	'In'	'Out'
['Speed']	1 – 7	

Status Available:

N/A

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type: Ethernet (HTTP)

Default Port: 80

Logon Credentials Supported: Yes

Multi-Connection Capabilities: Undetermined

Port Changeability: Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device: