

---

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

---

## Device Specifications

Device Type: Video Projector  
Manufacturer: Canon  
Firmware Version: N/A  
Model(s): CLP-507FHD, GL-750FHD

## Tested on the Following Software and Firmware Versions

| IP Link Pro Control Processor Firmware | Global Scriptor Version |
|----------------------------------------|-------------------------|
| 3.03.0000-b006                         | 2.3.0                   |

## Version History

| Module Version | Date      | Notes           |
|----------------|-----------|-----------------|
| 1_0_0_0        | 5/15/2019 | Initial Version |

---

## Module Notes

- Status is not supported.

## Supported Classes and Examples

|                                                                                                 |
|-------------------------------------------------------------------------------------------------|
| <b>SerialClass</b>                                                                              |
| InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='CLP-507FHD')               |
| <b>SerialOverEthernetClass</b>                                                                  |
| InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='CLP-507FHD') |

## Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

|                                                         |                                                    |                                                 |                                             |
|---------------------------------------------------------|----------------------------------------------------|-------------------------------------------------|---------------------------------------------|
| <b>Command</b><br><b>Input</b>                          | Value<br>'HDMI 1'<br>'VGA 2'<br>'S-Video'<br>'USB' | Value<br>'HDMI 2 (MHL)'<br>'Video'<br>'Network' | Value<br>'VGA 1'<br>'Component'<br>'Memory' |
| # Input example<br>InterfaceName.Set('Input', 'HDMI 1') |                                                    |                                                 |                                             |
| <b>Command</b><br><b>Power</b>                          | Value<br>'On'                                      | Value<br>'On Immediately'                       | Value<br>'Off'                              |
| # Power example<br>InterfaceName.Set('Power', 'On')     |                                                    |                                                 |                                             |

---

---

## Cable and Adapter Requirements

Captive Screw to Female DB9 RS-232 Serial Cable

## Notes for the Device

---

---

## Serial communication

**Port Type:** RS-232

**Baud Rate:** 19200


**Data Bits:** 8

**Parity:** None


**Stop Bits:** One

**Flow Control:** None

## Pin Assignments Diagram



| Signal | Main Cable | Pin | Signal |
|--------|------------|-----|--------|
| TxD    | →          | 2   | RxD    |
| RxD    | ←          | 3   | TxD    |
| GND    |            | 5   | GND    |



---

## Appendix A. Set Commands

|                      |         |
|----------------------|---------|
| Input Component      | C33\x0D |
| Input HDMI 1         | C36\x0D |
| Input HDMI 2 (MHL)   | C37\x0D |
| Input Memory         | C16\x0D |
| Input Network        | C15\x0D |
| Input S-Video        | C34\x0D |
| Input USB            | C17\x0D |
| Input VGA 1          | C05\x0D |
| Input VGA 2          | C06\x04 |
| Input Video          | C07\x0D |
| Power Off            | C02\x0D |
| Power On             | C00\x0D |
| Power On Immediately | C01\x0D |