

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Other
 Manufacturer: Catch Technologies
 Firmware Version: v1.04
 Model(s): Hushbutton, HB-PCI

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.04.0001-b002	2.3.0

Version History

Module Version	Date	Notes
1_0_0_0	7/19/2019	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`

Supported Class and Example

EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 23, Model='Hushbutton')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format with Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command	Value	Value	Value
PortLED	'Red'	'Green'	'Off'
Qualifier Key	Qualifier Value		
'Input'	'1' – '8'		
# PortLED example InterfaceName.Set('PortLED', 'Red', {'Input': '1'})			
Command	Value	Value	Value
PortLEDAI	'Red'	'Green'	'Off'
# PortLEDAll example InterfaceName.Set('PortLEDAll', 'Red')			

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and it is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command	Value	Value
ConnectionStatus	'Connected'	'Disconnected'
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)		
Command	Value	Value
PortLED ¹	'Red'	'Green'
Qualifier Key	Qualifier Value	Value
'Input'	'1' – '8'	'Off'
# PortLED example InterfaceName.Update('PortLED') Value = InterfaceName.ReadStatus('PortLED', {'Input': '1'}) InterfaceName.SubscribeStatus('PortLED', None, FeedbackHandler)		
Command	Value	Value
SwitchPressStatus ¹	'Pressed'	'Released'
Qualifier Key	Qualifier Value	
'Input'	'1' – '8'	
# SwitchPressStatus example InterfaceName.Update('SwitchPressStatus') Value = InterfaceName.ReadStatus('SwitchPressStatus', {'Input': '1'}) InterfaceName.SubscribeStatus('SwitchPressStatus', None, FeedbackHandler)		

¹ Qualifier parameters is not required when calling the Update method with this command because the response returns statuses for all qualifier states.

Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet

Default Port: 23

Logon Credentials Supported: No

Multi-Connection Capabilities: No

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

Appendix A. Set Commands

Port LED All Green	{=a00ffffff}{=a00ffffff}
Port LED All Off	{=a000000ff}
Port LED All Red	{=aff0000ff}{=aff0000ff}
Port LED Green Input 1	{=10111}
Port LED Green Input 8	{=80111}
Port LED Off Input 1	{=10001}
Port LED Off Input 8	{=80001}
Port LED Red Input 1	{=11001}
Port LED Red Input 8	{=81001}

Appendix B. Update Commands

Port Status	{?a}
Switch Press Status	{?s}