

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Signal Processor
Manufacturer: Christie
Firmware Version: N/A
Model(s): Spyder X20

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.05.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_1_0	4/28/2017	Initial Version

Control Commands, States, and Qualifiers:

BasicPreset	1 – 50
['Preset Type']	'Learn' 'Recall'
InputConfiguration	1 – 50
['Configuration Type']	'Learn' 'Recall'
['Layer']	1 – 16
InputLevelAdjust	None
['Brightness']	0 to 2 in steps of 0.1
['Contrast']	0 to 2.5 in steps of 0.1
['Hue']	-180 to 180 in steps of 1
['Saturation']	0 to 2 in steps of 0.1
['Layer']	1 to 16 in steps of 1
OutputFreeze	'On' 'Off'
['Output']	1 – 8
RecallScriptCue	None
['Register ID']	1 – 50
['Script Cue Number']	1 – 50

Status Available: N/A

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 38400


Data Bits: 8

Parity: Odd


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



RS232 DB9 Male
Video Processor

General Notes:

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	11116
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Undetermined

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands (Serial)

Basic Preset 1 Preset Type Learn	BPL 1\x0D
Basic Preset 1 Preset Type Recall	BPR 1\x0D
Basic Preset 50 Preset Type Learn	BPL 50\x0D
Basic Preset 50 Preset Type Recall	BPR 50\x0D
Input Configuration 1 Configuration Type Learn Layer 1	ICL 1 2\x0D
Input Configuration 1 Configuration Type Learn Layer 16	ICL 1 17\x0D
Input Configuration 1 Configuration Type Recall Layer 1	ICR 1 2\x0D
Input Configuration 1 Configuration Type Recall Layer 16	ICR 1 17\x0D
Input Configuration 50 Configuration Type Learn Layer 1	ICL 50 2\x0D
Input Configuration 50 Configuration Type Learn Layer 16	ICL 50 17\x0D
Input Configuration 50 Configuration Type Recall Layer 1	ICR 50 2\x0D
Input Configuration 50 Configuration Type Recall Layer 16	ICR 50 17\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 1 Contrast 0.0 Saturation 0.0	ILA 0.0 0.0 180 0.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 1 Contrast 0.0 Saturation 0.0	ILA 0.0 0.0 -180 0.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 1 Contrast 0.0 Saturation 2.0	ILA 0.0 0.0 180 2.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 1 Contrast 0.0 Saturation 2.0	ILA 0.0 0.0 -180 2.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 1 Contrast 2.5 Saturation 0.0	ILA 0.0 2.5 180 0.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 1 Contrast 2.5 Saturation 0.0	ILA 0.0 2.5 -180 0.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 1 Contrast 2.5 Saturation 2.0	ILA 0.0 2.5 180 2.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 1 Contrast 2.5 Saturation 2.0	ILA 0.0 2.5 -180 2.0 2\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 16 Contrast 0.0 Saturation 0.0	ILA 0.0 0.0 180 0.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 16 Contrast 0.0 Saturation 0.0	ILA 0.0 0.0 -180 0.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 16 Contrast 0.0 Saturation 2.0	ILA 0.0 0.0 180 2.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 16 Contrast 0.0 Saturation 2.0	ILA 0.0 0.0 -180 2.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 16 Contrast 2.5 Saturation 0.0	ILA 0.0 2.5 180 0.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 16 Contrast 2.5 Saturation 0.0	ILA 0.0 2.5 -180 0.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue 180 Layer 16 Contrast 2.5 Saturation 2.0	ILA 0.0 2.5 180 2.0 17\x0D
Input Level Adjust None Brightness 0.0 Hue -180 Layer 16 Contrast 2.5 Saturation 2.0	ILA 0.0 2.5 -180 2.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 1 Contrast 0.0 Saturation 0.0	ILA 2.0 0.0 180 0.0 2\x0D

Input Level Adjust None Brightness 2.0 Hue -180 Layer 1 Contrast 0.0 Saturation 0.0	ILA 2.0 0.0 -180 0.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 1 Contrast 0.0 Saturation 2.0	ILA 2.0 0.0 180 2.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 1 Contrast 0.0 Saturation 2.0	ILA 2.0 0.0 -180 2.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 1 Contrast 2.5 Saturation 0.0	ILA 2.0 2.5 180 0.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 1 Contrast 2.5 Saturation 0.0	ILA 2.0 2.5 -180 0.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 1 Contrast 2.5 Saturation 2.0	ILA 2.0 2.5 180 2.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 1 Contrast 2.5 Saturation 2.0	ILA 2.0 2.5 -180 2.0 2\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 16 Contrast 0.0 Saturation 0.0	ILA 2.0 0.0 180 0.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 16 Contrast 0.0 Saturation 0.0	ILA 2.0 0.0 -180 0.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 16 Contrast 0.0 Saturation 2.0	ILA 2.0 0.0 180 2.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 16 Contrast 0.0 Saturation 2.0	ILA 2.0 0.0 -180 2.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 16 Contrast 2.5 Saturation 0.0	ILA 2.0 2.5 180 0.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 16 Contrast 2.5 Saturation 0.0	ILA 2.0 2.5 -180 0.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue 180 Layer 16 Contrast 2.5 Saturation 2.0	ILA 2.0 2.5 180 2.0 17\x0D
Input Level Adjust None Brightness 2.0 Hue -180 Layer 16 Contrast 2.5 Saturation 2.0	ILA 2.0 2.5 -180 2.0 17\x0D
Output Freeze Off Output 1	OFZ 0 0\x0D
Output Freeze Off Output 8	OFZ 0 7\x0D
Output Freeze On Output 1	OFZ 1 0\x0D
Output Freeze On Output 8	OFZ 1 7\x0D
Recall Script Cue None Register ID 1 Script Cue Number 1	RSC 0 1 R\x0D
Recall Script Cue None Register ID 1 Script Cue Number 50	RSC 0 50 R\x0D
Recall Script Cue None Register ID 50 Script Cue Number 1	RSC 5009 1 R\x0D
Recall Script Cue None Register ID 50 Script Cue Number 50	RSC 5009 50 R\x0D

Appendix B. Set Commands (Ethernet)

Basic Preset 1 Preset Type Learn	spyder\x00\x00\x00\x00BPL 1
Basic Preset 1 Preset Type Recall	spyder\x00\x00\x00\x00BPR 1
Basic Preset 50 Preset Type Learn	spyder\x00\x00\x00\x00BPL 50
Basic Preset 50 Preset Type Recall	spyder\x00\x00\x00\x00BPR 50
Input Configuration 1 Layer 1 Configuration Type Learn	spyder\x00\x00\x00\x00ICL 1 2
Input Configuration 1 Layer 1 Configuration Type Recall	spyder\x00\x00\x00\x00ICR 1 2
Input Configuration 1 Layer 16 Configuration Type Learn	spyder\x00\x00\x00\x00ICL 1 17
Input Configuration 1 Layer 16 Configuration Type Recall	spyder\x00\x00\x00\x00ICR 1 17
Input Configuration 50 Layer 1 Configuration Type Learn	spyder\x00\x00\x00\x00ICL 50 2
Input Configuration 50 Layer 1 Configuration Type Recall	spyder\x00\x00\x00\x00ICR 50 2
Input Configuration 50 Layer 16 Configuration Type Learn	spyder\x00\x00\x00\x00ICL 50 17
Input Configuration 50 Layer 16 Configuration Type Recall	spyder\x00\x00\x00\x00ICR 50 17
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 0.0 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 180 0.0 2
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 0.0 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 -180 0.0 2
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 0.0 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 180 0.0 2
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 0.0 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 -180 0.0 2
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 0.0 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 180 0.0 17
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 0.0 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 -180 0.0 17
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 0.0 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 180 0.0 17
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 0.0 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 -180 0.0 17
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 2.5 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 180 0.0 2
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 2.5 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 -180 0.0 2
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 2.5 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 180 0.0 2
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 2.5 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 -180 0.0 2
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 2.5 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 180 0.0 17
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 2.5 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 -180 0.0 17
Input Level Adjust None Hue 180 Saturation 0.0 Contrast 2.5 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 180 0.0 17
Input Level Adjust None Hue -180 Saturation 0.0 Contrast 2.5 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 -180 0.0 17
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 0.0 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 180 2.0 2

Input Level Adjust None Hue -180 Saturation 2.0 Contrast 0.0 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 -180 2.0 2
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 0.0 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 180 2.0 2
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 0.0 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 -180 2.0 2
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 0.0 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 180 2.0 17
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 0.0 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 0.0 -180 2.0 17
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 0.0 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 180 2.0 17
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 0.0 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 0.0 -180 2.0 17
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 2.5 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 180 2.0 2
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 2.5 Layer 1 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 -180 2.0 2
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 2.5 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 180 2.0 2
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 2.5 Layer 1 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 -180 2.0 2
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 2.5 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 180 2.0 17
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 2.5 Layer 16 Brightness 0.0	spyder\x00\x00\x00\x00ILA 0.0 2.5 -180 2.0 17
Input Level Adjust None Hue 180 Saturation 2.0 Contrast 2.5 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 180 2.0 17
Input Level Adjust None Hue -180 Saturation 2.0 Contrast 2.5 Layer 16 Brightness 2.0	spyder\x00\x00\x00\x00ILA 2.0 2.5 -180 2.0 17
Output Freeze Off Output 1	spyder\x00\x00\x00\x00OFZ 0 0
Output Freeze Off Output 8	spyder\x00\x00\x00\x00OFZ 0 7
Output Freeze On Output 1	spyder\x00\x00\x00\x00OFZ 1 0
Output Freeze On Output 8	spyder\x00\x00\x00\x00OFZ 1 7
Recall Script Cue None Script Cue Number 1 Register ID 1	spyder\x00\x00\x00\x00RSC 0 1 R
Recall Script Cue None Script Cue Number 1 Register ID 50	spyder\x00\x00\x00\x00RSC 5009 1 R
Recall Script Cue None Script Cue Number 50 Register ID 1	spyder\x00\x00\x00\x00RSC 0 50 R
Recall Script Cue None Script Cue Number 50 Register ID 50	spyder\x00\x00\x00\x00RSC 5009 50 R