

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): D12WU-H, D12HD-H

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.01.0000-b004	2.01.0000-b003	1.0.5

Version History

Module Version	Date	Notes
1_0_2_0	6/14/2016	Fixed Input and Auto Image.
1_0_1_0	3/23/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- ConnectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.ConnectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Auto'	'Full Size'	'Full Width'
	'Full Height'	'Native'	'Custom'
	'4:3'	'Letterbox'	'3D Mode'
AutoImage	None		
Freeze	'On'	'Off'	
Input	'VGA'	'BNC'	'HDMI 1'
	'HDMI 2'	'DVI-D'	'DisplayPort'
	'3G-SDI'	'HDBaseT'	'CVBS'
	'Presenter'	'Card Reader'	'Mini USB'
LampMode	'High'	'Eco'	'Power'
LampSelect	'Lamp 1 Only'	'Lamp 2 Only'	'Lamp 1 and 2'
OnScreenDisplay	'On'	'Off'	
PIPMode	'On'	'Off'	
Power	'On'	'Off'	
PresentationMode	'Presentation'	'Video'	'Bright'
	'Real'	'DICOM SIM'	'2D High Speed'
	'User'		
Shutter	'On'	'Off'	

Status Available:

AspectRatio	'Auto' 'Full Height' '4:3'	'Full Size' 'Native' 'Letterbox'	'Full Width' 'Custom' '3D Mode'
ConnectionStatus	'Connected' 'Disconnected'		
Freeze	'On' 'Off'		
Input	'VGA' 'HDMI 2' '3G-SDI' 'Presenter'	'BNC' 'DVI-D' 'HDBaseT' 'Card Reader'	'HDMI 1' 'DisplayPort' 'CVBS' 'Mini USB'
LampMode	'High' 'Eco' 'Power'		
LampSelect	'Lamp 1 Only' 'Lamp 2 Only' 'Lamp 1 and 2'		
LampUsage	Hours		
['Lamp Number']	'1' – '2'		
OnScreenDisplay	'On' 'Off'		
OperationHours	Hours		
PIPMODE	'On' 'Off'		
Power	'On' 'Off' 'Cooling Down' 'Warming Up'		
PresentationMode	'Presentation' 'Real' '3D'	'Video' 'DICOM SIM' 'User'	'Bright' '2D High Speed'
Shutter	'On' 'Off'		


Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable


Notes for the Device:**Serial communication:**

Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram

Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND

**General Notes:**

Network communication:

When configuring the Ethernet interface, be sure the device settings match that of the GS interface settings.

Port Type:	Ethernet
Default Port:	3002
Logon Credentials Supported:	No
Multi-Connection Capabilities:	Undetermined
Port Changeability:	Yes

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device: