

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): DHD400S, DUW350S

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_1_0	1/26/2017	Fixed the format of commands and statuses. Add SerialOverEthernetClass.
1_0_0_0	5/26/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:

AspectRatio	'Auto' '16:10 (Ultra Wide)'	'4:3'	'16:9'
AutoImage	None		
AVMute	'On'	'Off'	
ColorMode	'Bright' 'Game'	'PC' 'User'	'Movie'
DigitalZoom	'Up'	'Down'	
Freeze	'On'	'Off'	
Input	'VGA 1' 'HDMI 2'	'VGA 2' 'Video'	'HDMI 1' 'Multimedia'
MenuNavigation	'Up' 'Down'	'Left' 'Menu'	'Right'
Mute	'On'	'Off'	
Power	'On'	'Off'	
Volume	0 to 30 in steps of 1		

Status Available:

AspectRatio	'Auto'	'4:3'	'16:9'
	'16:10 (Ultra Wide)'		
ColorMode	'Bright'	'PC'	'Movie'
	'Game'	'User'	
ConnectionStatus	'Connected'	'Disconnected'	
Input	'VGA 1'	'VGA 2'	'HDMI 1'
	'HDMI 2'	'Video'	'Multimedia'
	'None'		
LampUsage	Hours		
Power	'On'	'Off'	

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS232 Serial Cable

Notes for the Device:

Serial communication:

Port Type: RS-232

Baud Rate: 19200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND



General Notes:

Appendix A. Set Commands

Aspect Ratio 16:10 (Ultra Wide)	(ASP 4)\x0D
Aspect Ratio 16:9	(ASP 3)\x0D
Aspect Ratio 4:3	(ASP 2)\x0D
Aspect Ratio Auto	(ASP 1)\x0D
Auto Image None	(RSC 1)\x0D
AV Mute Off	(AVM 0)\x0D
AV Mute On	(AVM 1)\x0D
Color Mode Bright	(PST 1)\x0D
Color Mode Game	(PST 4)\x0D
Color Mode Movie	(PST 3)\x0D
Color Mode PC	(PST 2)\x0D
Color Mode User	(PST 5)\x0D
Digital Zoom Down	(DZM 0)\x0D
Digital Zoom Up	(DZM 1)\x0D
Freeze Off	(FRZ 0)\x0D
Freeze On	(FRZ 1)\x0D
Input HDMI 1	(SIN 3)\x0D
Input HDMI 2	(SIN 4)\x0D
Input Multimedia	(SIN 6)\x0D
Input VGA 1	(SIN 1)\x0D
Input VGA 2	(SIN 2)\x0D
Input Video	(SIN 5)\x0D
Menu Navigation Down	(KEY 4)\x0D
Menu Navigation Left	(KEY 2)\x0D
Menu Navigation Menu	(KEY 5)\x0D
Menu Navigation Right	(KEY 3)\x0D
Menu Navigation Up	(KEY 1)\x0D
Mute Off	(MUT 0)\x0D
Mute On	(MUT 1)\x0D
Power Off	(PWR 0)\x0D
Power On	(PWR 1)\x0D
Volume 0	(VOL 0)\x0D
Volume 30	(VOL 30)\x0D

Appendix B. Query Commands

Aspect Ratio	(ASP ?)\x0D
Color Mode	(PST ?)\x0D
Input	(SIN ?)\x0D
Power	(SST ?)\x0D