

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Video Projector
Manufacturer: Christie
Firmware Version: N/A
Model(s): DHD550-G, DWU550-G

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_2_0	12/21/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example:
InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example:
InterfaceName.connectionCounter = 5

Control Commands, States, and Qualifiers:

AspectRatio	'Auto' 'Letterbox' 'Full Height'	'Native' 'Full Size'	'4:3' 'Full Width'
AutoImage	None		
ClosedCaption	'Off'	'CC1'	'CC2'
Freeze	'On'	'Off'	
Input	'VGA' 'Display Port' 'Composite' 'Card Reader'	'HDMI' 'Component' 'USB'	'DVI' 'S-Video' 'Christie Presenter'
Keypad	'0' – '9'		
LampMode	'Normal'	'Eco'	'Auto'
MenuNavigation	'Menu' 'Down' 'Enter'	'Up' 'Left'	'Right' 'Exit'
OnScreenDisplay	'On'	'Off'	
PIPMode	'On'	'Off'	
PIPPosition	'Left' 'Bottom' 'Top Left'	'Top' 'Bottom Right' 'Top Right'	'Right' 'Bottom Left'
PIPSize	'Small'	'Medium'	'Large'
PIPSwap	None		
Power	'On'	'Off'	
VideoMute	'On'	'Off'	

Status Available:

AspectRatio	'Auto' 'Letterbox' 'Full Height'	'Native' 'Full Size'	'4:3' 'Full Width'
ClosedCaption	'Off'	'CC1'	'CC2'
ConnectionStatus	'Connected'	'Disconnected'	
Freeze	'On'	'Off'	
Input	'VGA' 'Display Port' 'Composite' 'Card Reader'	'HDMI' 'Component' 'USB'	'DVI' 'S-Video' 'Christie Presenter'
LampMode	'Normal'	'Eco'	'Auto'
LampUsage	Hours		
OnScreenDisplay	'On'	'Off'	
PIPMODE	'On'	'Off'	
PIPPosition	'Left' 'Bottom' 'Top Left'	'Top' 'Bottom Right' 'Top Right'	'Right' 'Bottom Left'
PIPSize	'Small'	'Medium'	'Large'
Power	'On' 'Warming Up'	'Off'	'Cooling Down'
VideoMute	'On'	'Off'	

Cable and Adapter Requirements:

Captive Screw to Female DB9 RS-232 Serial Cable

Notes for the Device:


"Serial port echo" needs to be OFF.

Serial communication:


Port Type: RS-232
Baud Rate: 115200
Data Bits: 8

Parity: None
Stop Bits: 1
Flow Control: None

Pin Assignments Diagram:



Signal	Main Cable	Pin	Signal
TxD	→	2	RxD
RxD	←	3	TxD
GND	→	5	GND



Serial Driver Configuration Description:

Notes for the Device:

Network communication:

When configuring the Ethernet driver, be sure device settings match that of the GC configuration.

Port Type: Ethernet

Default Port: 3002

**Logon Credentials
Supported:** No

**Multi-Connection
Capabilities:** No

Port Changeability: Yes

Ethernet Driver Configuration Description:

Notes for the Device:

Appendix A. Set Commands (Serial)

Aspect Ratio 4:3	(SZP2)
Aspect Ratio Auto	(SZP0)
Aspect Ratio Full Height	(SZP6)
Aspect Ratio Full Size	(SZP4)
Aspect Ratio Full Width	(SZP5)
Aspect Ratio Letterbox	(SZP3)
Aspect Ratio Native	(SZP1)
Auto Image None	(AIM1)
Closed Caption CC1	(CLC1)
Closed Caption CC2	(CLC2)
Closed Caption Off	(CLC0)
Freeze Off	(FRZ0)
Freeze On	(FRZ1)
Input Card Reader	(SIN11)
Input Christie Presenter	(SIN10)
Input Component	(SIN7)
Input Composite	(SIN9)
Input Display Port	(SIN6)
Input DVI	(SIN5)
Input HDMI	(SIN4)
Input S-Video	(SIN8)
Input USB	(SIN12)
Input VGA	(SIN1)
Keypad 0	(KEY36)
Keypad 1	(KEY26)
Keypad 2	(KEY27)
Keypad 3	(KEY28)
Keypad 4	(KEY29)
Keypad 5	(KEY30)
Keypad 6	(KEY31)
Keypad 7	(KEY32)
Keypad 8	(KEY33)
Keypad 9	(KEY34)
Lamp Mode Auto	(LPM1)
Lamp Mode Eco	(LPM2)
Lamp Mode Normal	(LPM0)
Menu Navigation Down	(KEY42)
Menu Navigation Enter	(KEY40)
Menu Navigation Exit	(KEY20)
Menu Navigation Left	(KEY39)
Menu Navigation Menu	(KEY19)
Menu Navigation Right	(KEY41)
Menu Navigation Up	(KEY38)
On Screen Display Off	(OSD0)
On Screen Display On	(OSD1)
PIP Mode Off	(PIP0)

PIP Mode On	(PIP1)
PIP Position Bottom	(PPP3)
PIP Position Bottom Left	(PPP5)
PIP Position Bottom Right	(PPP4)
PIP Position Left	(PPP0)
PIP Position Right	(PPP2)
PIP Position Top	(PPP1)
PIP Position Top Left	(PPP6)
PIP Position Top Right	(PPP7)
PIP Size Large	(PHS2)
PIP Size Medium	(PHS1)
PIP Size Small	(PHS0)
PIP Swap None	(PPS1)
Power Off	(PWR0)
Power On	(PWR1)
Video Mute Off	(SHU0)
Video Mute On	(SHU1)

Appendix B. Query Commands (Serial)

Aspect Ratio	(SZP?)
Closed Caption	(CLC?)
Freeze	(FRZ?)
Input	(SIN?)
Lamp Mode	(LPM?)
Lamp Usage	(LIF+LP1H?)
On Screen Display	(OSD?)
PIP Mode	(PIP?)
PIP Position	(PPP?)
PIP Size	(PHS?)
Power	(PWR?)
Video Mute	(SHU?)