

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

---

---

## Device Specifications

Device Type: Video Projector  
Manufacturer: Christie  
Firmware Version: N/A  
Model(s): LHD878-DS, LWU755-DS, LWU900-DS

## Tested on the Following Software and Firmware Versions

| IP Link Pro Control Processor Firmware | Global Scriptor Version |
|----------------------------------------|-------------------------|
| 3.02.0000-b013                         | 2.2.0                   |

## Version History

| Module Version | Date      | Notes           |
|----------------|-----------|-----------------|
| 1_0_0_0        | 3/21/2019 | Initial Version |

---

## Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.  
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.  
Example: `InterfaceName.connectionCounter = 5`

## Supported Classes and Examples

|                                                                                                             |
|-------------------------------------------------------------------------------------------------------------|
| <b>SerialClass</b>                                                                                          |
| <code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='LHD878-DS')</code>               |
| <b>SerialOverEthernetClass</b>                                                                              |
| <code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='LHD878-DS')</code> |
| <b>EthernetClass</b>                                                                                        |
| <code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 23, Model='LHD878-DS')</code>             |

## Control Commands

Format with Qualifier:

InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})

Format with Qualifier:

InterfaceName.Set(Command, Value)

|                                                                                    |                                                   |                                       |                               |
|------------------------------------------------------------------------------------|---------------------------------------------------|---------------------------------------|-------------------------------|
| Command<br><b>AspectRatio<sup>1</sup></b>                                          | Value<br>'4:3'<br>'Native'<br>'16:10'             | Value<br>'16:9'<br>'Zoom'             | Value<br>'Normal'<br>'14:9'   |
| # AspectRatio example<br>InterfaceName.Set('AspectRatio', '4:3')                   |                                                   |                                       |                               |
| Command<br><b>AudioMute</b>                                                        | Value<br>'On'                                     | Value<br>'Off'                        |                               |
| # AudioMute example<br>InterfaceName.Set('AudioMute', 'On')                        |                                                   |                                       |                               |
| Command<br><b>AutoImage</b>                                                        | Value<br>'None'                                   |                                       |                               |
| # AutoImage example<br>InterfaceName.Set('AutoImage', None)                        |                                                   |                                       |                               |
| Command<br><b>AVMute</b>                                                           | Value<br>'On'                                     | Value<br>'Off'                        |                               |
| # AVMute example<br>InterfaceName.Set('AVMute', 'On')                              |                                                   |                                       |                               |
| Command<br><b>ClosedCaption</b>                                                    | Value<br>'On'                                     | Value<br>'Off'                        | Value<br>'Auto'               |
| # ClosedCaption example<br>InterfaceName.Set('ClosedCaption', 'On')                |                                                   |                                       |                               |
| Command<br><b>ClosedCaptionChannel</b>                                             | Value<br>'CC1'<br>'CC4'                           | Value<br>'CC2'                        | Value<br>'CC3'                |
| # ClosedCaptionChannel example<br>InterfaceName.Set('ClosedCaptionChannel', 'CC1') |                                                   |                                       |                               |
| Command<br><b>ClosedCaptionMode</b>                                                | Value<br>'Captions'                               | Value<br>'Text'                       |                               |
| # ClosedCaptionMode example<br>InterfaceName.Set('ClosedCaptionMode', 'Captions')  |                                                   |                                       |                               |
| Command<br><b>Freeze</b>                                                           | Value<br>'On'                                     | Value<br>'Off'                        |                               |
| # Freeze example<br>InterfaceName.Set('Freeze', 'On')                              |                                                   |                                       |                               |
| Command<br><b>Input</b>                                                            | Value<br>'Computer'<br>'DisplayPort'<br>'HDBaseT' | Value<br>'Video'<br>'HDMI 1'<br>'LAN' | Value<br>'3G-SDI'<br>'HDMI 2' |
| # Input example<br>InterfaceName.Set('Input', 'Computer')                          |                                                   |                                       |                               |
| Command<br><b>KeypadLock</b>                                                       | Value<br>'On'                                     | Value<br>'Off'                        |                               |
| # KeypadLock example<br>InterfaceName.Set('KeypadLock', 'On')                      |                                                   |                                       |                               |

|                                                                                      |                                                             |                                                 |                                         |
|--------------------------------------------------------------------------------------|-------------------------------------------------------------|-------------------------------------------------|-----------------------------------------|
| <b>Command</b><br><b>Power</b>                                                       | Value<br>'On'                                               | Value<br>'Off'                                  |                                         |
| # Power example<br>InterfaceName.Set('Power', 'On')                                  |                                                             |                                                 |                                         |
| <b>Command</b><br><b>VideoMute</b>                                                   | Value<br>'On'                                               | Value<br>'Off'                                  |                                         |
| # VideoMute example<br>InterfaceName.Set('VideoMute', 'On')                          |                                                             |                                                 |                                         |
| <b>Command</b><br><b>VolumeStep</b> <sup>2</sup>                                     | Value<br>'Up'                                               | Value<br>'Down'                                 |                                         |
| <b>Qualifier Key</b><br>'Input'                                                      | Qualifier Value<br>'Computer'<br>'DisplayPort'<br>'HDBaseT' | Qualifier Value<br>'Video'<br>'HDMI 1'<br>'LAN' | Qualifier Value<br>'3G-SDI'<br>'HDMI 2' |
| # VolumeStep example<br>InterfaceName.Set('VolumeStep', 'Up', {'Input': 'Computer'}) |                                                             |                                                 |                                         |

<sup>1</sup> This command will only work when there's an Input signal connected to the device.

<sup>2</sup> This command is dependent on the Input selected.

## Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

### Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

### Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

|                                                                                                                                                                                                                            |                                       |                           |                             |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------|---------------------------|-----------------------------|
| <b>Command</b><br><b>AspectRatio<sup>1</sup></b>                                                                                                                                                                           | Value<br>'4:3'<br>'Native'<br>'16:10' | Value<br>'16:9'<br>'Zoom' | Value<br>'Normal'<br>'14:9' |
| # AspectRatio example<br>InterfaceName.Update('AspectRatio')<br>Value = InterfaceName.ReadStatus('AspectRatio')<br>InterfaceName.SubscribeStatus('AspectRatio', None, FeedbackHandler)                                     |                                       |                           |                             |
| <b>Command</b><br><b>AudioMute</b>                                                                                                                                                                                         | Value<br>'On'                         | Value<br>'Off'            |                             |
| # AudioMute example<br>InterfaceName.Update('AudioMute')<br>Value = InterfaceName.ReadStatus('AudioMute')<br>InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)                                             |                                       |                           |                             |
| <b>Command</b><br><b>AVMute</b>                                                                                                                                                                                            | Value<br>'On'                         | Value<br>'Off'            |                             |
| # AVMute example<br>InterfaceName.Update('AVMute')<br>Value = InterfaceName.ReadStatus('AVMute')<br>InterfaceName.SubscribeStatus('AVMute', None, FeedbackHandler)                                                         |                                       |                           |                             |
| <b>Command</b><br><b>ClosedCaption</b>                                                                                                                                                                                     | Value<br>'On'                         | Value<br>'Off'            | Value<br>'Auto'             |
| # ClosedCaption example<br>InterfaceName.Update('ClosedCaption')<br>Value = InterfaceName.ReadStatus('ClosedCaption')<br>InterfaceName.SubscribeStatus('ClosedCaption', None, FeedbackHandler)                             |                                       |                           |                             |
| <b>Command</b><br><b>ClosedCaptionChannel</b>                                                                                                                                                                              | Value<br>'CC1'<br>'CC4'               | Value<br>'CC2'            | Value<br>'CC3'              |
| # ClosedCaptionChannel example<br>InterfaceName.Update('ClosedCaptionChannel')<br>Value = InterfaceName.ReadStatus('ClosedCaptionChannel')<br>InterfaceName.SubscribeStatus('ClosedCaptionChannel', None, FeedbackHandler) |                                       |                           |                             |
| <b>Command</b><br><b>ClosedCaptionMode</b>                                                                                                                                                                                 | Value<br>'Captions'                   | Value<br>'Text'           |                             |
| # ClosedCaptionMode example<br>InterfaceName.Update('ClosedCaptionMode')<br>Value = InterfaceName.ReadStatus('ClosedCaptionMode')<br>InterfaceName.SubscribeStatus('ClosedCaptionMode', None, FeedbackHandler)             |                                       |                           |                             |

# Global Scriptor Module Communication Sheet

|                                                                                                                                                                                            |                                                        |                                        |                                       |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------|----------------------------------------|---------------------------------------|
| <b>Command</b><br><b>ConnectionStatus</b>                                                                                                                                                  | Value<br>'Connected'                                   | Value<br>'Disconnected'                |                                       |
| Value = InterfaceName.ReadStatus('ConnectionStatus')<br>InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)                                                           |                                                        |                                        |                                       |
| <b>Command</b><br><b>DeviceStatus</b>                                                                                                                                                      | Value<br>'Normal'<br>'Laser Error'<br>'Filter Warning' | Value<br>'Cover Error'<br>'Temp Error' | Value<br>'Fan Error'<br>'Other Error' |
| # DeviceStatus example<br>InterfaceName.Update('DeviceStatus')<br>Value = InterfaceName.ReadStatus('DeviceStatus')<br>InterfaceName.SubscribeStatus('DeviceStatus', None, FeedbackHandler) |                                                        |                                        |                                       |
| <b>Command</b><br><b>FilterUsage</b>                                                                                                                                                       | Value<br>Hours                                         |                                        |                                       |
| # FilterUsage example<br>InterfaceName.Update('FilterUsage')<br>Value = InterfaceName.ReadStatus('FilterUsage')<br>InterfaceName.SubscribeStatus('FilterUsage', None, FeedbackHandler)     |                                                        |                                        |                                       |
| <b>Command</b><br><b>Freeze</b>                                                                                                                                                            | Value<br>'On'                                          | Value<br>'Off'                         |                                       |
| # Freeze example<br>InterfaceName.Update('Freeze')<br>Value = InterfaceName.ReadStatus('Freeze')<br>InterfaceName.SubscribeStatus('Freeze', None, FeedbackHandler)                         |                                                        |                                        |                                       |
| <b>Command</b><br><b>Input</b>                                                                                                                                                             | Value<br>'Computer'<br>'DisplayPort'<br>'HDBaseT'      | Value<br>'Video'<br>'HDMI 1'<br>'LAN'  | Value<br>'3G-SDI'<br>'HDMI 2'         |
| # Input example<br>InterfaceName.Update('Input')<br>Value = InterfaceName.ReadStatus('Input')<br>InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)                             |                                                        |                                        |                                       |
| <b>Command</b><br><b>KeypadLock</b>                                                                                                                                                        | Value<br>'On'                                          | Value<br>'Off'                         |                                       |
| # KeypadLock example<br>InterfaceName.Update('KeypadLock')<br>Value = InterfaceName.ReadStatus('KeypadLock')<br>InterfaceName.SubscribeStatus('KeypadLock', None, FeedbackHandler)         |                                                        |                                        |                                       |
| <b>Command</b><br><b>LampUsage</b>                                                                                                                                                         | Value<br>Hours                                         |                                        |                                       |
| # LampUsage example<br>InterfaceName.Update('LampUsage')<br>Value = InterfaceName.ReadStatus('LampUsage')<br>InterfaceName.SubscribeStatus('LampUsage', None, FeedbackHandler)             |                                                        |                                        |                                       |
| <b>Command</b><br><b>Power</b>                                                                                                                                                             | Value<br>'On'                                          | Value<br>'Off'                         | Value<br>'Cooling Down'               |
| # Power example<br>InterfaceName.Update('Power')<br>Value = InterfaceName.ReadStatus('Power')<br>InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)                             |                                                        |                                        |                                       |
| <b>Command</b><br><b>VideoMute</b>                                                                                                                                                         | Value<br>'On'                                          | Value<br>'Off'                         |                                       |
| # VideoMute example<br>InterfaceName.Update('VideoMute')<br>Value = InterfaceName.ReadStatus('VideoMute')<br>InterfaceName.SubscribeStatus('VideoMute', None, FeedbackHandler)             |                                                        |                                        |                                       |

|                                                                                                                                                                                                                                                              |                                                                    |                                                        |                                                |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------|--------------------------------------------------------|------------------------------------------------|
| <b>Command</b><br><b>VolumeLevelStatus</b>                                                                                                                                                                                                                   | <b>Value</b><br>0 – 48                                             |                                                        |                                                |
| <b>Qualifier Key</b><br><b>'Input'</b>                                                                                                                                                                                                                       | <b>Qualifier Value</b><br>'Computer'<br>'DisplayPort'<br>'HDBaseT' | <b>Qualifier Value</b><br>'Video'<br>'HDMI 1'<br>'LAN' | <b>Qualifier Value</b><br>'3G-SDI'<br>'HDMI 2' |
| # VolumeLevelStatus example<br>InterfaceName.Update('VolumeLevelStatus', {'Input': 'Computer'})<br>Value = InterfaceName.ReadStatus('VolumeLevelStatus', {'Input': 'Computer'})<br>InterfaceName.SubscribeStatus('VolumeLevelStatus', None, FeedbackHandler) |                                                                    |                                                        |                                                |

<sup>1</sup> This command will only work when there's an Input signal connected to the device.

---

## Cable and Adapter Requirements

---

### Notes for the Device

- In order for the Serial driver to work on the Menu section of the device go to Advance Menu → Option → Service → Communication → Communication Type → Off.

---

### Serial communication

**Port Type:** RS-232

**Baud Rate:** 19200


**Data Bits:** 8

**Parity:** None


**Stop Bits:** One

**Flow Control:** None

### Pin Assignments Diagram



| Signal | Main Cable | Pin | Signal |
|--------|------------|-----|--------|
| TxD    |            | 3   | TxD    |
| RxD    |            | 2   | RxD    |
| GND    |            | 5   | GND    |



---

---

## Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

|                                       |              |
|---------------------------------------|--------------|
| <b>Port Type:</b>                     | Ethernet     |
| <b>Default Port:</b>                  | 23           |
| <b>Logon Credentials Supported:</b>   | Undetermined |
| <b>Multi-Connection Capabilities:</b> | Undetermined |
| <b>Port Changeability:</b>            | Yes          |

---

---

## Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

## Notes for the Device

- In order for the Ethernet driver to work, the settings below must be set on the device.
  - Menu → Advanced Menu → Option → Service → Communication → Communication Type → Network Bridge (Wired)
  - Menu → Advanced Menu → Option → Service → Control Terminal → Wired Network → LAN
  - Menu → Advanced Menu → Network → Third Party Control → Extron

## Appendix A. Set Commands

|                                    |                                                    |
|------------------------------------|----------------------------------------------------|
| Aspect Ratio 14:9                  | \xBE\xEF\x03\x06\x00\xCE\xD6\x01\x00\x08 \x09\x00  |
| Aspect Ratio 16:10                 | \xBE\xEF\x03\x06\x00>\xD6\x01\x00\x08 \x0A\x00     |
| Aspect Ratio 16:9                  | \xBE\xEF\x03\x06\x00\x0E\xD1\x01\x00\x08 \x01\x00  |
| Aspect Ratio 4:3                   | \xBE\xEF\x03\x06\x00\x9E\xD0\x01\x00\x08 \x00\x00  |
| Aspect Ratio Native                | \xBE\xEF\x03\x06\x00^\xD7\x01\x00\x08 \x08\x00     |
| Aspect Ratio Normal                | \xBE\xEF\x03\x06\x00^\xDD\x01\x00\x08 \x10\x00     |
| Aspect Ratio Zoom                  | \xBE\xEF\x03\x06\x00\x9E\xC4\x01\x00\x08 0\x00     |
| Audio Mute Off                     | \xBE\xEF\x03\x06\x00F\xD3\x01\x00\x02 \x00\x00     |
| Audio Mute On                      | \xBE\xEF\x03\x06\x00\xD6\xD2\x01\x00\x02 \x01\x00  |
| Auto Image None                    | \xBE\xEF\x03\x06\x00\x91\xD0\x06\x00\x0A \x00\x00  |
| AV Mute Off                        | \xBE\xEF\x03\x06\x00\xFE\xF0\x01\x00\xA0 \x00\x00  |
| AV Mute On                         | \xBE\xEF\x03\x06\x00n\xF1\x01\x00\xA0 \x01\x00     |
| Closed Caption Auto                | \xBE\xEF\x03\x06\x00\x9Ac\x01\x00\x007\x02\x00     |
| Closed Caption Channel CC1         | \xBE\xEF\x03\x06\x00\xD2b\x01\x00\x027\x01\x00     |
| Closed Caption Channel CC2         | \xBE\xEF\x03\x06\x00"b\x01\x00\x027\x02\x00        |
| Closed Caption Channel CC3         | \xBE\xEF\x03\x06\x00\xB2c\x01\x00\x027\x03\x00     |
| Closed Caption Channel CC4         | \xBE\xEF\x03\x06\x00\x82a\x01\x00\x027\x04\x00     |
| Closed Caption Mode Captions       | \xBE\xEF\x03\x06\x00\x06c\x01\x00\x017\x00\x00     |
| Closed Caption Mode Text           | \xBE\xEF\x03\x06\x00\x96b\x01\x00\x017\x01\x00     |
| Closed Caption Off                 | \xBE\xEF\x03\x06\x00\xFAb\x01\x00\x007\x00\x00     |
| Closed Caption On                  | \xBE\xEF\x03\x06\x00jc\x01\x00\x007\x01\x00        |
| Freeze Off                         | \xBE\xEF\x03\x06\x00\x83\xD2\x01\x00\x020\x00\x00  |
| Freeze On                          | \xBE\xEF\x03\x06\x00\x13\xD3\x01\x00\x020\x01\x00  |
| Input 3G-SDI                       | \xBE\xEF\x03\x06\x00^\xDE\x01\x00\x00 \x12\x00     |
| Input Computer                     | \xBE\xEF\x03\x06\x00\xFE\xD2\x01\x00\x00 \x00\x00  |
| Input DisplayPort                  | \xBE\xEF\x03\x06\x00\xCE\xDF\x01\x00\x00 \x13\x00  |
| Input HDBaseT                      | \xBE\xEF\x03\x06\x00\xAE\xDE\x01\x00\x00 \x11\x00  |
| Input HDMI 1                       | \xBE\xEF\x03\x06\x00\x0E\xD2\x01\x00\x00 \x03\x00  |
| Input HDMI 2                       | \xBE\xEF\x03\x06\x00n\xD6\x01\x00\x00 \x0D\x00     |
| Input LAN                          | \xBE\xEF\x03\x06\x00\xCE\xD5\x01\x00\x00 \x0B\x00  |
| Input Video                        | \xBE\xEF\x03\x06\x00n\xD3\x01\x00\x00 \x01\x00     |
| Keypad Lock Off                    | \xBE\xEF\x03\x06\x00\x03\x96\x01\x00\x11\$\x00\x00 |
| Keypad Lock On                     | \xBE\xEF\x03\x06\x00\x93\x97\x01\x00\x11\$\x01\x00 |
| Power Off                          | \xBE\xEF\x03\x06\x00*\xD3\x01\x00\x00` \x00\x00    |
| Power On                           | \xBE\xEF\x03\x06\x00\xBA\xD2\x01\x00\x00` \x01\x00 |
| Video Mute Off                     | \xBE\xEF\x03\x06\x00\xFB\xD8\x01\x00 0\x00\x00     |
| Video Mute On                      | \xBE\xEF\x03\x06\x00k\xD9\x01\x00 0\x01\x00        |
| Volume Step Down Input 3G-SDI      | \xBE\xEF\x03\x06\x00v\xE4\x05\x00\xE5 \x00\x00     |
| Volume Step Down Input Computer    | \xBE\xEF\x03\x06\x00z\xCD\x05\x00` \x00\x00        |
| Volume Step Down Input DisplayPort | \xBE\xEF\x03\x06\x00\xB6\xE0\x05\x00\xF5 \x00\x00  |
| Volume Step Down Input HDBaseT     | \xBE\xEF\x03\x06\x00v\xEB\x05\x00\xD5 \x00\x00     |
| Volume Step Down Input HDMI 1      | \xBE\xEF\x03\x06\x00>\xCD\x05\x00c \x00\x00        |

## Global Scripter Module Communication Sheet

|                                         |                                                   |
|-----------------------------------------|---------------------------------------------------|
| <b>Volume Step Down Input HDMI 2</b>    | \xBE\xEF\x03\x06\x00\xD6\xCF\x05\x00m \x00\x00    |
| <b>Volume Step Down Input LAN</b>       | \xBE\xEF\x03\x06\x00^\xCF\x05\x00k \x00\x00       |
| <b>Volume Step Down Input Video</b>     | \xBE\xEF\x03\x06\x00\x86\xCC\x05\x00a \x00\x00    |
| <b>Volume Step Up Input 3G-SDI</b>      | \xBE\xEF\x03\x06\x00\xA7\xE5\x04\x00\xE5 \x00\x00 |
| <b>Volume Step Up Input Computer</b>    | \xBE\xEF\x03\x06\x00\xAB\xCC\x04\x00` \x00\x00    |
| <b>Volume Step Up Input DisplayPort</b> | \xBE\xEF\x03\x06\x00g\xE1\x04\x00\xF5 \x00\x00    |
| <b>Volume Step Up Input HDBaseT</b>     | \xBE\xEF\x03\x06\x00\xA7\xEA\x04\x00\xD5 \x00\x00 |
| <b>Volume Step Up Input HDMI 1</b>      | \xBE\xEF\x03\x06\x00\xEF\xCC\x04\x00c \x00\x00    |
| <b>Volume Step Up Input HDMI 2</b>      | \xBE\xEF\x03\x06\x00\x07\xCE\x04\x00m \x00\x00    |
| <b>Volume Step Up Input LAN</b>         | \xBE\xEF\x03\x06\x00\x8F\xCE\x04\x00k \x00\x00    |
| <b>Volume Step Up Input Video</b>       | \xBE\xEF\x03\x06\x00W\xCD\x04\x00a \x00\x00       |

## Appendix B. Update Commands

|                                       |                                                      |
|---------------------------------------|------------------------------------------------------|
| Aspect Ratio                          | \xBE\xEF\x03\x06\x00\xAD\xD0\x02\x00\x08 \x00\x00    |
| Audio Mute                            | \xBE\xEF\x03\x06\x00u\xD3\x02\x00\x02 \x00\x00       |
| AV Mute                               | \xBE\xEF\x03\x06\x00\xCD\xF0\x02\x00\xA0 \x00\x00    |
| Closed Caption                        | \xBE\xEF\x03\x06\x00\xC9b\x02\x00\x007\x00\x00       |
| Closed Caption Channel                | \xBE\xEF\x03\x06\x00qc\x02\x00\x027\x00\x00          |
| Closed Caption Mode                   | \xBE\xEF\x03\x06\x005c\x02\x00\x017\x00\x00          |
| Device Status                         | \xBE\xEF\x03\x06\x00\xD9\xD8\x02\x00 ` \x00\x00      |
| Filter Usage                          | \xBE\xEF\x03\x06\x00\xC2\xF0\x02\x00\xA0\x10\x00\x00 |
| Freeze                                | \xBE\xEF\x03\x06\x00\xB0\xD2\x02\x00\x020\x00\x00    |
| Input                                 | \xBE\xEF\x03\x06\x00\xCD\xD2\x02\x00\x00 \x00\x00    |
| Keypad Lock                           | \xBE\xEF\x03\x06\x000\x96\x02\x00\x11\$\x00\x00      |
| Lamp Usage                            | \xBE\xEF\x03\x06\x00\xC2\xFF\x02\x00\x90\x10\x00\x00 |
| Power                                 | \xBE\xEF\x03\x06\x00\x19\xD3\x02\x00\x00` \x00\x00   |
| Video Mute                            | \xBE\xEF\x03\x06\x00\xC8\xD8\x02\x00 0\x00\x00       |
| Volume Level Status Input 3G-SDI      | \xBE\xEF\x03\x06\x00\xC1\xE5\x02\x00\xE5 \x00\x00    |
| Volume Level Status Input Computer    | \xBE\xEF\x03\x06\x00\xCD\xCC\x02\x00` \x00\x00       |
| Volume Level Status Input DisplayPort | \xBE\xEF\x03\x06\x00\x01\xE1\x02\x00\xF5 \x00\x00    |
| Volume Level Status Input HDBaseT     | \xBE\xEF\x03\x06\x00\xC1\xEA\x02\x00\xD5 \x00\x00    |
| Volume Level Status Input HDMI 1      | \xBE\xEF\x03\x06\x00\x89\xCC\x02\x00c \x00\x00       |
| Volume Level Status Input HDMI 2      | \xBE\xEF\x03\x06\x00a\xCE\x02\x00m \x00\x00          |
| Volume Level Status Input LAN         | \xBE\xEF\x03\x06\x00\xE9\xCE\x02\x00k \x00\x00       |
| Volume Level Status Input Video       | \xBE\xEF\x03\x06\x001\xCD\x02\x00a \x00\x00          |