

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Lighting Control
Manufacturer: Clipsal
Firmware Version: N/A
Model(s): C-Bus PC Interface 5500PC

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.00.0000-b022	2.0.0

Version History

Module Version	Date	Notes
1_3_2_0	10/29/2018	Added Status for DimLevel. Removed ConnectionStatus. Fixed Checksum. Added more Lightning Appliaiton Address.
1_2_0_0	7/24/2018	Added SwitchLight status command. Added DeviceInitialization command. Changed default baud rate to 9600.
1_1_0_0	1/17/2018	Added ConnectionStatus. Consolidated DIMLevel and SwitchLight commands.
1_0_0_0	10/25/2016	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- Checksum variable must be set accordingly. Default value is 'Enabled'. Checksum can be set to 'Enabled' and the module will send a checksum byte to the device. Checksum can be set to 'Disabled' and the device will not look for a checksum byte in the command strings.
Example: `InterfaceName.Checksum = 'Enabled'`
- Module does not support any Update or ConnectionStatus.

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='C-Bus PC Interface 5500PC')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='C-Bus PC Interface 5500PC')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command DeviceInitialization 1	Value None		
# DeviceInitialization example InterfaceName.Set('DeviceInitialization')			
Command DimLevel	Value 0 to 255 in steps of 1		
Qualifier Key 'Lighting Application Address'	Qualifier Value '48' – '255'		
Qualifier Key 'Group Address'	Qualifier Value '0' – '255'		
Qualifier Key 'Dimming Rate'	Qualifier Value 'Instantaneous'	Qualifier Value '4 seconds'	Qualifier Value '8 seconds'
	'12 seconds'	'20 seconds'	'30 seconds'
	'40 seconds'	'1 minute'	'1.5 minutes'
	'2 minutes'	'3 minutes'	'5 minutes'
	'7 minutes'	'10 minutes'	'15 minutes'
	'17 minutes'		
	# DimLevel example InterfaceName.Set('DimLevel', 255, {'Lighting Application Address': '48', 'Group Address': '0', 'Dimming Rate': 'Instantaneous'})		
Command SwitchLight	Value 'On'	Value 'Off'	
Qualifier Key 'Lighting Application Address'	Qualifier Value '48' – '95'		
Qualifier Key 'Group Address'	Qualifier Value '0' – '255'		
# SwitchLight example InterfaceName.Set('SwitchLight', 'On', {'Lighting Application Address': '48', 'Group Address': '0'})			

¹ Send this command to Initialize the device settings. This command takes 4 seconds to execute as the device requires time to process the data. Do not send any other command within this 4 seconds as this will be delay.

Status Available

DimLevel and SwitchLight do not support the Update function.

Format with Qualifier:

```
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'}, FeedbackHandler)
FeedbackHandler will be called only when the specified qualifier gets a new status.
```

Format without Qualifier:

```
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command DimLevel	Value 0 to 255 in steps of 1		
Qualifier Key 'Lighting Application Address'	Qualifier Value '48' – '255'		
Qualifier Key 'Group Address'	Qualifier Value '0' – '255'		
Qualifier Key 'Dimming Rate'	Qualifier Value 'Instantaneous' '12 seconds' '40 seconds' '2 minutes' '7 minutes' '17 minutes'	Qualifier Value '4 seconds' '20 seconds' '1 minute' '3 minutes' '10 minutes'	Qualifier Value '8 seconds' '30 seconds' '1.5 minutes' '5 minutes' '15 minutes'
# DimLevel examples Value = InterfaceName.ReadStatus('DimLevel', {'Lighting Application Address': '48', 'Group Address': '0', 'Dimming Rate': 'Instantaneous'}) InterfaceName.SubscribeStatus('DimLevel', None, FeedbackHandler)			
Command SwitchLight	Value 'On'	Value 'Off'	
Qualifier Key 'Lighting Application Address'	Qualifier Value '48' – '255'		
Qualifier Key 'Group Address'	Qualifier Value '0' – '255'		
# SwitchLight examples Value = InterfaceName.ReadStatus('SwitchLight', {'Lighting Application Address': '48', 'Group Address': '0'}) InterfaceName.SubscribeStatus('SwitchLight', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to Male DB9 RS-232 Serial Cable. This device also supports Captive Screw to RJ45, consult the device documentation for wiring diagram.

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD	→	3	RxD
RxD	←	2	TxD
GND	→	5	GND



Appendix A. Set Commands (Checksum - Enabled)

Dim Level 0 Group Address 0 Dimming Rate 1 minute Lighting Application Address 48	\0530003A000091\x0D
Dim Level 0 Group Address 0 Dimming Rate 1 minute Lighting Application Address 95	\055F003A000062\x0D
Dim Level 0 Group Address 0 Dimming Rate 1.5 minutes Lighting Application Address 48	\05300042000089\x0D
Dim Level 0 Group Address 0 Dimming Rate 1.5 minutes Lighting Application Address 95	\055F004200005A\x0D
Dim Level 0 Group Address 0 Dimming Rate 10 minutes Lighting Application Address 48	\0530006A000061\x0D
Dim Level 0 Group Address 0 Dimming Rate 10 minutes Lighting Application Address 95	\055F006A000032\x0D
Dim Level 0 Group Address 0 Dimming Rate 12 seconds Lighting Application Address 48	\0530001A0000B1\x0D
Dim Level 0 Group Address 0 Dimming Rate 12 seconds Lighting Application Address 95	\055F001A000082\x0D
Dim Level 0 Group Address 0 Dimming Rate 15 minutes Lighting Application Address 48	\05300072000059\x0D
Dim Level 0 Group Address 0 Dimming Rate 15 minutes Lighting Application Address 95	\055F007200002A\x0D
Dim Level 0 Group Address 0 Dimming Rate 17 minutes Lighting Application Address 48	\0530007A000051\x0D
Dim Level 0 Group Address 0 Dimming Rate 17 minutes Lighting Application Address 95	\055F007A000022\x0D
Dim Level 0 Group Address 0 Dimming Rate 2 minutes Lighting Application Address 48	\0530004A000081\x0D
Dim Level 0 Group Address 0 Dimming Rate 2 minutes Lighting Application Address 95	\055F004A000052\x0D
Dim Level 0 Group Address 0 Dimming Rate 20 seconds Lighting Application Address 48	\053000220000A9\x0D
Dim Level 0 Group Address 0 Dimming Rate 20 seconds Lighting Application Address 95	\055F002200007A\x0D
Dim Level 0 Group Address 0 Dimming Rate 3 minutes Lighting Application Address 48	\05300052000079\x0D
Dim Level 0 Group Address 0 Dimming Rate 3 minutes Lighting Application Address 95	\055F005200004A\x0D
Dim Level 0 Group Address 0 Dimming Rate 30 seconds Lighting Application Address 48	\0530002A0000A1\x0D

Global Scripter Module Communication Sheet

Revision: 10/29/2018

Dim Level 0 Group Address 0 Dimming Rate 30 seconds Lighting Application Address 95	\055F002A000072\x0D
Dim Level 0 Group Address 0 Dimming Rate 4 seconds Lighting Application Address 48	\0530000A0000C1\x0D
Dim Level 0 Group Address 0 Dimming Rate 4 seconds Lighting Application Address 95	\055F000A000092\x0D
Dim Level 0 Group Address 0 Dimming Rate 40 seconds Lighting Application Address 48	\05300032000099\x0D
Dim Level 0 Group Address 0 Dimming Rate 40 seconds Lighting Application Address 95	\055F003200006A\x0D
Dim Level 0 Group Address 0 Dimming Rate 5 minutes Lighting Application Address 48	\0530005A000071\x0D
Dim Level 0 Group Address 0 Dimming Rate 5 minutes Lighting Application Address 95	\055F005A000042\x0D
Dim Level 0 Group Address 0 Dimming Rate 7 minutes Lighting Application Address 48	\05300062000069\x0D
Dim Level 0 Group Address 0 Dimming Rate 7 minutes Lighting Application Address 95	\055F006200003A\x0D
Dim Level 0 Group Address 0 Dimming Rate 8 seconds Lighting Application Address 48	\053000120000B9\x0D
Dim Level 0 Group Address 0 Dimming Rate 8 seconds Lighting Application Address 95	\055F001200008A\x0D
Dim Level 0 Group Address 0 Dimming Rate Instantaneous Lighting Application Address 48	\053000020000C9\x0D
Dim Level 0 Group Address 0 Dimming Rate Instantaneous Lighting Application Address 95	\055F000200009A\x0D
Dim Level 0 Group Address 255 Dimming Rate 1 minute Lighting Application Address 48	\0530003AFF0092\x0D
Dim Level 0 Group Address 255 Dimming Rate 1 minute Lighting Application Address 95	\055F003AFF0063\x0D
Dim Level 0 Group Address 255 Dimming Rate 1.5 minutes Lighting Application Address 48	\05300042FF008A\x0D
Dim Level 0 Group Address 255 Dimming Rate 1.5 minutes Lighting Application Address 95	\055F0042FF005B\x0D
Dim Level 0 Group Address 255 Dimming Rate 10 minutes Lighting Application Address 48	\0530006AFF0062\x0D
Dim Level 0 Group Address 255 Dimming Rate 10 minutes Lighting Application Address 95	\055F006AFF0033\x0D
Dim Level 0 Group Address 255 Dimming Rate 12 seconds Lighting Application Address 48	\0530001AFF00B2\x0D

Global Scripter Module Communication Sheet

Dim Level 0 Group Address 255 Dimming Rate 12 seconds Lighting Application Address 95	\055F001AFF0083\x0D
Dim Level 0 Group Address 255 Dimming Rate 15 minutes Lighting Application Address 48	\05300072FF005A\x0D
Dim Level 0 Group Address 255 Dimming Rate 15 minutes Lighting Application Address 95	\055F0072FF002B\x0D
Dim Level 0 Group Address 255 Dimming Rate 17 minutes Lighting Application Address 48	\0530007AFF0052\x0D
Dim Level 0 Group Address 255 Dimming Rate 17 minutes Lighting Application Address 95	\055F007AFF0023\x0D
Dim Level 0 Group Address 255 Dimming Rate 2 minutes Lighting Application Address 48	\0530004AFF0082\x0D
Dim Level 0 Group Address 255 Dimming Rate 2 minutes Lighting Application Address 95	\055F004AFF0053\x0D
Dim Level 0 Group Address 255 Dimming Rate 20 seconds Lighting Application Address 48	\05300022FF00AA\x0D
Dim Level 0 Group Address 255 Dimming Rate 20 seconds Lighting Application Address 95	\055F0022FF007B\x0D
Dim Level 0 Group Address 255 Dimming Rate 3 minutes Lighting Application Address 48	\05300052FF007A\x0D
Dim Level 0 Group Address 255 Dimming Rate 3 minutes Lighting Application Address 95	\055F0052FF004B\x0D
Dim Level 0 Group Address 255 Dimming Rate 30 seconds Lighting Application Address 48	\0530002AFF00A2\x0D
Dim Level 0 Group Address 255 Dimming Rate 30 seconds Lighting Application Address 95	\055F002AFF0073\x0D
Dim Level 0 Group Address 255 Dimming Rate 4 seconds Lighting Application Address 48	\0530000AFF00C2\x0D
Dim Level 0 Group Address 255 Dimming Rate 4 seconds Lighting Application Address 95	\055F000AFF0093\x0D
Dim Level 0 Group Address 255 Dimming Rate 40 seconds Lighting Application Address 48	\05300032FF009A\x0D
Dim Level 0 Group Address 255 Dimming Rate 40 seconds Lighting Application Address 95	\055F0032FF006B\x0D
Dim Level 0 Group Address 255 Dimming Rate 5 minutes Lighting Application Address 48	\0530005AFF0072\x0D
Dim Level 0 Group Address 255 Dimming Rate 5 minutes Lighting Application Address 95	\055F005AFF0043\x0D
Dim Level 0 Group Address 255 Dimming Rate 7 minutes Lighting Application Address 48	\05300062FF006A\x0D

Global Scripter Module Communication Sheet

Revision: 10/29/2018

Dim Level 0 Group Address 255 Dimming Rate 7 minutes Lighting Application Address 95	\055F0062FF003B\x0D
Dim Level 0 Group Address 255 Dimming Rate 8 seconds Lighting Application Address 48	\05300012FF00BA\x0D
Dim Level 0 Group Address 255 Dimming Rate 8 seconds Lighting Application Address 95	\055F0012FF008B\x0D
Dim Level 0 Group Address 255 Dimming Rate Instantaneous Lighting Application Address 48	\05300002FF00CA\x0D
Dim Level 0 Group Address 255 Dimming Rate Instantaneous Lighting Application Address 95	\055F0002FF009B\x0D
Dim Level 255 Group Address 0 Dimming Rate 1 minute Lighting Application Address 48	\0530003A00FF92\x0D
Dim Level 255 Group Address 0 Dimming Rate 1 minute Lighting Application Address 95	\055F003A00FF63\x0D
Dim Level 255 Group Address 0 Dimming Rate 1.5 minutes Lighting Application Address 48	\0530004200FF8A\x0D
Dim Level 255 Group Address 0 Dimming Rate 1.5 minutes Lighting Application Address 95	\055F004200FF5B\x0D
Dim Level 255 Group Address 0 Dimming Rate 10 minutes Lighting Application Address 48	\0530006A00FF62\x0D
Dim Level 255 Group Address 0 Dimming Rate 10 minutes Lighting Application Address 95	\055F006A00FF33\x0D
Dim Level 255 Group Address 0 Dimming Rate 12 seconds Lighting Application Address 48	\0530001A00FFB2\x0D
Dim Level 255 Group Address 0 Dimming Rate 12 seconds Lighting Application Address 95	\055F001A00FF83\x0D
Dim Level 255 Group Address 0 Dimming Rate 15 minutes Lighting Application Address 48	\0530007200FF5A\x0D
Dim Level 255 Group Address 0 Dimming Rate 15 minutes Lighting Application Address 95	\055F007200FF2B\x0D
Dim Level 255 Group Address 0 Dimming Rate 17 minutes Lighting Application Address 48	\0530007A00FF52\x0D
Dim Level 255 Group Address 0 Dimming Rate 17 minutes Lighting Application Address 95	\055F007A00FF23\x0D
Dim Level 255 Group Address 0 Dimming Rate 2 minutes Lighting Application Address 48	\0530004A00FF82\x0D
Dim Level 255 Group Address 0 Dimming Rate 2 minutes Lighting Application Address 95	\055F004A00FF53\x0D
Dim Level 255 Group Address 0 Dimming Rate 20 seconds Lighting Application Address 48	\0530002200FFAA\x0D

Global Scripter Module Communication Sheet

Revision: 10/29/2018

Dim Level 255 Group Address 0 Dimming Rate 20 seconds Lighting Application Address 95	\055F002200FF7B\x0D
Dim Level 255 Group Address 0 Dimming Rate 3 minutes Lighting Application Address 48	\0530005200FF7A\x0D
Dim Level 255 Group Address 0 Dimming Rate 3 minutes Lighting Application Address 95	\055F005200FF4B\x0D
Dim Level 255 Group Address 0 Dimming Rate 30 seconds Lighting Application Address 48	\0530002A00FFA2\x0D
Dim Level 255 Group Address 0 Dimming Rate 30 seconds Lighting Application Address 95	\055F002A00FF73\x0D
Dim Level 255 Group Address 0 Dimming Rate 4 seconds Lighting Application Address 48	\0530000A00FFC2\x0D
Dim Level 255 Group Address 0 Dimming Rate 4 seconds Lighting Application Address 95	\055F000A00FF93\x0D
Dim Level 255 Group Address 0 Dimming Rate 40 seconds Lighting Application Address 48	\0530003200FF9A\x0D
Dim Level 255 Group Address 0 Dimming Rate 40 seconds Lighting Application Address 95	\055F003200FF6B\x0D
Dim Level 255 Group Address 0 Dimming Rate 5 minutes Lighting Application Address 48	\0530005A00FF72\x0D
Dim Level 255 Group Address 0 Dimming Rate 5 minutes Lighting Application Address 95	\055F005A00FF43\x0D
Dim Level 255 Group Address 0 Dimming Rate 7 minutes Lighting Application Address 48	\0530006200FF6A\x0D
Dim Level 255 Group Address 0 Dimming Rate 7 minutes Lighting Application Address 95	\055F006200FF3B\x0D
Dim Level 255 Group Address 0 Dimming Rate 8 seconds Lighting Application Address 48	\0530001200FFBA\x0D
Dim Level 255 Group Address 0 Dimming Rate 8 seconds Lighting Application Address 95	\055F001200FF8B\x0D
Dim Level 255 Group Address 0 Dimming Rate Instantaneous Lighting Application Address 48	\0530000200FFCA\x0D
Dim Level 255 Group Address 0 Dimming Rate Instantaneous Lighting Application Address 95	\055F000200FF9B\x0D
Dim Level 255 Group Address 255 Dimming Rate 1 minute Lighting Application Address 48	\0530003AFFFF93\x0D
Dim Level 255 Group Address 255 Dimming Rate 1 minute Lighting Application Address 95	\055F003AFFFF64\x0D
Dim Level 255 Group Address 255 Dimming Rate 1.5 minutes Lighting Application Address 48	\05300042FFFF8B\x0D

Global Scripter Module Communication Sheet

Revision: 10/29/2018

Dim Level 255 Group Address 255 Dimming Rate 1.5 minutes Lighting Application Address 95	\055F0042FFFF5C\x0D
Dim Level 255 Group Address 255 Dimming Rate 10 minutes Lighting Application Address 48	\0530006AFFFF63\x0D
Dim Level 255 Group Address 255 Dimming Rate 10 minutes Lighting Application Address 95	\055F006AFFFF34\x0D
Dim Level 255 Group Address 255 Dimming Rate 12 seconds Lighting Application Address 48	\0530001AFFFFB3\x0D
Dim Level 255 Group Address 255 Dimming Rate 12 seconds Lighting Application Address 95	\055F001AFFFF84\x0D
Dim Level 255 Group Address 255 Dimming Rate 15 minutes Lighting Application Address 48	\05300072FFFF5B\x0D
Dim Level 255 Group Address 255 Dimming Rate 15 minutes Lighting Application Address 95	\055F0072FFFF2C\x0D
Dim Level 255 Group Address 255 Dimming Rate 17 minutes Lighting Application Address 48	\0530007AFFFF53\x0D
Dim Level 255 Group Address 255 Dimming Rate 17 minutes Lighting Application Address 95	\055F007AFFFF24\x0D
Dim Level 255 Group Address 255 Dimming Rate 2 minutes Lighting Application Address 48	\0530004AFFFF83\x0D
Dim Level 255 Group Address 255 Dimming Rate 2 minutes Lighting Application Address 95	\055F004AFFFF54\x0D
Dim Level 255 Group Address 255 Dimming Rate 20 seconds Lighting Application Address 48	\05300022FFFFAB\x0D
Dim Level 255 Group Address 255 Dimming Rate 20 seconds Lighting Application Address 95	\055F0022FFFF7C\x0D
Dim Level 255 Group Address 255 Dimming Rate 3 minutes Lighting Application Address 48	\05300052FFFF7B\x0D
Dim Level 255 Group Address 255 Dimming Rate 3 minutes Lighting Application Address 95	\055F0052FFFF4C\x0D
Dim Level 255 Group Address 255 Dimming Rate 30 seconds Lighting Application Address 48	\0530002AFFFFA3\x0D
Dim Level 255 Group Address 255 Dimming Rate 30 seconds Lighting Application Address 95	\055F002AFFFF74\x0D
Dim Level 255 Group Address 255 Dimming Rate 4 seconds Lighting Application Address 48	\0530000AFFFFC3\x0D
Dim Level 255 Group Address 255 Dimming Rate 4 seconds Lighting Application Address 95	\055F000AFFFF94\x0D
Dim Level 255 Group Address 255 Dimming Rate 40 seconds Lighting Application Address 48	\05300032FFFF9B\x0D

Global Scripter Module Communication Sheet

Revision: 10/29/2018

Dim Level 255 Group Address 255 Dimming Rate 40 seconds Lighting Application Address 95	\055F0032FFFF6C\x0D
Dim Level 255 Group Address 255 Dimming Rate 5 minutes Lighting Application Address 48	\0530005AFFFF73\x0D
Dim Level 255 Group Address 255 Dimming Rate 5 minutes Lighting Application Address 95	\055F005AFFFF44\x0D
Dim Level 255 Group Address 255 Dimming Rate 7 minutes Lighting Application Address 48	\05300062FFFF6B\x0D
Dim Level 255 Group Address 255 Dimming Rate 7 minutes Lighting Application Address 95	\055F0062FFFF3C\x0D
Dim Level 255 Group Address 255 Dimming Rate 8 seconds Lighting Application Address 48	\05300012FFFFBB\x0D
Dim Level 255 Group Address 255 Dimming Rate 8 seconds Lighting Application Address 95	\055F0012FFFF8C\x0D
Dim Level 255 Group Address 255 Dimming Rate Instantaneous Lighting Application Address 48	\05300002FFFFCB\x0D
Dim Level 255 Group Address 255 Dimming Rate Instantaneous Lighting Application Address 95	\055F0002FFFF9C\x0D
Switch Light Off Group Address 0 Lighting Application Address 48	\0530000100CA\x0D
Switch Light Off Group Address 0 Lighting Application Address 95	\055F0001009B\x0D
Switch Light Off Group Address 255 Lighting Application Address 48	\05300001FFCB\x0D
Switch Light Off Group Address 255 Lighting Application Address 95	\055F0001FF9C\x0D
Switch Light On Group Address 0 Lighting Application Address 48	\053000790052\x0D
Switch Light On Group Address 0 Lighting Application Address 95	\055F00790023\x0D
Switch Light On Group Address 255 Lighting Application Address 48	\05300079FF53\x0D
Switch Light On Group Address 255 Lighting Application Address 95	\055F0079FF24\x0D