

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Audio Processor
Manufacturer: ClearOne
Firmware Version: Interact Pro - 1.0.41.0
Interact AT - 1.0.40.0
Model(s): Interact AT, Interact Pro

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_5_1_0	3/8/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- If using this module with any Extron Electronics product with only 3-wire serial control, the ClearOne device flow control must be disabled. The ClearOne device settings can be configured using the manufacturer's control software.
- If login credentials are required, deviceUsername and devicePassword must be set accordingly. Default username is 'Clearone' and default password is 'Interact'.

Example: InterfaceName.deviceUsername = 'Clearone'
InterfaceName.devicePassword = 'Interact'

Control Commands, States, and Qualifiers:

AutoAnswer	'On'	'Off'	
ClearEffect	'On'	'Off'	
DTMF	'0' – '9' 'C' '*'	'A' 'D' ' '	'B' '#'
GlobalMute	'On'	'Off'	
Hook	'Off' 'Dial'	'On' 'Redial'	'Flash'
['Number']⁴	'String'		
LineInputGain¹	-65 to 20 in steps of 0.1 dB		
['LineInput']	'1' – '2'		
LineInputGain²	-14 to 18 in steps of 0.1 dB		
['LineInput']	'1' – '2'		
LineInputMute	'Off'	'On'	
['LineInput']	'1' – '2'		
Matrix^{1,3}	'Cross point off'	'Cross point on'	'Gated'
['Source']	'Mic Input 1' 'Mic Input 4' 'Mic Input 7' 'Mic Input 10' 'Mic Input 13' 'Mic Input 16' 'Telco RX' 'Processing A'	'Mic Input 2' 'Mic Input 5' 'Mic Input 8' 'Mic Input 11' 'Mic Input 14' 'Line Input 1' 'USB RX' 'Processing B'	'Mic Input 3' 'Mic Input 6' 'Mic Input 9' 'Mic Input 12' 'Mic Input 15' 'Line Input 2' 'Headset RX' 'Processing C'
['Destination']	'Output 1' 'Output 4' 'Output 7' 'USB TX' 'Processing B' 'Virtual Ref 2'	'Output 2' 'Output 5' 'Output 8' 'Headset TX' 'Processing C'	'Output 3' 'Output 6' 'Telco TX' 'Processing A' 'Virtual Ref 1'
Matrix^{2,3}	'Cross point off'	'Cross point on'	
['Source']	'Mic A1' 'Mic B1' 'Mic C1' 'Line Input'	'Mic A2' 'Mic B2' 'Mic C2' 'Telco RX'	'Mic A3' 'Mic B3' 'Mic C3' 'USB RX'

['Destination']	'Loud Speaker' 'USB TX'	'Line Output' 'Record'	'Telco TX'
MatrixLevel ^{1,3}	-18 to 0 in steps of 0.1 dB		
['Source']	'Mic Input 1' 'Mic Input 4' 'Mic Input 7' 'Mic Input 10' 'Mic Input 13' 'Mic Input 16' 'Telco RX' 'Processing A'	'Mic Input 2' 'Mic Input 5' 'Mic Input 8' 'Mic Input 11' 'Mic Input 14' 'Line Input 1' 'USB RX' 'Processing B'	'Mic Input 3' 'Mic Input 6' 'Mic Input 9' 'Mic Input 12' 'Mic Input 15' 'Line Input 2' 'Headset RX' 'Processing C'
['Destination']	'Output 1' 'Output 4' 'Output 7' 'USB TX' 'Processing B' 'Virtual Ref 2'	'Output 2' 'Output 5' 'Output 8' 'Headset TX' 'Processing C'	'Output 3' 'Output 6' 'Telco TX' 'Processing A' 'Virtual Ref 1'
MatrixLevel ^{2,3}	-18 to 0 in steps of 0.1 dB		
['Source']	'Mic A1' 'Mic B1' 'Mic C1' 'Line Input'	'Mic A2' 'Mic B2' 'Mic C2' 'Telco RX'	'Mic A3' 'Mic B3' 'Mic C3' 'USB RX'
['Destination']	'Loud Speaker' 'USB TX'	'Line Output' 'Record'	'Telco TX'
MicGain ¹	-65 to 20 in steps of 0.1 dB		
['Mic']	'1' – '16'		
MicGain ²	-14 to 18 in steps of 0.1 dB		
['Mic']	'1' – '9'		
MicMute ¹	'On'	'Off'	
['Mic']	'1' – '16'		
MicMute ²	'On'	'Off'	
['Mic']	'1' – '9'		
OutputGain ¹	-65 to 20 in steps of 0.1 dB		
['Output']	'1' – '8'		
OutputGain ²	-14 to 18 in steps of 0.1 dB		
['Output']	'1' – '3'		

OutputMute ²	'On'	'Off'
['Output']	'1' – '3'	
OutputMute ¹	'On'	'Off'
['Output']	'1' – '8'	
PhoneReceiveGain ¹	-65 to 20 in steps of 0.1 dB	
PhoneReceiveGain ²	-14 to 18 in steps of 0.1 dB	
PhoneReceiveMute	'On'	'Off'
PhoneTransmitGain ¹	-65 to 20 in steps of 0.1 dB	
PhoneTransmitGain ²	-14 to 18 in steps of 0.1 dB	
PhoneTransmitMute	'On'	'Off'
Preset	'1' – '4'	
ProcessingChannelGain ²	-65 to 20 in steps of 0.1 dB	
['ProcessingChannel']	'A'	'B' 'C'
ProcessingChannelMute ²	'On'	'Off'
['ProcessingChannel']	'A'	'B' 'C'
RingerEnable	'Off'	'On'
SpeedDial	'1' – '33'	
USBInGain ²	-14 to 18 in steps of 0.1 dB	
USBInGain ¹	-65 to 20 in steps of 0.1 dB	
USBInMute	'On'	'Off'
USBOutGain ²	-14 to 18 in steps of 0.1 dB	
USBOutGain ¹	-65 to 20 in steps of 0.1 dB	
USBOutMute	'On'	'Off'

¹ For Interact Pro only.

² For Interact AT only.

³ Gated and Non-Gated applied to Mic inputs only. On, Off, and Toggle apply to non-Mic inputs only. For routing, please refer to user manual or Interact Pro software.

⁴ Required only for Dial command.

Status Available:

AutoAnswer	'On'	'Off'	
ClearEffect	'On'	'Off'	
ConnectionStatus	'Connected'	'Disconnected'	
GlobalMute	'On'	'Off'	
Hook	'Off'	'On'	'Ringing'
LineInputGain ¹	-65 to 20 in steps of 0.1 dB		
['LineInput']	'1' – '2'		
LineInputGain ²	-14 to 18 in steps of 0.1 dB		
['LineInput']	'1' – '2'		
LineInputMute	'Off'	'On'	
['LineInput']	'1' – '2'		
Matrix ¹	'Cross point off' 'Routing Prohibited'	'Cross point on'	'Gated'
['Source']	'Mic Input 1' 'Mic Input 4' 'Mic Input 7' 'Mic Input 10' 'Mic Input 13' 'Mic Input 16' 'Telco RX' 'Processing A'	'Mic Input 2' 'Mic Input 5' 'Mic Input 8' 'Mic Input 11' 'Mic Input 14' 'Line Input 1' 'USB RX' 'Processing B'	'Mic Input 3' 'Mic Input 6' 'Mic Input 9' 'Mic Input 12' 'Mic Input 15' 'Line Input 2' 'Headset RX' 'Processing C'
['Destination']	'Output 1' 'Output 4' 'Output 7' 'USB TX' 'Processing B' 'Virtual Ref 2'	'Output 2' 'Output 5' 'Output 8' 'Headset TX' 'Processing C'	'Output 3' 'Output 6' 'Telco TX' 'Processing A' 'Virtual Ref 1'
Matrix ²	'Cross point off'	'Cross point on'	'Routing Prohibited'
['Source']	'Mic A1' 'Mic B1' 'Mic C1' 'Line Input'	'Mic A2' 'Mic B2' 'Mic C2' 'Telco RX'	'Mic A3' 'Mic B3' 'Mic C3' 'USB RX'
['Destination']	'Loud Speaker' 'USB TX'	'Line Output' 'Record'	'Telco TX'
MatrixLevel ¹	-18 to 0 in steps of 0.1 dB		

['Source']	'Mic Input 1'	'Mic Input 2'	'Mic Input 3'
	'Mic Input 4'	'Mic Input 5'	'Mic Input 6'
	'Mic Input 7'	'Mic Input 8'	'Mic Input 9'
	'Mic Input 10'	'Mic Input 11'	'Mic Input 12'
	'Mic Input 13'	'Mic Input 14'	'Mic Input 15'
	'Mic Input 16'	'Line Input 1'	'Line Input 2'
	'Telco RX'	'USB RX'	'Headset RX'
	'Processing A'	'Processing B'	'Processing C'
['Destination']	'Output 1'	'Output 2'	'Output 3'
	'Output 4'	'Output 5'	'Output 6'
	'Output 7'	'Output 8'	'Telco TX'
	'USB TX'	'Headset TX'	'Processing A'
	'Processing B'	'Processing C'	'Virtual Ref 1'
	'Virtual Ref 2'		
MatrixLevel ²	-18 to 0 in steps of 0.1 dB		
['Source']	'Mic A1'	'Mic A2'	'Mic A3'
	'Mic B1'	'Mic B2'	'Mic B3'
	'Mic C1'	'Mic C2'	'Mic C3'
	'Line Input'	'Telco RX'	'USB RX'
['Destination']	'Loud Speaker'	'Line Output'	'Telco TX'
	'USB TX'	'Record'	
MicGain ¹	-65 to 20 in steps of 0.1 dB		
['Mic']	'1' – '16'		
MicGain ²	-14 to 18 in steps of 0.1 dB		
['Mic']	'1' – '9'		
MicMute ¹	'On'	'Off'	
['Mic']	'1' – '16'		
MicMute ²	'On'	'Off'	
['Mic']	'1' – '9'		
OutputGain ¹	-65 to 20 in steps of 0.1 dB		
['Output']	'1' – '8'		
OutputGain ²	-14 to 18 in steps of 0.1 dB		
['Output']	'1' – '3'		
OutputMute ²	'On'	'Off'	
['Output']	'1' – '3'		
OutputMute ¹	'On'	'Off'	

['Output']	'1' – '8'
PhoneReceiveGain ¹	-65 to 20 in steps of 0.1 dB
PhoneReceiveGain ²	-14 to 18 in steps of 0.1 dB
PhoneReceiveMute	'On' 'Off'
PhoneTransmitGain ¹	-65 to 20 in steps of 0.1 dB
PhoneTransmitGain ²	-14 to 18 in steps of 0.1 dB
PhoneTransmitMute	'On' 'Off'
ProcessingChannelGain ²	-65 to 20 in steps of 0.1 dB
['ProcessingChannel']	'A' 'B' 'C'
ProcessingChannelMute ²	'On' 'Off'
['ProcessingChannel']	'A' 'B' 'C'
RingerEnable	'Off' 'On'
USBInGain ²	-14 to 18 in steps of 0.1 dB
USBInGain ¹	-65 to 20 in steps of 0.1 dB
USBInMute	'On' 'Off'
USBOutGain ²	-14 to 18 in steps of 0.1 dB
USBOutGain ¹	-65 to 20 in steps of 0.1 dB
USBOutMute	'On' 'Off'

¹ For Interact Pro only.

² For Interact AT only.

³ Gated and Non-Gated applied to Mic inputs only. On, Off, and Toggle apply to non-Mic inputs only. For routing, please refer to user manual or Interact Pro software.

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device:


- Devices have different numbers of inputs, outputs, faders, microphones and processing. Please refer to owner manual.

Serial communication:


Port Type: RS-232
Baud Rate: 57600
Data Bits: 8

Parity: None
Stop Bits: One
Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND



General Notes:

Network communication:

When configuring the Ethernet module, be sure device settings match that of the GCP configuration.

Port Type:	Ethernet
Default Port:	23
Logon Credentials Supported:	Yes
Default Username:	Clearone
Default Password:	Interact
Multi-Connection Capabilities:	Yes
Port Changeability:	No

Ethernet Module Configuration Description:

Please refer to user manual for settings and changes to the network communication

Notes for the Device:

Appendix A. Set Commands (Interact AT)

Auto Answer Off	#J0 AA 1 0\x0D
Auto Answer On	#J0 AA 1 1\x0D
Clear Effect Off	#J0 CLEAREFFECT 1 0\x0D
Clear Effect On	#J0 CLEAREFFECT 1 1\x0D
DTMF 0	#J0 DIAL 1 0\x0D
DTMF 9	#J0 DIAL 1 9\x0D
DTMF #	#J0 DIAL 1 #\x0D
DTMF *	#J0 DIAL 1 *\x0D
DTMF ,	#J0 DIAL 1 ,\x0D
DTMF A	#J0 DIAL 1 A\x0D
DTMF B	#J0 DIAL 1 B\x0D
DTMF C	#J0 DIAL 1 C\x0D
DTMF D	#J0 DIAL 1 D\x0D
Global Mute Off	#J0 GMUTE M 0\x0D
Global Mute On	#J0 GMUTE M 1\x0D
Hook Dial	#J0 DIAL 1 8006339876\x0D
Hook Flash	#J0 HOOK 1\x0D
Hook Off	#J0 TE 1 1\x0D
Hook On	#J0 TE 1 0\x0D
Hook Redial	#J0 REDIAL 1\x0D
Line Input Gain -14.0 LineInput 1	#J0 GAIN 1 L -14.0 A\x0D
Line Input Gain 18.0 LineInput 1	#J0 GAIN 1 L 18.0 A\x0D
Line Input Gain -14.0 LineInput 2	#J0 GAIN 2 L -14.0 A\x0D
Line Input Gain 18.0 LineInput 2	#J0 GAIN 2 L 18.0 A\x0D
Line Input Mute Off LineInput 1	#J0 MUTE 1 L 0\x0D
Line Input Mute On LineInput 1	#J0 MUTE 1 L 1\x0D
Line Input Mute Off LineInput 2	#J0 MUTE 2 L 0\x0D
Line Input Mute On LineInput 2	#J0 MUTE 2 L 1\x0D
Matrix Cross point off Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T 0\x0D
Matrix Cross point on Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T 1\x0D
Matrix Gated Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T 4\x0D
Matrix Cross point off Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D 0\x0D
Matrix Cross point on Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D 1\x0D
Matrix Gated Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D 4\x0D
Matrix Cross point off Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T 0\x0D
Matrix Cross point on Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T 1\x0D
Matrix Gated Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T 4\x0D
Matrix Cross point off Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D 0\x0D

Global Scripter Module Communication Sheet

Matrix Cross point on Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D 1\X0D
Matrix Gated Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D 4\X0D
Matrix Cross point off Source Line Input Destination Line Output	#J0 MTRX 2 L 2 O 0\X0D
Matrix Cross point on Source Line Input Destination Line Output	#J0 MTRX 2 L 2 O 1\X0D
Matrix Cross point off Source Line Input Destination Loud Speaker	#J0 MTRX 2 L 1 O 0\X0D
Matrix Cross point on Source Line Input Destination Loud Speaker	#J0 MTRX 2 L 1 O 1\X0D
Matrix Cross point off Source Line Input Destination Record	#J0 MTRX 2 L 3 O 0\X0D
Matrix Cross point on Source Line Input Destination Record	#J0 MTRX 2 L 3 O 1\X0D
Matrix Cross point off Source Line Input Destination Telco TX	#J0 MTRX 2 L 1 T 0\X0D
Matrix Cross point on Source Line Input Destination Telco TX	#J0 MTRX 2 L 1 T 1\X0D
Matrix Cross point off Source Line Input Destination USB TX	#J0 MTRX 2 L 1 D 0\X0D
Matrix Cross point on Source Line Input Destination USB TX	#J0 MTRX 2 L 1 D 1\X0D
Matrix Cross point off Source Mic A1 Destination Line Output	#J0 MTRX 1 M 2 O 0\X0D
Matrix Cross point on Source Mic A1 Destination Line Output	#J0 MTRX 1 M 2 O 1\X0D
Matrix Cross point off Source Mic A1 Destination Loud Speaker	#J0 MTRX 1 M 1 O 0\X0D
Matrix Cross point on Source Mic A1 Destination Loud Speaker	#J0 MTRX 1 M 1 O 1\X0D
Matrix Cross point off Source Mic A1 Destination Record	#J0 MTRX 1 M 3 O 0\X0D
Matrix Cross point on Source Mic A1 Destination Record	#J0 MTRX 1 M 3 O 1\X0D
Matrix Cross point off Source Mic A1 Destination Telco TX	#J0 MTRX 1 M 1 T 0\X0D
Matrix Cross point on Source Mic A1 Destination Telco TX	#J0 MTRX 1 M 1 T 1\X0D
Matrix Cross point off Source Mic A1 Destination USB TX	#J0 MTRX 1 M 1 D 0\X0D
Matrix Cross point on Source Mic A1 Destination USB TX	#J0 MTRX 1 M 1 D 1\X0D
Matrix Cross point off Source Mic A2 Destination Line Output	#J0 MTRX 2 M 2 O 0\X0D
Matrix Cross point on Source Mic A2 Destination Line Output	#J0 MTRX 2 M 2 O 1\X0D
Matrix Cross point off Source Mic A2 Destination Loud Speaker	#J0 MTRX 2 M 1 O 0\X0D
Matrix Cross point on Source Mic A2 Destination Loud Speaker	#J0 MTRX 2 M 1 O 1\X0D
Matrix Cross point off Source Mic A2 Destination Record	#J0 MTRX 2 M 3 O 0\X0D
Matrix Cross point on Source Mic A2 Destination Record	#J0 MTRX 2 M 3 O 1\X0D
Matrix Cross point off Source Mic A2 Destination Telco TX	#J0 MTRX 2 M 1 T 0\X0D
Matrix Cross point on Source Mic A2 Destination Telco TX	#J0 MTRX 2 M 1 T 1\X0D
Matrix Cross point off Source Mic A2 Destination USB TX	#J0 MTRX 2 M 1 D 0\X0D
Matrix Cross point on Source Mic A2 Destination USB TX	#J0 MTRX 2 M 1 D 1\X0D
Matrix Cross point off Source Mic A3 Destination Line Output	#J0 MTRX 3 M 2 O 0\X0D
Matrix Cross point on Source Mic A3 Destination Line Output	#J0 MTRX 3 M 2 O 1\X0D
Matrix Cross point off Source Mic A3 Destination Loud Speaker	#J0 MTRX 3 M 1 O 0\X0D
Matrix Cross point on Source Mic A3 Destination Loud Speaker	#J0 MTRX 3 M 1 O 1\X0D
Matrix Cross point off Source Mic A3 Destination Record	#J0 MTRX 3 M 3 O 0\X0D
Matrix Cross point on Source Mic A3 Destination Record	#J0 MTRX 3 M 3 O 1\X0D
Matrix Cross point off Source Mic A3 Destination Telco TX	#J0 MTRX 3 M 1 T 0\X0D
Matrix Cross point on Source Mic A3 Destination Telco TX	#J0 MTRX 3 M 1 T 1\X0D
Matrix Cross point off Source Mic A3 Destination USB TX	#J0 MTRX 3 M 1 D 0\X0D

Global Scripter Module Communication Sheet

Matrix Cross point on Source Mic A3 Destination USB TX	#J0 MTRX 3 M 1 D 1\x0D
Matrix Cross point off Source Mic B1 Destination Line Output	#J0 MTRX 4 M 2 O 0\x0D
Matrix Cross point on Source Mic B1 Destination Line Output	#J0 MTRX 4 M 2 O 1\x0D
Matrix Cross point off Source Mic B1 Destination Loud Speaker	#J0 MTRX 4 M 1 O 0\x0D
Matrix Cross point on Source Mic B1 Destination Loud Speaker	#J0 MTRX 4 M 1 O 1\x0D
Matrix Cross point off Source Mic B1 Destination Record	#J0 MTRX 4 M 3 O 0\x0D
Matrix Cross point on Source Mic B1 Destination Record	#J0 MTRX 4 M 3 O 1\x0D
Matrix Cross point off Source Mic B1 Destination Telco TX	#J0 MTRX 4 M 1 T 0\x0D
Matrix Cross point on Source Mic B1 Destination Telco TX	#J0 MTRX 4 M 1 T 1\x0D
Matrix Cross point off Source Mic B1 Destination USB TX	#J0 MTRX 4 M 1 D 0\x0D
Matrix Cross point on Source Mic B1 Destination USB TX	#J0 MTRX 4 M 1 D 1\x0D
Matrix Cross point off Source Mic B2 Destination Line Output	#J0 MTRX 5 M 2 O 0\x0D
Matrix Cross point on Source Mic B2 Destination Line Output	#J0 MTRX 5 M 2 O 1\x0D
Matrix Cross point off Source Mic B2 Destination Loud Speaker	#J0 MTRX 5 M 1 O 0\x0D
Matrix Cross point on Source Mic B2 Destination Loud Speaker	#J0 MTRX 5 M 1 O 1\x0D
Matrix Cross point off Source Mic B2 Destination Record	#J0 MTRX 5 M 3 O 0\x0D
Matrix Cross point on Source Mic B2 Destination Record	#J0 MTRX 5 M 3 O 1\x0D
Matrix Cross point off Source Mic B2 Destination Telco TX	#J0 MTRX 5 M 1 T 0\x0D
Matrix Cross point on Source Mic B2 Destination Telco TX	#J0 MTRX 5 M 1 T 1\x0D
Matrix Cross point off Source Mic B2 Destination USB TX	#J0 MTRX 5 M 1 D 0\x0D
Matrix Cross point on Source Mic B2 Destination USB TX	#J0 MTRX 5 M 1 D 1\x0D
Matrix Cross point off Source Mic B3 Destination Line Output	#J0 MTRX 6 M 2 O 0\x0D
Matrix Cross point on Source Mic B3 Destination Line Output	#J0 MTRX 6 M 2 O 1\x0D
Matrix Cross point off Source Mic B3 Destination Loud Speaker	#J0 MTRX 6 M 1 O 0\x0D
Matrix Cross point on Source Mic B3 Destination Loud Speaker	#J0 MTRX 6 M 1 O 1\x0D
Matrix Cross point off Source Mic B3 Destination Record	#J0 MTRX 6 M 3 O 0\x0D
Matrix Cross point on Source Mic B3 Destination Record	#J0 MTRX 6 M 3 O 1\x0D
Matrix Cross point off Source Mic B3 Destination Telco TX	#J0 MTRX 6 M 1 T 0\x0D
Matrix Cross point on Source Mic B3 Destination Telco TX	#J0 MTRX 6 M 1 T 1\x0D
Matrix Cross point off Source Mic B3 Destination USB TX	#J0 MTRX 6 M 1 D 0\x0D
Matrix Cross point on Source Mic B3 Destination USB TX	#J0 MTRX 6 M 1 D 1\x0D
Matrix Cross point off Source Mic C1 Destination Line Output	#J0 MTRX 7 M 2 O 0\x0D
Matrix Cross point on Source Mic C1 Destination Line Output	#J0 MTRX 7 M 2 O 1\x0D
Matrix Cross point off Source Mic C1 Destination Loud Speaker	#J0 MTRX 7 M 1 O 0\x0D
Matrix Cross point on Source Mic C1 Destination Loud Speaker	#J0 MTRX 7 M 1 O 1\x0D
Matrix Cross point off Source Mic C1 Destination Record	#J0 MTRX 7 M 3 O 0\x0D
Matrix Cross point on Source Mic C1 Destination Record	#J0 MTRX 7 M 3 O 1\x0D
Matrix Cross point off Source Mic C1 Destination Telco TX	#J0 MTRX 7 M 1 T 0\x0D
Matrix Cross point on Source Mic C1 Destination Telco TX	#J0 MTRX 7 M 1 T 1\x0D
Matrix Cross point off Source Mic C1 Destination USB TX	#J0 MTRX 7 M 1 D 0\x0D
Matrix Cross point on Source Mic C1 Destination USB TX	#J0 MTRX 7 M 1 D 1\x0D

Global Scripter Module Communication Sheet

Matrix Cross point off Source Mic C2 Destination Line Output	#J0 MTRX 8 M 2 O 0\0D
Matrix Cross point on Source Mic C2 Destination Line Output	#J0 MTRX 8 M 2 O 1\0D
Matrix Cross point off Source Mic C2 Destination Loud Speaker	#J0 MTRX 8 M 1 O 0\0D
Matrix Cross point on Source Mic C2 Destination Loud Speaker	#J0 MTRX 8 M 1 O 1\0D
Matrix Cross point off Source Mic C2 Destination Record	#J0 MTRX 8 M 3 O 0\0D
Matrix Cross point on Source Mic C2 Destination Record	#J0 MTRX 8 M 3 O 1\0D
Matrix Cross point off Source Mic C2 Destination Telco TX	#J0 MTRX 8 M 1 T 0\0D
Matrix Cross point on Source Mic C2 Destination Telco TX	#J0 MTRX 8 M 1 T 1\0D
Matrix Cross point off Source Mic C2 Destination USB TX	#J0 MTRX 8 M 1 D 0\0D
Matrix Cross point on Source Mic C2 Destination USB TX	#J0 MTRX 8 M 1 D 1\0D
Matrix Cross point off Source Mic C3 Destination Line Output	#J0 MTRX 9 M 2 O 0\0D
Matrix Cross point on Source Mic C3 Destination Line Output	#J0 MTRX 9 M 2 O 1\0D
Matrix Cross point off Source Mic C3 Destination Loud Speaker	#J0 MTRX 9 M 1 O 0\0D
Matrix Cross point on Source Mic C3 Destination Loud Speaker	#J0 MTRX 9 M 1 O 1\0D
Matrix Cross point off Source Mic C3 Destination Record	#J0 MTRX 9 M 3 O 0\0D
Matrix Cross point on Source Mic C3 Destination Record	#J0 MTRX 9 M 3 O 1\0D
Matrix Cross point off Source Mic C3 Destination Telco TX	#J0 MTRX 9 M 1 T 0\0D
Matrix Cross point on Source Mic C3 Destination Telco TX	#J0 MTRX 9 M 1 T 1\0D
Matrix Cross point off Source Mic C3 Destination USB TX	#J0 MTRX 9 M 1 D 0\0D
Matrix Cross point on Source Mic C3 Destination USB TX	#J0 MTRX 9 M 1 D 1\0D
Matrix Cross point off Source Telco RX Destination Line Output	#J0 MTRX 1 R 2 O 0\0D
Matrix Cross point on Source Telco RX Destination Line Output	#J0 MTRX 1 R 2 O 1\0D
Matrix Cross point off Source Telco RX Destination Loud Speaker	#J0 MTRX 1 R 1 O 0\0D
Matrix Cross point on Source Telco RX Destination Loud Speaker	#J0 MTRX 1 R 1 O 1\0D
Matrix Cross point off Source Telco RX Destination Record	#J0 MTRX 1 R 3 O 0\0D
Matrix Cross point on Source Telco RX Destination Record	#J0 MTRX 1 R 3 O 1\0D
Matrix Cross point off Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T 0\0D
Matrix Cross point on Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T 1\0D
Matrix Cross point off Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D 0\0D
Matrix Cross point on Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D 1\0D
Matrix Cross point off Source USB RX Destination Line Output	#J0 MTRX 1 W 2 O 0\0D
Matrix Cross point on Source USB RX Destination Line Output	#J0 MTRX 1 W 2 O 1\0D
Matrix Cross point off Source USB RX Destination Loud Speaker	#J0 MTRX 1 W 1 O 0\0D
Matrix Cross point on Source USB RX Destination Loud Speaker	#J0 MTRX 1 W 1 O 1\0D
Matrix Cross point off Source USB RX Destination Record	#J0 MTRX 1 W 3 O 0\0D
Matrix Cross point on Source USB RX Destination Record	#J0 MTRX 1 W 3 O 1\0D
Matrix Cross point off Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T 0\0D
Matrix Cross point on Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T 1\0D
Matrix Cross point off Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D 0\0D
Matrix Cross point on Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D 1\0D
Matrix Level -18 Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T -18.0 A\0D

Matrix Level 0 Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T 0.0 A\x0D
Matrix Level -18 Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D 0.0 A\x0D
Matrix Level -18 Source Line Input Destination Line Output	#J0 MTRXLVL 2 L 2 O -18.0 A\x0D
Matrix Level 0 Source Line Input Destination Line Output	#J0 MTRXLVL 2 L 2 O 0.0 A\x0D
Matrix Level -18 Source Line Input Destination Loud Speaker	#J0 MTRXLVL 2 L 1 O -18.0 A\x0D
Matrix Level 0 Source Line Input Destination Loud Speaker	#J0 MTRXLVL 2 L 1 O 0.0 A\x0D
Matrix Level -18 Source Line Input Destination Record	#J0 MTRXLVL 2 L 3 O -18.0 A\x0D
Matrix Level 0 Source Line Input Destination Record	#J0 MTRXLVL 2 L 3 O 0.0 A\x0D
Matrix Level -18 Source Line Input Destination Telco TX	#J0 MTRXLVL 2 L 1 T -18.0 A\x0D
Matrix Level 0 Source Line Input Destination Telco TX	#J0 MTRXLVL 2 L 1 T 0.0 A\x0D
Matrix Level -18 Source Line Input Destination USB TX	#J0 MTRXLVL 2 L 1 D -18.0 A\x0D
Matrix Level 0 Source Line Input Destination USB TX	#J0 MTRXLVL 2 L 1 D 0.0 A\x0D
Matrix Level -18 Source Mic A1 Destination Line Output	#J0 MTRXLVL 1 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic A1 Destination Line Output	#J0 MTRXLVL 1 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic A1 Destination Loud Speaker	#J0 MTRXLVL 1 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic A1 Destination Loud Speaker	#J0 MTRXLVL 1 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic A1 Destination Record	#J0 MTRXLVL 1 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic A1 Destination Record	#J0 MTRXLVL 1 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic A1 Destination Telco TX	#J0 MTRXLVL 1 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic A1 Destination Telco TX	#J0 MTRXLVL 1 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic A1 Destination USB TX	#J0 MTRXLVL 1 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic A1 Destination USB TX	#J0 MTRXLVL 1 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic A2 Destination Line Output	#J0 MTRXLVL 2 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic A2 Destination Line Output	#J0 MTRXLVL 2 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic A2 Destination Loud Speaker	#J0 MTRXLVL 2 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic A2 Destination Loud Speaker	#J0 MTRXLVL 2 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic A2 Destination Record	#J0 MTRXLVL 2 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic A2 Destination Record	#J0 MTRXLVL 2 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic A2 Destination Telco TX	#J0 MTRXLVL 2 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic A2 Destination Telco TX	#J0 MTRXLVL 2 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic A2 Destination USB TX	#J0 MTRXLVL 2 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic A2 Destination USB TX	#J0 MTRXLVL 2 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic A3 Destination Line Output	#J0 MTRXLVL 3 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic A3 Destination Line Output	#J0 MTRXLVL 3 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic A3 Destination Loud Speaker	#J0 MTRXLVL 3 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic A3 Destination Loud Speaker	#J0 MTRXLVL 3 M 1 O 0.0 A\x0D

Global Scripter Module Communication Sheet

Matrix Level -18 Source Mic A3 Destination Record	#J0 MTRXLVL 3 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic A3 Destination Record	#J0 MTRXLVL 3 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic A3 Destination Telco TX	#J0 MTRXLVL 3 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic A3 Destination Telco TX	#J0 MTRXLVL 3 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic A3 Destination USB TX	#J0 MTRXLVL 3 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic A3 Destination USB TX	#J0 MTRXLVL 3 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic B1 Destination Line Output	#J0 MTRXLVL 4 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic B1 Destination Line Output	#J0 MTRXLVL 4 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic B1 Destination Loud Speaker	#J0 MTRXLVL 4 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic B1 Destination Loud Speaker	#J0 MTRXLVL 4 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic B1 Destination Record	#J0 MTRXLVL 4 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic B1 Destination Record	#J0 MTRXLVL 4 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic B1 Destination Telco TX	#J0 MTRXLVL 4 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic B1 Destination Telco TX	#J0 MTRXLVL 4 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic B1 Destination USB TX	#J0 MTRXLVL 4 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic B1 Destination USB TX	#J0 MTRXLVL 4 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic B2 Destination Line Output	#J0 MTRXLVL 5 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic B2 Destination Line Output	#J0 MTRXLVL 5 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic B2 Destination Loud Speaker	#J0 MTRXLVL 5 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic B2 Destination Loud Speaker	#J0 MTRXLVL 5 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic B2 Destination Record	#J0 MTRXLVL 5 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic B2 Destination Record	#J0 MTRXLVL 5 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic B2 Destination Telco TX	#J0 MTRXLVL 5 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic B2 Destination Telco TX	#J0 MTRXLVL 5 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic B2 Destination USB TX	#J0 MTRXLVL 5 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic B2 Destination USB TX	#J0 MTRXLVL 5 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic B3 Destination Line Output	#J0 MTRXLVL 6 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic B3 Destination Line Output	#J0 MTRXLVL 6 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic B3 Destination Loud Speaker	#J0 MTRXLVL 6 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic B3 Destination Loud Speaker	#J0 MTRXLVL 6 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic B3 Destination Record	#J0 MTRXLVL 6 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic B3 Destination Record	#J0 MTRXLVL 6 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic B3 Destination Telco TX	#J0 MTRXLVL 6 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic B3 Destination Telco TX	#J0 MTRXLVL 6 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic B3 Destination USB TX	#J0 MTRXLVL 6 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic B3 Destination USB TX	#J0 MTRXLVL 6 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic C1 Destination Line Output	#J0 MTRXLVL 7 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic C1 Destination Line Output	#J0 MTRXLVL 7 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic C1 Destination Loud Speaker	#J0 MTRXLVL 7 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic C1 Destination Loud Speaker	#J0 MTRXLVL 7 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic C1 Destination Record	#J0 MTRXLVL 7 M 3 O -18.0 A\x0D

Global Scripter Module Communication Sheet

Matrix Level 0 Source Mic C1 Destination Record	#J0 MTRXLVL 7 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic C1 Destination Telco TX	#J0 MTRXLVL 7 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic C1 Destination Telco TX	#J0 MTRXLVL 7 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic C1 Destination USB TX	#J0 MTRXLVL 7 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic C1 Destination USB TX	#J0 MTRXLVL 7 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic C2 Destination Line Output	#J0 MTRXLVL 8 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic C2 Destination Line Output	#J0 MTRXLVL 8 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic C2 Destination Loud Speaker	#J0 MTRXLVL 8 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic C2 Destination Loud Speaker	#J0 MTRXLVL 8 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic C2 Destination Record	#J0 MTRXLVL 8 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic C2 Destination Record	#J0 MTRXLVL 8 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic C2 Destination Telco TX	#J0 MTRXLVL 8 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic C2 Destination Telco TX	#J0 MTRXLVL 8 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic C2 Destination USB TX	#J0 MTRXLVL 8 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic C2 Destination USB TX	#J0 MTRXLVL 8 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic C3 Destination Line Output	#J0 MTRXLVL 9 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic C3 Destination Line Output	#J0 MTRXLVL 9 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic C3 Destination Loud Speaker	#J0 MTRXLVL 9 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic C3 Destination Loud Speaker	#J0 MTRXLVL 9 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic C3 Destination Record	#J0 MTRXLVL 9 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic C3 Destination Record	#J0 MTRXLVL 9 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic C3 Destination Telco TX	#J0 MTRXLVL 9 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic C3 Destination Telco TX	#J0 MTRXLVL 9 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic C3 Destination USB TX	#J0 MTRXLVL 9 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic C3 Destination USB TX	#J0 MTRXLVL 9 M 1 D 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Line Output	#J0 MTRXLVL 1 R 2 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Line Output	#J0 MTRXLVL 1 R 2 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Loud Speaker	#J0 MTRXLVL 1 R 1 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Loud Speaker	#J0 MTRXLVL 1 R 1 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Record	#J0 MTRXLVL 1 R 3 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Record	#J0 MTRXLVL 1 R 3 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Line Output	#J0 MTRXLVL 1 W 2 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Line Output	#J0 MTRXLVL 1 W 2 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Loud Speaker	#J0 MTRXLVL 1 W 1 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Loud Speaker	#J0 MTRXLVL 1 W 1 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Record	#J0 MTRXLVL 1 W 3 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Record	#J0 MTRXLVL 1 W 3 O 0.0 A\x0D

Matrix Level -18 Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T 0.0 A\x0D
Matrix Level -18 Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D 0.0 A\x0D
Mic Gain -14.0 Mic 1	#J0 GAIN 1 M -14.0 A\x0D
Mic Gain 18.0 Mic 1	#J0 GAIN 1 M 18.0 A\x0D
Mic Gain -14.0 Mic 9	#J0 GAIN 9 M -14.0 A\x0D
Mic Gain 18.0 Mic 9	#J0 GAIN 9 M 18.0 A\x0D
Mic Mute Off Mic 1	#J0 MUTE 1 M 0\x0D
Mic Mute On Mic 1	#J0 MUTE 1 M 1\x0D
Mic Mute Off Mic 1	#J0 MUTE 1 M 0\x0D
Mic Mute On Mic 1	#J0 MUTE 1 M 1\x0D
Mic Mute Off Mic 9	#J0 MUTE 9 M 0\x0D
Mic Mute On Mic 9	#J0 MUTE 9 M 1\x0D
Output Gain -14.0 Output 1	#J0 GAIN 1 O -14.0 A\x0D
Output Gain 18.0 Output 1	#J0 GAIN 1 O 18.0 A\x0D
Output Gain -14.0 Output 3	#J0 GAIN 3 O -14.0 A\x0D
Output Gain 18.0 Output 3	#J0 GAIN 3 O 18.0 A\x0D
Output Mute Off Output 1	#J0 MUTE 1 O 0\x0D
Output Mute On Output 1	#J0 MUTE 1 O 1\x0D
Output Mute Off Output 3	#J0 MUTE 3 O 0\x0D
Output Mute On Output 3	#J0 MUTE 3 O 1\x0D
Output Mute Off Output 1	#J0 MUTE 1 O 0\x0D
Output Mute On Output 1	#J0 MUTE 1 O 1\x0D
Phone Receive Gain -14.0	#J0 GAIN 1 R -14.0 A\x0D
Phone Receive Gain 18.0	#J0 GAIN 1 R 18.0 A\x0D
Phone Receive Mute Off	#J0 MUTE 1 R 0\x0D
Phone Receive Mute On	#J0 MUTE 1 R 1\x0D
Phone Transmit Gain -14.0	#J0 GAIN 1 T -14.0 A\x0D
Phone Transmit Gain 18.0	#J0 GAIN 1 T 18.0 A\x0D
Phone Transmit Mute Off	#J0 MUTE 1 T 0\x0D
Phone Transmit Mute On	#J0 MUTE 1 T 1\x0D
Preset 1	#J0 CPRESET 1\x0D
Preset 4	#J0 CPRESET 4\x0D
Ringer Enable Off	#J0 RINGEREN 1 0\x0D
Ringer Enable On	#J0 RINGEREN 1 1\x0D
Speed Dial 1	#J0 SPEEDDIAL 1 1\x0D
Speed Dial 33	#J0 SPEEDDIAL 1 33\x0D
USB In Gain -14.0	#J0 GAIN 1 W -14.0 A\x0D
USB In Gain 18.0	#J0 GAIN 1 W 18.0 A\x0D
USB In Mute Off	#J0 MUTE 1 W 0\x0D

USB In Mute On	#J0 MUTE 1 W 1\x0D
USB Out Gain -14.0	#J0 GAIN 1 D -14.0 A\x0D
USB Out Gain 18.0	#J0 GAIN 1 D 18.0 A\x0D
USB Out Mute Off	#J0 MUTE 1 D 0\x0D
USB Out Mute On	#J0 MUTE 1 D 1\x0D

Appendix B. Query Commands (Interact AT)

Auto Answer	#J0 AA 1\x0D
Clear Effect	#J0 CLEAREFFECT 1\x0D
Global Mute	#J0 GMUTE M\x0D
Hook	#J0 TE 1\x0D
Line Input Gain LineInput 1	#J0 GAIN 1 L\x0D
Line Input Gain LineInput 2	#J0 GAIN 2 L\x0D
Line Input Gain LineInput 1	#J0 GAIN 1 L\x0D
Line Input Gain LineInput 2	#J0 GAIN 2 L\x0D
Line Input Mute LineInput 1	#J0 MUTE 1 L\x0D
Line Input Mute LineInput 2	#J0 MUTE 2 L\x0D
Matrix Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T\x0D
Matrix Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D\x0D
Matrix Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T\x0D
Matrix Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D\x0D
Matrix Source Line Input Destination Line Output	#J0 MTRX 2 L 2 O\x0D
Matrix Source Line Input Destination Loud Speaker	#J0 MTRX 2 L 1 O\x0D
Matrix Source Line Input Destination Record	#J0 MTRX 2 L 3 O\x0D
Matrix Source Line Input Destination Telco TX	#J0 MTRX 2 L 1 T\x0D
Matrix Source Line Input Destination USB TX	#J0 MTRX 2 L 1 D\x0D
Matrix Source Mic A1 Destination Line Output	#J0 MTRX 1 M 2 O\x0D
Matrix Source Mic A1 Destination Loud Speaker	#J0 MTRX 1 M 1 O\x0D
Matrix Source Mic A1 Destination Record	#J0 MTRX 1 M 3 O\x0D
Matrix Source Mic A1 Destination Telco TX	#J0 MTRX 1 M 1 T\x0D
Matrix Source Mic A1 Destination USB TX	#J0 MTRX 1 M 1 D\x0D
Matrix Source Mic A2 Destination Line Output	#J0 MTRX 2 M 2 O\x0D
Matrix Source Mic A2 Destination Loud Speaker	#J0 MTRX 2 M 1 O\x0D
Matrix Source Mic A2 Destination Record	#J0 MTRX 2 M 3 O\x0D
Matrix Source Mic A2 Destination Telco TX	#J0 MTRX 2 M 1 T\x0D
Matrix Source Mic A2 Destination USB TX	#J0 MTRX 2 M 1 D\x0D
Matrix Source Mic A3 Destination Line Output	#J0 MTRX 3 M 2 O\x0D
Matrix Source Mic A3 Destination Loud Speaker	#J0 MTRX 3 M 1 O\x0D

Global Scripter Module Communication Sheet

Matrix Source Mic A3 Destination Record	#J0 MTRX 3 M 3 O\x0D
Matrix Source Mic A3 Destination Telco TX	#J0 MTRX 3 M 1 T\x0D
Matrix Source Mic A3 Destination USB TX	#J0 MTRX 3 M 1 D\x0D
Matrix Source Mic B1 Destination Line Output	#J0 MTRX 4 M 2 O\x0D
Matrix Source Mic B1 Destination Loud Speaker	#J0 MTRX 4 M 1 O\x0D
Matrix Source Mic B1 Destination Record	#J0 MTRX 4 M 3 O\x0D
Matrix Source Mic B1 Destination Telco TX	#J0 MTRX 4 M 1 T\x0D
Matrix Source Mic B1 Destination USB TX	#J0 MTRX 4 M 1 D\x0D
Matrix Source Mic B2 Destination Line Output	#J0 MTRX 5 M 2 O\x0D
Matrix Source Mic B2 Destination Loud Speaker	#J0 MTRX 5 M 1 O\x0D
Matrix Source Mic B2 Destination Record	#J0 MTRX 5 M 3 O\x0D
Matrix Source Mic B2 Destination Telco TX	#J0 MTRX 5 M 1 T\x0D
Matrix Source Mic B2 Destination USB TX	#J0 MTRX 5 M 1 D\x0D
Matrix Source Mic B3 Destination Line Output	#J0 MTRX 6 M 2 O\x0D
Matrix Source Mic B3 Destination Loud Speaker	#J0 MTRX 6 M 1 O\x0D
Matrix Source Mic B3 Destination Record	#J0 MTRX 6 M 3 O\x0D
Matrix Source Mic B3 Destination Telco TX	#J0 MTRX 6 M 1 T\x0D
Matrix Source Mic B3 Destination USB TX	#J0 MTRX 6 M 1 D\x0D
Matrix Source Mic C1 Destination Line Output	#J0 MTRX 7 M 2 O\x0D
Matrix Source Mic C1 Destination Loud Speaker	#J0 MTRX 7 M 1 O\x0D
Matrix Source Mic C1 Destination Record	#J0 MTRX 7 M 3 O\x0D
Matrix Source Mic C1 Destination Telco TX	#J0 MTRX 7 M 1 T\x0D
Matrix Source Mic C1 Destination USB TX	#J0 MTRX 7 M 1 D\x0D
Matrix Source Mic C2 Destination Line Output	#J0 MTRX 8 M 2 O\x0D
Matrix Source Mic C2 Destination Loud Speaker	#J0 MTRX 8 M 1 O\x0D
Matrix Source Mic C2 Destination Record	#J0 MTRX 8 M 3 O\x0D
Matrix Source Mic C2 Destination Telco TX	#J0 MTRX 8 M 1 T\x0D
Matrix Source Mic C2 Destination USB TX	#J0 MTRX 8 M 1 D\x0D
Matrix Source Mic C3 Destination Line Output	#J0 MTRX 9 M 2 O\x0D
Matrix Source Mic C3 Destination Loud Speaker	#J0 MTRX 9 M 1 O\x0D
Matrix Source Mic C3 Destination Record	#J0 MTRX 9 M 3 O\x0D
Matrix Source Mic C3 Destination Telco TX	#J0 MTRX 9 M 1 T\x0D
Matrix Source Mic C3 Destination USB TX	#J0 MTRX 9 M 1 D\x0D
Matrix Source Telco RX Destination Line Output	#J0 MTRX 1 R 2 O\x0D
Matrix Source Telco RX Destination Loud Speaker	#J0 MTRX 1 R 1 O\x0D
Matrix Source Telco RX Destination Record	#J0 MTRX 1 R 3 O\x0D
Matrix Source Telco RX Destination Telco TX	#J0 MTRX 1 R 1 T\x0D
Matrix Source Telco RX Destination USB TX	#J0 MTRX 1 R 1 D\x0D
Matrix Source USB RX Destination Line Output	#J0 MTRX 1 W 2 O\x0D
Matrix Source USB RX Destination Loud Speaker	#J0 MTRX 1 W 1 O\x0D
Matrix Source USB RX Destination Record	#J0 MTRX 1 W 3 O\x0D

Global Scripter Module Communication Sheet

Matrix Source USB RX Destination Telco TX	#J0 MTRX 1 W 1 T\x0D
Matrix Source USB RX Destination USB TX	#J0 MTRX 1 W 1 D\x0D
Matrix Level Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T\x0D
Matrix Level Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D\x0D
Matrix Level Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T\x0D
Matrix Level Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D\x0D
Matrix Level Source Line Input Destination Line Output	#J0 MTRXLVL 2 L 2 O\x0D
Matrix Level Source Line Input Destination Loud Speaker	#J0 MTRXLVL 2 L 1 O\x0D
Matrix Level Source Line Input Destination Record	#J0 MTRXLVL 2 L 3 O\x0D
Matrix Level Source Line Input Destination Telco TX	#J0 MTRXLVL 2 L 1 T\x0D
Matrix Level Source Line Input Destination USB TX	#J0 MTRXLVL 2 L 1 D\x0D
Matrix Level Source Mic A1 Destination Line Output	#J0 MTRXLVL 1 M 2 O\x0D
Matrix Level Source Mic A1 Destination Loud Speaker	#J0 MTRXLVL 1 M 1 O\x0D
Matrix Level Source Mic A1 Destination Record	#J0 MTRXLVL 1 M 3 O\x0D
Matrix Level Source Mic A1 Destination Telco TX	#J0 MTRXLVL 1 M 1 T\x0D
Matrix Level Source Mic A1 Destination USB TX	#J0 MTRXLVL 1 M 1 D\x0D
Matrix Level Source Mic A2 Destination Line Output	#J0 MTRXLVL 2 M 2 O\x0D
Matrix Level Source Mic A2 Destination Loud Speaker	#J0 MTRXLVL 2 M 1 O\x0D
Matrix Level Source Mic A2 Destination Record	#J0 MTRXLVL 2 M 3 O\x0D
Matrix Level Source Mic A2 Destination Telco TX	#J0 MTRXLVL 2 M 1 T\x0D
Matrix Level Source Mic A2 Destination USB TX	#J0 MTRXLVL 2 M 1 D\x0D
Matrix Level Source Mic A3 Destination Line Output	#J0 MTRXLVL 3 M 2 O\x0D
Matrix Level Source Mic A3 Destination Loud Speaker	#J0 MTRXLVL 3 M 1 O\x0D
Matrix Level Source Mic A3 Destination Record	#J0 MTRXLVL 3 M 3 O\x0D
Matrix Level Source Mic A3 Destination Telco TX	#J0 MTRXLVL 3 M 1 T\x0D
Matrix Level Source Mic A3 Destination USB TX	#J0 MTRXLVL 3 M 1 D\x0D
Matrix Level Source Mic B1 Destination Line Output	#J0 MTRXLVL 4 M 2 O\x0D
Matrix Level Source Mic B1 Destination Loud Speaker	#J0 MTRXLVL 4 M 1 O\x0D
Matrix Level Source Mic B1 Destination Record	#J0 MTRXLVL 4 M 3 O\x0D
Matrix Level Source Mic B1 Destination Telco TX	#J0 MTRXLVL 4 M 1 T\x0D
Matrix Level Source Mic B1 Destination USB TX	#J0 MTRXLVL 4 M 1 D\x0D
Matrix Level Source Mic B2 Destination Line Output	#J0 MTRXLVL 5 M 2 O\x0D
Matrix Level Source Mic B2 Destination Loud Speaker	#J0 MTRXLVL 5 M 1 O\x0D
Matrix Level Source Mic B2 Destination Record	#J0 MTRXLVL 5 M 3 O\x0D
Matrix Level Source Mic B2 Destination Telco TX	#J0 MTRXLVL 5 M 1 T\x0D
Matrix Level Source Mic B2 Destination USB TX	#J0 MTRXLVL 5 M 1 D\x0D
Matrix Level Source Mic B3 Destination Line Output	#J0 MTRXLVL 6 M 2 O\x0D
Matrix Level Source Mic B3 Destination Loud Speaker	#J0 MTRXLVL 6 M 1 O\x0D
Matrix Level Source Mic B3 Destination Record	#J0 MTRXLVL 6 M 3 O\x0D
Matrix Level Source Mic B3 Destination Telco TX	#J0 MTRXLVL 6 M 1 T\x0D
Matrix Level Source Mic B3 Destination USB TX	#J0 MTRXLVL 6 M 1 D\x0D

Global Scripter Module Communication Sheet

Matrix Level Source Mic C1 Destination Line Output	#J0 MTRXLVL 7 M 2 O\x0D
Matrix Level Source Mic C1 Destination Loud Speaker	#J0 MTRXLVL 7 M 1 O\x0D
Matrix Level Source Mic C1 Destination Record	#J0 MTRXLVL 7 M 3 O\x0D
Matrix Level Source Mic C1 Destination Telco TX	#J0 MTRXLVL 7 M 1 T\x0D
Matrix Level Source Mic C1 Destination USB TX	#J0 MTRXLVL 7 M 1 D\x0D
Matrix Level Source Mic C2 Destination Line Output	#J0 MTRXLVL 8 M 2 O\x0D
Matrix Level Source Mic C2 Destination Loud Speaker	#J0 MTRXLVL 8 M 1 O\x0D
Matrix Level Source Mic C2 Destination Record	#J0 MTRXLVL 8 M 3 O\x0D
Matrix Level Source Mic C2 Destination Telco TX	#J0 MTRXLVL 8 M 1 T\x0D
Matrix Level Source Mic C2 Destination USB TX	#J0 MTRXLVL 8 M 1 D\x0D
Matrix Level Source Mic C3 Destination Line Output	#J0 MTRXLVL 9 M 2 O\x0D
Matrix Level Source Mic C3 Destination Loud Speaker	#J0 MTRXLVL 9 M 1 O\x0D
Matrix Level Source Mic C3 Destination Record	#J0 MTRXLVL 9 M 3 O\x0D
Matrix Level Source Mic C3 Destination Telco TX	#J0 MTRXLVL 9 M 1 T\x0D
Matrix Level Source Mic C3 Destination USB TX	#J0 MTRXLVL 9 M 1 D\x0D
Matrix Level Source Telco RX Destination Line Output	#J0 MTRXLVL 1 R 2 O\x0D
Matrix Level Source Telco RX Destination Loud Speaker	#J0 MTRXLVL 1 R 1 O\x0D
Matrix Level Source Telco RX Destination Record	#J0 MTRXLVL 1 R 3 O\x0D
Matrix Level Source Telco RX Destination Telco TX	#J0 MTRXLVL 1 R 1 T\x0D
Matrix Level Source Telco RX Destination USB TX	#J0 MTRXLVL 1 R 1 D\x0D
Matrix Level Source USB RX Destination Line Output	#J0 MTRXLVL 1 W 2 O\x0D
Matrix Level Source USB RX Destination Loud Speaker	#J0 MTRXLVL 1 W 1 O\x0D
Matrix Level Source USB RX Destination Record	#J0 MTRXLVL 1 W 3 O\x0D
Matrix Level Source USB RX Destination Telco TX	#J0 MTRXLVL 1 W 1 T\x0D
Matrix Level Source USB RX Destination USB TX	#J0 MTRXLVL 1 W 1 D\x0D
Mic Gain Mic 1	#J0 GAIN 1 M\x0D
Mic Gain Mic 1	#J0 GAIN 1 M\x0D
Mic Gain Mic 9	#J0 GAIN 9 M\x0D
Mic Mute Mic 1	#J0 MUTE 1 M\x0D
Mic Mute Mic 1	#J0 MUTE 1 M\x0D
Mic Mute Mic 9	#J0 MUTE 9 M\x0D
Output Gain Output 1	#J0 GAIN 1 O\x0D
Output Gain Output 1	#J0 GAIN 1 O\x0D
Output Gain Output 3	#J0 GAIN 3 O\x0D
Output Mute Output 1	#J0 MUTE 1 O\x0D
Output Mute Output 3	#J0 MUTE 3 O\x0D
Output Mute Output 1	#J0 MUTE 1 O\x0D
Phone Receive Gain	#J0 GAIN 1 R\x0D
Phone Receive Gain	#J0 GAIN 1 R\x0D
Phone Receive Mute	#J0 MUTE 1 R\x0D
Phone Transmit Gain	#J0 GAIN 1 T\x0D

Phone Transmit Gain	#J0 GAIN 1 T\x0D
Phone Transmit Mute	#J0 MUTE 1 T\x0D
Ringer Enable	#J0 RINGEREN 1\x0D
USB In Gain	#J0 GAIN 1 W\x0D
USB In Gain	#J0 GAIN 1 W\x0D
USB In Mute	#J0 MUTE 1 W\x0D
USB Out Gain	#J0 GAIN 1 D\x0D
USB Out Gain	#J0 GAIN 1 D\x0D
USB Out Mute	#J0 MUTE 1 D\x0D

Appendix C. Set Commands (Interact Pro)

Auto Answer Off	#K0 AA 1 0\x0D
Auto Answer On	#K0 AA 1 1\x0D
Clear Effect Off	#K0 CLEAREFFECT 1 0\x0D
Clear Effect On	#K0 CLEAREFFECT 1 1\x0D
DTMF 0	#K0 DIAL 1 0\x0D
DTMF 9	#K0 DIAL 1 9\x0D
DTMF #	#K0 DIAL 1 #\x0D
DTMF *	#K0 DIAL 1 *\x0D
DTMF ,	#K0 DIAL 1 ,\x0D
DTMF A	#K0 DIAL 1 A\x0D
DTMF B	#K0 DIAL 1 B\x0D
DTMF C	#K0 DIAL 1 C\x0D
DTMF D	#K0 DIAL 1 D\x0D
Global Mute Off	#K0 GMUTE M 0\x0D
Global Mute On	#K0 GMUTE M 1\x0D
Hook Dial	#K0 DIAL 1 8006339876\x0D
Hook Flash	#K0 HOOK 1\x0D
Hook Off	#K0 TE 1 1\x0D
Hook On	#K0 TE 1 0\x0D
Hook Redial	#K0 REDIAL 1\x0D
Line Input Gain -65.0 LineInput 1	#K0 GAIN 1 L -65.0 A\x0D
Line Input Gain 20.0 LineInput 1	#K0 GAIN 1 L 20.0 A\x0D
Line Input Gain -65.0 LineInput 2	#K0 GAIN 2 L -65.0 A\x0D
Line Input Gain 20.0 LineInput 2	#K0 GAIN 2 L 20.0 A\x0D
Line Input Gain -14.0 LineInput 1	#K0 GAIN 1 L -14.0 A\x0D
Line Input Gain 18.0 LineInput 1	#K0 GAIN 1 L 18.0 A\x0D
Line Input Gain -14.0 LineInput 2	#K0 GAIN 2 L -14.0 A\x0D

Line Input Gain 18.0 LineInput 2	#K0 GAIN 2 L 18.0 A\x0D
Line Input Mute Off LineInput 1	#K0 MUTE 1 L 0\x0D
Line Input Mute On LineInput 1	#K0 MUTE 1 L 1\x0D
Line Input Mute Off LineInput 2	#K0 MUTE 2 L 0\x0D
Line Input Mute On LineInput 2	#K0 MUTE 2 L 1\x0D
Matrix Cross point off Source Headset RX Destination Headset TX	#K0 MTRX 1 N 1 H 0\x0D
Matrix Cross point on Source Headset RX Destination Headset TX	#K0 MTRX 1 N 1 H 1\x0D
Matrix Gated Source Headset RX Destination Headset TX	#K0 MTRX 1 N 1 H 4\x0D
Matrix Cross point off Source Headset RX Destination Output 1	#K0 MTRX 1 N 1 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 1	#K0 MTRX 1 N 1 O 1\x0D
Matrix Gated Source Headset RX Destination Output 1	#K0 MTRX 1 N 1 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 2	#K0 MTRX 1 N 2 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 2	#K0 MTRX 1 N 2 O 1\x0D
Matrix Gated Source Headset RX Destination Output 2	#K0 MTRX 1 N 2 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 3	#K0 MTRX 1 N 3 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 3	#K0 MTRX 1 N 3 O 1\x0D
Matrix Gated Source Headset RX Destination Output 3	#K0 MTRX 1 N 3 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 4	#K0 MTRX 1 N 4 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 4	#K0 MTRX 1 N 4 O 1\x0D
Matrix Gated Source Headset RX Destination Output 4	#K0 MTRX 1 N 4 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 5	#K0 MTRX 1 N 5 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 5	#K0 MTRX 1 N 5 O 1\x0D
Matrix Gated Source Headset RX Destination Output 5	#K0 MTRX 1 N 5 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 6	#K0 MTRX 1 N 6 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 6	#K0 MTRX 1 N 6 O 1\x0D
Matrix Gated Source Headset RX Destination Output 6	#K0 MTRX 1 N 6 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 7	#K0 MTRX 1 N 7 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 7	#K0 MTRX 1 N 7 O 1\x0D
Matrix Gated Source Headset RX Destination Output 7	#K0 MTRX 1 N 7 O 4\x0D
Matrix Cross point off Source Headset RX Destination Output 8	#K0 MTRX 1 N 8 O 0\x0D
Matrix Cross point on Source Headset RX Destination Output 8	#K0 MTRX 1 N 8 O 1\x0D
Matrix Gated Source Headset RX Destination Output 8	#K0 MTRX 1 N 8 O 4\x0D
Matrix Cross point off Source Headset RX Destination Processing A	#K0 MTRX 1 N A P 0\x0D
Matrix Cross point on Source Headset RX Destination Processing A	#K0 MTRX 1 N A P 1\x0D
Matrix Gated Source Headset RX Destination Processing A	#K0 MTRX 1 N A P 4\x0D
Matrix Cross point off Source Headset RX Destination Processing B	#K0 MTRX 1 N B P 0\x0D
Matrix Cross point on Source Headset RX Destination Processing B	#K0 MTRX 1 N B P 1\x0D
Matrix Gated Source Headset RX Destination Processing B	#K0 MTRX 1 N B P 4\x0D
Matrix Cross point off Source Headset RX Destination Processing C	#K0 MTRX 1 N C P 0\x0D
Matrix Cross point on Source Headset RX Destination Processing C	#K0 MTRX 1 N C P 1\x0D
Matrix Gated Source Headset RX Destination Processing C	#K0 MTRX 1 N C P 4\x0D

Matrix Cross point off Source Headset RX Destination Telco TX	#K0 MTRX 1 N 1 T 0\x0D
Matrix Cross point on Source Headset RX Destination Telco TX	#K0 MTRX 1 N 1 T 1\x0D
Matrix Gated Source Headset RX Destination Telco TX	#K0 MTRX 1 N 1 T 4\x0D
Matrix Cross point off Source Headset RX Destination USB TX	#K0 MTRX 1 N 1 D 0\x0D
Matrix Cross point on Source Headset RX Destination USB TX	#K0 MTRX 1 N 1 D 1\x0D
Matrix Gated Source Headset RX Destination USB TX	#K0 MTRX 1 N 1 D 4\x0D
Matrix Cross point off Source Headset RX Destination Virtual Ref 1	#K0 MTRX 1 N 1 D 0\x0D
Matrix Cross point on Source Headset RX Destination Virtual Ref 1	#K0 MTRX 1 N 1 D 1\x0D
Matrix Gated Source Headset RX Destination Virtual Ref 1	#K0 MTRX 1 N 1 D 4\x0D
Matrix Cross point off Source Headset RX Destination Virtual Ref 2	#K0 MTRX 1 N 2 D 0\x0D
Matrix Cross point on Source Headset RX Destination Virtual Ref 2	#K0 MTRX 1 N 2 D 1\x0D
Matrix Gated Source Headset RX Destination Virtual Ref 2	#K0 MTRX 1 N 2 D 4\x0D
Matrix Cross point off Source Line Input 1 Destination Headset TX	#K0 MTRX 1 L 1 H 0\x0D
Matrix Cross point on Source Line Input 1 Destination Headset TX	#K0 MTRX 1 L 1 H 1\x0D
Matrix Gated Source Line Input 1 Destination Headset TX	#K0 MTRX 1 L 1 H 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 1	#K0 MTRX 1 L 1 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 1	#K0 MTRX 1 L 1 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 1	#K0 MTRX 1 L 1 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 2	#K0 MTRX 1 L 2 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 2	#K0 MTRX 1 L 2 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 2	#K0 MTRX 1 L 2 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 3	#K0 MTRX 1 L 3 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 3	#K0 MTRX 1 L 3 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 3	#K0 MTRX 1 L 3 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 4	#K0 MTRX 1 L 4 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 4	#K0 MTRX 1 L 4 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 4	#K0 MTRX 1 L 4 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 5	#K0 MTRX 1 L 5 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 5	#K0 MTRX 1 L 5 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 5	#K0 MTRX 1 L 5 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 6	#K0 MTRX 1 L 6 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 6	#K0 MTRX 1 L 6 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 6	#K0 MTRX 1 L 6 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 7	#K0 MTRX 1 L 7 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 7	#K0 MTRX 1 L 7 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 7	#K0 MTRX 1 L 7 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Output 8	#K0 MTRX 1 L 8 O 0\x0D
Matrix Cross point on Source Line Input 1 Destination Output 8	#K0 MTRX 1 L 8 O 1\x0D
Matrix Gated Source Line Input 1 Destination Output 8	#K0 MTRX 1 L 8 O 4\x0D
Matrix Cross point off Source Line Input 1 Destination Processing A	#K0 MTRX 1 L A P 0\x0D
Matrix Cross point on Source Line Input 1 Destination Processing A	#K0 MTRX 1 L A P 1\x0D

Matrix Gated Source Line Input 1 Destination Processing A	#K0 MTRX 1 L A P 4\x0D
Matrix Cross point off Source Line Input 1 Destination Processing B	#K0 MTRX 1 L B P 0\x0D
Matrix Cross point on Source Line Input 1 Destination Processing B	#K0 MTRX 1 L B P 1\x0D
Matrix Gated Source Line Input 1 Destination Processing B	#K0 MTRX 1 L B P 4\x0D
Matrix Cross point off Source Line Input 1 Destination Processing C	#K0 MTRX 1 L C P 0\x0D
Matrix Cross point on Source Line Input 1 Destination Processing C	#K0 MTRX 1 L C P 1\x0D
Matrix Gated Source Line Input 1 Destination Processing C	#K0 MTRX 1 L C P 4\x0D
Matrix Cross point off Source Line Input 1 Destination Telco TX	#K0 MTRX 1 L 1 T 0\x0D
Matrix Cross point on Source Line Input 1 Destination Telco TX	#K0 MTRX 1 L 1 T 1\x0D
Matrix Gated Source Line Input 1 Destination Telco TX	#K0 MTRX 1 L 1 T 4\x0D
Matrix Cross point off Source Line Input 1 Destination USB TX	#K0 MTRX 1 L 1 D 0\x0D
Matrix Cross point on Source Line Input 1 Destination USB TX	#K0 MTRX 1 L 1 D 1\x0D
Matrix Gated Source Line Input 1 Destination USB TX	#K0 MTRX 1 L 1 D 4\x0D
Matrix Cross point off Source Line Input 1 Destination Virtual Ref 1	#K0 MTRX 1 L 1 D 0\x0D
Matrix Cross point on Source Line Input 1 Destination Virtual Ref 1	#K0 MTRX 1 L 1 D 1\x0D
Matrix Gated Source Line Input 1 Destination Virtual Ref 1	#K0 MTRX 1 L 1 D 4\x0D
Matrix Cross point off Source Line Input 1 Destination Virtual Ref 2	#K0 MTRX 1 L 2 D 0\x0D
Matrix Cross point on Source Line Input 1 Destination Virtual Ref 2	#K0 MTRX 1 L 2 D 1\x0D
Matrix Gated Source Line Input 1 Destination Virtual Ref 2	#K0 MTRX 1 L 2 D 4\x0D
Matrix Cross point off Source Line Input 2 Destination Headset TX	#K0 MTRX 2 L 1 H 0\x0D
Matrix Cross point on Source Line Input 2 Destination Headset TX	#K0 MTRX 2 L 1 H 1\x0D
Matrix Gated Source Line Input 2 Destination Headset TX	#K0 MTRX 2 L 1 H 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 1	#K0 MTRX 2 L 1 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 1	#K0 MTRX 2 L 1 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 1	#K0 MTRX 2 L 1 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 2	#K0 MTRX 2 L 2 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 2	#K0 MTRX 2 L 2 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 2	#K0 MTRX 2 L 2 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 3	#K0 MTRX 2 L 3 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 3	#K0 MTRX 2 L 3 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 3	#K0 MTRX 2 L 3 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 4	#K0 MTRX 2 L 4 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 4	#K0 MTRX 2 L 4 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 4	#K0 MTRX 2 L 4 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 5	#K0 MTRX 2 L 5 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 5	#K0 MTRX 2 L 5 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 5	#K0 MTRX 2 L 5 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 6	#K0 MTRX 2 L 6 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 6	#K0 MTRX 2 L 6 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 6	#K0 MTRX 2 L 6 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 7	#K0 MTRX 2 L 7 O 0\x0D

Matrix Cross point on Source Line Input 2 Destination Output 7	#K0 MTRX 2 L 7 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 7	#K0 MTRX 2 L 7 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Output 8	#K0 MTRX 2 L 8 O 0\x0D
Matrix Cross point on Source Line Input 2 Destination Output 8	#K0 MTRX 2 L 8 O 1\x0D
Matrix Gated Source Line Input 2 Destination Output 8	#K0 MTRX 2 L 8 O 4\x0D
Matrix Cross point off Source Line Input 2 Destination Processing A	#K0 MTRX 2 L A P 0\x0D
Matrix Cross point on Source Line Input 2 Destination Processing A	#K0 MTRX 2 L A P 1\x0D
Matrix Gated Source Line Input 2 Destination Processing A	#K0 MTRX 2 L A P 4\x0D
Matrix Cross point off Source Line Input 2 Destination Processing B	#K0 MTRX 2 L B P 0\x0D
Matrix Cross point on Source Line Input 2 Destination Processing B	#K0 MTRX 2 L B P 1\x0D
Matrix Gated Source Line Input 2 Destination Processing B	#K0 MTRX 2 L B P 4\x0D
Matrix Cross point off Source Line Input 2 Destination Processing C	#K0 MTRX 2 L C P 0\x0D
Matrix Cross point on Source Line Input 2 Destination Processing C	#K0 MTRX 2 L C P 1\x0D
Matrix Gated Source Line Input 2 Destination Processing C	#K0 MTRX 2 L C P 4\x0D
Matrix Cross point off Source Line Input 2 Destination Telco TX	#K0 MTRX 2 L 1 T 0\x0D
Matrix Cross point on Source Line Input 2 Destination Telco TX	#K0 MTRX 2 L 1 T 1\x0D
Matrix Gated Source Line Input 2 Destination Telco TX	#K0 MTRX 2 L 1 T 4\x0D
Matrix Cross point off Source Line Input 2 Destination USB TX	#K0 MTRX 2 L 1 D 0\x0D
Matrix Cross point on Source Line Input 2 Destination USB TX	#K0 MTRX 2 L 1 D 1\x0D
Matrix Gated Source Line Input 2 Destination USB TX	#K0 MTRX 2 L 1 D 4\x0D
Matrix Cross point off Source Line Input 2 Destination Virtual Ref 1	#K0 MTRX 2 L 1 D 0\x0D
Matrix Cross point on Source Line Input 2 Destination Virtual Ref 1	#K0 MTRX 2 L 1 D 1\x0D
Matrix Gated Source Line Input 2 Destination Virtual Ref 1	#K0 MTRX 2 L 1 D 4\x0D
Matrix Cross point off Source Line Input 2 Destination Virtual Ref 2	#K0 MTRX 2 L 2 D 0\x0D
Matrix Cross point on Source Line Input 2 Destination Virtual Ref 2	#K0 MTRX 2 L 2 D 1\x0D
Matrix Gated Source Line Input 2 Destination Virtual Ref 2	#K0 MTRX 2 L 2 D 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Headset TX	#K0 MTRX 1 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Headset TX	#K0 MTRX 1 M 1 H 1\x0D
Matrix Gated Source Mic Input 1 Destination Headset TX	#K0 MTRX 1 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 1	#K0 MTRX 1 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 1	#K0 MTRX 1 M 1 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 1	#K0 MTRX 1 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 2	#K0 MTRX 1 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 2	#K0 MTRX 1 M 2 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 2	#K0 MTRX 1 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 3	#K0 MTRX 1 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 3	#K0 MTRX 1 M 3 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 3	#K0 MTRX 1 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 4	#K0 MTRX 1 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 4	#K0 MTRX 1 M 4 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 4	#K0 MTRX 1 M 4 O 4\x0D

Matrix Cross point off Source Mic Input 1 Destination Output 5	#K0 MTRX 1 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 5	#K0 MTRX 1 M 5 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 5	#K0 MTRX 1 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 6	#K0 MTRX 1 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 6	#K0 MTRX 1 M 6 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 6	#K0 MTRX 1 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 7	#K0 MTRX 1 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 7	#K0 MTRX 1 M 7 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 7	#K0 MTRX 1 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Output 8	#K0 MTRX 1 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Output 8	#K0 MTRX 1 M 8 O 1\x0D
Matrix Gated Source Mic Input 1 Destination Output 8	#K0 MTRX 1 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Processing A	#K0 MTRX 1 M A P 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Processing A	#K0 MTRX 1 M A P 1\x0D
Matrix Gated Source Mic Input 1 Destination Processing A	#K0 MTRX 1 M A P 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Processing B	#K0 MTRX 1 M B P 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Processing B	#K0 MTRX 1 M B P 1\x0D
Matrix Gated Source Mic Input 1 Destination Processing B	#K0 MTRX 1 M B P 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Processing C	#K0 MTRX 1 M C P 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Processing C	#K0 MTRX 1 M C P 1\x0D
Matrix Gated Source Mic Input 1 Destination Processing C	#K0 MTRX 1 M C P 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Telco TX	#K0 MTRX 1 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Telco TX	#K0 MTRX 1 M 1 T 1\x0D
Matrix Gated Source Mic Input 1 Destination Telco TX	#K0 MTRX 1 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 1 Destination USB TX	#K0 MTRX 1 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 1 Destination USB TX	#K0 MTRX 1 M 1 D 1\x0D
Matrix Gated Source Mic Input 1 Destination USB TX	#K0 MTRX 1 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRX 1 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRX 1 M 1 D 1\x0D
Matrix Gated Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRX 1 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRX 1 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRX 1 M 2 D 1\x0D
Matrix Gated Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRX 1 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Headset TX	#K0 MTRX 10 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Headset TX	#K0 MTRX 10 M 1 H 1\x0D
Matrix Gated Source Mic Input 10 Destination Headset TX	#K0 MTRX 10 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 1	#K0 MTRX 10 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 1	#K0 MTRX 10 M 1 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 1	#K0 MTRX 10 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 2	#K0 MTRX 10 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 2	#K0 MTRX 10 M 2 O 1\x0D

Matrix Gated Source Mic Input 10 Destination Output 2	#K0 MTRX 10 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 3	#K0 MTRX 10 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 3	#K0 MTRX 10 M 3 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 3	#K0 MTRX 10 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 4	#K0 MTRX 10 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 4	#K0 MTRX 10 M 4 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 4	#K0 MTRX 10 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 5	#K0 MTRX 10 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 5	#K0 MTRX 10 M 5 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 5	#K0 MTRX 10 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 6	#K0 MTRX 10 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 6	#K0 MTRX 10 M 6 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 6	#K0 MTRX 10 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 7	#K0 MTRX 10 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 7	#K0 MTRX 10 M 7 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 7	#K0 MTRX 10 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Output 8	#K0 MTRX 10 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Output 8	#K0 MTRX 10 M 8 O 1\x0D
Matrix Gated Source Mic Input 10 Destination Output 8	#K0 MTRX 10 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Processing A	#K0 MTRX 10 M A P 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Processing A	#K0 MTRX 10 M A P 1\x0D
Matrix Gated Source Mic Input 10 Destination Processing A	#K0 MTRX 10 M A P 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Processing B	#K0 MTRX 10 M B P 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Processing B	#K0 MTRX 10 M B P 1\x0D
Matrix Gated Source Mic Input 10 Destination Processing B	#K0 MTRX 10 M B P 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Processing C	#K0 MTRX 10 M C P 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Processing C	#K0 MTRX 10 M C P 1\x0D
Matrix Gated Source Mic Input 10 Destination Processing C	#K0 MTRX 10 M C P 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Telco TX	#K0 MTRX 10 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Telco TX	#K0 MTRX 10 M 1 T 1\x0D
Matrix Gated Source Mic Input 10 Destination Telco TX	#K0 MTRX 10 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 10 Destination USB TX	#K0 MTRX 10 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 10 Destination USB TX	#K0 MTRX 10 M 1 D 1\x0D
Matrix Gated Source Mic Input 10 Destination USB TX	#K0 MTRX 10 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRX 10 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRX 10 M 1 D 1\x0D
Matrix Gated Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRX 10 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRX 10 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRX 10 M 2 D 1\x0D
Matrix Gated Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRX 10 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Headset TX	#K0 MTRX 11 M 1 H 0\x0D

Matrix Cross point on Source Mic Input 11 Destination Headset TX	#K0 MTRX 11 M 1 H 1\x0D
Matrix Gated Source Mic Input 11 Destination Headset TX	#K0 MTRX 11 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 1	#K0 MTRX 11 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 1	#K0 MTRX 11 M 1 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 1	#K0 MTRX 11 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 2	#K0 MTRX 11 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 2	#K0 MTRX 11 M 2 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 2	#K0 MTRX 11 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 3	#K0 MTRX 11 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 3	#K0 MTRX 11 M 3 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 3	#K0 MTRX 11 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 4	#K0 MTRX 11 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 4	#K0 MTRX 11 M 4 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 4	#K0 MTRX 11 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 5	#K0 MTRX 11 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 5	#K0 MTRX 11 M 5 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 5	#K0 MTRX 11 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 6	#K0 MTRX 11 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 6	#K0 MTRX 11 M 6 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 6	#K0 MTRX 11 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 7	#K0 MTRX 11 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 7	#K0 MTRX 11 M 7 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 7	#K0 MTRX 11 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Output 8	#K0 MTRX 11 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Output 8	#K0 MTRX 11 M 8 O 1\x0D
Matrix Gated Source Mic Input 11 Destination Output 8	#K0 MTRX 11 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Processing A	#K0 MTRX 11 M A P 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Processing A	#K0 MTRX 11 M A P 1\x0D
Matrix Gated Source Mic Input 11 Destination Processing A	#K0 MTRX 11 M A P 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Processing B	#K0 MTRX 11 M B P 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Processing B	#K0 MTRX 11 M B P 1\x0D
Matrix Gated Source Mic Input 11 Destination Processing B	#K0 MTRX 11 M B P 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Processing C	#K0 MTRX 11 M C P 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Processing C	#K0 MTRX 11 M C P 1\x0D
Matrix Gated Source Mic Input 11 Destination Processing C	#K0 MTRX 11 M C P 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Telco TX	#K0 MTRX 11 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Telco TX	#K0 MTRX 11 M 1 T 1\x0D
Matrix Gated Source Mic Input 11 Destination Telco TX	#K0 MTRX 11 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 11 Destination USB TX	#K0 MTRX 11 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 11 Destination USB TX	#K0 MTRX 11 M 1 D 1\x0D
Matrix Gated Source Mic Input 11 Destination USB TX	#K0 MTRX 11 M 1 D 4\x0D

Global Scripter Module Communication Sheet

Matrix Cross point off Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRX 11 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRX 11 M 1 D 1\x0D
Matrix Gated Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRX 11 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRX 11 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRX 11 M 2 D 1\x0D
Matrix Gated Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRX 11 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Headset TX	#K0 MTRX 12 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Headset TX	#K0 MTRX 12 M 1 H 1\x0D
Matrix Gated Source Mic Input 12 Destination Headset TX	#K0 MTRX 12 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 1	#K0 MTRX 12 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 1	#K0 MTRX 12 M 1 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 1	#K0 MTRX 12 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 2	#K0 MTRX 12 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 2	#K0 MTRX 12 M 2 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 2	#K0 MTRX 12 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 3	#K0 MTRX 12 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 3	#K0 MTRX 12 M 3 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 3	#K0 MTRX 12 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 4	#K0 MTRX 12 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 4	#K0 MTRX 12 M 4 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 4	#K0 MTRX 12 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 5	#K0 MTRX 12 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 5	#K0 MTRX 12 M 5 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 5	#K0 MTRX 12 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 6	#K0 MTRX 12 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 6	#K0 MTRX 12 M 6 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 6	#K0 MTRX 12 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 7	#K0 MTRX 12 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 7	#K0 MTRX 12 M 7 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 7	#K0 MTRX 12 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Output 8	#K0 MTRX 12 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Output 8	#K0 MTRX 12 M 8 O 1\x0D
Matrix Gated Source Mic Input 12 Destination Output 8	#K0 MTRX 12 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Processing A	#K0 MTRX 12 M A P 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Processing A	#K0 MTRX 12 M A P 1\x0D
Matrix Gated Source Mic Input 12 Destination Processing A	#K0 MTRX 12 M A P 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Processing B	#K0 MTRX 12 M B P 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Processing B	#K0 MTRX 12 M B P 1\x0D
Matrix Gated Source Mic Input 12 Destination Processing B	#K0 MTRX 12 M B P 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Processing C	#K0 MTRX 12 M C P 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Processing C	#K0 MTRX 12 M C P 1\x0D

Matrix Gated Source Mic Input 12 Destination Processing C	#K0 MTRX 12 M C P 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Telco TX	#K0 MTRX 12 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Telco TX	#K0 MTRX 12 M 1 T 1\x0D
Matrix Gated Source Mic Input 12 Destination Telco TX	#K0 MTRX 12 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 12 Destination USB TX	#K0 MTRX 12 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 12 Destination USB TX	#K0 MTRX 12 M 1 D 1\x0D
Matrix Gated Source Mic Input 12 Destination USB TX	#K0 MTRX 12 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRX 12 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRX 12 M 1 D 1\x0D
Matrix Gated Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRX 12 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRX 12 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRX 12 M 2 D 1\x0D
Matrix Gated Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRX 12 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Headset TX	#K0 MTRX 13 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Headset TX	#K0 MTRX 13 M 1 H 1\x0D
Matrix Gated Source Mic Input 13 Destination Headset TX	#K0 MTRX 13 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 1	#K0 MTRX 13 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 1	#K0 MTRX 13 M 1 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 1	#K0 MTRX 13 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 2	#K0 MTRX 13 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 2	#K0 MTRX 13 M 2 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 2	#K0 MTRX 13 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 3	#K0 MTRX 13 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 3	#K0 MTRX 13 M 3 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 3	#K0 MTRX 13 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 4	#K0 MTRX 13 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 4	#K0 MTRX 13 M 4 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 4	#K0 MTRX 13 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 5	#K0 MTRX 13 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 5	#K0 MTRX 13 M 5 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 5	#K0 MTRX 13 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 6	#K0 MTRX 13 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 6	#K0 MTRX 13 M 6 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 6	#K0 MTRX 13 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 7	#K0 MTRX 13 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 7	#K0 MTRX 13 M 7 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 7	#K0 MTRX 13 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Output 8	#K0 MTRX 13 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Output 8	#K0 MTRX 13 M 8 O 1\x0D
Matrix Gated Source Mic Input 13 Destination Output 8	#K0 MTRX 13 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Processing A	#K0 MTRX 13 M A P 0\x0D

Matrix Cross point on Source Mic Input 13 Destination Processing A	#K0 MTRX 13 M A P 1\x0D
Matrix Gated Source Mic Input 13 Destination Processing A	#K0 MTRX 13 M A P 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Processing B	#K0 MTRX 13 M B P 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Processing B	#K0 MTRX 13 M B P 1\x0D
Matrix Gated Source Mic Input 13 Destination Processing B	#K0 MTRX 13 M B P 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Processing C	#K0 MTRX 13 M C P 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Processing C	#K0 MTRX 13 M C P 1\x0D
Matrix Gated Source Mic Input 13 Destination Processing C	#K0 MTRX 13 M C P 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Telco TX	#K0 MTRX 13 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Telco TX	#K0 MTRX 13 M 1 T 1\x0D
Matrix Gated Source Mic Input 13 Destination Telco TX	#K0 MTRX 13 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 13 Destination USB TX	#K0 MTRX 13 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 13 Destination USB TX	#K0 MTRX 13 M 1 D 1\x0D
Matrix Gated Source Mic Input 13 Destination USB TX	#K0 MTRX 13 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRX 13 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRX 13 M 1 D 1\x0D
Matrix Gated Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRX 13 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRX 13 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRX 13 M 2 D 1\x0D
Matrix Gated Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRX 13 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Headset TX	#K0 MTRX 14 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Headset TX	#K0 MTRX 14 M 1 H 1\x0D
Matrix Gated Source Mic Input 14 Destination Headset TX	#K0 MTRX 14 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 1	#K0 MTRX 14 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 1	#K0 MTRX 14 M 1 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 1	#K0 MTRX 14 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 2	#K0 MTRX 14 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 2	#K0 MTRX 14 M 2 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 2	#K0 MTRX 14 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 3	#K0 MTRX 14 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 3	#K0 MTRX 14 M 3 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 3	#K0 MTRX 14 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 4	#K0 MTRX 14 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 4	#K0 MTRX 14 M 4 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 4	#K0 MTRX 14 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 5	#K0 MTRX 14 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 5	#K0 MTRX 14 M 5 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 5	#K0 MTRX 14 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 6	#K0 MTRX 14 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 6	#K0 MTRX 14 M 6 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 6	#K0 MTRX 14 M 6 O 4\x0D

Matrix Cross point off Source Mic Input 14 Destination Output 7	#K0 MTRX 14 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 7	#K0 MTRX 14 M 7 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 7	#K0 MTRX 14 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Output 8	#K0 MTRX 14 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Output 8	#K0 MTRX 14 M 8 O 1\x0D
Matrix Gated Source Mic Input 14 Destination Output 8	#K0 MTRX 14 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Processing A	#K0 MTRX 14 M A P 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Processing A	#K0 MTRX 14 M A P 1\x0D
Matrix Gated Source Mic Input 14 Destination Processing A	#K0 MTRX 14 M A P 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Processing B	#K0 MTRX 14 M B P 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Processing B	#K0 MTRX 14 M B P 1\x0D
Matrix Gated Source Mic Input 14 Destination Processing B	#K0 MTRX 14 M B P 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Processing C	#K0 MTRX 14 M C P 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Processing C	#K0 MTRX 14 M C P 1\x0D
Matrix Gated Source Mic Input 14 Destination Processing C	#K0 MTRX 14 M C P 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Telco TX	#K0 MTRX 14 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Telco TX	#K0 MTRX 14 M 1 T 1\x0D
Matrix Gated Source Mic Input 14 Destination Telco TX	#K0 MTRX 14 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 14 Destination USB TX	#K0 MTRX 14 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 14 Destination USB TX	#K0 MTRX 14 M 1 D 1\x0D
Matrix Gated Source Mic Input 14 Destination USB TX	#K0 MTRX 14 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRX 14 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRX 14 M 1 D 1\x0D
Matrix Gated Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRX 14 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRX 14 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRX 14 M 2 D 1\x0D
Matrix Gated Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRX 14 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Headset TX	#K0 MTRX 15 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Headset TX	#K0 MTRX 15 M 1 H 1\x0D
Matrix Gated Source Mic Input 15 Destination Headset TX	#K0 MTRX 15 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 1	#K0 MTRX 15 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 1	#K0 MTRX 15 M 1 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 1	#K0 MTRX 15 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 2	#K0 MTRX 15 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 2	#K0 MTRX 15 M 2 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 2	#K0 MTRX 15 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 3	#K0 MTRX 15 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 3	#K0 MTRX 15 M 3 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 3	#K0 MTRX 15 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 4	#K0 MTRX 15 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 4	#K0 MTRX 15 M 4 O 1\x0D

Matrix Gated Source Mic Input 15 Destination Output 4	#K0 MTRX 15 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 5	#K0 MTRX 15 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 5	#K0 MTRX 15 M 5 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 5	#K0 MTRX 15 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 6	#K0 MTRX 15 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 6	#K0 MTRX 15 M 6 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 6	#K0 MTRX 15 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 7	#K0 MTRX 15 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 7	#K0 MTRX 15 M 7 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 7	#K0 MTRX 15 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Output 8	#K0 MTRX 15 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Output 8	#K0 MTRX 15 M 8 O 1\x0D
Matrix Gated Source Mic Input 15 Destination Output 8	#K0 MTRX 15 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Processing A	#K0 MTRX 15 M A P 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Processing A	#K0 MTRX 15 M A P 1\x0D
Matrix Gated Source Mic Input 15 Destination Processing A	#K0 MTRX 15 M A P 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Processing B	#K0 MTRX 15 M B P 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Processing B	#K0 MTRX 15 M B P 1\x0D
Matrix Gated Source Mic Input 15 Destination Processing B	#K0 MTRX 15 M B P 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Processing C	#K0 MTRX 15 M C P 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Processing C	#K0 MTRX 15 M C P 1\x0D
Matrix Gated Source Mic Input 15 Destination Processing C	#K0 MTRX 15 M C P 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Telco TX	#K0 MTRX 15 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Telco TX	#K0 MTRX 15 M 1 T 1\x0D
Matrix Gated Source Mic Input 15 Destination Telco TX	#K0 MTRX 15 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 15 Destination USB TX	#K0 MTRX 15 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 15 Destination USB TX	#K0 MTRX 15 M 1 D 1\x0D
Matrix Gated Source Mic Input 15 Destination USB TX	#K0 MTRX 15 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRX 15 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRX 15 M 1 D 1\x0D
Matrix Gated Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRX 15 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRX 15 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRX 15 M 2 D 1\x0D
Matrix Gated Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRX 15 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Headset TX	#K0 MTRX 16 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Headset TX	#K0 MTRX 16 M 1 H 1\x0D
Matrix Gated Source Mic Input 16 Destination Headset TX	#K0 MTRX 16 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 1	#K0 MTRX 16 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 1	#K0 MTRX 16 M 1 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 1	#K0 MTRX 16 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 2	#K0 MTRX 16 M 2 O 0\x0D

Matrix Cross point on Source Mic Input 16 Destination Output 2	#K0 MTRX 16 M 2 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 2	#K0 MTRX 16 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 3	#K0 MTRX 16 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 3	#K0 MTRX 16 M 3 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 3	#K0 MTRX 16 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 4	#K0 MTRX 16 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 4	#K0 MTRX 16 M 4 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 4	#K0 MTRX 16 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 5	#K0 MTRX 16 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 5	#K0 MTRX 16 M 5 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 5	#K0 MTRX 16 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 6	#K0 MTRX 16 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 6	#K0 MTRX 16 M 6 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 6	#K0 MTRX 16 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 7	#K0 MTRX 16 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 7	#K0 MTRX 16 M 7 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 7	#K0 MTRX 16 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Output 8	#K0 MTRX 16 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Output 8	#K0 MTRX 16 M 8 O 1\x0D
Matrix Gated Source Mic Input 16 Destination Output 8	#K0 MTRX 16 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Processing A	#K0 MTRX 16 M A P 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Processing A	#K0 MTRX 16 M A P 1\x0D
Matrix Gated Source Mic Input 16 Destination Processing A	#K0 MTRX 16 M A P 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Processing B	#K0 MTRX 16 M B P 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Processing B	#K0 MTRX 16 M B P 1\x0D
Matrix Gated Source Mic Input 16 Destination Processing B	#K0 MTRX 16 M B P 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Processing C	#K0 MTRX 16 M C P 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Processing C	#K0 MTRX 16 M C P 1\x0D
Matrix Gated Source Mic Input 16 Destination Processing C	#K0 MTRX 16 M C P 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Telco TX	#K0 MTRX 16 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Telco TX	#K0 MTRX 16 M 1 T 1\x0D
Matrix Gated Source Mic Input 16 Destination Telco TX	#K0 MTRX 16 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 16 Destination USB TX	#K0 MTRX 16 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 16 Destination USB TX	#K0 MTRX 16 M 1 D 1\x0D
Matrix Gated Source Mic Input 16 Destination USB TX	#K0 MTRX 16 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRX 16 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRX 16 M 1 D 1\x0D
Matrix Gated Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRX 16 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRX 16 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRX 16 M 2 D 1\x0D
Matrix Gated Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRX 16 M 2 D 4\x0D

Matrix Cross point off Source Mic Input 2 Destination Headset TX	#K0 MTRX 2 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Headset TX	#K0 MTRX 2 M 1 H 1\x0D
Matrix Gated Source Mic Input 2 Destination Headset TX	#K0 MTRX 2 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 1	#K0 MTRX 2 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 1	#K0 MTRX 2 M 1 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 1	#K0 MTRX 2 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 2	#K0 MTRX 2 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 2	#K0 MTRX 2 M 2 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 2	#K0 MTRX 2 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 3	#K0 MTRX 2 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 3	#K0 MTRX 2 M 3 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 3	#K0 MTRX 2 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 4	#K0 MTRX 2 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 4	#K0 MTRX 2 M 4 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 4	#K0 MTRX 2 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 5	#K0 MTRX 2 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 5	#K0 MTRX 2 M 5 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 5	#K0 MTRX 2 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 6	#K0 MTRX 2 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 6	#K0 MTRX 2 M 6 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 6	#K0 MTRX 2 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 7	#K0 MTRX 2 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 7	#K0 MTRX 2 M 7 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 7	#K0 MTRX 2 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Output 8	#K0 MTRX 2 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Output 8	#K0 MTRX 2 M 8 O 1\x0D
Matrix Gated Source Mic Input 2 Destination Output 8	#K0 MTRX 2 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Processing A	#K0 MTRX 2 M A P 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Processing A	#K0 MTRX 2 M A P 1\x0D
Matrix Gated Source Mic Input 2 Destination Processing A	#K0 MTRX 2 M A P 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Processing B	#K0 MTRX 2 M B P 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Processing B	#K0 MTRX 2 M B P 1\x0D
Matrix Gated Source Mic Input 2 Destination Processing B	#K0 MTRX 2 M B P 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Processing C	#K0 MTRX 2 M C P 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Processing C	#K0 MTRX 2 M C P 1\x0D
Matrix Gated Source Mic Input 2 Destination Processing C	#K0 MTRX 2 M C P 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Telco TX	#K0 MTRX 2 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Telco TX	#K0 MTRX 2 M 1 T 1\x0D
Matrix Gated Source Mic Input 2 Destination Telco TX	#K0 MTRX 2 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 2 Destination USB TX	#K0 MTRX 2 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 2 Destination USB TX	#K0 MTRX 2 M 1 D 1\x0D

Matrix Gated Source Mic Input 2 Destination USB TX	#K0 MTRX 2 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRX 2 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRX 2 M 1 D 1\x0D
Matrix Gated Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRX 2 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRX 2 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRX 2 M 2 D 1\x0D
Matrix Gated Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRX 2 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Headset TX	#K0 MTRX 3 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Headset TX	#K0 MTRX 3 M 1 H 1\x0D
Matrix Gated Source Mic Input 3 Destination Headset TX	#K0 MTRX 3 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 1	#K0 MTRX 3 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 1	#K0 MTRX 3 M 1 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 1	#K0 MTRX 3 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 2	#K0 MTRX 3 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 2	#K0 MTRX 3 M 2 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 2	#K0 MTRX 3 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 3	#K0 MTRX 3 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 3	#K0 MTRX 3 M 3 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 3	#K0 MTRX 3 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 4	#K0 MTRX 3 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 4	#K0 MTRX 3 M 4 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 4	#K0 MTRX 3 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 5	#K0 MTRX 3 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 5	#K0 MTRX 3 M 5 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 5	#K0 MTRX 3 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 6	#K0 MTRX 3 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 6	#K0 MTRX 3 M 6 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 6	#K0 MTRX 3 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 7	#K0 MTRX 3 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 7	#K0 MTRX 3 M 7 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 7	#K0 MTRX 3 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Output 8	#K0 MTRX 3 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Output 8	#K0 MTRX 3 M 8 O 1\x0D
Matrix Gated Source Mic Input 3 Destination Output 8	#K0 MTRX 3 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Processing A	#K0 MTRX 3 M A P 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Processing A	#K0 MTRX 3 M A P 1\x0D
Matrix Gated Source Mic Input 3 Destination Processing A	#K0 MTRX 3 M A P 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Processing B	#K0 MTRX 3 M B P 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Processing B	#K0 MTRX 3 M B P 1\x0D
Matrix Gated Source Mic Input 3 Destination Processing B	#K0 MTRX 3 M B P 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Processing C	#K0 MTRX 3 M C P 0\x0D

Global Scripter Module Communication Sheet

Matrix Cross point on Source Mic Input 3 Destination Processing C	#K0 MTRX 3 M C P 1\x0D
Matrix Gated Source Mic Input 3 Destination Processing C	#K0 MTRX 3 M C P 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Telco TX	#K0 MTRX 3 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Telco TX	#K0 MTRX 3 M 1 T 1\x0D
Matrix Gated Source Mic Input 3 Destination Telco TX	#K0 MTRX 3 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 3 Destination USB TX	#K0 MTRX 3 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 3 Destination USB TX	#K0 MTRX 3 M 1 D 1\x0D
Matrix Gated Source Mic Input 3 Destination USB TX	#K0 MTRX 3 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRX 3 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRX 3 M 1 D 1\x0D
Matrix Gated Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRX 3 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRX 3 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRX 3 M 2 D 1\x0D
Matrix Gated Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRX 3 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Headset TX	#K0 MTRX 4 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Headset TX	#K0 MTRX 4 M 1 H 1\x0D
Matrix Gated Source Mic Input 4 Destination Headset TX	#K0 MTRX 4 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 1	#K0 MTRX 4 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 1	#K0 MTRX 4 M 1 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 1	#K0 MTRX 4 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 2	#K0 MTRX 4 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 2	#K0 MTRX 4 M 2 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 2	#K0 MTRX 4 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 3	#K0 MTRX 4 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 3	#K0 MTRX 4 M 3 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 3	#K0 MTRX 4 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 4	#K0 MTRX 4 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 4	#K0 MTRX 4 M 4 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 4	#K0 MTRX 4 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 5	#K0 MTRX 4 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 5	#K0 MTRX 4 M 5 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 5	#K0 MTRX 4 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 6	#K0 MTRX 4 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 6	#K0 MTRX 4 M 6 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 6	#K0 MTRX 4 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 7	#K0 MTRX 4 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 7	#K0 MTRX 4 M 7 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 7	#K0 MTRX 4 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 4 Destination Output 8	#K0 MTRX 4 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 4 Destination Output 8	#K0 MTRX 4 M 8 O 1\x0D
Matrix Gated Source Mic Input 4 Destination Output 8	#K0 MTRX 4 M 8 O 4\x0D

Global Scripter Module Communication Sheet

Matrix Cross point off Source Mic Input 4 Destination Processing A	#K0 MTRX 4 M A P 0\0D
Matrix Cross point on Source Mic Input 4 Destination Processing A	#K0 MTRX 4 M A P 1\0D
Matrix Gated Source Mic Input 4 Destination Processing A	#K0 MTRX 4 M A P 4\0D
Matrix Cross point off Source Mic Input 4 Destination Processing B	#K0 MTRX 4 M B P 0\0D
Matrix Cross point on Source Mic Input 4 Destination Processing B	#K0 MTRX 4 M B P 1\0D
Matrix Gated Source Mic Input 4 Destination Processing B	#K0 MTRX 4 M B P 4\0D
Matrix Cross point off Source Mic Input 4 Destination Processing C	#K0 MTRX 4 M C P 0\0D
Matrix Cross point on Source Mic Input 4 Destination Processing C	#K0 MTRX 4 M C P 1\0D
Matrix Gated Source Mic Input 4 Destination Processing C	#K0 MTRX 4 M C P 4\0D
Matrix Cross point off Source Mic Input 4 Destination Telco TX	#K0 MTRX 4 M 1 T 0\0D
Matrix Cross point on Source Mic Input 4 Destination Telco TX	#K0 MTRX 4 M 1 T 1\0D
Matrix Gated Source Mic Input 4 Destination Telco TX	#K0 MTRX 4 M 1 T 4\0D
Matrix Cross point off Source Mic Input 4 Destination USB TX	#K0 MTRX 4 M 1 D 0\0D
Matrix Cross point on Source Mic Input 4 Destination USB TX	#K0 MTRX 4 M 1 D 1\0D
Matrix Gated Source Mic Input 4 Destination USB TX	#K0 MTRX 4 M 1 D 4\0D
Matrix Cross point off Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRX 4 M 1 D 0\0D
Matrix Cross point on Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRX 4 M 1 D 1\0D
Matrix Gated Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRX 4 M 1 D 4\0D
Matrix Cross point off Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRX 4 M 2 D 0\0D
Matrix Cross point on Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRX 4 M 2 D 1\0D
Matrix Gated Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRX 4 M 2 D 4\0D
Matrix Cross point off Source Mic Input 5 Destination Headset TX	#K0 MTRX 5 M 1 H 0\0D
Matrix Cross point on Source Mic Input 5 Destination Headset TX	#K0 MTRX 5 M 1 H 1\0D
Matrix Gated Source Mic Input 5 Destination Headset TX	#K0 MTRX 5 M 1 H 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 1	#K0 MTRX 5 M 1 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 1	#K0 MTRX 5 M 1 O 1\0D
Matrix Gated Source Mic Input 5 Destination Output 1	#K0 MTRX 5 M 1 O 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 2	#K0 MTRX 5 M 2 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 2	#K0 MTRX 5 M 2 O 1\0D
Matrix Gated Source Mic Input 5 Destination Output 2	#K0 MTRX 5 M 2 O 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 3	#K0 MTRX 5 M 3 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 3	#K0 MTRX 5 M 3 O 1\0D
Matrix Gated Source Mic Input 5 Destination Output 3	#K0 MTRX 5 M 3 O 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 4	#K0 MTRX 5 M 4 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 4	#K0 MTRX 5 M 4 O 1\0D
Matrix Gated Source Mic Input 5 Destination Output 4	#K0 MTRX 5 M 4 O 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 5	#K0 MTRX 5 M 5 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 5	#K0 MTRX 5 M 5 O 1\0D
Matrix Gated Source Mic Input 5 Destination Output 5	#K0 MTRX 5 M 5 O 4\0D
Matrix Cross point off Source Mic Input 5 Destination Output 6	#K0 MTRX 5 M 6 O 0\0D
Matrix Cross point on Source Mic Input 5 Destination Output 6	#K0 MTRX 5 M 6 O 1\0D

Matrix Gated Source Mic Input 5 Destination Output 6	#K0 MTRX 5 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Output 7	#K0 MTRX 5 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Output 7	#K0 MTRX 5 M 7 O 1\x0D
Matrix Gated Source Mic Input 5 Destination Output 7	#K0 MTRX 5 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Output 8	#K0 MTRX 5 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Output 8	#K0 MTRX 5 M 8 O 1\x0D
Matrix Gated Source Mic Input 5 Destination Output 8	#K0 MTRX 5 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Processing A	#K0 MTRX 5 M A P 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Processing A	#K0 MTRX 5 M A P 1\x0D
Matrix Gated Source Mic Input 5 Destination Processing A	#K0 MTRX 5 M A P 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Processing B	#K0 MTRX 5 M B P 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Processing B	#K0 MTRX 5 M B P 1\x0D
Matrix Gated Source Mic Input 5 Destination Processing B	#K0 MTRX 5 M B P 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Processing C	#K0 MTRX 5 M C P 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Processing C	#K0 MTRX 5 M C P 1\x0D
Matrix Gated Source Mic Input 5 Destination Processing C	#K0 MTRX 5 M C P 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Telco TX	#K0 MTRX 5 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Telco TX	#K0 MTRX 5 M 1 T 1\x0D
Matrix Gated Source Mic Input 5 Destination Telco TX	#K0 MTRX 5 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 5 Destination USB TX	#K0 MTRX 5 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 5 Destination USB TX	#K0 MTRX 5 M 1 D 1\x0D
Matrix Gated Source Mic Input 5 Destination USB TX	#K0 MTRX 5 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRX 5 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRX 5 M 1 D 1\x0D
Matrix Gated Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRX 5 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRX 5 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRX 5 M 2 D 1\x0D
Matrix Gated Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRX 5 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Headset TX	#K0 MTRX 6 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Headset TX	#K0 MTRX 6 M 1 H 1\x0D
Matrix Gated Source Mic Input 6 Destination Headset TX	#K0 MTRX 6 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 1	#K0 MTRX 6 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 1	#K0 MTRX 6 M 1 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 1	#K0 MTRX 6 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 2	#K0 MTRX 6 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 2	#K0 MTRX 6 M 2 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 2	#K0 MTRX 6 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 3	#K0 MTRX 6 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 3	#K0 MTRX 6 M 3 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 3	#K0 MTRX 6 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 4	#K0 MTRX 6 M 4 O 0\x0D

Matrix Cross point on Source Mic Input 6 Destination Output 4	#K0 MTRX 6 M 4 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 4	#K0 MTRX 6 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 5	#K0 MTRX 6 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 5	#K0 MTRX 6 M 5 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 5	#K0 MTRX 6 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 6	#K0 MTRX 6 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 6	#K0 MTRX 6 M 6 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 6	#K0 MTRX 6 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 7	#K0 MTRX 6 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 7	#K0 MTRX 6 M 7 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 7	#K0 MTRX 6 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Output 8	#K0 MTRX 6 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Output 8	#K0 MTRX 6 M 8 O 1\x0D
Matrix Gated Source Mic Input 6 Destination Output 8	#K0 MTRX 6 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Processing A	#K0 MTRX 6 M A P 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Processing A	#K0 MTRX 6 M A P 1\x0D
Matrix Gated Source Mic Input 6 Destination Processing A	#K0 MTRX 6 M A P 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Processing B	#K0 MTRX 6 M B P 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Processing B	#K0 MTRX 6 M B P 1\x0D
Matrix Gated Source Mic Input 6 Destination Processing B	#K0 MTRX 6 M B P 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Processing C	#K0 MTRX 6 M C P 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Processing C	#K0 MTRX 6 M C P 1\x0D
Matrix Gated Source Mic Input 6 Destination Processing C	#K0 MTRX 6 M C P 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Telco TX	#K0 MTRX 6 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Telco TX	#K0 MTRX 6 M 1 T 1\x0D
Matrix Gated Source Mic Input 6 Destination Telco TX	#K0 MTRX 6 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 6 Destination USB TX	#K0 MTRX 6 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 6 Destination USB TX	#K0 MTRX 6 M 1 D 1\x0D
Matrix Gated Source Mic Input 6 Destination USB TX	#K0 MTRX 6 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRX 6 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRX 6 M 1 D 1\x0D
Matrix Gated Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRX 6 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRX 6 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRX 6 M 2 D 1\x0D
Matrix Gated Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRX 6 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Headset TX	#K0 MTRX 7 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Headset TX	#K0 MTRX 7 M 1 H 1\x0D
Matrix Gated Source Mic Input 7 Destination Headset TX	#K0 MTRX 7 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 1	#K0 MTRX 7 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 1	#K0 MTRX 7 M 1 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 1	#K0 MTRX 7 M 1 O 4\x0D

Matrix Cross point off Source Mic Input 7 Destination Output 2	#K0 MTRX 7 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 2	#K0 MTRX 7 M 2 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 2	#K0 MTRX 7 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 3	#K0 MTRX 7 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 3	#K0 MTRX 7 M 3 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 3	#K0 MTRX 7 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 4	#K0 MTRX 7 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 4	#K0 MTRX 7 M 4 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 4	#K0 MTRX 7 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 5	#K0 MTRX 7 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 5	#K0 MTRX 7 M 5 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 5	#K0 MTRX 7 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 6	#K0 MTRX 7 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 6	#K0 MTRX 7 M 6 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 6	#K0 MTRX 7 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 7	#K0 MTRX 7 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 7	#K0 MTRX 7 M 7 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 7	#K0 MTRX 7 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Output 8	#K0 MTRX 7 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Output 8	#K0 MTRX 7 M 8 O 1\x0D
Matrix Gated Source Mic Input 7 Destination Output 8	#K0 MTRX 7 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Processing A	#K0 MTRX 7 M A P 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Processing A	#K0 MTRX 7 M A P 1\x0D
Matrix Gated Source Mic Input 7 Destination Processing A	#K0 MTRX 7 M A P 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Processing B	#K0 MTRX 7 M B P 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Processing B	#K0 MTRX 7 M B P 1\x0D
Matrix Gated Source Mic Input 7 Destination Processing B	#K0 MTRX 7 M B P 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Processing C	#K0 MTRX 7 M C P 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Processing C	#K0 MTRX 7 M C P 1\x0D
Matrix Gated Source Mic Input 7 Destination Processing C	#K0 MTRX 7 M C P 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Telco TX	#K0 MTRX 7 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Telco TX	#K0 MTRX 7 M 1 T 1\x0D
Matrix Gated Source Mic Input 7 Destination Telco TX	#K0 MTRX 7 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 7 Destination USB TX	#K0 MTRX 7 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 7 Destination USB TX	#K0 MTRX 7 M 1 D 1\x0D
Matrix Gated Source Mic Input 7 Destination USB TX	#K0 MTRX 7 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRX 7 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRX 7 M 1 D 1\x0D
Matrix Gated Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRX 7 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRX 7 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRX 7 M 2 D 1\x0D

Matrix Gated Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRX 7 M 2 D 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Headset TX	#K0 MTRX 8 M 1 H 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Headset TX	#K0 MTRX 8 M 1 H 1\x0D
Matrix Gated Source Mic Input 8 Destination Headset TX	#K0 MTRX 8 M 1 H 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 1	#K0 MTRX 8 M 1 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 1	#K0 MTRX 8 M 1 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 1	#K0 MTRX 8 M 1 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 2	#K0 MTRX 8 M 2 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 2	#K0 MTRX 8 M 2 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 2	#K0 MTRX 8 M 2 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 3	#K0 MTRX 8 M 3 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 3	#K0 MTRX 8 M 3 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 3	#K0 MTRX 8 M 3 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 4	#K0 MTRX 8 M 4 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 4	#K0 MTRX 8 M 4 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 4	#K0 MTRX 8 M 4 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 5	#K0 MTRX 8 M 5 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 5	#K0 MTRX 8 M 5 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 5	#K0 MTRX 8 M 5 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 6	#K0 MTRX 8 M 6 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 6	#K0 MTRX 8 M 6 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 6	#K0 MTRX 8 M 6 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 7	#K0 MTRX 8 M 7 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 7	#K0 MTRX 8 M 7 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 7	#K0 MTRX 8 M 7 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Output 8	#K0 MTRX 8 M 8 O 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Output 8	#K0 MTRX 8 M 8 O 1\x0D
Matrix Gated Source Mic Input 8 Destination Output 8	#K0 MTRX 8 M 8 O 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Processing A	#K0 MTRX 8 M A P 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Processing A	#K0 MTRX 8 M A P 1\x0D
Matrix Gated Source Mic Input 8 Destination Processing A	#K0 MTRX 8 M A P 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Processing B	#K0 MTRX 8 M B P 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Processing B	#K0 MTRX 8 M B P 1\x0D
Matrix Gated Source Mic Input 8 Destination Processing B	#K0 MTRX 8 M B P 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Processing C	#K0 MTRX 8 M C P 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Processing C	#K0 MTRX 8 M C P 1\x0D
Matrix Gated Source Mic Input 8 Destination Processing C	#K0 MTRX 8 M C P 4\x0D
Matrix Cross point off Source Mic Input 8 Destination Telco TX	#K0 MTRX 8 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 8 Destination Telco TX	#K0 MTRX 8 M 1 T 1\x0D
Matrix Gated Source Mic Input 8 Destination Telco TX	#K0 MTRX 8 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 8 Destination USB TX	#K0 MTRX 8 M 1 D 0\x0D

Matrix Cross point on Source Mic Input 8 Destination USB TX	#K0 MTRX 8 M 1 D 1\0D
Matrix Gated Source Mic Input 8 Destination USB TX	#K0 MTRX 8 M 1 D 4\0D
Matrix Cross point off Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRX 8 M 1 D 0\0D
Matrix Cross point on Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRX 8 M 1 D 1\0D
Matrix Gated Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRX 8 M 1 D 4\0D
Matrix Cross point off Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRX 8 M 2 D 0\0D
Matrix Cross point on Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRX 8 M 2 D 1\0D
Matrix Gated Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRX 8 M 2 D 4\0D
Matrix Cross point off Source Mic Input 9 Destination Headset TX	#K0 MTRX 9 M 1 H 0\0D
Matrix Cross point on Source Mic Input 9 Destination Headset TX	#K0 MTRX 9 M 1 H 1\0D
Matrix Gated Source Mic Input 9 Destination Headset TX	#K0 MTRX 9 M 1 H 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 1	#K0 MTRX 9 M 1 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 1	#K0 MTRX 9 M 1 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 1	#K0 MTRX 9 M 1 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 2	#K0 MTRX 9 M 2 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 2	#K0 MTRX 9 M 2 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 2	#K0 MTRX 9 M 2 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 3	#K0 MTRX 9 M 3 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 3	#K0 MTRX 9 M 3 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 3	#K0 MTRX 9 M 3 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 4	#K0 MTRX 9 M 4 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 4	#K0 MTRX 9 M 4 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 4	#K0 MTRX 9 M 4 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 5	#K0 MTRX 9 M 5 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 5	#K0 MTRX 9 M 5 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 5	#K0 MTRX 9 M 5 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 6	#K0 MTRX 9 M 6 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 6	#K0 MTRX 9 M 6 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 6	#K0 MTRX 9 M 6 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 7	#K0 MTRX 9 M 7 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 7	#K0 MTRX 9 M 7 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 7	#K0 MTRX 9 M 7 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Output 8	#K0 MTRX 9 M 8 O 0\0D
Matrix Cross point on Source Mic Input 9 Destination Output 8	#K0 MTRX 9 M 8 O 1\0D
Matrix Gated Source Mic Input 9 Destination Output 8	#K0 MTRX 9 M 8 O 4\0D
Matrix Cross point off Source Mic Input 9 Destination Processing A	#K0 MTRX 9 M A P 0\0D
Matrix Cross point on Source Mic Input 9 Destination Processing A	#K0 MTRX 9 M A P 1\0D
Matrix Gated Source Mic Input 9 Destination Processing A	#K0 MTRX 9 M A P 4\0D
Matrix Cross point off Source Mic Input 9 Destination Processing B	#K0 MTRX 9 M B P 0\0D
Matrix Cross point on Source Mic Input 9 Destination Processing B	#K0 MTRX 9 M B P 1\0D
Matrix Gated Source Mic Input 9 Destination Processing B	#K0 MTRX 9 M B P 4\0D

Global Scripter Module Communication Sheet

Matrix Cross point off Source Mic Input 9 Destination Processing C	#K0 MTRX 9 M C P 0\x0D
Matrix Cross point on Source Mic Input 9 Destination Processing C	#K0 MTRX 9 M C P 1\x0D
Matrix Gated Source Mic Input 9 Destination Processing C	#K0 MTRX 9 M C P 4\x0D
Matrix Cross point off Source Mic Input 9 Destination Telco TX	#K0 MTRX 9 M 1 T 0\x0D
Matrix Cross point on Source Mic Input 9 Destination Telco TX	#K0 MTRX 9 M 1 T 1\x0D
Matrix Gated Source Mic Input 9 Destination Telco TX	#K0 MTRX 9 M 1 T 4\x0D
Matrix Cross point off Source Mic Input 9 Destination USB TX	#K0 MTRX 9 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 9 Destination USB TX	#K0 MTRX 9 M 1 D 1\x0D
Matrix Gated Source Mic Input 9 Destination USB TX	#K0 MTRX 9 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRX 9 M 1 D 0\x0D
Matrix Cross point on Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRX 9 M 1 D 1\x0D
Matrix Gated Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRX 9 M 1 D 4\x0D
Matrix Cross point off Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRX 9 M 2 D 0\x0D
Matrix Cross point on Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRX 9 M 2 D 1\x0D
Matrix Gated Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRX 9 M 2 D 4\x0D
Matrix Cross point off Source Processing A Destination Headset TX	#K0 MTRX A P 1 H 0\x0D
Matrix Cross point on Source Processing A Destination Headset TX	#K0 MTRX A P 1 H 1\x0D
Matrix Gated Source Processing A Destination Headset TX	#K0 MTRX A P 1 H 4\x0D
Matrix Cross point off Source Processing A Destination Output 1	#K0 MTRX A P 1 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 1	#K0 MTRX A P 1 O 1\x0D
Matrix Gated Source Processing A Destination Output 1	#K0 MTRX A P 1 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 2	#K0 MTRX A P 2 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 2	#K0 MTRX A P 2 O 1\x0D
Matrix Gated Source Processing A Destination Output 2	#K0 MTRX A P 2 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 3	#K0 MTRX A P 3 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 3	#K0 MTRX A P 3 O 1\x0D
Matrix Gated Source Processing A Destination Output 3	#K0 MTRX A P 3 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 4	#K0 MTRX A P 4 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 4	#K0 MTRX A P 4 O 1\x0D
Matrix Gated Source Processing A Destination Output 4	#K0 MTRX A P 4 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 5	#K0 MTRX A P 5 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 5	#K0 MTRX A P 5 O 1\x0D
Matrix Gated Source Processing A Destination Output 5	#K0 MTRX A P 5 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 6	#K0 MTRX A P 6 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 6	#K0 MTRX A P 6 O 1\x0D
Matrix Gated Source Processing A Destination Output 6	#K0 MTRX A P 6 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 7	#K0 MTRX A P 7 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 7	#K0 MTRX A P 7 O 1\x0D
Matrix Gated Source Processing A Destination Output 7	#K0 MTRX A P 7 O 4\x0D
Matrix Cross point off Source Processing A Destination Output 8	#K0 MTRX A P 8 O 0\x0D
Matrix Cross point on Source Processing A Destination Output 8	#K0 MTRX A P 8 O 1\x0D

Matrix Gated Source Processing A Destination Output 8	#K0 MTRX A P 8 O 4\x0D
Matrix Cross point off Source Processing A Destination Processing A	#K0 MTRX A P A P 0\x0D
Matrix Cross point on Source Processing A Destination Processing A	#K0 MTRX A P A P 1\x0D
Matrix Gated Source Processing A Destination Processing A	#K0 MTRX A P A P 4\x0D
Matrix Cross point off Source Processing A Destination Processing B	#K0 MTRX A P B P 0\x0D
Matrix Cross point on Source Processing A Destination Processing B	#K0 MTRX A P B P 1\x0D
Matrix Gated Source Processing A Destination Processing B	#K0 MTRX A P B P 4\x0D
Matrix Cross point off Source Processing A Destination Processing C	#K0 MTRX A P C P 0\x0D
Matrix Cross point on Source Processing A Destination Processing C	#K0 MTRX A P C P 1\x0D
Matrix Gated Source Processing A Destination Processing C	#K0 MTRX A P C P 4\x0D
Matrix Cross point off Source Processing A Destination Telco TX	#K0 MTRX A P 1 T 0\x0D
Matrix Cross point on Source Processing A Destination Telco TX	#K0 MTRX A P 1 T 1\x0D
Matrix Gated Source Processing A Destination Telco TX	#K0 MTRX A P 1 T 4\x0D
Matrix Cross point off Source Processing A Destination USB TX	#K0 MTRX A P 1 D 0\x0D
Matrix Cross point on Source Processing A Destination USB TX	#K0 MTRX A P 1 D 1\x0D
Matrix Gated Source Processing A Destination USB TX	#K0 MTRX A P 1 D 4\x0D
Matrix Cross point off Source Processing A Destination Virtual Ref 1	#K0 MTRX A P 1 D 0\x0D
Matrix Cross point on Source Processing A Destination Virtual Ref 1	#K0 MTRX A P 1 D 1\x0D
Matrix Gated Source Processing A Destination Virtual Ref 1	#K0 MTRX A P 1 D 4\x0D
Matrix Cross point off Source Processing A Destination Virtual Ref 2	#K0 MTRX A P 2 D 0\x0D
Matrix Cross point on Source Processing A Destination Virtual Ref 2	#K0 MTRX A P 2 D 1\x0D
Matrix Gated Source Processing A Destination Virtual Ref 2	#K0 MTRX A P 2 D 4\x0D
Matrix Cross point off Source Processing B Destination Headset TX	#K0 MTRX B P 1 H 0\x0D
Matrix Cross point on Source Processing B Destination Headset TX	#K0 MTRX B P 1 H 1\x0D
Matrix Gated Source Processing B Destination Headset TX	#K0 MTRX B P 1 H 4\x0D
Matrix Cross point off Source Processing B Destination Output 1	#K0 MTRX B P 1 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 1	#K0 MTRX B P 1 O 1\x0D
Matrix Gated Source Processing B Destination Output 1	#K0 MTRX B P 1 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 2	#K0 MTRX B P 2 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 2	#K0 MTRX B P 2 O 1\x0D
Matrix Gated Source Processing B Destination Output 2	#K0 MTRX B P 2 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 3	#K0 MTRX B P 3 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 3	#K0 MTRX B P 3 O 1\x0D
Matrix Gated Source Processing B Destination Output 3	#K0 MTRX B P 3 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 4	#K0 MTRX B P 4 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 4	#K0 MTRX B P 4 O 1\x0D
Matrix Gated Source Processing B Destination Output 4	#K0 MTRX B P 4 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 5	#K0 MTRX B P 5 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 5	#K0 MTRX B P 5 O 1\x0D
Matrix Gated Source Processing B Destination Output 5	#K0 MTRX B P 5 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 6	#K0 MTRX B P 6 O 0\x0D

Matrix Cross point on Source Processing B Destination Output 6	#K0 MTRX B P 6 O 1\x0D
Matrix Gated Source Processing B Destination Output 6	#K0 MTRX B P 6 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 7	#K0 MTRX B P 7 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 7	#K0 MTRX B P 7 O 1\x0D
Matrix Gated Source Processing B Destination Output 7	#K0 MTRX B P 7 O 4\x0D
Matrix Cross point off Source Processing B Destination Output 8	#K0 MTRX B P 8 O 0\x0D
Matrix Cross point on Source Processing B Destination Output 8	#K0 MTRX B P 8 O 1\x0D
Matrix Gated Source Processing B Destination Output 8	#K0 MTRX B P 8 O 4\x0D
Matrix Cross point off Source Processing B Destination Processing A	#K0 MTRX B P A P 0\x0D
Matrix Cross point on Source Processing B Destination Processing A	#K0 MTRX B P A P 1\x0D
Matrix Gated Source Processing B Destination Processing A	#K0 MTRX B P A P 4\x0D
Matrix Cross point off Source Processing B Destination Processing B	#K0 MTRX B P B P 0\x0D
Matrix Cross point on Source Processing B Destination Processing B	#K0 MTRX B P B P 1\x0D
Matrix Gated Source Processing B Destination Processing B	#K0 MTRX B P B P 4\x0D
Matrix Cross point off Source Processing B Destination Processing C	#K0 MTRX B P C P 0\x0D
Matrix Cross point on Source Processing B Destination Processing C	#K0 MTRX B P C P 1\x0D
Matrix Gated Source Processing B Destination Processing C	#K0 MTRX B P C P 4\x0D
Matrix Cross point off Source Processing B Destination Telco TX	#K0 MTRX B P 1 T 0\x0D
Matrix Cross point on Source Processing B Destination Telco TX	#K0 MTRX B P 1 T 1\x0D
Matrix Gated Source Processing B Destination Telco TX	#K0 MTRX B P 1 T 4\x0D
Matrix Cross point off Source Processing B Destination USB TX	#K0 MTRX B P 1 D 0\x0D
Matrix Cross point on Source Processing B Destination USB TX	#K0 MTRX B P 1 D 1\x0D
Matrix Gated Source Processing B Destination USB TX	#K0 MTRX B P 1 D 4\x0D
Matrix Cross point off Source Processing B Destination Virtual Ref 1	#K0 MTRX B P 1 D 0\x0D
Matrix Cross point on Source Processing B Destination Virtual Ref 1	#K0 MTRX B P 1 D 1\x0D
Matrix Gated Source Processing B Destination Virtual Ref 1	#K0 MTRX B P 1 D 4\x0D
Matrix Cross point off Source Processing B Destination Virtual Ref 2	#K0 MTRX B P 2 D 0\x0D
Matrix Cross point on Source Processing B Destination Virtual Ref 2	#K0 MTRX B P 2 D 1\x0D
Matrix Gated Source Processing B Destination Virtual Ref 2	#K0 MTRX B P 2 D 4\x0D
Matrix Cross point off Source Processing C Destination Headset TX	#K0 MTRX C P 1 H 0\x0D
Matrix Cross point on Source Processing C Destination Headset TX	#K0 MTRX C P 1 H 1\x0D
Matrix Gated Source Processing C Destination Headset TX	#K0 MTRX C P 1 H 4\x0D
Matrix Cross point off Source Processing C Destination Output 1	#K0 MTRX C P 1 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 1	#K0 MTRX C P 1 O 1\x0D
Matrix Gated Source Processing C Destination Output 1	#K0 MTRX C P 1 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 2	#K0 MTRX C P 2 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 2	#K0 MTRX C P 2 O 1\x0D
Matrix Gated Source Processing C Destination Output 2	#K0 MTRX C P 2 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 3	#K0 MTRX C P 3 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 3	#K0 MTRX C P 3 O 1\x0D
Matrix Gated Source Processing C Destination Output 3	#K0 MTRX C P 3 O 4\x0D

Matrix Cross point off Source Processing C Destination Output 4	#K0 MTRX C P 4 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 4	#K0 MTRX C P 4 O 1\x0D
Matrix Gated Source Processing C Destination Output 4	#K0 MTRX C P 4 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 5	#K0 MTRX C P 5 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 5	#K0 MTRX C P 5 O 1\x0D
Matrix Gated Source Processing C Destination Output 5	#K0 MTRX C P 5 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 6	#K0 MTRX C P 6 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 6	#K0 MTRX C P 6 O 1\x0D
Matrix Gated Source Processing C Destination Output 6	#K0 MTRX C P 6 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 7	#K0 MTRX C P 7 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 7	#K0 MTRX C P 7 O 1\x0D
Matrix Gated Source Processing C Destination Output 7	#K0 MTRX C P 7 O 4\x0D
Matrix Cross point off Source Processing C Destination Output 8	#K0 MTRX C P 8 O 0\x0D
Matrix Cross point on Source Processing C Destination Output 8	#K0 MTRX C P 8 O 1\x0D
Matrix Gated Source Processing C Destination Output 8	#K0 MTRX C P 8 O 4\x0D
Matrix Cross point off Source Processing C Destination Processing A	#K0 MTRX C P A P 0\x0D
Matrix Cross point on Source Processing C Destination Processing A	#K0 MTRX C P A P 1\x0D
Matrix Gated Source Processing C Destination Processing A	#K0 MTRX C P A P 4\x0D
Matrix Cross point off Source Processing C Destination Processing B	#K0 MTRX C P B P 0\x0D
Matrix Cross point on Source Processing C Destination Processing B	#K0 MTRX C P B P 1\x0D
Matrix Gated Source Processing C Destination Processing B	#K0 MTRX C P B P 4\x0D
Matrix Cross point off Source Processing C Destination Processing C	#K0 MTRX C P C P 0\x0D
Matrix Cross point on Source Processing C Destination Processing C	#K0 MTRX C P C P 1\x0D
Matrix Gated Source Processing C Destination Processing C	#K0 MTRX C P C P 4\x0D
Matrix Cross point off Source Processing C Destination Telco TX	#K0 MTRX C P 1 T 0\x0D
Matrix Cross point on Source Processing C Destination Telco TX	#K0 MTRX C P 1 T 1\x0D
Matrix Gated Source Processing C Destination Telco TX	#K0 MTRX C P 1 T 4\x0D
Matrix Cross point off Source Processing C Destination USB TX	#K0 MTRX C P 1 D 0\x0D
Matrix Cross point on Source Processing C Destination USB TX	#K0 MTRX C P 1 D 1\x0D
Matrix Gated Source Processing C Destination USB TX	#K0 MTRX C P 1 D 4\x0D
Matrix Cross point off Source Processing C Destination Virtual Ref 1	#K0 MTRX C P 1 D 0\x0D
Matrix Cross point on Source Processing C Destination Virtual Ref 1	#K0 MTRX C P 1 D 1\x0D
Matrix Gated Source Processing C Destination Virtual Ref 1	#K0 MTRX C P 1 D 4\x0D
Matrix Cross point off Source Processing C Destination Virtual Ref 2	#K0 MTRX C P 2 D 0\x0D
Matrix Cross point on Source Processing C Destination Virtual Ref 2	#K0 MTRX C P 2 D 1\x0D
Matrix Gated Source Processing C Destination Virtual Ref 2	#K0 MTRX C P 2 D 4\x0D
Matrix Cross point off Source Telco RX Destination Headset TX	#K0 MTRX 1 R 1 H 0\x0D
Matrix Cross point on Source Telco RX Destination Headset TX	#K0 MTRX 1 R 1 H 1\x0D
Matrix Gated Source Telco RX Destination Headset TX	#K0 MTRX 1 R 1 H 4\x0D
Matrix Cross point off Source Telco RX Destination Output 1	#K0 MTRX 1 R 1 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 1	#K0 MTRX 1 R 1 O 1\x0D

Matrix Gated Source Telco RX Destination Output 1	#K0 MTRX 1 R 1 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 2	#K0 MTRX 1 R 2 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 2	#K0 MTRX 1 R 2 O 1\x0D
Matrix Gated Source Telco RX Destination Output 2	#K0 MTRX 1 R 2 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 3	#K0 MTRX 1 R 3 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 3	#K0 MTRX 1 R 3 O 1\x0D
Matrix Gated Source Telco RX Destination Output 3	#K0 MTRX 1 R 3 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 4	#K0 MTRX 1 R 4 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 4	#K0 MTRX 1 R 4 O 1\x0D
Matrix Gated Source Telco RX Destination Output 4	#K0 MTRX 1 R 4 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 5	#K0 MTRX 1 R 5 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 5	#K0 MTRX 1 R 5 O 1\x0D
Matrix Gated Source Telco RX Destination Output 5	#K0 MTRX 1 R 5 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 6	#K0 MTRX 1 R 6 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 6	#K0 MTRX 1 R 6 O 1\x0D
Matrix Gated Source Telco RX Destination Output 6	#K0 MTRX 1 R 6 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 7	#K0 MTRX 1 R 7 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 7	#K0 MTRX 1 R 7 O 1\x0D
Matrix Gated Source Telco RX Destination Output 7	#K0 MTRX 1 R 7 O 4\x0D
Matrix Cross point off Source Telco RX Destination Output 8	#K0 MTRX 1 R 8 O 0\x0D
Matrix Cross point on Source Telco RX Destination Output 8	#K0 MTRX 1 R 8 O 1\x0D
Matrix Gated Source Telco RX Destination Output 8	#K0 MTRX 1 R 8 O 4\x0D
Matrix Cross point off Source Telco RX Destination Processing A	#K0 MTRX 1 R A P 0\x0D
Matrix Cross point on Source Telco RX Destination Processing A	#K0 MTRX 1 R A P 1\x0D
Matrix Gated Source Telco RX Destination Processing A	#K0 MTRX 1 R A P 4\x0D
Matrix Cross point off Source Telco RX Destination Processing B	#K0 MTRX 1 R B P 0\x0D
Matrix Cross point on Source Telco RX Destination Processing B	#K0 MTRX 1 R B P 1\x0D
Matrix Gated Source Telco RX Destination Processing B	#K0 MTRX 1 R B P 4\x0D
Matrix Cross point off Source Telco RX Destination Processing C	#K0 MTRX 1 R C P 0\x0D
Matrix Cross point on Source Telco RX Destination Processing C	#K0 MTRX 1 R C P 1\x0D
Matrix Gated Source Telco RX Destination Processing C	#K0 MTRX 1 R C P 4\x0D
Matrix Cross point off Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T 0\x0D
Matrix Cross point on Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T 1\x0D
Matrix Gated Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T 4\x0D
Matrix Cross point off Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D 0\x0D
Matrix Cross point on Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D 1\x0D
Matrix Gated Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D 4\x0D
Matrix Cross point off Source Telco RX Destination Virtual Ref 1	#K0 MTRX 1 R 1 D 0\x0D
Matrix Cross point on Source Telco RX Destination Virtual Ref 1	#K0 MTRX 1 R 1 D 1\x0D
Matrix Gated Source Telco RX Destination Virtual Ref 1	#K0 MTRX 1 R 1 D 4\x0D
Matrix Cross point off Source Telco RX Destination Virtual Ref 2	#K0 MTRX 1 R 2 D 0\x0D

Matrix Cross point on Source Telco RX Destination Virtual Ref 2	#K0 MTRX 1 R 2 D 1\x0D
Matrix Gated Source Telco RX Destination Virtual Ref 2	#K0 MTRX 1 R 2 D 4\x0D
Matrix Cross point off Source USB RX Destination Headset TX	#K0 MTRX 1 W 1 H 0\x0D
Matrix Cross point on Source USB RX Destination Headset TX	#K0 MTRX 1 W 1 H 1\x0D
Matrix Gated Source USB RX Destination Headset TX	#K0 MTRX 1 W 1 H 4\x0D
Matrix Cross point off Source USB RX Destination Output 1	#K0 MTRX 1 W 1 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 1	#K0 MTRX 1 W 1 O 1\x0D
Matrix Gated Source USB RX Destination Output 1	#K0 MTRX 1 W 1 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 2	#K0 MTRX 1 W 2 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 2	#K0 MTRX 1 W 2 O 1\x0D
Matrix Gated Source USB RX Destination Output 2	#K0 MTRX 1 W 2 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 3	#K0 MTRX 1 W 3 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 3	#K0 MTRX 1 W 3 O 1\x0D
Matrix Gated Source USB RX Destination Output 3	#K0 MTRX 1 W 3 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 4	#K0 MTRX 1 W 4 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 4	#K0 MTRX 1 W 4 O 1\x0D
Matrix Gated Source USB RX Destination Output 4	#K0 MTRX 1 W 4 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 5	#K0 MTRX 1 W 5 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 5	#K0 MTRX 1 W 5 O 1\x0D
Matrix Gated Source USB RX Destination Output 5	#K0 MTRX 1 W 5 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 6	#K0 MTRX 1 W 6 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 6	#K0 MTRX 1 W 6 O 1\x0D
Matrix Gated Source USB RX Destination Output 6	#K0 MTRX 1 W 6 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 7	#K0 MTRX 1 W 7 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 7	#K0 MTRX 1 W 7 O 1\x0D
Matrix Gated Source USB RX Destination Output 7	#K0 MTRX 1 W 7 O 4\x0D
Matrix Cross point off Source USB RX Destination Output 8	#K0 MTRX 1 W 8 O 0\x0D
Matrix Cross point on Source USB RX Destination Output 8	#K0 MTRX 1 W 8 O 1\x0D
Matrix Gated Source USB RX Destination Output 8	#K0 MTRX 1 W 8 O 4\x0D
Matrix Cross point off Source USB RX Destination Processing A	#K0 MTRX 1 W A P 0\x0D
Matrix Cross point on Source USB RX Destination Processing A	#K0 MTRX 1 W A P 1\x0D
Matrix Gated Source USB RX Destination Processing A	#K0 MTRX 1 W A P 4\x0D
Matrix Cross point off Source USB RX Destination Processing B	#K0 MTRX 1 W B P 0\x0D
Matrix Cross point on Source USB RX Destination Processing B	#K0 MTRX 1 W B P 1\x0D
Matrix Gated Source USB RX Destination Processing B	#K0 MTRX 1 W B P 4\x0D
Matrix Cross point off Source USB RX Destination Processing C	#K0 MTRX 1 W C P 0\x0D
Matrix Cross point on Source USB RX Destination Processing C	#K0 MTRX 1 W C P 1\x0D
Matrix Gated Source USB RX Destination Processing C	#K0 MTRX 1 W C P 4\x0D
Matrix Cross point off Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T 0\x0D
Matrix Cross point on Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T 1\x0D
Matrix Gated Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T 4\x0D

Matrix Cross point off Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D 0\0D
Matrix Cross point on Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D 1\0D
Matrix Gated Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D 4\0D
Matrix Cross point off Source USB RX Destination Virtual Ref 1	#K0 MTRX 1 W 1 D 0\0D
Matrix Cross point on Source USB RX Destination Virtual Ref 1	#K0 MTRX 1 W 1 D 1\0D
Matrix Gated Source USB RX Destination Virtual Ref 1	#K0 MTRX 1 W 1 D 4\0D
Matrix Cross point off Source USB RX Destination Virtual Ref 2	#K0 MTRX 1 W 2 D 0\0D
Matrix Cross point on Source USB RX Destination Virtual Ref 2	#K0 MTRX 1 W 2 D 1\0D
Matrix Gated Source USB RX Destination Virtual Ref 2	#K0 MTRX 1 W 2 D 4\0D
Matrix Cross point off Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T 0\0D
Matrix Cross point on Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T 1\0D
Matrix Cross point off Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D 0\0D
Matrix Cross point on Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D 1\0D
Matrix Cross point off Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T 0\0D
Matrix Cross point on Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T 1\0D
Matrix Cross point off Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D 0\0D
Matrix Cross point on Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D 1\0D
Matrix Level -18 Source Headset RX Destination Headset TX	#K0 MTRXLVL 1 N 1 H -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Headset TX	#K0 MTRXLVL 1 N 1 H 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 1	#K0 MTRXLVL 1 N 1 O -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Output 1	#K0 MTRXLVL 1 N 1 O 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 2	#K0 MTRXLVL 1 N 2 O -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Output 2	#K0 MTRXLVL 1 N 2 O 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 3	#K0 MTRXLVL 1 N 3 O -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Output 3	#K0 MTRXLVL 1 N 3 O 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 4	#K0 MTRXLVL 1 N 4 O -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Output 4	#K0 MTRXLVL 1 N 4 O 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 5	#K0 MTRXLVL 1 N 5 O -18.0 A\0D
Matrix Level 0 Source Headset RX Destination Output 5	#K0 MTRXLVL 1 N 5 O 0.0 A\0D
Matrix Level -18 Source Headset RX Destination Output 6	#K0 MTRXLVL 1 N 6 O -18.0 A\0D

Matrix Level 0 Source Headset RX Destination Output 6	#K0 MTRXLVL 1 N 6 O 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Output 7	#K0 MTRXLVL 1 N 7 O -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Output 7	#K0 MTRXLVL 1 N 7 O 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Output 8	#K0 MTRXLVL 1 N 8 O -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Output 8	#K0 MTRXLVL 1 N 8 O 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Processing A	#K0 MTRXLVL 1 N A P -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Processing A	#K0 MTRXLVL 1 N A P 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Processing B	#K0 MTRXLVL 1 N B P -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Processing B	#K0 MTRXLVL 1 N B P 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Processing C	#K0 MTRXLVL 1 N C P -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Processing C	#K0 MTRXLVL 1 N C P 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Telco TX	#K0 MTRXLVL 1 N 1 T -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Telco TX	#K0 MTRXLVL 1 N 1 T 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination USB TX	#K0 MTRXLVL 1 N 1 D -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination USB TX	#K0 MTRXLVL 1 N 1 D 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Virtual Ref 1	#K0 MTRXLVL 1 N 1 D -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Virtual Ref 1	#K0 MTRXLVL 1 N 1 D 0.0 A\x0D
Matrix Level -18 Source Headset RX Destination Virtual Ref 2	#K0 MTRXLVL 1 N 2 D -18.0 A\x0D
Matrix Level 0 Source Headset RX Destination Virtual Ref 2	#K0 MTRXLVL 1 N 2 D 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Headset TX	#K0 MTRXLVL 1 L 1 H -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Headset TX	#K0 MTRXLVL 1 L 1 H 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 1	#K0 MTRXLVL 1 L 1 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 1	#K0 MTRXLVL 1 L 1 O 0.0 A\x0D

Matrix Level -18 Source Line Input 1 Destination Output 2	#K0 MTRXLVL 1 L 2 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 2	#K0 MTRXLVL 1 L 2 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 3	#K0 MTRXLVL 1 L 3 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 3	#K0 MTRXLVL 1 L 3 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 4	#K0 MTRXLVL 1 L 4 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 4	#K0 MTRXLVL 1 L 4 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 5	#K0 MTRXLVL 1 L 5 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 5	#K0 MTRXLVL 1 L 5 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 6	#K0 MTRXLVL 1 L 6 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 6	#K0 MTRXLVL 1 L 6 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 7	#K0 MTRXLVL 1 L 7 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 7	#K0 MTRXLVL 1 L 7 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Output 8	#K0 MTRXLVL 1 L 8 O -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Output 8	#K0 MTRXLVL 1 L 8 O 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Processing A	#K0 MTRXLVL 1 L A P -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Processing A	#K0 MTRXLVL 1 L A P 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Processing B	#K0 MTRXLVL 1 L B P -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Processing B	#K0 MTRXLVL 1 L B P 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Processing C	#K0 MTRXLVL 1 L C P -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Processing C	#K0 MTRXLVL 1 L C P 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Telco TX	#K0 MTRXLVL 1 L 1 T -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Telco TX	#K0 MTRXLVL 1 L 1 T 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination USB TX	#K0 MTRXLVL 1 L 1 D -18.0 A\x0D

Matrix Level 0 Source Line Input 1 Destination USB TX	#K0 MTRXLVL 1 L 1 D 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 L 1 D -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 L 1 D 0.0 A\x0D
Matrix Level -18 Source Line Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 L 2 D -18.0 A\x0D
Matrix Level 0 Source Line Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 L 2 D 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Headset TX	#K0 MTRXLVL 2 L 1 H -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Headset TX	#K0 MTRXLVL 2 L 1 H 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 1	#K0 MTRXLVL 2 L 1 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 1	#K0 MTRXLVL 2 L 1 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 2	#K0 MTRXLVL 2 L 2 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 2	#K0 MTRXLVL 2 L 2 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 3	#K0 MTRXLVL 2 L 3 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 3	#K0 MTRXLVL 2 L 3 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 4	#K0 MTRXLVL 2 L 4 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 4	#K0 MTRXLVL 2 L 4 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 5	#K0 MTRXLVL 2 L 5 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 5	#K0 MTRXLVL 2 L 5 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 6	#K0 MTRXLVL 2 L 6 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 6	#K0 MTRXLVL 2 L 6 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 7	#K0 MTRXLVL 2 L 7 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 7	#K0 MTRXLVL 2 L 7 O 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Output 8	#K0 MTRXLVL 2 L 8 O -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Output 8	#K0 MTRXLVL 2 L 8 O 0.0 A\x0D

Matrix Level -18 Source Line Input 2 Destination Processing A	#K0 MTRXLVL 2 L A P -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Processing A	#K0 MTRXLVL 2 L A P 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Processing B	#K0 MTRXLVL 2 L B P -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Processing B	#K0 MTRXLVL 2 L B P 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Processing C	#K0 MTRXLVL 2 L C P -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Processing C	#K0 MTRXLVL 2 L C P 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Telco TX	#K0 MTRXLVL 2 L 1 T -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Telco TX	#K0 MTRXLVL 2 L 1 T 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination USB TX	#K0 MTRXLVL 2 L 1 D -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination USB TX	#K0 MTRXLVL 2 L 1 D 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 L 1 D -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 L 1 D 0.0 A\x0D
Matrix Level -18 Source Line Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 L 2 D -18.0 A\x0D
Matrix Level 0 Source Line Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 L 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Headset TX	#K0 MTRXLVL 1 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Headset TX	#K0 MTRXLVL 1 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 1	#K0 MTRXLVL 1 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 1	#K0 MTRXLVL 1 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 2	#K0 MTRXLVL 1 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 2	#K0 MTRXLVL 1 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 3	#K0 MTRXLVL 1 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 3	#K0 MTRXLVL 1 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 4	#K0 MTRXLVL 1 M 4 O -18.0 A\x0D

Matrix Level 0 Source Mic Input 1 Destination Output 4	#K0 MTRXLVL 1 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 5	#K0 MTRXLVL 1 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 5	#K0 MTRXLVL 1 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 6	#K0 MTRXLVL 1 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 6	#K0 MTRXLVL 1 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 7	#K0 MTRXLVL 1 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 7	#K0 MTRXLVL 1 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Output 8	#K0 MTRXLVL 1 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Output 8	#K0 MTRXLVL 1 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Processing A	#K0 MTRXLVL 1 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Processing A	#K0 MTRXLVL 1 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Processing B	#K0 MTRXLVL 1 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Processing B	#K0 MTRXLVL 1 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Processing C	#K0 MTRXLVL 1 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Processing C	#K0 MTRXLVL 1 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Telco TX	#K0 MTRXLVL 1 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Telco TX	#K0 MTRXLVL 1 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination USB TX	#K0 MTRXLVL 1 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination USB TX	#K0 MTRXLVL 1 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 M 2 D 0.0 A\x0D

Matrix Level -18 Source Mic Input 10 Destination Headset TX	#K0 MTRXLVL 10 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Headset TX	#K0 MTRXLVL 10 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 1	#K0 MTRXLVL 10 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 1	#K0 MTRXLVL 10 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 2	#K0 MTRXLVL 10 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 2	#K0 MTRXLVL 10 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 3	#K0 MTRXLVL 10 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 3	#K0 MTRXLVL 10 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 4	#K0 MTRXLVL 10 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 4	#K0 MTRXLVL 10 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 5	#K0 MTRXLVL 10 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 5	#K0 MTRXLVL 10 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 6	#K0 MTRXLVL 10 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 6	#K0 MTRXLVL 10 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 7	#K0 MTRXLVL 10 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 7	#K0 MTRXLVL 10 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Output 8	#K0 MTRXLVL 10 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Output 8	#K0 MTRXLVL 10 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Processing A	#K0 MTRXLVL 10 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Processing A	#K0 MTRXLVL 10 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Processing B	#K0 MTRXLVL 10 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Processing B	#K0 MTRXLVL 10 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Processing C	#K0 MTRXLVL 10 M C P -18.0 A\x0D

Matrix Level 0 Source Mic Input 10 Destination Processing C	#K0 MTRXLVL 10 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Telco TX	#K0 MTRXLVL 10 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Telco TX	#K0 MTRXLVL 10 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination USB TX	#K0 MTRXLVL 10 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination USB TX	#K0 MTRXLVL 10 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRXLVL 10 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRXLVL 10 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRXLVL 10 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRXLVL 10 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Headset TX	#K0 MTRXLVL 11 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Headset TX	#K0 MTRXLVL 11 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 1	#K0 MTRXLVL 11 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 1	#K0 MTRXLVL 11 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 2	#K0 MTRXLVL 11 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 2	#K0 MTRXLVL 11 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 3	#K0 MTRXLVL 11 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 3	#K0 MTRXLVL 11 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 4	#K0 MTRXLVL 11 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 4	#K0 MTRXLVL 11 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 5	#K0 MTRXLVL 11 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 5	#K0 MTRXLVL 11 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 6	#K0 MTRXLVL 11 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 6	#K0 MTRXLVL 11 M 6 O 0.0 A\x0D

Matrix Level -18 Source Mic Input 11 Destination Output 7	#K0 MTRXLVL 11 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 7	#K0 MTRXLVL 11 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Output 8	#K0 MTRXLVL 11 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Output 8	#K0 MTRXLVL 11 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Processing A	#K0 MTRXLVL 11 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Processing A	#K0 MTRXLVL 11 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Processing B	#K0 MTRXLVL 11 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Processing B	#K0 MTRXLVL 11 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Processing C	#K0 MTRXLVL 11 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Processing C	#K0 MTRXLVL 11 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Telco TX	#K0 MTRXLVL 11 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Telco TX	#K0 MTRXLVL 11 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination USB TX	#K0 MTRXLVL 11 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination USB TX	#K0 MTRXLVL 11 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRXLVL 11 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRXLVL 11 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRXLVL 11 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRXLVL 11 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Headset TX	#K0 MTRXLVL 12 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Headset TX	#K0 MTRXLVL 12 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 1	#K0 MTRXLVL 12 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 1	#K0 MTRXLVL 12 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 2	#K0 MTRXLVL 12 M 2 O -18.0 A\x0D

Matrix Level 0 Source Mic Input 12 Destination Output 2	#K0 MTRXLVL 12 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 3	#K0 MTRXLVL 12 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 3	#K0 MTRXLVL 12 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 4	#K0 MTRXLVL 12 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 4	#K0 MTRXLVL 12 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 5	#K0 MTRXLVL 12 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 5	#K0 MTRXLVL 12 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 6	#K0 MTRXLVL 12 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 6	#K0 MTRXLVL 12 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 7	#K0 MTRXLVL 12 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 7	#K0 MTRXLVL 12 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Output 8	#K0 MTRXLVL 12 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Output 8	#K0 MTRXLVL 12 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Processing A	#K0 MTRXLVL 12 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Processing A	#K0 MTRXLVL 12 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Processing B	#K0 MTRXLVL 12 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Processing B	#K0 MTRXLVL 12 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Processing C	#K0 MTRXLVL 12 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Processing C	#K0 MTRXLVL 12 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Telco TX	#K0 MTRXLVL 12 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Telco TX	#K0 MTRXLVL 12 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination USB TX	#K0 MTRXLVL 12 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination USB TX	#K0 MTRXLVL 12 M 1 D 0.0 A\x0D

Matrix Level -18 Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRXLVL 12 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRXLVL 12 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRXLVL 12 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRXLVL 12 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Headset TX	#K0 MTRXLVL 13 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Headset TX	#K0 MTRXLVL 13 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 1	#K0 MTRXLVL 13 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 1	#K0 MTRXLVL 13 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 2	#K0 MTRXLVL 13 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 2	#K0 MTRXLVL 13 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 3	#K0 MTRXLVL 13 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 3	#K0 MTRXLVL 13 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 4	#K0 MTRXLVL 13 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 4	#K0 MTRXLVL 13 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 5	#K0 MTRXLVL 13 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 5	#K0 MTRXLVL 13 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 6	#K0 MTRXLVL 13 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 6	#K0 MTRXLVL 13 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 7	#K0 MTRXLVL 13 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 7	#K0 MTRXLVL 13 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Output 8	#K0 MTRXLVL 13 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Output 8	#K0 MTRXLVL 13 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Processing A	#K0 MTRXLVL 13 M A P -18.0 A\x0D

Matrix Level 0 Source Mic Input 13 Destination Processing A	#K0 MTRXLVL 13 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Processing B	#K0 MTRXLVL 13 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Processing B	#K0 MTRXLVL 13 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Processing C	#K0 MTRXLVL 13 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Processing C	#K0 MTRXLVL 13 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Telco TX	#K0 MTRXLVL 13 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Telco TX	#K0 MTRXLVL 13 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination USB TX	#K0 MTRXLVL 13 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination USB TX	#K0 MTRXLVL 13 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRXLVL 13 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRXLVL 13 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRXLVL 13 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRXLVL 13 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Headset TX	#K0 MTRXLVL 14 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Headset TX	#K0 MTRXLVL 14 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 1	#K0 MTRXLVL 14 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 1	#K0 MTRXLVL 14 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 2	#K0 MTRXLVL 14 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 2	#K0 MTRXLVL 14 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 3	#K0 MTRXLVL 14 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 3	#K0 MTRXLVL 14 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 4	#K0 MTRXLVL 14 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 4	#K0 MTRXLVL 14 M 4 O 0.0 A\x0D

Matrix Level -18 Source Mic Input 14 Destination Output 5	#K0 MTRXLVL 14 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 5	#K0 MTRXLVL 14 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 6	#K0 MTRXLVL 14 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 6	#K0 MTRXLVL 14 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 7	#K0 MTRXLVL 14 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 7	#K0 MTRXLVL 14 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Output 8	#K0 MTRXLVL 14 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Output 8	#K0 MTRXLVL 14 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Processing A	#K0 MTRXLVL 14 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Processing A	#K0 MTRXLVL 14 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Processing B	#K0 MTRXLVL 14 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Processing B	#K0 MTRXLVL 14 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Processing C	#K0 MTRXLVL 14 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Processing C	#K0 MTRXLVL 14 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Telco TX	#K0 MTRXLVL 14 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Telco TX	#K0 MTRXLVL 14 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination USB TX	#K0 MTRXLVL 14 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination USB TX	#K0 MTRXLVL 14 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRXLVL 14 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRXLVL 14 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRXLVL 14 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRXLVL 14 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Headset TX	#K0 MTRXLVL 15 M 1 H -18.0 A\x0D

Matrix Level 0 Source Mic Input 15 Destination Headset TX	#K0 MTRXLVL 15 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 1	#K0 MTRXLVL 15 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 1	#K0 MTRXLVL 15 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 2	#K0 MTRXLVL 15 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 2	#K0 MTRXLVL 15 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 3	#K0 MTRXLVL 15 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 3	#K0 MTRXLVL 15 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 4	#K0 MTRXLVL 15 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 4	#K0 MTRXLVL 15 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 5	#K0 MTRXLVL 15 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 5	#K0 MTRXLVL 15 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 6	#K0 MTRXLVL 15 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 6	#K0 MTRXLVL 15 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 7	#K0 MTRXLVL 15 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 7	#K0 MTRXLVL 15 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Output 8	#K0 MTRXLVL 15 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Output 8	#K0 MTRXLVL 15 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Processing A	#K0 MTRXLVL 15 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Processing A	#K0 MTRXLVL 15 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Processing B	#K0 MTRXLVL 15 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Processing B	#K0 MTRXLVL 15 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Processing C	#K0 MTRXLVL 15 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Processing C	#K0 MTRXLVL 15 M C P 0.0 A\x0D

Matrix Level -18 Source Mic Input 15 Destination Telco TX	#K0 MTRXLVL 15 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Telco TX	#K0 MTRXLVL 15 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination USB TX	#K0 MTRXLVL 15 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination USB TX	#K0 MTRXLVL 15 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRXLVL 15 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRXLVL 15 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRXLVL 15 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRXLVL 15 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Headset TX	#K0 MTRXLVL 16 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Headset TX	#K0 MTRXLVL 16 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 1	#K0 MTRXLVL 16 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 1	#K0 MTRXLVL 16 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 2	#K0 MTRXLVL 16 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 2	#K0 MTRXLVL 16 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 3	#K0 MTRXLVL 16 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 3	#K0 MTRXLVL 16 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 4	#K0 MTRXLVL 16 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 4	#K0 MTRXLVL 16 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 5	#K0 MTRXLVL 16 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 5	#K0 MTRXLVL 16 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 6	#K0 MTRXLVL 16 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 6	#K0 MTRXLVL 16 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 7	#K0 MTRXLVL 16 M 7 O -18.0 A\x0D

Matrix Level 0 Source Mic Input 16 Destination Output 7	#K0 MTRXLVL 16 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Output 8	#K0 MTRXLVL 16 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Output 8	#K0 MTRXLVL 16 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Processing A	#K0 MTRXLVL 16 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Processing A	#K0 MTRXLVL 16 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Processing B	#K0 MTRXLVL 16 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Processing B	#K0 MTRXLVL 16 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Processing C	#K0 MTRXLVL 16 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Processing C	#K0 MTRXLVL 16 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Telco TX	#K0 MTRXLVL 16 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Telco TX	#K0 MTRXLVL 16 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination USB TX	#K0 MTRXLVL 16 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination USB TX	#K0 MTRXLVL 16 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRXLVL 16 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRXLVL 16 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRXLVL 16 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRXLVL 16 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Headset TX	#K0 MTRXLVL 2 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Headset TX	#K0 MTRXLVL 2 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 1	#K0 MTRXLVL 2 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 1	#K0 MTRXLVL 2 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 2	#K0 MTRXLVL 2 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 2	#K0 MTRXLVL 2 M 2 O 0.0 A\x0D

Matrix Level -18 Source Mic Input 2 Destination Output 3	#K0 MTRXLVL 2 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 3	#K0 MTRXLVL 2 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 4	#K0 MTRXLVL 2 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 4	#K0 MTRXLVL 2 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 5	#K0 MTRXLVL 2 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 5	#K0 MTRXLVL 2 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 6	#K0 MTRXLVL 2 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 6	#K0 MTRXLVL 2 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 7	#K0 MTRXLVL 2 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 7	#K0 MTRXLVL 2 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Output 8	#K0 MTRXLVL 2 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Output 8	#K0 MTRXLVL 2 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Processing A	#K0 MTRXLVL 2 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Processing A	#K0 MTRXLVL 2 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Processing B	#K0 MTRXLVL 2 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Processing B	#K0 MTRXLVL 2 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Processing C	#K0 MTRXLVL 2 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Processing C	#K0 MTRXLVL 2 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Telco TX	#K0 MTRXLVL 2 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Telco TX	#K0 MTRXLVL 2 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination USB TX	#K0 MTRXLVL 2 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination USB TX	#K0 MTRXLVL 2 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 M 1 D -18.0 A\x0D

Matrix Level 0 Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Headset TX	#K0 MTRXLVL 3 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Headset TX	#K0 MTRXLVL 3 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 1	#K0 MTRXLVL 3 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 1	#K0 MTRXLVL 3 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 2	#K0 MTRXLVL 3 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 2	#K0 MTRXLVL 3 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 3	#K0 MTRXLVL 3 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 3	#K0 MTRXLVL 3 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 4	#K0 MTRXLVL 3 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 4	#K0 MTRXLVL 3 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 5	#K0 MTRXLVL 3 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 5	#K0 MTRXLVL 3 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 6	#K0 MTRXLVL 3 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 6	#K0 MTRXLVL 3 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 7	#K0 MTRXLVL 3 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 7	#K0 MTRXLVL 3 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Output 8	#K0 MTRXLVL 3 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Output 8	#K0 MTRXLVL 3 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Processing A	#K0 MTRXLVL 3 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Processing A	#K0 MTRXLVL 3 M A P 0.0 A\x0D

Matrix Level -18 Source Mic Input 3 Destination Processing B	#K0 MTRXLVL 3 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Processing B	#K0 MTRXLVL 3 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Processing C	#K0 MTRXLVL 3 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Processing C	#K0 MTRXLVL 3 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Telco TX	#K0 MTRXLVL 3 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Telco TX	#K0 MTRXLVL 3 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination USB TX	#K0 MTRXLVL 3 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination USB TX	#K0 MTRXLVL 3 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRXLVL 3 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRXLVL 3 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRXLVL 3 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRXLVL 3 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Headset TX	#K0 MTRXLVL 4 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Headset TX	#K0 MTRXLVL 4 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 1	#K0 MTRXLVL 4 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 1	#K0 MTRXLVL 4 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 2	#K0 MTRXLVL 4 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 2	#K0 MTRXLVL 4 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 3	#K0 MTRXLVL 4 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 3	#K0 MTRXLVL 4 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 4	#K0 MTRXLVL 4 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 4	#K0 MTRXLVL 4 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 5	#K0 MTRXLVL 4 M 5 O -18.0 A\x0D

Matrix Level 0 Source Mic Input 4 Destination Output 5	#K0 MTRXLVL 4 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 6	#K0 MTRXLVL 4 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 6	#K0 MTRXLVL 4 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 7	#K0 MTRXLVL 4 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 7	#K0 MTRXLVL 4 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Output 8	#K0 MTRXLVL 4 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Output 8	#K0 MTRXLVL 4 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Processing A	#K0 MTRXLVL 4 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Processing A	#K0 MTRXLVL 4 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Processing B	#K0 MTRXLVL 4 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Processing B	#K0 MTRXLVL 4 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Processing C	#K0 MTRXLVL 4 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Processing C	#K0 MTRXLVL 4 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Telco TX	#K0 MTRXLVL 4 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Telco TX	#K0 MTRXLVL 4 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination USB TX	#K0 MTRXLVL 4 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination USB TX	#K0 MTRXLVL 4 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRXLVL 4 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRXLVL 4 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRXLVL 4 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRXLVL 4 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Headset TX	#K0 MTRXLVL 5 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Headset TX	#K0 MTRXLVL 5 M 1 H 0.0 A\x0D

Matrix Level -18 Source Mic Input 5 Destination Output 1	#K0 MTRXLVL 5 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 1	#K0 MTRXLVL 5 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 2	#K0 MTRXLVL 5 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 2	#K0 MTRXLVL 5 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 3	#K0 MTRXLVL 5 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 3	#K0 MTRXLVL 5 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 4	#K0 MTRXLVL 5 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 4	#K0 MTRXLVL 5 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 5	#K0 MTRXLVL 5 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 5	#K0 MTRXLVL 5 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 6	#K0 MTRXLVL 5 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 6	#K0 MTRXLVL 5 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 7	#K0 MTRXLVL 5 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 7	#K0 MTRXLVL 5 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Output 8	#K0 MTRXLVL 5 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Output 8	#K0 MTRXLVL 5 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Processing A	#K0 MTRXLVL 5 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Processing A	#K0 MTRXLVL 5 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Processing B	#K0 MTRXLVL 5 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Processing B	#K0 MTRXLVL 5 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Processing C	#K0 MTRXLVL 5 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Processing C	#K0 MTRXLVL 5 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Telco TX	#K0 MTRXLVL 5 M 1 T -18.0 A\x0D

Matrix Level 0 Source Mic Input 5 Destination Telco TX	#K0 MTRXLVL 5 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination USB TX	#K0 MTRXLVL 5 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination USB TX	#K0 MTRXLVL 5 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRXLVL 5 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRXLVL 5 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRXLVL 5 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRXLVL 5 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Headset TX	#K0 MTRXLVL 6 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Headset TX	#K0 MTRXLVL 6 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 1	#K0 MTRXLVL 6 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 1	#K0 MTRXLVL 6 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 2	#K0 MTRXLVL 6 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 2	#K0 MTRXLVL 6 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 3	#K0 MTRXLVL 6 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 3	#K0 MTRXLVL 6 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 4	#K0 MTRXLVL 6 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 4	#K0 MTRXLVL 6 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 5	#K0 MTRXLVL 6 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 5	#K0 MTRXLVL 6 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 6	#K0 MTRXLVL 6 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 6	#K0 MTRXLVL 6 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Output 7	#K0 MTRXLVL 6 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 7	#K0 MTRXLVL 6 M 7 O 0.0 A\x0D

Matrix Level -18 Source Mic Input 6 Destination Output 8	#K0 MTRXLVL 6 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Output 8	#K0 MTRXLVL 6 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Processing A	#K0 MTRXLVL 6 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Processing A	#K0 MTRXLVL 6 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Processing B	#K0 MTRXLVL 6 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Processing B	#K0 MTRXLVL 6 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Processing C	#K0 MTRXLVL 6 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Processing C	#K0 MTRXLVL 6 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Telco TX	#K0 MTRXLVL 6 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Telco TX	#K0 MTRXLVL 6 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination USB TX	#K0 MTRXLVL 6 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination USB TX	#K0 MTRXLVL 6 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRXLVL 6 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRXLVL 6 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRXLVL 6 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRXLVL 6 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Headset TX	#K0 MTRXLVL 7 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Headset TX	#K0 MTRXLVL 7 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 1	#K0 MTRXLVL 7 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 1	#K0 MTRXLVL 7 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 2	#K0 MTRXLVL 7 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 2	#K0 MTRXLVL 7 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 3	#K0 MTRXLVL 7 M 3 O -18.0 A\x0D

Matrix Level 0 Source Mic Input 7 Destination Output 3	#K0 MTRXLVL 7 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 4	#K0 MTRXLVL 7 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 4	#K0 MTRXLVL 7 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 5	#K0 MTRXLVL 7 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 5	#K0 MTRXLVL 7 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 6	#K0 MTRXLVL 7 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 6	#K0 MTRXLVL 7 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 7	#K0 MTRXLVL 7 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 7	#K0 MTRXLVL 7 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Output 8	#K0 MTRXLVL 7 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Output 8	#K0 MTRXLVL 7 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Processing A	#K0 MTRXLVL 7 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Processing A	#K0 MTRXLVL 7 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Processing B	#K0 MTRXLVL 7 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Processing B	#K0 MTRXLVL 7 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Processing C	#K0 MTRXLVL 7 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Processing C	#K0 MTRXLVL 7 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Telco TX	#K0 MTRXLVL 7 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Telco TX	#K0 MTRXLVL 7 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination USB TX	#K0 MTRXLVL 7 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination USB TX	#K0 MTRXLVL 7 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRXLVL 7 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRXLVL 7 M 1 D 0.0 A\x0D

Matrix Level -18 Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRXLVL 7 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRXLVL 7 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Headset TX	#K0 MTRXLVL 8 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Headset TX	#K0 MTRXLVL 8 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 1	#K0 MTRXLVL 8 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 1	#K0 MTRXLVL 8 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 2	#K0 MTRXLVL 8 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 2	#K0 MTRXLVL 8 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 3	#K0 MTRXLVL 8 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 3	#K0 MTRXLVL 8 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 4	#K0 MTRXLVL 8 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 4	#K0 MTRXLVL 8 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 5	#K0 MTRXLVL 8 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 5	#K0 MTRXLVL 8 M 5 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 6	#K0 MTRXLVL 8 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 6	#K0 MTRXLVL 8 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 7	#K0 MTRXLVL 8 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 7	#K0 MTRXLVL 8 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Output 8	#K0 MTRXLVL 8 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Output 8	#K0 MTRXLVL 8 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Processing A	#K0 MTRXLVL 8 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Processing A	#K0 MTRXLVL 8 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Processing B	#K0 MTRXLVL 8 M B P -18.0 A\x0D

Matrix Level 0 Source Mic Input 8 Destination Processing B	#K0 MTRXLVL 8 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Processing C	#K0 MTRXLVL 8 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Processing C	#K0 MTRXLVL 8 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Telco TX	#K0 MTRXLVL 8 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Telco TX	#K0 MTRXLVL 8 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination USB TX	#K0 MTRXLVL 8 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination USB TX	#K0 MTRXLVL 8 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRXLVL 8 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRXLVL 8 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRXLVL 8 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRXLVL 8 M 2 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Headset TX	#K0 MTRXLVL 9 M 1 H -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Headset TX	#K0 MTRXLVL 9 M 1 H 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 1	#K0 MTRXLVL 9 M 1 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 1	#K0 MTRXLVL 9 M 1 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 2	#K0 MTRXLVL 9 M 2 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 2	#K0 MTRXLVL 9 M 2 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 3	#K0 MTRXLVL 9 M 3 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 3	#K0 MTRXLVL 9 M 3 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 4	#K0 MTRXLVL 9 M 4 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 4	#K0 MTRXLVL 9 M 4 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 5	#K0 MTRXLVL 9 M 5 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 5	#K0 MTRXLVL 9 M 5 O 0.0 A\x0D

Matrix Level -18 Source Mic Input 9 Destination Output 6	#K0 MTRXLVL 9 M 6 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 6	#K0 MTRXLVL 9 M 6 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 7	#K0 MTRXLVL 9 M 7 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 7	#K0 MTRXLVL 9 M 7 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Output 8	#K0 MTRXLVL 9 M 8 O -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Output 8	#K0 MTRXLVL 9 M 8 O 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Processing A	#K0 MTRXLVL 9 M A P -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Processing A	#K0 MTRXLVL 9 M A P 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Processing B	#K0 MTRXLVL 9 M B P -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Processing B	#K0 MTRXLVL 9 M B P 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Processing C	#K0 MTRXLVL 9 M C P -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Processing C	#K0 MTRXLVL 9 M C P 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Telco TX	#K0 MTRXLVL 9 M 1 T -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Telco TX	#K0 MTRXLVL 9 M 1 T 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination USB TX	#K0 MTRXLVL 9 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination USB TX	#K0 MTRXLVL 9 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRXLVL 9 M 1 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRXLVL 9 M 1 D 0.0 A\x0D
Matrix Level -18 Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRXLVL 9 M 2 D -18.0 A\x0D
Matrix Level 0 Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRXLVL 9 M 2 D 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Headset TX	#K0 MTRXLVL A P 1 H -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Headset TX	#K0 MTRXLVL A P 1 H 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 1	#K0 MTRXLVL A P 1 O -18.0 A\x0D

Matrix Level 0 Source Processing A Destination Output 1	#K0 MTRXLVL A P 1 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 2	#K0 MTRXLVL A P 2 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 2	#K0 MTRXLVL A P 2 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 3	#K0 MTRXLVL A P 3 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 3	#K0 MTRXLVL A P 3 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 4	#K0 MTRXLVL A P 4 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 4	#K0 MTRXLVL A P 4 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 5	#K0 MTRXLVL A P 5 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 5	#K0 MTRXLVL A P 5 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 6	#K0 MTRXLVL A P 6 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 6	#K0 MTRXLVL A P 6 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 7	#K0 MTRXLVL A P 7 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 7	#K0 MTRXLVL A P 7 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Output 8	#K0 MTRXLVL A P 8 O -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Output 8	#K0 MTRXLVL A P 8 O 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Processing A	#K0 MTRXLVL A P A P -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Processing A	#K0 MTRXLVL A P A P 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Processing B	#K0 MTRXLVL A P B P -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Processing B	#K0 MTRXLVL A P B P 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Processing C	#K0 MTRXLVL A P C P -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Processing C	#K0 MTRXLVL A P C P 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Telco TX	#K0 MTRXLVL A P 1 T -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Telco TX	#K0 MTRXLVL A P 1 T 0.0 A\x0D

Matrix Level -18 Source Processing A Destination USB TX	#K0 MTRXLVL A P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing A Destination USB TX	#K0 MTRXLVL A P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Virtual Ref 1	#K0 MTRXLVL A P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Virtual Ref 1	#K0 MTRXLVL A P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing A Destination Virtual Ref 2	#K0 MTRXLVL A P 2 D -18.0 A\x0D
Matrix Level 0 Source Processing A Destination Virtual Ref 2	#K0 MTRXLVL A P 2 D 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Headset TX	#K0 MTRXLVL B P 1 H -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Headset TX	#K0 MTRXLVL B P 1 H 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 1	#K0 MTRXLVL B P 1 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 1	#K0 MTRXLVL B P 1 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 2	#K0 MTRXLVL B P 2 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 2	#K0 MTRXLVL B P 2 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 3	#K0 MTRXLVL B P 3 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 3	#K0 MTRXLVL B P 3 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 4	#K0 MTRXLVL B P 4 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 4	#K0 MTRXLVL B P 4 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 5	#K0 MTRXLVL B P 5 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 5	#K0 MTRXLVL B P 5 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 6	#K0 MTRXLVL B P 6 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 6	#K0 MTRXLVL B P 6 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 7	#K0 MTRXLVL B P 7 O -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Output 7	#K0 MTRXLVL B P 7 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Output 8	#K0 MTRXLVL B P 8 O -18.0 A\x0D

Matrix Level 0 Source Processing B Destination Output 8	#K0 MTRXLVL B P 8 O 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Processing A	#K0 MTRXLVL B P A P -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Processing A	#K0 MTRXLVL B P A P 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Processing B	#K0 MTRXLVL B P B P -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Processing B	#K0 MTRXLVL B P B P 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Processing C	#K0 MTRXLVL B P C P -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Processing C	#K0 MTRXLVL B P C P 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Telco TX	#K0 MTRXLVL B P 1 T -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Telco TX	#K0 MTRXLVL B P 1 T 0.0 A\x0D
Matrix Level -18 Source Processing B Destination USB TX	#K0 MTRXLVL B P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing B Destination USB TX	#K0 MTRXLVL B P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Virtual Ref 1	#K0 MTRXLVL B P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Virtual Ref 1	#K0 MTRXLVL B P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing B Destination Virtual Ref 2	#K0 MTRXLVL B P 2 D -18.0 A\x0D
Matrix Level 0 Source Processing B Destination Virtual Ref 2	#K0 MTRXLVL B P 2 D 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Headset TX	#K0 MTRXLVL C P 1 H -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Headset TX	#K0 MTRXLVL C P 1 H 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 1	#K0 MTRXLVL C P 1 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 1	#K0 MTRXLVL C P 1 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 2	#K0 MTRXLVL C P 2 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 2	#K0 MTRXLVL C P 2 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 3	#K0 MTRXLVL C P 3 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 3	#K0 MTRXLVL C P 3 O 0.0 A\x0D

Matrix Level -18 Source Processing C Destination Output 4	#K0 MTRXLVL C P 4 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 4	#K0 MTRXLVL C P 4 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 5	#K0 MTRXLVL C P 5 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 5	#K0 MTRXLVL C P 5 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 6	#K0 MTRXLVL C P 6 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 6	#K0 MTRXLVL C P 6 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 7	#K0 MTRXLVL C P 7 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 7	#K0 MTRXLVL C P 7 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Output 8	#K0 MTRXLVL C P 8 O -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Output 8	#K0 MTRXLVL C P 8 O 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Processing A	#K0 MTRXLVL C P A P -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Processing A	#K0 MTRXLVL C P A P 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Processing B	#K0 MTRXLVL C P B P -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Processing B	#K0 MTRXLVL C P B P 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Processing C	#K0 MTRXLVL C P C P -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Processing C	#K0 MTRXLVL C P C P 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Telco TX	#K0 MTRXLVL C P 1 T -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Telco TX	#K0 MTRXLVL C P 1 T 0.0 A\x0D
Matrix Level -18 Source Processing C Destination USB TX	#K0 MTRXLVL C P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing C Destination USB TX	#K0 MTRXLVL C P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Virtual Ref 1	#K0 MTRXLVL C P 1 D -18.0 A\x0D
Matrix Level 0 Source Processing C Destination Virtual Ref 1	#K0 MTRXLVL C P 1 D 0.0 A\x0D
Matrix Level -18 Source Processing C Destination Virtual Ref 2	#K0 MTRXLVL C P 2 D -18.0 A\x0D

Matrix Level 0 Source Processing C Destination Virtual Ref 2	#K0 MTRXLVL C P 2 D 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Headset TX	#K0 MTRXLVL 1 R 1 H -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Headset TX	#K0 MTRXLVL 1 R 1 H 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 1	#K0 MTRXLVL 1 R 1 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 1	#K0 MTRXLVL 1 R 1 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 2	#K0 MTRXLVL 1 R 2 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 2	#K0 MTRXLVL 1 R 2 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 3	#K0 MTRXLVL 1 R 3 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 3	#K0 MTRXLVL 1 R 3 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 4	#K0 MTRXLVL 1 R 4 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 4	#K0 MTRXLVL 1 R 4 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 5	#K0 MTRXLVL 1 R 5 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 5	#K0 MTRXLVL 1 R 5 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 6	#K0 MTRXLVL 1 R 6 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 6	#K0 MTRXLVL 1 R 6 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 7	#K0 MTRXLVL 1 R 7 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 7	#K0 MTRXLVL 1 R 7 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Output 8	#K0 MTRXLVL 1 R 8 O -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Output 8	#K0 MTRXLVL 1 R 8 O 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Processing A	#K0 MTRXLVL 1 R A P -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Processing A	#K0 MTRXLVL 1 R A P 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Processing B	#K0 MTRXLVL 1 R B P -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Processing B	#K0 MTRXLVL 1 R B P 0.0 A\x0D

Matrix Level -18 Source Telco RX Destination Processing C	#K0 MTRXLVL 1 R C P -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Processing C	#K0 MTRXLVL 1 R C P 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Virtual Ref 1	#K0 MTRXLVL 1 R 1 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Virtual Ref 1	#K0 MTRXLVL 1 R 1 D 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Virtual Ref 2	#K0 MTRXLVL 1 R 2 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Virtual Ref 2	#K0 MTRXLVL 1 R 2 D 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Headset TX	#K0 MTRXLVL 1 W 1 H -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Headset TX	#K0 MTRXLVL 1 W 1 H 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 1	#K0 MTRXLVL 1 W 1 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 1	#K0 MTRXLVL 1 W 1 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 2	#K0 MTRXLVL 1 W 2 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 2	#K0 MTRXLVL 1 W 2 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 3	#K0 MTRXLVL 1 W 3 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 3	#K0 MTRXLVL 1 W 3 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 4	#K0 MTRXLVL 1 W 4 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 4	#K0 MTRXLVL 1 W 4 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 5	#K0 MTRXLVL 1 W 5 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 5	#K0 MTRXLVL 1 W 5 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 6	#K0 MTRXLVL 1 W 6 O -18.0 A\x0D

Matrix Level 0 Source USB RX Destination Output 6	#K0 MTRXLVL 1 W 6 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 7	#K0 MTRXLVL 1 W 7 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 7	#K0 MTRXLVL 1 W 7 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Output 8	#K0 MTRXLVL 1 W 8 O -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Output 8	#K0 MTRXLVL 1 W 8 O 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Processing A	#K0 MTRXLVL 1 W A P -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Processing A	#K0 MTRXLVL 1 W A P 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Processing B	#K0 MTRXLVL 1 W B P -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Processing B	#K0 MTRXLVL 1 W B P 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Processing C	#K0 MTRXLVL 1 W C P -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Processing C	#K0 MTRXLVL 1 W C P 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T 0.0 A\x0D
Matrix Level -18 Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Virtual Ref 1	#K0 MTRXLVL 1 W 1 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Virtual Ref 1	#K0 MTRXLVL 1 W 1 D 0.0 A\x0D
Matrix Level -18 Source USB RX Destination Virtual Ref 2	#K0 MTRXLVL 1 W 2 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Virtual Ref 2	#K0 MTRXLVL 1 W 2 D 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T 0.0 A\x0D
Matrix Level -18 Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D -18.0 A\x0D
Matrix Level 0 Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D 0.0 A\x0D

Matrix Level -18 Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T -18.0 A\x0D
Matrix Level 0 Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T 0.0 A\x0D
Matrix Level -18 Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D -18.0 A\x0D
Matrix Level 0 Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D 0.0 A\x0D
Mic Gain -65.0 Mic 1	#K0 GAIN 1 M -65.0 A\x0D
Mic Gain 20.0 Mic 1	#K0 GAIN 1 M 20.0 A\x0D
Mic Gain -65.0 Mic 16	#K0 GAIN 16 M -65.0 A\x0D
Mic Gain 20.0 Mic 16	#K0 GAIN 16 M 20.0 A\x0D
Mic Gain -14.0 Mic 1	#K0 GAIN 1 M -14.0 A\x0D
Mic Gain 18.0 Mic 1	#K0 GAIN 1 M 18.0 A\x0D
Mic Gain -14.0 Mic 9	#K0 GAIN 9 M -14.0 A\x0D
Mic Gain 18.0 Mic 9	#K0 GAIN 9 M 18.0 A\x0D
Mic Mute Off Mic 1	#K0 MUTE 1 M 0\x0D
Mic Mute On Mic 1	#K0 MUTE 1 M 1\x0D
Mic Mute Off Mic 16	#K0 MUTE 16 M 0\x0D
Mic Mute On Mic 16	#K0 MUTE 16 M 1\x0D
Mic Mute Off Mic 1	#K0 MUTE 1 M 0\x0D
Mic Mute On Mic 1	#K0 MUTE 1 M 1\x0D
Mic Mute Off Mic 9	#K0 MUTE 9 M 0\x0D
Mic Mute On Mic 9	#K0 MUTE 9 M 1\x0D
Output Gain -65.0 Output 1	#K0 GAIN 1 O -65.0 A\x0D
Output Gain 20.0 Output 1	#K0 GAIN 1 O 20.0 A\x0D
Output Gain -65.0 Output 8	#K0 GAIN 8 O -65.0 A\x0D
Output Gain 20.0 Output 8	#K0 GAIN 8 O 20.0 A\x0D
Output Gain -14.0 Output 1	#K0 GAIN 1 O -14.0 A\x0D
Output Gain 18.0 Output 1	#K0 GAIN 1 O 18.0 A\x0D
Output Gain -14.0 Output 3	#K0 GAIN 3 O -14.0 A\x0D
Output Gain 18.0 Output 3	#K0 GAIN 3 O 18.0 A\x0D
Output Mute Off Output 1	#K0 MUTE 1 O 0\x0D
Output Mute On Output 1	#K0 MUTE 1 O 1\x0D
Output Mute Off Output 3	#K0 MUTE 3 O 0\x0D
Output Mute On Output 3	#K0 MUTE 3 O 1\x0D
Output Mute Off Output 1	#K0 MUTE 1 O 0\x0D
Output Mute On Output 1	#K0 MUTE 1 O 1\x0D
Output Mute Off Output 8	#K0 MUTE 8 O 0\x0D
Output Mute On Output 8	#K0 MUTE 8 O 1\x0D
Phone Receive Gain -65.0	#K0 GAIN 1 R -65.0 A\x0D
Phone Receive Gain 20.0	#K0 GAIN 1 R 20.0 A\x0D

Phone Receive Gain -14.0	#K0 GAIN 1 R -14.0 A\x0D
Phone Receive Gain 18.0	#K0 GAIN 1 R 18.0 A\x0D
Phone Receive Mute Off	#K0 MUTE 1 R 0\x0D
Phone Receive Mute On	#K0 MUTE 1 R 1\x0D
Phone Transmit Gain -65.0	#K0 GAIN 1 T -65.0 A\x0D
Phone Transmit Gain 20.0	#K0 GAIN 1 T 20.0 A\x0D
Phone Transmit Gain -14.0	#K0 GAIN 1 T -14.0 A\x0D
Phone Transmit Gain 18.0	#K0 GAIN 1 T 18.0 A\x0D
Phone Transmit Mute Off	#K0 MUTE 1 T 0\x0D
Phone Transmit Mute On	#K0 MUTE 1 T 1\x0D
Preset 1	#K0 CPRESET 1\x0D
Preset 4	#K0 CPRESET 4\x0D
Processing Channel Gain -65.0 ProcessingChannel A	#K0 GAIN A P -65.0 A\x0D
Processing Channel Gain 20.0 ProcessingChannel A	#K0 GAIN A P 20.0 A\x0D
Processing Channel Gain -65.0 ProcessingChannel B	#K0 GAIN B P -65.0 A\x0D
Processing Channel Gain 20.0 ProcessingChannel B	#K0 GAIN B P 20.0 A\x0D
Processing Channel Gain -65.0 ProcessingChannel C	#K0 GAIN C P -65.0 A\x0D
Processing Channel Gain 20.0 ProcessingChannel C	#K0 GAIN C P 20.0 A\x0D
Processing Channel Mute Off ProcessingChannel A	#K0 MUTE A P 0\x0D
Processing Channel Mute On ProcessingChannel A	#K0 MUTE A P 1\x0D
Processing Channel Mute Off ProcessingChannel B	#K0 MUTE B P 0\x0D
Processing Channel Mute On ProcessingChannel B	#K0 MUTE B P 1\x0D
Processing Channel Mute Off ProcessingChannel C	#K0 MUTE C P 0\x0D
Processing Channel Mute On ProcessingChannel C	#K0 MUTE C P 1\x0D
Ringer Enable Off	#K0 RINGEREN 1 0\x0D
Ringer Enable On	#K0 RINGEREN 1 1\x0D
Speed Dial 1	#K0 SPEEDDIAL 1 1\x0D
Speed Dial 33	#K0 SPEEDDIAL 1 33\x0D
USB In Gain -14.0	#K0 GAIN 1 W -14.0 A\x0D
USB In Gain 18.0	#K0 GAIN 1 W 18.0 A\x0D
USB In Gain -65.0	#K0 GAIN 1 W -65.0 A\x0D
USB In Gain 20.0	#K0 GAIN 1 W 20.0 A\x0D
USB In Mute Off	#K0 MUTE 1 W 0\x0D
USB In Mute On	#K0 MUTE 1 W 1\x0D
USB Out Gain -14.0	#K0 GAIN 1 D -14.0 A\x0D
USB Out Gain 18.0	#K0 GAIN 1 D 18.0 A\x0D
USB Out Gain -65.0	#K0 GAIN 1 D -65.0 A\x0D
USB Out Gain 20.0	#K0 GAIN 1 D 20.0 A\x0D
USB Out Mute Off	#K0 MUTE 1 D 0\x0D
USB Out Mute On	#K0 MUTE 1 D 1\x0D

Appendix D. Query Commands (Interact Pro)

Auto Answer	#K0 AA 1\x0D
Clear Effect	#K0 CLEAREFFECT 1\x0D
Global Mute	#K0 GMUTE M\x0D
Hook	#K0 TE 1\x0D
Line Input Gain LineInput 1	#K0 GAIN 1 L\x0D
Line Input Gain LineInput 2	#K0 GAIN 2 L\x0D
Line Input Gain LineInput 1	#K0 GAIN 1 L\x0D
Line Input Gain LineInput 2	#K0 GAIN 2 L\x0D
Line Input Mute LineInput 1	#K0 MUTE 1 L\x0D
Line Input Mute LineInput 2	#K0 MUTE 2 L\x0D
Matrix Source Headset RX Destination Headset TX	#K0 MTRX 1 N 1 H\x0D
Matrix Source Headset RX Destination Output 1	#K0 MTRX 1 N 1 O\x0D
Matrix Source Headset RX Destination Output 2	#K0 MTRX 1 N 2 O\x0D
Matrix Source Headset RX Destination Output 3	#K0 MTRX 1 N 3 O\x0D
Matrix Source Headset RX Destination Output 4	#K0 MTRX 1 N 4 O\x0D
Matrix Source Headset RX Destination Output 5	#K0 MTRX 1 N 5 O\x0D
Matrix Source Headset RX Destination Output 6	#K0 MTRX 1 N 6 O\x0D
Matrix Source Headset RX Destination Output 7	#K0 MTRX 1 N 7 O\x0D
Matrix Source Headset RX Destination Output 8	#K0 MTRX 1 N 8 O\x0D
Matrix Source Headset RX Destination Processing A	#K0 MTRX 1 N A P\x0D
Matrix Source Headset RX Destination Processing B	#K0 MTRX 1 N B P\x0D
Matrix Source Headset RX Destination Processing C	#K0 MTRX 1 N C P\x0D
Matrix Source Headset RX Destination Telco TX	#K0 MTRX 1 N 1 T\x0D
Matrix Source Headset RX Destination USB TX	#K0 MTRX 1 N 1 D\x0D
Matrix Source Headset RX Destination Virtual Ref 1	#K0 MTRX 1 N 1 D\x0D
Matrix Source Headset RX Destination Virtual Ref 2	#K0 MTRX 1 N 2 D\x0D
Matrix Source Line Input 1 Destination Headset TX	#K0 MTRX 1 L 1 H\x0D
Matrix Source Line Input 1 Destination Output 1	#K0 MTRX 1 L 1 O\x0D
Matrix Source Line Input 1 Destination Output 2	#K0 MTRX 1 L 2 O\x0D
Matrix Source Line Input 1 Destination Output 3	#K0 MTRX 1 L 3 O\x0D
Matrix Source Line Input 1 Destination Output 4	#K0 MTRX 1 L 4 O\x0D
Matrix Source Line Input 1 Destination Output 5	#K0 MTRX 1 L 5 O\x0D
Matrix Source Line Input 1 Destination Output 6	#K0 MTRX 1 L 6 O\x0D
Matrix Source Line Input 1 Destination Output 7	#K0 MTRX 1 L 7 O\x0D
Matrix Source Line Input 1 Destination Output 8	#K0 MTRX 1 L 8 O\x0D
Matrix Source Line Input 1 Destination Processing A	#K0 MTRX 1 L A P\x0D
Matrix Source Line Input 1 Destination Processing B	#K0 MTRX 1 L B P\x0D
Matrix Source Line Input 1 Destination Processing C	#K0 MTRX 1 L C P\x0D

Matrix Source Line Input 1 Destination Telco TX	#K0 MTRX 1 L 1 T\x0D
Matrix Source Line Input 1 Destination USB TX	#K0 MTRX 1 L 1 D\x0D
Matrix Source Line Input 1 Destination Virtual Ref 1	#K0 MTRX 1 L 1 D\x0D
Matrix Source Line Input 1 Destination Virtual Ref 2	#K0 MTRX 1 L 2 D\x0D
Matrix Source Line Input 2 Destination Headset TX	#K0 MTRX 2 L 1 H\x0D
Matrix Source Line Input 2 Destination Output 1	#K0 MTRX 2 L 1 O\x0D
Matrix Source Line Input 2 Destination Output 2	#K0 MTRX 2 L 2 O\x0D
Matrix Source Line Input 2 Destination Output 3	#K0 MTRX 2 L 3 O\x0D
Matrix Source Line Input 2 Destination Output 4	#K0 MTRX 2 L 4 O\x0D
Matrix Source Line Input 2 Destination Output 5	#K0 MTRX 2 L 5 O\x0D
Matrix Source Line Input 2 Destination Output 6	#K0 MTRX 2 L 6 O\x0D
Matrix Source Line Input 2 Destination Output 7	#K0 MTRX 2 L 7 O\x0D
Matrix Source Line Input 2 Destination Output 8	#K0 MTRX 2 L 8 O\x0D
Matrix Source Line Input 2 Destination Processing A	#K0 MTRX 2 L A P\x0D
Matrix Source Line Input 2 Destination Processing B	#K0 MTRX 2 L B P\x0D
Matrix Source Line Input 2 Destination Processing C	#K0 MTRX 2 L C P\x0D
Matrix Source Line Input 2 Destination Telco TX	#K0 MTRX 2 L 1 T\x0D
Matrix Source Line Input 2 Destination USB TX	#K0 MTRX 2 L 1 D\x0D
Matrix Source Line Input 2 Destination Virtual Ref 1	#K0 MTRX 2 L 1 D\x0D
Matrix Source Line Input 2 Destination Virtual Ref 2	#K0 MTRX 2 L 2 D\x0D
Matrix Source Mic Input 1 Destination Headset TX	#K0 MTRX 1 M 1 H\x0D
Matrix Source Mic Input 1 Destination Output 1	#K0 MTRX 1 M 1 O\x0D
Matrix Source Mic Input 1 Destination Output 2	#K0 MTRX 1 M 2 O\x0D
Matrix Source Mic Input 1 Destination Output 3	#K0 MTRX 1 M 3 O\x0D
Matrix Source Mic Input 1 Destination Output 4	#K0 MTRX 1 M 4 O\x0D
Matrix Source Mic Input 1 Destination Output 5	#K0 MTRX 1 M 5 O\x0D
Matrix Source Mic Input 1 Destination Output 6	#K0 MTRX 1 M 6 O\x0D
Matrix Source Mic Input 1 Destination Output 7	#K0 MTRX 1 M 7 O\x0D
Matrix Source Mic Input 1 Destination Output 8	#K0 MTRX 1 M 8 O\x0D
Matrix Source Mic Input 1 Destination Processing A	#K0 MTRX 1 M A P\x0D
Matrix Source Mic Input 1 Destination Processing B	#K0 MTRX 1 M B P\x0D
Matrix Source Mic Input 1 Destination Processing C	#K0 MTRX 1 M C P\x0D
Matrix Source Mic Input 1 Destination Telco TX	#K0 MTRX 1 M 1 T\x0D
Matrix Source Mic Input 1 Destination USB TX	#K0 MTRX 1 M 1 D\x0D
Matrix Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRX 1 M 1 D\x0D
Matrix Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRX 1 M 2 D\x0D
Matrix Source Mic Input 10 Destination Headset TX	#K0 MTRX 10 M 1 H\x0D
Matrix Source Mic Input 10 Destination Output 1	#K0 MTRX 10 M 1 O\x0D
Matrix Source Mic Input 10 Destination Output 2	#K0 MTRX 10 M 2 O\x0D
Matrix Source Mic Input 10 Destination Output 3	#K0 MTRX 10 M 3 O\x0D
Matrix Source Mic Input 10 Destination Output 4	#K0 MTRX 10 M 4 O\x0D

Matrix Source Mic Input 10 Destination Output 5	#K0 MTRX 10 M 5 O\x0D
Matrix Source Mic Input 10 Destination Output 6	#K0 MTRX 10 M 6 O\x0D
Matrix Source Mic Input 10 Destination Output 7	#K0 MTRX 10 M 7 O\x0D
Matrix Source Mic Input 10 Destination Output 8	#K0 MTRX 10 M 8 O\x0D
Matrix Source Mic Input 10 Destination Processing A	#K0 MTRX 10 M A P\x0D
Matrix Source Mic Input 10 Destination Processing B	#K0 MTRX 10 M B P\x0D
Matrix Source Mic Input 10 Destination Processing C	#K0 MTRX 10 M C P\x0D
Matrix Source Mic Input 10 Destination Telco TX	#K0 MTRX 10 M 1 T\x0D
Matrix Source Mic Input 10 Destination USB TX	#K0 MTRX 10 M 1 D\x0D
Matrix Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRX 10 M 1 D\x0D
Matrix Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRX 10 M 2 D\x0D
Matrix Source Mic Input 11 Destination Headset TX	#K0 MTRX 11 M 1 H\x0D
Matrix Source Mic Input 11 Destination Output 1	#K0 MTRX 11 M 1 O\x0D
Matrix Source Mic Input 11 Destination Output 2	#K0 MTRX 11 M 2 O\x0D
Matrix Source Mic Input 11 Destination Output 3	#K0 MTRX 11 M 3 O\x0D
Matrix Source Mic Input 11 Destination Output 4	#K0 MTRX 11 M 4 O\x0D
Matrix Source Mic Input 11 Destination Output 5	#K0 MTRX 11 M 5 O\x0D
Matrix Source Mic Input 11 Destination Output 6	#K0 MTRX 11 M 6 O\x0D
Matrix Source Mic Input 11 Destination Output 7	#K0 MTRX 11 M 7 O\x0D
Matrix Source Mic Input 11 Destination Output 8	#K0 MTRX 11 M 8 O\x0D
Matrix Source Mic Input 11 Destination Processing A	#K0 MTRX 11 M A P\x0D
Matrix Source Mic Input 11 Destination Processing B	#K0 MTRX 11 M B P\x0D
Matrix Source Mic Input 11 Destination Processing C	#K0 MTRX 11 M C P\x0D
Matrix Source Mic Input 11 Destination Telco TX	#K0 MTRX 11 M 1 T\x0D
Matrix Source Mic Input 11 Destination USB TX	#K0 MTRX 11 M 1 D\x0D
Matrix Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRX 11 M 1 D\x0D
Matrix Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRX 11 M 2 D\x0D
Matrix Source Mic Input 12 Destination Headset TX	#K0 MTRX 12 M 1 H\x0D
Matrix Source Mic Input 12 Destination Output 1	#K0 MTRX 12 M 1 O\x0D
Matrix Source Mic Input 12 Destination Output 2	#K0 MTRX 12 M 2 O\x0D
Matrix Source Mic Input 12 Destination Output 3	#K0 MTRX 12 M 3 O\x0D
Matrix Source Mic Input 12 Destination Output 4	#K0 MTRX 12 M 4 O\x0D
Matrix Source Mic Input 12 Destination Output 5	#K0 MTRX 12 M 5 O\x0D
Matrix Source Mic Input 12 Destination Output 6	#K0 MTRX 12 M 6 O\x0D
Matrix Source Mic Input 12 Destination Output 7	#K0 MTRX 12 M 7 O\x0D
Matrix Source Mic Input 12 Destination Output 8	#K0 MTRX 12 M 8 O\x0D
Matrix Source Mic Input 12 Destination Processing A	#K0 MTRX 12 M A P\x0D
Matrix Source Mic Input 12 Destination Processing B	#K0 MTRX 12 M B P\x0D
Matrix Source Mic Input 12 Destination Processing C	#K0 MTRX 12 M C P\x0D
Matrix Source Mic Input 12 Destination Telco TX	#K0 MTRX 12 M 1 T\x0D
Matrix Source Mic Input 12 Destination USB TX	#K0 MTRX 12 M 1 D\x0D

Matrix Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRX 12 M 1 D\x0D
Matrix Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRX 12 M 2 D\x0D
Matrix Source Mic Input 13 Destination Headset TX	#K0 MTRX 13 M 1 H\x0D
Matrix Source Mic Input 13 Destination Output 1	#K0 MTRX 13 M 1 O\x0D
Matrix Source Mic Input 13 Destination Output 2	#K0 MTRX 13 M 2 O\x0D
Matrix Source Mic Input 13 Destination Output 3	#K0 MTRX 13 M 3 O\x0D
Matrix Source Mic Input 13 Destination Output 4	#K0 MTRX 13 M 4 O\x0D
Matrix Source Mic Input 13 Destination Output 5	#K0 MTRX 13 M 5 O\x0D
Matrix Source Mic Input 13 Destination Output 6	#K0 MTRX 13 M 6 O\x0D
Matrix Source Mic Input 13 Destination Output 7	#K0 MTRX 13 M 7 O\x0D
Matrix Source Mic Input 13 Destination Output 8	#K0 MTRX 13 M 8 O\x0D
Matrix Source Mic Input 13 Destination Processing A	#K0 MTRX 13 M A P\x0D
Matrix Source Mic Input 13 Destination Processing B	#K0 MTRX 13 M B P\x0D
Matrix Source Mic Input 13 Destination Processing C	#K0 MTRX 13 M C P\x0D
Matrix Source Mic Input 13 Destination Telco TX	#K0 MTRX 13 M 1 T\x0D
Matrix Source Mic Input 13 Destination USB TX	#K0 MTRX 13 M 1 D\x0D
Matrix Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRX 13 M 1 D\x0D
Matrix Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRX 13 M 2 D\x0D
Matrix Source Mic Input 14 Destination Headset TX	#K0 MTRX 14 M 1 H\x0D
Matrix Source Mic Input 14 Destination Output 1	#K0 MTRX 14 M 1 O\x0D
Matrix Source Mic Input 14 Destination Output 2	#K0 MTRX 14 M 2 O\x0D
Matrix Source Mic Input 14 Destination Output 3	#K0 MTRX 14 M 3 O\x0D
Matrix Source Mic Input 14 Destination Output 4	#K0 MTRX 14 M 4 O\x0D
Matrix Source Mic Input 14 Destination Output 5	#K0 MTRX 14 M 5 O\x0D
Matrix Source Mic Input 14 Destination Output 6	#K0 MTRX 14 M 6 O\x0D
Matrix Source Mic Input 14 Destination Output 7	#K0 MTRX 14 M 7 O\x0D
Matrix Source Mic Input 14 Destination Output 8	#K0 MTRX 14 M 8 O\x0D
Matrix Source Mic Input 14 Destination Processing A	#K0 MTRX 14 M A P\x0D
Matrix Source Mic Input 14 Destination Processing B	#K0 MTRX 14 M B P\x0D
Matrix Source Mic Input 14 Destination Processing C	#K0 MTRX 14 M C P\x0D
Matrix Source Mic Input 14 Destination Telco TX	#K0 MTRX 14 M 1 T\x0D
Matrix Source Mic Input 14 Destination USB TX	#K0 MTRX 14 M 1 D\x0D
Matrix Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRX 14 M 1 D\x0D
Matrix Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRX 14 M 2 D\x0D
Matrix Source Mic Input 15 Destination Headset TX	#K0 MTRX 15 M 1 H\x0D
Matrix Source Mic Input 15 Destination Output 1	#K0 MTRX 15 M 1 O\x0D
Matrix Source Mic Input 15 Destination Output 2	#K0 MTRX 15 M 2 O\x0D
Matrix Source Mic Input 15 Destination Output 3	#K0 MTRX 15 M 3 O\x0D
Matrix Source Mic Input 15 Destination Output 4	#K0 MTRX 15 M 4 O\x0D
Matrix Source Mic Input 15 Destination Output 5	#K0 MTRX 15 M 5 O\x0D
Matrix Source Mic Input 15 Destination Output 6	#K0 MTRX 15 M 6 O\x0D

Matrix Source Mic Input 15 Destination Output 7	#K0 MTRX 15 M 7 O\x0D
Matrix Source Mic Input 15 Destination Output 8	#K0 MTRX 15 M 8 O\x0D
Matrix Source Mic Input 15 Destination Processing A	#K0 MTRX 15 M A P\x0D
Matrix Source Mic Input 15 Destination Processing B	#K0 MTRX 15 M B P\x0D
Matrix Source Mic Input 15 Destination Processing C	#K0 MTRX 15 M C P\x0D
Matrix Source Mic Input 15 Destination Telco TX	#K0 MTRX 15 M 1 T\x0D
Matrix Source Mic Input 15 Destination USB TX	#K0 MTRX 15 M 1 D\x0D
Matrix Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRX 15 M 1 D\x0D
Matrix Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRX 15 M 2 D\x0D
Matrix Source Mic Input 16 Destination Headset TX	#K0 MTRX 16 M 1 H\x0D
Matrix Source Mic Input 16 Destination Output 1	#K0 MTRX 16 M 1 O\x0D
Matrix Source Mic Input 16 Destination Output 2	#K0 MTRX 16 M 2 O\x0D
Matrix Source Mic Input 16 Destination Output 3	#K0 MTRX 16 M 3 O\x0D
Matrix Source Mic Input 16 Destination Output 4	#K0 MTRX 16 M 4 O\x0D
Matrix Source Mic Input 16 Destination Output 5	#K0 MTRX 16 M 5 O\x0D
Matrix Source Mic Input 16 Destination Output 6	#K0 MTRX 16 M 6 O\x0D
Matrix Source Mic Input 16 Destination Output 7	#K0 MTRX 16 M 7 O\x0D
Matrix Source Mic Input 16 Destination Output 8	#K0 MTRX 16 M 8 O\x0D
Matrix Source Mic Input 16 Destination Processing A	#K0 MTRX 16 M A P\x0D
Matrix Source Mic Input 16 Destination Processing B	#K0 MTRX 16 M B P\x0D
Matrix Source Mic Input 16 Destination Processing C	#K0 MTRX 16 M C P\x0D
Matrix Source Mic Input 16 Destination Telco TX	#K0 MTRX 16 M 1 T\x0D
Matrix Source Mic Input 16 Destination USB TX	#K0 MTRX 16 M 1 D\x0D
Matrix Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRX 16 M 1 D\x0D
Matrix Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRX 16 M 2 D\x0D
Matrix Source Mic Input 2 Destination Headset TX	#K0 MTRX 2 M 1 H\x0D
Matrix Source Mic Input 2 Destination Output 1	#K0 MTRX 2 M 1 O\x0D
Matrix Source Mic Input 2 Destination Output 2	#K0 MTRX 2 M 2 O\x0D
Matrix Source Mic Input 2 Destination Output 3	#K0 MTRX 2 M 3 O\x0D
Matrix Source Mic Input 2 Destination Output 4	#K0 MTRX 2 M 4 O\x0D
Matrix Source Mic Input 2 Destination Output 5	#K0 MTRX 2 M 5 O\x0D
Matrix Source Mic Input 2 Destination Output 6	#K0 MTRX 2 M 6 O\x0D
Matrix Source Mic Input 2 Destination Output 7	#K0 MTRX 2 M 7 O\x0D
Matrix Source Mic Input 2 Destination Output 8	#K0 MTRX 2 M 8 O\x0D
Matrix Source Mic Input 2 Destination Processing A	#K0 MTRX 2 M A P\x0D
Matrix Source Mic Input 2 Destination Processing B	#K0 MTRX 2 M B P\x0D
Matrix Source Mic Input 2 Destination Processing C	#K0 MTRX 2 M C P\x0D
Matrix Source Mic Input 2 Destination Telco TX	#K0 MTRX 2 M 1 T\x0D
Matrix Source Mic Input 2 Destination USB TX	#K0 MTRX 2 M 1 D\x0D
Matrix Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRX 2 M 1 D\x0D
Matrix Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRX 2 M 2 D\x0D

Global Scripter Module Communication Sheet

Matrix Source Mic Input 3 Destination Headset TX	#K0 MTRX 3 M 1 H\x0D
Matrix Source Mic Input 3 Destination Output 1	#K0 MTRX 3 M 1 O\x0D
Matrix Source Mic Input 3 Destination Output 2	#K0 MTRX 3 M 2 O\x0D
Matrix Source Mic Input 3 Destination Output 3	#K0 MTRX 3 M 3 O\x0D
Matrix Source Mic Input 3 Destination Output 4	#K0 MTRX 3 M 4 O\x0D
Matrix Source Mic Input 3 Destination Output 5	#K0 MTRX 3 M 5 O\x0D
Matrix Source Mic Input 3 Destination Output 6	#K0 MTRX 3 M 6 O\x0D
Matrix Source Mic Input 3 Destination Output 7	#K0 MTRX 3 M 7 O\x0D
Matrix Source Mic Input 3 Destination Output 8	#K0 MTRX 3 M 8 O\x0D
Matrix Source Mic Input 3 Destination Processing A	#K0 MTRX 3 M A P\x0D
Matrix Source Mic Input 3 Destination Processing B	#K0 MTRX 3 M B P\x0D
Matrix Source Mic Input 3 Destination Processing C	#K0 MTRX 3 M C P\x0D
Matrix Source Mic Input 3 Destination Telco TX	#K0 MTRX 3 M 1 T\x0D
Matrix Source Mic Input 3 Destination USB TX	#K0 MTRX 3 M 1 D\x0D
Matrix Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRX 3 M 1 D\x0D
Matrix Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRX 3 M 2 D\x0D
Matrix Source Mic Input 4 Destination Headset TX	#K0 MTRX 4 M 1 H\x0D
Matrix Source Mic Input 4 Destination Output 1	#K0 MTRX 4 M 1 O\x0D
Matrix Source Mic Input 4 Destination Output 2	#K0 MTRX 4 M 2 O\x0D
Matrix Source Mic Input 4 Destination Output 3	#K0 MTRX 4 M 3 O\x0D
Matrix Source Mic Input 4 Destination Output 4	#K0 MTRX 4 M 4 O\x0D
Matrix Source Mic Input 4 Destination Output 5	#K0 MTRX 4 M 5 O\x0D
Matrix Source Mic Input 4 Destination Output 6	#K0 MTRX 4 M 6 O\x0D
Matrix Source Mic Input 4 Destination Output 7	#K0 MTRX 4 M 7 O\x0D
Matrix Source Mic Input 4 Destination Output 8	#K0 MTRX 4 M 8 O\x0D
Matrix Source Mic Input 4 Destination Processing A	#K0 MTRX 4 M A P\x0D
Matrix Source Mic Input 4 Destination Processing B	#K0 MTRX 4 M B P\x0D
Matrix Source Mic Input 4 Destination Processing C	#K0 MTRX 4 M C P\x0D
Matrix Source Mic Input 4 Destination Telco TX	#K0 MTRX 4 M 1 T\x0D
Matrix Source Mic Input 4 Destination USB TX	#K0 MTRX 4 M 1 D\x0D
Matrix Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRX 4 M 1 D\x0D
Matrix Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRX 4 M 2 D\x0D
Matrix Source Mic Input 5 Destination Headset TX	#K0 MTRX 5 M 1 H\x0D
Matrix Source Mic Input 5 Destination Output 1	#K0 MTRX 5 M 1 O\x0D
Matrix Source Mic Input 5 Destination Output 2	#K0 MTRX 5 M 2 O\x0D
Matrix Source Mic Input 5 Destination Output 3	#K0 MTRX 5 M 3 O\x0D
Matrix Source Mic Input 5 Destination Output 4	#K0 MTRX 5 M 4 O\x0D
Matrix Source Mic Input 5 Destination Output 5	#K0 MTRX 5 M 5 O\x0D
Matrix Source Mic Input 5 Destination Output 6	#K0 MTRX 5 M 6 O\x0D
Matrix Source Mic Input 5 Destination Output 7	#K0 MTRX 5 M 7 O\x0D
Matrix Source Mic Input 5 Destination Output 8	#K0 MTRX 5 M 8 O\x0D

Global Scripter Module Communication Sheet

Matrix Source Mic Input 5 Destination Processing A	#K0 MTRX 5 M A P\x0D
Matrix Source Mic Input 5 Destination Processing B	#K0 MTRX 5 M B P\x0D
Matrix Source Mic Input 5 Destination Processing C	#K0 MTRX 5 M C P\x0D
Matrix Source Mic Input 5 Destination Telco TX	#K0 MTRX 5 M 1 T\x0D
Matrix Source Mic Input 5 Destination USB TX	#K0 MTRX 5 M 1 D\x0D
Matrix Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRX 5 M 1 D\x0D
Matrix Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRX 5 M 2 D\x0D
Matrix Source Mic Input 6 Destination Headset TX	#K0 MTRX 6 M 1 H\x0D
Matrix Source Mic Input 6 Destination Output 1	#K0 MTRX 6 M 1 O\x0D
Matrix Source Mic Input 6 Destination Output 2	#K0 MTRX 6 M 2 O\x0D
Matrix Source Mic Input 6 Destination Output 3	#K0 MTRX 6 M 3 O\x0D
Matrix Source Mic Input 6 Destination Output 4	#K0 MTRX 6 M 4 O\x0D
Matrix Source Mic Input 6 Destination Output 5	#K0 MTRX 6 M 5 O\x0D
Matrix Source Mic Input 6 Destination Output 6	#K0 MTRX 6 M 6 O\x0D
Matrix Source Mic Input 6 Destination Output 7	#K0 MTRX 6 M 7 O\x0D
Matrix Source Mic Input 6 Destination Output 8	#K0 MTRX 6 M 8 O\x0D
Matrix Source Mic Input 6 Destination Processing A	#K0 MTRX 6 M A P\x0D
Matrix Source Mic Input 6 Destination Processing B	#K0 MTRX 6 M B P\x0D
Matrix Source Mic Input 6 Destination Processing C	#K0 MTRX 6 M C P\x0D
Matrix Source Mic Input 6 Destination Telco TX	#K0 MTRX 6 M 1 T\x0D
Matrix Source Mic Input 6 Destination USB TX	#K0 MTRX 6 M 1 D\x0D
Matrix Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRX 6 M 1 D\x0D
Matrix Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRX 6 M 2 D\x0D
Matrix Source Mic Input 7 Destination Headset TX	#K0 MTRX 7 M 1 H\x0D
Matrix Source Mic Input 7 Destination Output 1	#K0 MTRX 7 M 1 O\x0D
Matrix Source Mic Input 7 Destination Output 2	#K0 MTRX 7 M 2 O\x0D
Matrix Source Mic Input 7 Destination Output 3	#K0 MTRX 7 M 3 O\x0D
Matrix Source Mic Input 7 Destination Output 4	#K0 MTRX 7 M 4 O\x0D
Matrix Source Mic Input 7 Destination Output 5	#K0 MTRX 7 M 5 O\x0D
Matrix Source Mic Input 7 Destination Output 6	#K0 MTRX 7 M 6 O\x0D
Matrix Source Mic Input 7 Destination Output 7	#K0 MTRX 7 M 7 O\x0D
Matrix Source Mic Input 7 Destination Output 8	#K0 MTRX 7 M 8 O\x0D
Matrix Source Mic Input 7 Destination Processing A	#K0 MTRX 7 M A P\x0D
Matrix Source Mic Input 7 Destination Processing B	#K0 MTRX 7 M B P\x0D
Matrix Source Mic Input 7 Destination Processing C	#K0 MTRX 7 M C P\x0D
Matrix Source Mic Input 7 Destination Telco TX	#K0 MTRX 7 M 1 T\x0D
Matrix Source Mic Input 7 Destination USB TX	#K0 MTRX 7 M 1 D\x0D
Matrix Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRX 7 M 1 D\x0D
Matrix Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRX 7 M 2 D\x0D
Matrix Source Mic Input 8 Destination Headset TX	#K0 MTRX 8 M 1 H\x0D
Matrix Source Mic Input 8 Destination Output 1	#K0 MTRX 8 M 1 O\x0D

Global Scripter Module Communication Sheet

Matrix Source Mic Input 8 Destination Output 2	#K0 MTRX 8 M 2 O\x0D
Matrix Source Mic Input 8 Destination Output 3	#K0 MTRX 8 M 3 O\x0D
Matrix Source Mic Input 8 Destination Output 4	#K0 MTRX 8 M 4 O\x0D
Matrix Source Mic Input 8 Destination Output 5	#K0 MTRX 8 M 5 O\x0D
Matrix Source Mic Input 8 Destination Output 6	#K0 MTRX 8 M 6 O\x0D
Matrix Source Mic Input 8 Destination Output 7	#K0 MTRX 8 M 7 O\x0D
Matrix Source Mic Input 8 Destination Output 8	#K0 MTRX 8 M 8 O\x0D
Matrix Source Mic Input 8 Destination Processing A	#K0 MTRX 8 M A P\x0D
Matrix Source Mic Input 8 Destination Processing B	#K0 MTRX 8 M B P\x0D
Matrix Source Mic Input 8 Destination Processing C	#K0 MTRX 8 M C P\x0D
Matrix Source Mic Input 8 Destination Telco TX	#K0 MTRX 8 M 1 T\x0D
Matrix Source Mic Input 8 Destination USB TX	#K0 MTRX 8 M 1 D\x0D
Matrix Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRX 8 M 1 D\x0D
Matrix Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRX 8 M 2 D\x0D
Matrix Source Mic Input 9 Destination Headset TX	#K0 MTRX 9 M 1 H\x0D
Matrix Source Mic Input 9 Destination Output 1	#K0 MTRX 9 M 1 O\x0D
Matrix Source Mic Input 9 Destination Output 2	#K0 MTRX 9 M 2 O\x0D
Matrix Source Mic Input 9 Destination Output 3	#K0 MTRX 9 M 3 O\x0D
Matrix Source Mic Input 9 Destination Output 4	#K0 MTRX 9 M 4 O\x0D
Matrix Source Mic Input 9 Destination Output 5	#K0 MTRX 9 M 5 O\x0D
Matrix Source Mic Input 9 Destination Output 6	#K0 MTRX 9 M 6 O\x0D
Matrix Source Mic Input 9 Destination Output 7	#K0 MTRX 9 M 7 O\x0D
Matrix Source Mic Input 9 Destination Output 8	#K0 MTRX 9 M 8 O\x0D
Matrix Source Mic Input 9 Destination Processing A	#K0 MTRX 9 M A P\x0D
Matrix Source Mic Input 9 Destination Processing B	#K0 MTRX 9 M B P\x0D
Matrix Source Mic Input 9 Destination Processing C	#K0 MTRX 9 M C P\x0D
Matrix Source Mic Input 9 Destination Telco TX	#K0 MTRX 9 M 1 T\x0D
Matrix Source Mic Input 9 Destination USB TX	#K0 MTRX 9 M 1 D\x0D
Matrix Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRX 9 M 1 D\x0D
Matrix Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRX 9 M 2 D\x0D
Matrix Source Processing A Destination Headset TX	#K0 MTRX A P 1 H\x0D
Matrix Source Processing A Destination Output 1	#K0 MTRX A P 1 O\x0D
Matrix Source Processing A Destination Output 2	#K0 MTRX A P 2 O\x0D
Matrix Source Processing A Destination Output 3	#K0 MTRX A P 3 O\x0D
Matrix Source Processing A Destination Output 4	#K0 MTRX A P 4 O\x0D
Matrix Source Processing A Destination Output 5	#K0 MTRX A P 5 O\x0D
Matrix Source Processing A Destination Output 6	#K0 MTRX A P 6 O\x0D
Matrix Source Processing A Destination Output 7	#K0 MTRX A P 7 O\x0D
Matrix Source Processing A Destination Output 8	#K0 MTRX A P 8 O\x0D
Matrix Source Processing A Destination Processing A	#K0 MTRX A P A P\x0D
Matrix Source Processing A Destination Processing B	#K0 MTRX A P B P\x0D

Matrix Source Processing A Destination Processing C	#K0 MTRX A P C P\x0D
Matrix Source Processing A Destination Telco TX	#K0 MTRX A P 1 T\x0D
Matrix Source Processing A Destination USB TX	#K0 MTRX A P 1 D\x0D
Matrix Source Processing A Destination Virtual Ref 1	#K0 MTRX A P 1 D\x0D
Matrix Source Processing A Destination Virtual Ref 2	#K0 MTRX A P 2 D\x0D
Matrix Source Processing B Destination Headset TX	#K0 MTRX B P 1 H\x0D
Matrix Source Processing B Destination Output 1	#K0 MTRX B P 1 O\x0D
Matrix Source Processing B Destination Output 2	#K0 MTRX B P 2 O\x0D
Matrix Source Processing B Destination Output 3	#K0 MTRX B P 3 O\x0D
Matrix Source Processing B Destination Output 4	#K0 MTRX B P 4 O\x0D
Matrix Source Processing B Destination Output 5	#K0 MTRX B P 5 O\x0D
Matrix Source Processing B Destination Output 6	#K0 MTRX B P 6 O\x0D
Matrix Source Processing B Destination Output 7	#K0 MTRX B P 7 O\x0D
Matrix Source Processing B Destination Output 8	#K0 MTRX B P 8 O\x0D
Matrix Source Processing B Destination Processing A	#K0 MTRX B P A P\x0D
Matrix Source Processing B Destination Processing B	#K0 MTRX B P B P\x0D
Matrix Source Processing B Destination Processing C	#K0 MTRX B P C P\x0D
Matrix Source Processing B Destination Telco TX	#K0 MTRX B P 1 T\x0D
Matrix Source Processing B Destination USB TX	#K0 MTRX B P 1 D\x0D
Matrix Source Processing B Destination Virtual Ref 1	#K0 MTRX B P 1 D\x0D
Matrix Source Processing B Destination Virtual Ref 2	#K0 MTRX B P 2 D\x0D
Matrix Source Processing C Destination Headset TX	#K0 MTRX C P 1 H\x0D
Matrix Source Processing C Destination Output 1	#K0 MTRX C P 1 O\x0D
Matrix Source Processing C Destination Output 2	#K0 MTRX C P 2 O\x0D
Matrix Source Processing C Destination Output 3	#K0 MTRX C P 3 O\x0D
Matrix Source Processing C Destination Output 4	#K0 MTRX C P 4 O\x0D
Matrix Source Processing C Destination Output 5	#K0 MTRX C P 5 O\x0D
Matrix Source Processing C Destination Output 6	#K0 MTRX C P 6 O\x0D
Matrix Source Processing C Destination Output 7	#K0 MTRX C P 7 O\x0D
Matrix Source Processing C Destination Output 8	#K0 MTRX C P 8 O\x0D
Matrix Source Processing C Destination Processing A	#K0 MTRX C P A P\x0D
Matrix Source Processing C Destination Processing B	#K0 MTRX C P B P\x0D
Matrix Source Processing C Destination Processing C	#K0 MTRX C P C P\x0D
Matrix Source Processing C Destination Telco TX	#K0 MTRX C P 1 T\x0D
Matrix Source Processing C Destination USB TX	#K0 MTRX C P 1 D\x0D
Matrix Source Processing C Destination Virtual Ref 1	#K0 MTRX C P 1 D\x0D
Matrix Source Processing C Destination Virtual Ref 2	#K0 MTRX C P 2 D\x0D
Matrix Source Telco RX Destination Headset TX	#K0 MTRX 1 R 1 H\x0D
Matrix Source Telco RX Destination Output 1	#K0 MTRX 1 R 1 O\x0D
Matrix Source Telco RX Destination Output 2	#K0 MTRX 1 R 2 O\x0D
Matrix Source Telco RX Destination Output 3	#K0 MTRX 1 R 3 O\x0D

Matrix Source Telco RX Destination Output 4	#K0 MTRX 1 R 4 O\x0D
Matrix Source Telco RX Destination Output 5	#K0 MTRX 1 R 5 O\x0D
Matrix Source Telco RX Destination Output 6	#K0 MTRX 1 R 6 O\x0D
Matrix Source Telco RX Destination Output 7	#K0 MTRX 1 R 7 O\x0D
Matrix Source Telco RX Destination Output 8	#K0 MTRX 1 R 8 O\x0D
Matrix Source Telco RX Destination Processing A	#K0 MTRX 1 R A P\x0D
Matrix Source Telco RX Destination Processing B	#K0 MTRX 1 R B P\x0D
Matrix Source Telco RX Destination Processing C	#K0 MTRX 1 R C P\x0D
Matrix Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T\x0D
Matrix Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D\x0D
Matrix Source Telco RX Destination Virtual Ref 1	#K0 MTRX 1 R 1 D\x0D
Matrix Source Telco RX Destination Virtual Ref 2	#K0 MTRX 1 R 2 D\x0D
Matrix Source USB RX Destination Headset TX	#K0 MTRX 1 W 1 H\x0D
Matrix Source USB RX Destination Output 1	#K0 MTRX 1 W 1 O\x0D
Matrix Source USB RX Destination Output 2	#K0 MTRX 1 W 2 O\x0D
Matrix Source USB RX Destination Output 3	#K0 MTRX 1 W 3 O\x0D
Matrix Source USB RX Destination Output 4	#K0 MTRX 1 W 4 O\x0D
Matrix Source USB RX Destination Output 5	#K0 MTRX 1 W 5 O\x0D
Matrix Source USB RX Destination Output 6	#K0 MTRX 1 W 6 O\x0D
Matrix Source USB RX Destination Output 7	#K0 MTRX 1 W 7 O\x0D
Matrix Source USB RX Destination Output 8	#K0 MTRX 1 W 8 O\x0D
Matrix Source USB RX Destination Processing A	#K0 MTRX 1 W A P\x0D
Matrix Source USB RX Destination Processing B	#K0 MTRX 1 W B P\x0D
Matrix Source USB RX Destination Processing C	#K0 MTRX 1 W C P\x0D
Matrix Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T\x0D
Matrix Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D\x0D
Matrix Source USB RX Destination Virtual Ref 1	#K0 MTRX 1 W 1 D\x0D
Matrix Source USB RX Destination Virtual Ref 2	#K0 MTRX 1 W 2 D\x0D
Matrix Source Telco RX Destination Telco TX	#K0 MTRX 1 R 1 T\x0D
Matrix Source Telco RX Destination USB TX	#K0 MTRX 1 R 1 D\x0D
Matrix Source USB RX Destination Telco TX	#K0 MTRX 1 W 1 T\x0D
Matrix Source USB RX Destination USB TX	#K0 MTRX 1 W 1 D\x0D
Matrix Level Source Headset RX Destination Headset TX	#K0 MTRXLVL 1 N 1 H\x0D
Matrix Level Source Headset RX Destination Output 1	#K0 MTRXLVL 1 N 1 O\x0D
Matrix Level Source Headset RX Destination Output 2	#K0 MTRXLVL 1 N 2 O\x0D
Matrix Level Source Headset RX Destination Output 3	#K0 MTRXLVL 1 N 3 O\x0D
Matrix Level Source Headset RX Destination Output 4	#K0 MTRXLVL 1 N 4 O\x0D
Matrix Level Source Headset RX Destination Output 5	#K0 MTRXLVL 1 N 5 O\x0D
Matrix Level Source Headset RX Destination Output 6	#K0 MTRXLVL 1 N 6 O\x0D
Matrix Level Source Headset RX Destination Output 7	#K0 MTRXLVL 1 N 7 O\x0D
Matrix Level Source Headset RX Destination Output 8	#K0 MTRXLVL 1 N 8 O\x0D

Matrix Level Source Headset RX Destination Processing A	#K0 MTRXLVL 1 N A P\x0D
Matrix Level Source Headset RX Destination Processing B	#K0 MTRXLVL 1 N B P\x0D
Matrix Level Source Headset RX Destination Processing C	#K0 MTRXLVL 1 N C P\x0D
Matrix Level Source Headset RX Destination Telco TX	#K0 MTRXLVL 1 N 1 T\x0D
Matrix Level Source Headset RX Destination USB TX	#K0 MTRXLVL 1 N 1 D\x0D
Matrix Level Source Headset RX Destination Virtual Ref 1	#K0 MTRXLVL 1 N 1 D\x0D
Matrix Level Source Headset RX Destination Virtual Ref 2	#K0 MTRXLVL 1 N 2 D\x0D
Matrix Level Source Line Input 1 Destination Headset TX	#K0 MTRXLVL 1 L 1 H\x0D
Matrix Level Source Line Input 1 Destination Output 1	#K0 MTRXLVL 1 L 1 O\x0D
Matrix Level Source Line Input 1 Destination Output 2	#K0 MTRXLVL 1 L 2 O\x0D
Matrix Level Source Line Input 1 Destination Output 3	#K0 MTRXLVL 1 L 3 O\x0D
Matrix Level Source Line Input 1 Destination Output 4	#K0 MTRXLVL 1 L 4 O\x0D
Matrix Level Source Line Input 1 Destination Output 5	#K0 MTRXLVL 1 L 5 O\x0D
Matrix Level Source Line Input 1 Destination Output 6	#K0 MTRXLVL 1 L 6 O\x0D
Matrix Level Source Line Input 1 Destination Output 7	#K0 MTRXLVL 1 L 7 O\x0D
Matrix Level Source Line Input 1 Destination Output 8	#K0 MTRXLVL 1 L 8 O\x0D
Matrix Level Source Line Input 1 Destination Processing A	#K0 MTRXLVL 1 L A P\x0D
Matrix Level Source Line Input 1 Destination Processing B	#K0 MTRXLVL 1 L B P\x0D
Matrix Level Source Line Input 1 Destination Processing C	#K0 MTRXLVL 1 L C P\x0D
Matrix Level Source Line Input 1 Destination Telco TX	#K0 MTRXLVL 1 L 1 T\x0D
Matrix Level Source Line Input 1 Destination USB TX	#K0 MTRXLVL 1 L 1 D\x0D
Matrix Level Source Line Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 L 1 D\x0D
Matrix Level Source Line Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 L 2 D\x0D
Matrix Level Source Line Input 2 Destination Headset TX	#K0 MTRXLVL 2 L 1 H\x0D
Matrix Level Source Line Input 2 Destination Output 1	#K0 MTRXLVL 2 L 1 O\x0D
Matrix Level Source Line Input 2 Destination Output 2	#K0 MTRXLVL 2 L 2 O\x0D
Matrix Level Source Line Input 2 Destination Output 3	#K0 MTRXLVL 2 L 3 O\x0D
Matrix Level Source Line Input 2 Destination Output 4	#K0 MTRXLVL 2 L 4 O\x0D
Matrix Level Source Line Input 2 Destination Output 5	#K0 MTRXLVL 2 L 5 O\x0D
Matrix Level Source Line Input 2 Destination Output 6	#K0 MTRXLVL 2 L 6 O\x0D
Matrix Level Source Line Input 2 Destination Output 7	#K0 MTRXLVL 2 L 7 O\x0D
Matrix Level Source Line Input 2 Destination Output 8	#K0 MTRXLVL 2 L 8 O\x0D
Matrix Level Source Line Input 2 Destination Processing A	#K0 MTRXLVL 2 L A P\x0D
Matrix Level Source Line Input 2 Destination Processing B	#K0 MTRXLVL 2 L B P\x0D
Matrix Level Source Line Input 2 Destination Processing C	#K0 MTRXLVL 2 L C P\x0D
Matrix Level Source Line Input 2 Destination Telco TX	#K0 MTRXLVL 2 L 1 T\x0D
Matrix Level Source Line Input 2 Destination USB TX	#K0 MTRXLVL 2 L 1 D\x0D
Matrix Level Source Line Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 L 1 D\x0D
Matrix Level Source Line Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 L 2 D\x0D
Matrix Level Source Mic Input 1 Destination Headset TX	#K0 MTRXLVL 1 M 1 H\x0D
Matrix Level Source Mic Input 1 Destination Output 1	#K0 MTRXLVL 1 M 1 O\x0D

Matrix Level Source Mic Input 1 Destination Output 2	#K0 MTRXLVL 1 M 2 O\x0D
Matrix Level Source Mic Input 1 Destination Output 3	#K0 MTRXLVL 1 M 3 O\x0D
Matrix Level Source Mic Input 1 Destination Output 4	#K0 MTRXLVL 1 M 4 O\x0D
Matrix Level Source Mic Input 1 Destination Output 5	#K0 MTRXLVL 1 M 5 O\x0D
Matrix Level Source Mic Input 1 Destination Output 6	#K0 MTRXLVL 1 M 6 O\x0D
Matrix Level Source Mic Input 1 Destination Output 7	#K0 MTRXLVL 1 M 7 O\x0D
Matrix Level Source Mic Input 1 Destination Output 8	#K0 MTRXLVL 1 M 8 O\x0D
Matrix Level Source Mic Input 1 Destination Processing A	#K0 MTRXLVL 1 M A P\x0D
Matrix Level Source Mic Input 1 Destination Processing B	#K0 MTRXLVL 1 M B P\x0D
Matrix Level Source Mic Input 1 Destination Processing C	#K0 MTRXLVL 1 M C P\x0D
Matrix Level Source Mic Input 1 Destination Telco TX	#K0 MTRXLVL 1 M 1 T\x0D
Matrix Level Source Mic Input 1 Destination USB TX	#K0 MTRXLVL 1 M 1 D\x0D
Matrix Level Source Mic Input 1 Destination Virtual Ref 1	#K0 MTRXLVL 1 M 1 D\x0D
Matrix Level Source Mic Input 1 Destination Virtual Ref 2	#K0 MTRXLVL 1 M 2 D\x0D
Matrix Level Source Mic Input 10 Destination Headset TX	#K0 MTRXLVL 10 M 1 H\x0D
Matrix Level Source Mic Input 10 Destination Output 1	#K0 MTRXLVL 10 M 1 O\x0D
Matrix Level Source Mic Input 10 Destination Output 2	#K0 MTRXLVL 10 M 2 O\x0D
Matrix Level Source Mic Input 10 Destination Output 3	#K0 MTRXLVL 10 M 3 O\x0D
Matrix Level Source Mic Input 10 Destination Output 4	#K0 MTRXLVL 10 M 4 O\x0D
Matrix Level Source Mic Input 10 Destination Output 5	#K0 MTRXLVL 10 M 5 O\x0D
Matrix Level Source Mic Input 10 Destination Output 6	#K0 MTRXLVL 10 M 6 O\x0D
Matrix Level Source Mic Input 10 Destination Output 7	#K0 MTRXLVL 10 M 7 O\x0D
Matrix Level Source Mic Input 10 Destination Output 8	#K0 MTRXLVL 10 M 8 O\x0D
Matrix Level Source Mic Input 10 Destination Processing A	#K0 MTRXLVL 10 M A P\x0D
Matrix Level Source Mic Input 10 Destination Processing B	#K0 MTRXLVL 10 M B P\x0D
Matrix Level Source Mic Input 10 Destination Processing C	#K0 MTRXLVL 10 M C P\x0D
Matrix Level Source Mic Input 10 Destination Telco TX	#K0 MTRXLVL 10 M 1 T\x0D
Matrix Level Source Mic Input 10 Destination USB TX	#K0 MTRXLVL 10 M 1 D\x0D
Matrix Level Source Mic Input 10 Destination Virtual Ref 1	#K0 MTRXLVL 10 M 1 D\x0D
Matrix Level Source Mic Input 10 Destination Virtual Ref 2	#K0 MTRXLVL 10 M 2 D\x0D
Matrix Level Source Mic Input 11 Destination Headset TX	#K0 MTRXLVL 11 M 1 H\x0D
Matrix Level Source Mic Input 11 Destination Output 1	#K0 MTRXLVL 11 M 1 O\x0D
Matrix Level Source Mic Input 11 Destination Output 2	#K0 MTRXLVL 11 M 2 O\x0D
Matrix Level Source Mic Input 11 Destination Output 3	#K0 MTRXLVL 11 M 3 O\x0D
Matrix Level Source Mic Input 11 Destination Output 4	#K0 MTRXLVL 11 M 4 O\x0D
Matrix Level Source Mic Input 11 Destination Output 5	#K0 MTRXLVL 11 M 5 O\x0D
Matrix Level Source Mic Input 11 Destination Output 6	#K0 MTRXLVL 11 M 6 O\x0D
Matrix Level Source Mic Input 11 Destination Output 7	#K0 MTRXLVL 11 M 7 O\x0D
Matrix Level Source Mic Input 11 Destination Output 8	#K0 MTRXLVL 11 M 8 O\x0D
Matrix Level Source Mic Input 11 Destination Processing A	#K0 MTRXLVL 11 M A P\x0D
Matrix Level Source Mic Input 11 Destination Processing B	#K0 MTRXLVL 11 M B P\x0D

Global Scripter Module Communication Sheet

Matrix Level Source Mic Input 11 Destination Processing C	#K0 MTRXLVL 11 M C P\x0D
Matrix Level Source Mic Input 11 Destination Telco TX	#K0 MTRXLVL 11 M 1 T\x0D
Matrix Level Source Mic Input 11 Destination USB TX	#K0 MTRXLVL 11 M 1 D\x0D
Matrix Level Source Mic Input 11 Destination Virtual Ref 1	#K0 MTRXLVL 11 M 1 D\x0D
Matrix Level Source Mic Input 11 Destination Virtual Ref 2	#K0 MTRXLVL 11 M 2 D\x0D
Matrix Level Source Mic Input 12 Destination Headset TX	#K0 MTRXLVL 12 M 1 H\x0D
Matrix Level Source Mic Input 12 Destination Output 1	#K0 MTRXLVL 12 M 1 O\x0D
Matrix Level Source Mic Input 12 Destination Output 2	#K0 MTRXLVL 12 M 2 O\x0D
Matrix Level Source Mic Input 12 Destination Output 3	#K0 MTRXLVL 12 M 3 O\x0D
Matrix Level Source Mic Input 12 Destination Output 4	#K0 MTRXLVL 12 M 4 O\x0D
Matrix Level Source Mic Input 12 Destination Output 5	#K0 MTRXLVL 12 M 5 O\x0D
Matrix Level Source Mic Input 12 Destination Output 6	#K0 MTRXLVL 12 M 6 O\x0D
Matrix Level Source Mic Input 12 Destination Output 7	#K0 MTRXLVL 12 M 7 O\x0D
Matrix Level Source Mic Input 12 Destination Output 8	#K0 MTRXLVL 12 M 8 O\x0D
Matrix Level Source Mic Input 12 Destination Processing A	#K0 MTRXLVL 12 M A P\x0D
Matrix Level Source Mic Input 12 Destination Processing B	#K0 MTRXLVL 12 M B P\x0D
Matrix Level Source Mic Input 12 Destination Processing C	#K0 MTRXLVL 12 M C P\x0D
Matrix Level Source Mic Input 12 Destination Telco TX	#K0 MTRXLVL 12 M 1 T\x0D
Matrix Level Source Mic Input 12 Destination USB TX	#K0 MTRXLVL 12 M 1 D\x0D
Matrix Level Source Mic Input 12 Destination Virtual Ref 1	#K0 MTRXLVL 12 M 1 D\x0D
Matrix Level Source Mic Input 12 Destination Virtual Ref 2	#K0 MTRXLVL 12 M 2 D\x0D
Matrix Level Source Mic Input 13 Destination Headset TX	#K0 MTRXLVL 13 M 1 H\x0D
Matrix Level Source Mic Input 13 Destination Output 1	#K0 MTRXLVL 13 M 1 O\x0D
Matrix Level Source Mic Input 13 Destination Output 2	#K0 MTRXLVL 13 M 2 O\x0D
Matrix Level Source Mic Input 13 Destination Output 3	#K0 MTRXLVL 13 M 3 O\x0D
Matrix Level Source Mic Input 13 Destination Output 4	#K0 MTRXLVL 13 M 4 O\x0D
Matrix Level Source Mic Input 13 Destination Output 5	#K0 MTRXLVL 13 M 5 O\x0D
Matrix Level Source Mic Input 13 Destination Output 6	#K0 MTRXLVL 13 M 6 O\x0D
Matrix Level Source Mic Input 13 Destination Output 7	#K0 MTRXLVL 13 M 7 O\x0D
Matrix Level Source Mic Input 13 Destination Output 8	#K0 MTRXLVL 13 M 8 O\x0D
Matrix Level Source Mic Input 13 Destination Processing A	#K0 MTRXLVL 13 M A P\x0D
Matrix Level Source Mic Input 13 Destination Processing B	#K0 MTRXLVL 13 M B P\x0D
Matrix Level Source Mic Input 13 Destination Processing C	#K0 MTRXLVL 13 M C P\x0D
Matrix Level Source Mic Input 13 Destination Telco TX	#K0 MTRXLVL 13 M 1 T\x0D
Matrix Level Source Mic Input 13 Destination USB TX	#K0 MTRXLVL 13 M 1 D\x0D
Matrix Level Source Mic Input 13 Destination Virtual Ref 1	#K0 MTRXLVL 13 M 1 D\x0D
Matrix Level Source Mic Input 13 Destination Virtual Ref 2	#K0 MTRXLVL 13 M 2 D\x0D
Matrix Level Source Mic Input 14 Destination Headset TX	#K0 MTRXLVL 14 M 1 H\x0D
Matrix Level Source Mic Input 14 Destination Output 1	#K0 MTRXLVL 14 M 1 O\x0D
Matrix Level Source Mic Input 14 Destination Output 2	#K0 MTRXLVL 14 M 2 O\x0D
Matrix Level Source Mic Input 14 Destination Output 3	#K0 MTRXLVL 14 M 3 O\x0D

Matrix Level Source Mic Input 14 Destination Output 4	#K0 MTRXLVL 14 M 4 O\x0D
Matrix Level Source Mic Input 14 Destination Output 5	#K0 MTRXLVL 14 M 5 O\x0D
Matrix Level Source Mic Input 14 Destination Output 6	#K0 MTRXLVL 14 M 6 O\x0D
Matrix Level Source Mic Input 14 Destination Output 7	#K0 MTRXLVL 14 M 7 O\x0D
Matrix Level Source Mic Input 14 Destination Output 8	#K0 MTRXLVL 14 M 8 O\x0D
Matrix Level Source Mic Input 14 Destination Processing A	#K0 MTRXLVL 14 M A P\x0D
Matrix Level Source Mic Input 14 Destination Processing B	#K0 MTRXLVL 14 M B P\x0D
Matrix Level Source Mic Input 14 Destination Processing C	#K0 MTRXLVL 14 M C P\x0D
Matrix Level Source Mic Input 14 Destination Telco TX	#K0 MTRXLVL 14 M 1 T\x0D
Matrix Level Source Mic Input 14 Destination USB TX	#K0 MTRXLVL 14 M 1 D\x0D
Matrix Level Source Mic Input 14 Destination Virtual Ref 1	#K0 MTRXLVL 14 M 1 D\x0D
Matrix Level Source Mic Input 14 Destination Virtual Ref 2	#K0 MTRXLVL 14 M 2 D\x0D
Matrix Level Source Mic Input 15 Destination Headset TX	#K0 MTRXLVL 15 M 1 H\x0D
Matrix Level Source Mic Input 15 Destination Output 1	#K0 MTRXLVL 15 M 1 O\x0D
Matrix Level Source Mic Input 15 Destination Output 2	#K0 MTRXLVL 15 M 2 O\x0D
Matrix Level Source Mic Input 15 Destination Output 3	#K0 MTRXLVL 15 M 3 O\x0D
Matrix Level Source Mic Input 15 Destination Output 4	#K0 MTRXLVL 15 M 4 O\x0D
Matrix Level Source Mic Input 15 Destination Output 5	#K0 MTRXLVL 15 M 5 O\x0D
Matrix Level Source Mic Input 15 Destination Output 6	#K0 MTRXLVL 15 M 6 O\x0D
Matrix Level Source Mic Input 15 Destination Output 7	#K0 MTRXLVL 15 M 7 O\x0D
Matrix Level Source Mic Input 15 Destination Output 8	#K0 MTRXLVL 15 M 8 O\x0D
Matrix Level Source Mic Input 15 Destination Processing A	#K0 MTRXLVL 15 M A P\x0D
Matrix Level Source Mic Input 15 Destination Processing B	#K0 MTRXLVL 15 M B P\x0D
Matrix Level Source Mic Input 15 Destination Processing C	#K0 MTRXLVL 15 M C P\x0D
Matrix Level Source Mic Input 15 Destination Telco TX	#K0 MTRXLVL 15 M 1 T\x0D
Matrix Level Source Mic Input 15 Destination USB TX	#K0 MTRXLVL 15 M 1 D\x0D
Matrix Level Source Mic Input 15 Destination Virtual Ref 1	#K0 MTRXLVL 15 M 1 D\x0D
Matrix Level Source Mic Input 15 Destination Virtual Ref 2	#K0 MTRXLVL 15 M 2 D\x0D
Matrix Level Source Mic Input 16 Destination Headset TX	#K0 MTRXLVL 16 M 1 H\x0D
Matrix Level Source Mic Input 16 Destination Output 1	#K0 MTRXLVL 16 M 1 O\x0D
Matrix Level Source Mic Input 16 Destination Output 2	#K0 MTRXLVL 16 M 2 O\x0D
Matrix Level Source Mic Input 16 Destination Output 3	#K0 MTRXLVL 16 M 3 O\x0D
Matrix Level Source Mic Input 16 Destination Output 4	#K0 MTRXLVL 16 M 4 O\x0D
Matrix Level Source Mic Input 16 Destination Output 5	#K0 MTRXLVL 16 M 5 O\x0D
Matrix Level Source Mic Input 16 Destination Output 6	#K0 MTRXLVL 16 M 6 O\x0D
Matrix Level Source Mic Input 16 Destination Output 7	#K0 MTRXLVL 16 M 7 O\x0D
Matrix Level Source Mic Input 16 Destination Output 8	#K0 MTRXLVL 16 M 8 O\x0D
Matrix Level Source Mic Input 16 Destination Processing A	#K0 MTRXLVL 16 M A P\x0D
Matrix Level Source Mic Input 16 Destination Processing B	#K0 MTRXLVL 16 M B P\x0D
Matrix Level Source Mic Input 16 Destination Processing C	#K0 MTRXLVL 16 M C P\x0D
Matrix Level Source Mic Input 16 Destination Telco TX	#K0 MTRXLVL 16 M 1 T\x0D

Matrix Level Source Mic Input 16 Destination USB TX	#K0 MTRXLVL 16 M 1 D\x0D
Matrix Level Source Mic Input 16 Destination Virtual Ref 1	#K0 MTRXLVL 16 M 1 D\x0D
Matrix Level Source Mic Input 16 Destination Virtual Ref 2	#K0 MTRXLVL 16 M 2 D\x0D
Matrix Level Source Mic Input 2 Destination Headset TX	#K0 MTRXLVL 2 M 1 H\x0D
Matrix Level Source Mic Input 2 Destination Output 1	#K0 MTRXLVL 2 M 1 O\x0D
Matrix Level Source Mic Input 2 Destination Output 2	#K0 MTRXLVL 2 M 2 O\x0D
Matrix Level Source Mic Input 2 Destination Output 3	#K0 MTRXLVL 2 M 3 O\x0D
Matrix Level Source Mic Input 2 Destination Output 4	#K0 MTRXLVL 2 M 4 O\x0D
Matrix Level Source Mic Input 2 Destination Output 5	#K0 MTRXLVL 2 M 5 O\x0D
Matrix Level Source Mic Input 2 Destination Output 6	#K0 MTRXLVL 2 M 6 O\x0D
Matrix Level Source Mic Input 2 Destination Output 7	#K0 MTRXLVL 2 M 7 O\x0D
Matrix Level Source Mic Input 2 Destination Output 8	#K0 MTRXLVL 2 M 8 O\x0D
Matrix Level Source Mic Input 2 Destination Processing A	#K0 MTRXLVL 2 M A P\x0D
Matrix Level Source Mic Input 2 Destination Processing B	#K0 MTRXLVL 2 M B P\x0D
Matrix Level Source Mic Input 2 Destination Processing C	#K0 MTRXLVL 2 M C P\x0D
Matrix Level Source Mic Input 2 Destination Telco TX	#K0 MTRXLVL 2 M 1 T\x0D
Matrix Level Source Mic Input 2 Destination USB TX	#K0 MTRXLVL 2 M 1 D\x0D
Matrix Level Source Mic Input 2 Destination Virtual Ref 1	#K0 MTRXLVL 2 M 1 D\x0D
Matrix Level Source Mic Input 2 Destination Virtual Ref 2	#K0 MTRXLVL 2 M 2 D\x0D
Matrix Level Source Mic Input 3 Destination Headset TX	#K0 MTRXLVL 3 M 1 H\x0D
Matrix Level Source Mic Input 3 Destination Output 1	#K0 MTRXLVL 3 M 1 O\x0D
Matrix Level Source Mic Input 3 Destination Output 2	#K0 MTRXLVL 3 M 2 O\x0D
Matrix Level Source Mic Input 3 Destination Output 3	#K0 MTRXLVL 3 M 3 O\x0D
Matrix Level Source Mic Input 3 Destination Output 4	#K0 MTRXLVL 3 M 4 O\x0D
Matrix Level Source Mic Input 3 Destination Output 5	#K0 MTRXLVL 3 M 5 O\x0D
Matrix Level Source Mic Input 3 Destination Output 6	#K0 MTRXLVL 3 M 6 O\x0D
Matrix Level Source Mic Input 3 Destination Output 7	#K0 MTRXLVL 3 M 7 O\x0D
Matrix Level Source Mic Input 3 Destination Output 8	#K0 MTRXLVL 3 M 8 O\x0D
Matrix Level Source Mic Input 3 Destination Processing A	#K0 MTRXLVL 3 M A P\x0D
Matrix Level Source Mic Input 3 Destination Processing B	#K0 MTRXLVL 3 M B P\x0D
Matrix Level Source Mic Input 3 Destination Processing C	#K0 MTRXLVL 3 M C P\x0D
Matrix Level Source Mic Input 3 Destination Telco TX	#K0 MTRXLVL 3 M 1 T\x0D
Matrix Level Source Mic Input 3 Destination USB TX	#K0 MTRXLVL 3 M 1 D\x0D
Matrix Level Source Mic Input 3 Destination Virtual Ref 1	#K0 MTRXLVL 3 M 1 D\x0D
Matrix Level Source Mic Input 3 Destination Virtual Ref 2	#K0 MTRXLVL 3 M 2 D\x0D
Matrix Level Source Mic Input 4 Destination Headset TX	#K0 MTRXLVL 4 M 1 H\x0D
Matrix Level Source Mic Input 4 Destination Output 1	#K0 MTRXLVL 4 M 1 O\x0D
Matrix Level Source Mic Input 4 Destination Output 2	#K0 MTRXLVL 4 M 2 O\x0D
Matrix Level Source Mic Input 4 Destination Output 3	#K0 MTRXLVL 4 M 3 O\x0D
Matrix Level Source Mic Input 4 Destination Output 4	#K0 MTRXLVL 4 M 4 O\x0D
Matrix Level Source Mic Input 4 Destination Output 5	#K0 MTRXLVL 4 M 5 O\x0D

Matrix Level Source Mic Input 4 Destination Output 6	#K0 MTRXLVL 4 M 6 O\x0D
Matrix Level Source Mic Input 4 Destination Output 7	#K0 MTRXLVL 4 M 7 O\x0D
Matrix Level Source Mic Input 4 Destination Output 8	#K0 MTRXLVL 4 M 8 O\x0D
Matrix Level Source Mic Input 4 Destination Processing A	#K0 MTRXLVL 4 M A P\x0D
Matrix Level Source Mic Input 4 Destination Processing B	#K0 MTRXLVL 4 M B P\x0D
Matrix Level Source Mic Input 4 Destination Processing C	#K0 MTRXLVL 4 M C P\x0D
Matrix Level Source Mic Input 4 Destination Telco TX	#K0 MTRXLVL 4 M 1 T\x0D
Matrix Level Source Mic Input 4 Destination USB TX	#K0 MTRXLVL 4 M 1 D\x0D
Matrix Level Source Mic Input 4 Destination Virtual Ref 1	#K0 MTRXLVL 4 M 1 D\x0D
Matrix Level Source Mic Input 4 Destination Virtual Ref 2	#K0 MTRXLVL 4 M 2 D\x0D
Matrix Level Source Mic Input 5 Destination Headset TX	#K0 MTRXLVL 5 M 1 H\x0D
Matrix Level Source Mic Input 5 Destination Output 1	#K0 MTRXLVL 5 M 1 O\x0D
Matrix Level Source Mic Input 5 Destination Output 2	#K0 MTRXLVL 5 M 2 O\x0D
Matrix Level Source Mic Input 5 Destination Output 3	#K0 MTRXLVL 5 M 3 O\x0D
Matrix Level Source Mic Input 5 Destination Output 4	#K0 MTRXLVL 5 M 4 O\x0D
Matrix Level Source Mic Input 5 Destination Output 5	#K0 MTRXLVL 5 M 5 O\x0D
Matrix Level Source Mic Input 5 Destination Output 6	#K0 MTRXLVL 5 M 6 O\x0D
Matrix Level Source Mic Input 5 Destination Output 7	#K0 MTRXLVL 5 M 7 O\x0D
Matrix Level Source Mic Input 5 Destination Output 8	#K0 MTRXLVL 5 M 8 O\x0D
Matrix Level Source Mic Input 5 Destination Processing A	#K0 MTRXLVL 5 M A P\x0D
Matrix Level Source Mic Input 5 Destination Processing B	#K0 MTRXLVL 5 M B P\x0D
Matrix Level Source Mic Input 5 Destination Processing C	#K0 MTRXLVL 5 M C P\x0D
Matrix Level Source Mic Input 5 Destination Telco TX	#K0 MTRXLVL 5 M 1 T\x0D
Matrix Level Source Mic Input 5 Destination USB TX	#K0 MTRXLVL 5 M 1 D\x0D
Matrix Level Source Mic Input 5 Destination Virtual Ref 1	#K0 MTRXLVL 5 M 1 D\x0D
Matrix Level Source Mic Input 5 Destination Virtual Ref 2	#K0 MTRXLVL 5 M 2 D\x0D
Matrix Level Source Mic Input 6 Destination Headset TX	#K0 MTRXLVL 6 M 1 H\x0D
Matrix Level Source Mic Input 6 Destination Output 1	#K0 MTRXLVL 6 M 1 O\x0D
Matrix Level Source Mic Input 6 Destination Output 2	#K0 MTRXLVL 6 M 2 O\x0D
Matrix Level Source Mic Input 6 Destination Output 3	#K0 MTRXLVL 6 M 3 O\x0D
Matrix Level Source Mic Input 6 Destination Output 4	#K0 MTRXLVL 6 M 4 O\x0D
Matrix Level Source Mic Input 6 Destination Output 5	#K0 MTRXLVL 6 M 5 O\x0D
Matrix Level Source Mic Input 6 Destination Output 6	#K0 MTRXLVL 6 M 6 O\x0D
Matrix Level Source Mic Input 6 Destination Output 7	#K0 MTRXLVL 6 M 7 O\x0D
Matrix Level Source Mic Input 6 Destination Output 8	#K0 MTRXLVL 6 M 8 O\x0D
Matrix Level Source Mic Input 6 Destination Processing A	#K0 MTRXLVL 6 M A P\x0D
Matrix Level Source Mic Input 6 Destination Processing B	#K0 MTRXLVL 6 M B P\x0D
Matrix Level Source Mic Input 6 Destination Processing C	#K0 MTRXLVL 6 M C P\x0D
Matrix Level Source Mic Input 6 Destination Telco TX	#K0 MTRXLVL 6 M 1 T\x0D
Matrix Level Source Mic Input 6 Destination USB TX	#K0 MTRXLVL 6 M 1 D\x0D
Matrix Level Source Mic Input 6 Destination Virtual Ref 1	#K0 MTRXLVL 6 M 1 D\x0D

Matrix Level Source Mic Input 6 Destination Virtual Ref 2	#K0 MTRXLVL 6 M 2 D\x0D
Matrix Level Source Mic Input 7 Destination Headset TX	#K0 MTRXLVL 7 M 1 H\x0D
Matrix Level Source Mic Input 7 Destination Output 1	#K0 MTRXLVL 7 M 1 O\x0D
Matrix Level Source Mic Input 7 Destination Output 2	#K0 MTRXLVL 7 M 2 O\x0D
Matrix Level Source Mic Input 7 Destination Output 3	#K0 MTRXLVL 7 M 3 O\x0D
Matrix Level Source Mic Input 7 Destination Output 4	#K0 MTRXLVL 7 M 4 O\x0D
Matrix Level Source Mic Input 7 Destination Output 5	#K0 MTRXLVL 7 M 5 O\x0D
Matrix Level Source Mic Input 7 Destination Output 6	#K0 MTRXLVL 7 M 6 O\x0D
Matrix Level Source Mic Input 7 Destination Output 7	#K0 MTRXLVL 7 M 7 O\x0D
Matrix Level Source Mic Input 7 Destination Output 8	#K0 MTRXLVL 7 M 8 O\x0D
Matrix Level Source Mic Input 7 Destination Processing A	#K0 MTRXLVL 7 M A P\x0D
Matrix Level Source Mic Input 7 Destination Processing B	#K0 MTRXLVL 7 M B P\x0D
Matrix Level Source Mic Input 7 Destination Processing C	#K0 MTRXLVL 7 M C P\x0D
Matrix Level Source Mic Input 7 Destination Telco TX	#K0 MTRXLVL 7 M 1 T\x0D
Matrix Level Source Mic Input 7 Destination USB TX	#K0 MTRXLVL 7 M 1 D\x0D
Matrix Level Source Mic Input 7 Destination Virtual Ref 1	#K0 MTRXLVL 7 M 1 D\x0D
Matrix Level Source Mic Input 7 Destination Virtual Ref 2	#K0 MTRXLVL 7 M 2 D\x0D
Matrix Level Source Mic Input 8 Destination Headset TX	#K0 MTRXLVL 8 M 1 H\x0D
Matrix Level Source Mic Input 8 Destination Output 1	#K0 MTRXLVL 8 M 1 O\x0D
Matrix Level Source Mic Input 8 Destination Output 2	#K0 MTRXLVL 8 M 2 O\x0D
Matrix Level Source Mic Input 8 Destination Output 3	#K0 MTRXLVL 8 M 3 O\x0D
Matrix Level Source Mic Input 8 Destination Output 4	#K0 MTRXLVL 8 M 4 O\x0D
Matrix Level Source Mic Input 8 Destination Output 5	#K0 MTRXLVL 8 M 5 O\x0D
Matrix Level Source Mic Input 8 Destination Output 6	#K0 MTRXLVL 8 M 6 O\x0D
Matrix Level Source Mic Input 8 Destination Output 7	#K0 MTRXLVL 8 M 7 O\x0D
Matrix Level Source Mic Input 8 Destination Output 8	#K0 MTRXLVL 8 M 8 O\x0D
Matrix Level Source Mic Input 8 Destination Processing A	#K0 MTRXLVL 8 M A P\x0D
Matrix Level Source Mic Input 8 Destination Processing B	#K0 MTRXLVL 8 M B P\x0D
Matrix Level Source Mic Input 8 Destination Processing C	#K0 MTRXLVL 8 M C P\x0D
Matrix Level Source Mic Input 8 Destination Telco TX	#K0 MTRXLVL 8 M 1 T\x0D
Matrix Level Source Mic Input 8 Destination USB TX	#K0 MTRXLVL 8 M 1 D\x0D
Matrix Level Source Mic Input 8 Destination Virtual Ref 1	#K0 MTRXLVL 8 M 1 D\x0D
Matrix Level Source Mic Input 8 Destination Virtual Ref 2	#K0 MTRXLVL 8 M 2 D\x0D
Matrix Level Source Mic Input 9 Destination Headset TX	#K0 MTRXLVL 9 M 1 H\x0D
Matrix Level Source Mic Input 9 Destination Output 1	#K0 MTRXLVL 9 M 1 O\x0D
Matrix Level Source Mic Input 9 Destination Output 2	#K0 MTRXLVL 9 M 2 O\x0D
Matrix Level Source Mic Input 9 Destination Output 3	#K0 MTRXLVL 9 M 3 O\x0D
Matrix Level Source Mic Input 9 Destination Output 4	#K0 MTRXLVL 9 M 4 O\x0D
Matrix Level Source Mic Input 9 Destination Output 5	#K0 MTRXLVL 9 M 5 O\x0D
Matrix Level Source Mic Input 9 Destination Output 6	#K0 MTRXLVL 9 M 6 O\x0D
Matrix Level Source Mic Input 9 Destination Output 7	#K0 MTRXLVL 9 M 7 O\x0D

Matrix Level Source Mic Input 9 Destination Output 8	#K0 MTRXLVL 9 M 8 O\x0D
Matrix Level Source Mic Input 9 Destination Processing A	#K0 MTRXLVL 9 M A P\x0D
Matrix Level Source Mic Input 9 Destination Processing B	#K0 MTRXLVL 9 M B P\x0D
Matrix Level Source Mic Input 9 Destination Processing C	#K0 MTRXLVL 9 M C P\x0D
Matrix Level Source Mic Input 9 Destination Telco TX	#K0 MTRXLVL 9 M 1 T\x0D
Matrix Level Source Mic Input 9 Destination USB TX	#K0 MTRXLVL 9 M 1 D\x0D
Matrix Level Source Mic Input 9 Destination Virtual Ref 1	#K0 MTRXLVL 9 M 1 D\x0D
Matrix Level Source Mic Input 9 Destination Virtual Ref 2	#K0 MTRXLVL 9 M 2 D\x0D
Matrix Level Source Processing A Destination Headset TX	#K0 MTRXLVL A P 1 H\x0D
Matrix Level Source Processing A Destination Output 1	#K0 MTRXLVL A P 1 O\x0D
Matrix Level Source Processing A Destination Output 2	#K0 MTRXLVL A P 2 O\x0D
Matrix Level Source Processing A Destination Output 3	#K0 MTRXLVL A P 3 O\x0D
Matrix Level Source Processing A Destination Output 4	#K0 MTRXLVL A P 4 O\x0D
Matrix Level Source Processing A Destination Output 5	#K0 MTRXLVL A P 5 O\x0D
Matrix Level Source Processing A Destination Output 6	#K0 MTRXLVL A P 6 O\x0D
Matrix Level Source Processing A Destination Output 7	#K0 MTRXLVL A P 7 O\x0D
Matrix Level Source Processing A Destination Output 8	#K0 MTRXLVL A P 8 O\x0D
Matrix Level Source Processing A Destination Processing A	#K0 MTRXLVL A P A P\x0D
Matrix Level Source Processing A Destination Processing B	#K0 MTRXLVL A P B P\x0D
Matrix Level Source Processing A Destination Processing C	#K0 MTRXLVL A P C P\x0D
Matrix Level Source Processing A Destination Telco TX	#K0 MTRXLVL A P 1 T\x0D
Matrix Level Source Processing A Destination USB TX	#K0 MTRXLVL A P 1 D\x0D
Matrix Level Source Processing A Destination Virtual Ref 1	#K0 MTRXLVL A P 1 D\x0D
Matrix Level Source Processing A Destination Virtual Ref 2	#K0 MTRXLVL A P 2 D\x0D
Matrix Level Source Processing B Destination Headset TX	#K0 MTRXLVL B P 1 H\x0D
Matrix Level Source Processing B Destination Output 1	#K0 MTRXLVL B P 1 O\x0D
Matrix Level Source Processing B Destination Output 2	#K0 MTRXLVL B P 2 O\x0D
Matrix Level Source Processing B Destination Output 3	#K0 MTRXLVL B P 3 O\x0D
Matrix Level Source Processing B Destination Output 4	#K0 MTRXLVL B P 4 O\x0D
Matrix Level Source Processing B Destination Output 5	#K0 MTRXLVL B P 5 O\x0D
Matrix Level Source Processing B Destination Output 6	#K0 MTRXLVL B P 6 O\x0D
Matrix Level Source Processing B Destination Output 7	#K0 MTRXLVL B P 7 O\x0D
Matrix Level Source Processing B Destination Output 8	#K0 MTRXLVL B P 8 O\x0D
Matrix Level Source Processing B Destination Processing A	#K0 MTRXLVL B P A P\x0D
Matrix Level Source Processing B Destination Processing B	#K0 MTRXLVL B P B P\x0D
Matrix Level Source Processing B Destination Processing C	#K0 MTRXLVL B P C P\x0D
Matrix Level Source Processing B Destination Telco TX	#K0 MTRXLVL B P 1 T\x0D
Matrix Level Source Processing B Destination USB TX	#K0 MTRXLVL B P 1 D\x0D
Matrix Level Source Processing B Destination Virtual Ref 1	#K0 MTRXLVL B P 1 D\x0D
Matrix Level Source Processing B Destination Virtual Ref 2	#K0 MTRXLVL B P 2 D\x0D
Matrix Level Source Processing C Destination Headset TX	#K0 MTRXLVL C P 1 H\x0D

Matrix Level Source Processing C Destination Output 1	#K0 MTRXLVL C P 1 O\x0D
Matrix Level Source Processing C Destination Output 2	#K0 MTRXLVL C P 2 O\x0D
Matrix Level Source Processing C Destination Output 3	#K0 MTRXLVL C P 3 O\x0D
Matrix Level Source Processing C Destination Output 4	#K0 MTRXLVL C P 4 O\x0D
Matrix Level Source Processing C Destination Output 5	#K0 MTRXLVL C P 5 O\x0D
Matrix Level Source Processing C Destination Output 6	#K0 MTRXLVL C P 6 O\x0D
Matrix Level Source Processing C Destination Output 7	#K0 MTRXLVL C P 7 O\x0D
Matrix Level Source Processing C Destination Output 8	#K0 MTRXLVL C P 8 O\x0D
Matrix Level Source Processing C Destination Processing A	#K0 MTRXLVL C P A P\x0D
Matrix Level Source Processing C Destination Processing B	#K0 MTRXLVL C P B P\x0D
Matrix Level Source Processing C Destination Processing C	#K0 MTRXLVL C P C P\x0D
Matrix Level Source Processing C Destination Telco TX	#K0 MTRXLVL C P 1 T\x0D
Matrix Level Source Processing C Destination USB TX	#K0 MTRXLVL C P 1 D\x0D
Matrix Level Source Processing C Destination Virtual Ref 1	#K0 MTRXLVL C P 1 D\x0D
Matrix Level Source Processing C Destination Virtual Ref 2	#K0 MTRXLVL C P 2 D\x0D
Matrix Level Source Telco RX Destination Headset TX	#K0 MTRXLVL 1 R 1 H\x0D
Matrix Level Source Telco RX Destination Output 1	#K0 MTRXLVL 1 R 1 O\x0D
Matrix Level Source Telco RX Destination Output 2	#K0 MTRXLVL 1 R 2 O\x0D
Matrix Level Source Telco RX Destination Output 3	#K0 MTRXLVL 1 R 3 O\x0D
Matrix Level Source Telco RX Destination Output 4	#K0 MTRXLVL 1 R 4 O\x0D
Matrix Level Source Telco RX Destination Output 5	#K0 MTRXLVL 1 R 5 O\x0D
Matrix Level Source Telco RX Destination Output 6	#K0 MTRXLVL 1 R 6 O\x0D
Matrix Level Source Telco RX Destination Output 7	#K0 MTRXLVL 1 R 7 O\x0D
Matrix Level Source Telco RX Destination Output 8	#K0 MTRXLVL 1 R 8 O\x0D
Matrix Level Source Telco RX Destination Processing A	#K0 MTRXLVL 1 R A P\x0D
Matrix Level Source Telco RX Destination Processing B	#K0 MTRXLVL 1 R B P\x0D
Matrix Level Source Telco RX Destination Processing C	#K0 MTRXLVL 1 R C P\x0D
Matrix Level Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T\x0D
Matrix Level Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D\x0D
Matrix Level Source Telco RX Destination Virtual Ref 1	#K0 MTRXLVL 1 R 1 D\x0D
Matrix Level Source Telco RX Destination Virtual Ref 2	#K0 MTRXLVL 1 R 2 D\x0D
Matrix Level Source USB RX Destination Headset TX	#K0 MTRXLVL 1 W 1 H\x0D
Matrix Level Source USB RX Destination Output 1	#K0 MTRXLVL 1 W 1 O\x0D
Matrix Level Source USB RX Destination Output 2	#K0 MTRXLVL 1 W 2 O\x0D
Matrix Level Source USB RX Destination Output 3	#K0 MTRXLVL 1 W 3 O\x0D
Matrix Level Source USB RX Destination Output 4	#K0 MTRXLVL 1 W 4 O\x0D
Matrix Level Source USB RX Destination Output 5	#K0 MTRXLVL 1 W 5 O\x0D
Matrix Level Source USB RX Destination Output 6	#K0 MTRXLVL 1 W 6 O\x0D
Matrix Level Source USB RX Destination Output 7	#K0 MTRXLVL 1 W 7 O\x0D
Matrix Level Source USB RX Destination Output 8	#K0 MTRXLVL 1 W 8 O\x0D
Matrix Level Source USB RX Destination Processing A	#K0 MTRXLVL 1 W A P\x0D

Matrix Level Source USB RX Destination Processing B	#K0 MTRXLVL 1 W B P\0D
Matrix Level Source USB RX Destination Processing C	#K0 MTRXLVL 1 W C P\0D
Matrix Level Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T\0D
Matrix Level Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D\0D
Matrix Level Source USB RX Destination Virtual Ref 1	#K0 MTRXLVL 1 W 1 D\0D
Matrix Level Source USB RX Destination Virtual Ref 2	#K0 MTRXLVL 1 W 2 D\0D
Matrix Level Source Telco RX Destination Telco TX	#K0 MTRXLVL 1 R 1 T\0D
Matrix Level Source Telco RX Destination USB TX	#K0 MTRXLVL 1 R 1 D\0D
Matrix Level Source USB RX Destination Telco TX	#K0 MTRXLVL 1 W 1 T\0D
Matrix Level Source USB RX Destination USB TX	#K0 MTRXLVL 1 W 1 D\0D
Mic Gain Mic 1	#K0 GAIN 1 M\0D
Mic Gain Mic 16	#K0 GAIN 16 M\0D
Mic Gain Mic 1	#K0 GAIN 1 M\0D
Mic Gain Mic 9	#K0 GAIN 9 M\0D
Mic Mute Mic 1	#K0 MUTE 1 M\0D
Mic Mute Mic 16	#K0 MUTE 16 M\0D
Mic Mute Mic 1	#K0 MUTE 1 M\0D
Mic Mute Mic 9	#K0 MUTE 9 M\0D
Output Gain Output 1	#K0 GAIN 1 O\0D
Output Gain Output 8	#K0 GAIN 8 O\0D
Output Gain Output 1	#K0 GAIN 1 O\0D
Output Gain Output 3	#K0 GAIN 3 O\0D
Output Mute Output 1	#K0 MUTE 1 O\0D
Output Mute Output 3	#K0 MUTE 3 O\0D
Output Mute Output 1	#K0 MUTE 1 O\0D
Output Mute Output 8	#K0 MUTE 8 O\0D
Phone Receive Gain	#K0 GAIN 1 R\0D
Phone Receive Gain	#K0 GAIN 1 R\0D
Phone Receive Mute	#K0 MUTE 1 R\0D
Phone Transmit Gain	#K0 GAIN 1 T\0D
Phone Transmit Gain	#K0 GAIN 1 T\0D
Phone Transmit Mute	#K0 MUTE 1 T\0D
Processing Channel Gain ProcessingChannel A	#K0 GAIN A P\0D
Processing Channel Gain ProcessingChannel B	#K0 GAIN B P\0D
Processing Channel Gain ProcessingChannel C	#K0 GAIN C P\0D
Processing Channel Mute ProcessingChannel A	#K0 MUTE A P\0D
Processing Channel Mute ProcessingChannel B	#K0 MUTE B P\0D
Processing Channel Mute ProcessingChannel C	#K0 MUTE C P\0D
Ringer Enable	#K0 RINGEREN 1\0D
USB In Gain	#K0 GAIN 1 W\0D
USB In Gain	#K0 GAIN 1 W\0D

Global Scripter Module Communication Sheet

USB In Mute	#K0 MUTE 1 W\x0D
USB Out Gain	#K0 GAIN 1 D\x0D
USB Out Gain	#K0 GAIN 1 D\x0D
USB Out Mute	#K0 MUTE 1 D\x0D