

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Lighting Control
Manufacturer: Comm-Tec
Firmware Version: N/A
Model(s): CTG-LON/NX

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.05.0000-b007	2.01.0001-b001	1.2.3

Version History

Module Version	Date	Notes
1_0_0_0	4/13/2017	Initial Version

Module Notes

- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:


HVACMode	'HVAC_AUTO'	'HVAC_HEAT'	'HVAC_MRNG_WRMUP'
	'HVAC_COOL'	'HVAC_NIGHT_PURGE'	'HVAC_PRE_COOL'
	'HVAC_OFF'	'HVAC_TEST'	'HVAC_EMERG_HEAT'
	'HVAC_FAN_ONLY'	'HVAC_FREE_COOL'	'HVAC_ICE'
['ID']	'1' – '32'		
Occupancy	'Area is occupied'	'Area is unoccupied'	'Area is temporarily occupied for the bypass period'
	'Area is temporarily unoccupied'		
['ID']	'1' – '32'		
Preset	0 – 655352		
['ID']	'1' – '32'		
State	'0' – '1'		
['ID']	'1' – '16'		
['Bit']¹	'0' – '15'		
SwitchState	'0' – '1'		
['ID']	'1' – '64'		
SwitchValue	0 to 100 in steps of 0.5		
['ID']	'1' – '64'		

¹ Least significant bit is Bit 0.**Status Available:**

N/A

Cable and Adapter Requirements:

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 38400**Data Bits:** 8**Parity:** None**Stop Bits:** One**Flow Control:** None**Pin Assignments Diagram**

Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND

**General Notes:**

Appendix A. Set Commands

HVAC Mode HVAC_AUTO ID 1	\xFE0w642:1:0\xFF
HVAC Mode HVAC_AUTO ID 32	\xFE0w673:1:0\xFF
HVAC Mode HVAC_COOL ID 1	\xFE0w642:1:3\xFF
HVAC Mode HVAC_COOL ID 32	\xFE0w673:1:3\xFF
HVAC Mode HVAC_EMERG_HEAT ID 1	\xFE0w642:1:8\xFF
HVAC Mode HVAC_EMERG_HEAT ID 32	\xFE0w673:1:8\xFF
HVAC Mode HVAC_FAN_ONLY ID 1	\xFE0w642:1:9\xFF
HVAC Mode HVAC_FAN_ONLY ID 32	\xFE0w673:1:9\xFF
HVAC Mode HVAC_FREE_COOL ID 1	\xFE0w642:1:10\xFF
HVAC Mode HVAC_FREE_COOL ID 32	\xFE0w673:1:10\xFF
HVAC Mode HVAC_HEAT ID 1	\xFE0w642:1:1\xFF
HVAC Mode HVAC_HEAT ID 32	\xFE0w673:1:1\xFF
HVAC Mode HVAC_ICE ID 1	\xFE0w642:1:11\xFF
HVAC Mode HVAC_ICE ID 32	\xFE0w673:1:11\xFF
HVAC Mode HVAC_MRNG_WRMUP ID 1	\xFE0w642:1:2\xFF
HVAC Mode HVAC_MRNG_WRMUP ID 32	\xFE0w673:1:2\xFF
HVAC Mode HVAC_NIGHT_PURGE ID 1	\xFE0w642:1:4\xFF
HVAC Mode HVAC_NIGHT_PURGE ID 32	\xFE0w673:1:4\xFF
HVAC Mode HVAC_OFF ID 1	\xFE0w642:1:6\xFF
HVAC Mode HVAC_OFF ID 32	\xFE0w673:1:6\xFF
HVAC Mode HVAC_PRE_COOL ID 1	\xFE0w642:1:5\xFF
HVAC Mode HVAC_PRE_COOL ID 32	\xFE0w673:1:5\xFF
HVAC Mode HVAC_TEST ID 1	\xFE0w642:1:7\xFF
HVAC Mode HVAC_TEST ID 32	\xFE0w673:1:7\xFF
Occupancy Area is occupied ID 1	\xFE0w578:1:0\xFF
Occupancy Area is occupied ID 32	\xFE0w609:1:0\xFF
Occupancy Area is temporarily occupied for the bypass period ID 1	\xFE0w578:1:2\xFF
Occupancy Area is temporarily occupied for the bypass period ID 32	\xFE0w609:1:2\xFF
Occupancy Area is temporarily unoccupied ID 1	\xFE0w578:1:3\xFF
Occupancy Area is temporarily unoccupied ID 32	\xFE0w609:1:3\xFF
Occupancy Area is unoccupied ID 1	\xFE0w578:1:1\xFF
Occupancy Area is unoccupied ID 32	\xFE0w609:1:1\xFF
Preset 0 ID 1	\xFE0w384:1:0/2:0\xFF
Preset 0 ID 32	\xFE0w415:1:0/2:0\xFF
Preset 655352 ID 1	\xFE0w384:1:0/2:655352\xFF
Preset 655352 ID 32	\xFE0w415:1:0/2:655352\xFF
State 0 ID 1 Bit 0	\xFE0w144:1:0\xFF
State 0 ID 1 Bit 15	\xFE0w144:16:0\xFF
State 0 ID 16 Bit 0	\xFE0w159:1:0\xFF
State 0 ID 16 Bit 15	\xFE0w159:16:0\xFF
State 1 ID 1 Bit 0	\xFE0w144:1:1\xFF
State 1 ID 1 Bit 15	\xFE0w144:16:1\xFF
State 1 ID 16 Bit 0	\xFE0w159:1:1\xFF
State 1 ID 16 Bit 15	\xFE0w159:16:1\xFF
Switch State 0 ID 1	\xFE0w64:2:0\xFF

Global Scripter Module Communication Sheet

Switch State 0 ID 64	\xFE0w127:2:0\xFF
Switch State 1 ID 1	\xFE0w64:2:1\xFF
Switch State 1 ID 64	\xFE0w127:2:1\xFF
Switch Value 0 ID 1	\xFE0w64:1:0\xFF
Switch Value 0 ID 64	\xFE0w127:1:0\xFF
Switch Value 100 ID 1	\xFE0w64:1:100\xFF
Switch Value 100 ID 64	\xFE0w127:1:100\xFF