

This document provides additional assistance with wiring your Extron IPL PRO enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instruction, refer to the user's manual for the specific Extron IPL PRO enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Scaler
Manufacturer: Comm-Tec
Firmware Version: N/A
Model(s): UP-51T

Tested on the Following Software and Firmware Versions:

IP Link Pro Control Processor Firmware	Touch Link Panel Firmware	GS Version
2.04.0000-b007	2.01.0001-b001	1.2.2

Version History

Module Version	Date	Notes
1_0_0_0	1/5/2017	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'. Example: InterfaceName.Unidirectional = 'True'
- connectionCounter variable must be set the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15. Example: InterfaceName.connectionCounter = 5
- For Serial Over Ethernet support, SerialOverEthernetClass must be used. Example: InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', PortNum, Model='ModelName')

Control Commands, States, and Qualifiers:


AspectRatio	None		
AutoImage	None		
AutoSwitch	'On'	'Off'	
ExecutiveMode	'On'	'Off'	
Freeze	'On'	'Off'	
HDMIAudio	'On'	'Off'	
Input	'HDMI 1' 'VGA Port 1'	'HDMI 2' 'VGA Port 2'	'HDMI 3'
MenuNavigation	'Ok' 'Up' 'Exit'	'Left' 'Down'	'Right' 'Menu'
Mute	'On'	'Off'	
['Type']	'Line'	'Microphone'	
PictureMode	None		
Power	'On'	'Off'	
Resolution	'1360x768' '1280x800' '1600x1200'	'1024x768' '1920x1080'	'1280x720' '1920x1200'
VGAPortMode	'VGA'	'YPbPr'	'AV'
['Port']	'1' – '2'		
Volume	0 to 60 in steps of 1		
['Type']	'Line'	'Microphone'	

Status Available:

AspectRatioStatus	'16:9' 'Panorama' 'Zoom 2'	'4:3' 'Just Scan'	'Auto' 'Zoom 1'
ConnectionStatus	'Connected' 'Disconnected'		
ExecutiveMode	'On' 'Off'		
Freeze	'On' 'Off'		
HDMIAudio	'On' 'Off'		
Input	'HDMI 1' 'VGA Port 1'	'HDMI 2' 'VGA Port 2'	'HDMI 3'
Mute	'On' 'Off'		
['Type']	'Line' 'Microphone'		
PictureModeStatus	'Dynamic' 'User'	'Standard'	'Mild'
Resolution	'1360x768' '1280x800' '1600x1200'	'1024x768' '1920x1080'	'1280x720' '1920x1200'
Volume	0 to 60 in steps of 1		
['Type']	'Line' 'Microphone'		

Cable and Adapter Requirements:

Captive Screw to Captive Screw

Notes for the Device:**Serial communication:****Port Type:** RS-232**Baud Rate:** 9600**Data Bits:** 8**Parity:** None**Stop Bits:** One**Flow Control:** None**Pin Assignments Diagram**

Signal	Main Cable	Signal
TxD	→	RxD
RxD	←	TxD
GND		GND

**General Notes:**

Appendix A. Set Commands

Aspect Ratio None	50608%
Auto Image None	50606%
Auto Switch Off	50786%
Auto Switch On	50785%
Executive Mode Off	50605%
Executive Mode On	50604%
Freeze Off	50656%
Freeze On	50655%
HDMI Audio Off	50649%
HDMI Audio On	50648%
Input HDMI 1	50701%
Input HDMI 2	50702%
Input HDMI 3	50703%
Input VGA Port 1	50704%
Input VGA Port 2	50705%
Menu Navigation Down	50613%
Menu Navigation Exit	50618%
Menu Navigation Left	50610%
Menu Navigation Menu	50616%
Menu Navigation Ok	50609%
Menu Navigation Right	50611%
Menu Navigation Up	50612%
Mute Off Type Line	50601%
Mute Off Type Microphone	50723%
Mute On Type Line	50600%
Mute On Type Microphone	50722%
Picture Mode None	50614%
Power Off	50797%
Power On	50697%
Resolution 1024x768	50626%
Resolution 1280x720	50627%
Resolution 1280x800	50628%
Resolution 1360x768	50619%
Resolution 1600x1200	50621%
Resolution 1920x1080	50629%
Resolution 1920x1200	50620%
VGA Port Mode AV Port 1	50682%
VGA Port Mode AV Port 2	50685%
VGA Port Mode VGA Port 1	50680%
VGA Port Mode VGA Port 2	50683%
VGA Port Mode YPbPr Port 1	50681%
VGA Port Mode YPbPr Port 2	50684%
Volume 0 Type Line	50100.0%
Volume 0 Type Microphone	50800.0%
Volume 60 Type Line	50160.0%

Volume 60 Type Microphone	50860.0%
---------------------------	----------

Appendix B. Query Commands

Aspect Ratio Status	50635%
Executive Mode	50754%
Freeze	50753%
HDMI Audio	50652%
Input	50631%
Mute Type Line	50751%
Mute Type Microphone	50752%
Picture Mode Status	50633%
Resolution	50632%
Volume Type Line	50630%
Volume Type Microphone	50630%