# PingPong – operator cheat sheet

N1MM Logger+ multi-op · S55OO

## 1 · What the lamp shows

| Lamp | Means | You |
|---|---|---|
| — | Nobody on your band and mode is transmitting. | Operate normally. |
| CQ | A station on your band and mode is transmitting – its color, its message, its name (top left) and frequency (top right). | Inband: don't transmit over it. |
| GO | RUN has just finished (3 s) – the slot is free for the inband stations. | Now is the moment. First inband to transmit gets the slot. |
| WAIT · INB1 · 32 s | Another inband holds the slot. Your F1–F11, Enter, Insert are blocked. | Wait for RUN to transmit; frees itself after the release time. |
| BLOCKED · F1 | You pressed a blocked key – nothing was sent. | Wait, then press again. |
| F12 · RUN1 · 25 s | F12 call: the border blinks in the caller's color – "hold off, please". Your F-keys may be blocked meanwhile. | Stop transmitting. Left click on the lamp stops the blinking. |
| RUN1 · QRL? ⚡ | Urgent call (Shift+F2/F4) from a station on your band and mode – flashes fast (color ↔ white) as long as its message is sent. `PRIORITY` in the corner (Ctrl+F2/F4): your transmission was stopped, keys held. | Stop and listen – at once. |
| INB2 · INB | Lamp test from the master PC: purple ↔ white for 3 s, `TEST` in the corner. | Nothing – it shows your own name. |

## 2 · Your keys

| | |
|---|---|
| F12 in S&P | The S&P stations on your band blink in your color and hold off (call time, default 30 s). F12 again = end the call. |
| F12 in Run | **All** stations on your band hold off for a few seconds (default 5 s). |
| Shift+F2 / F4 | N1MM sends F2/F4 as usual, and every lamp on your band and mode flashes your name and the message while it is sent. |
| Ctrl+F2 / F4 | **Priority:** stations on your band and mode that transmit are stopped (Esc) and held; then your F2/F4 goes out – same flashing. |
| Run / S&P | Your role follows N1MM: Run = **RUN**, S&P = **INB** – nothing to set. |
| Mouse | Left click on lamp = stop blinking · right click = Options · Shift+F = compact lamp. |

"F12 busy · RUN2" = a call is already running on your band; wait until it ends.

## 3 · Taking turns (ping-pong)

**RUN transmits** → **GO** → **first INB takes slot** → **other INBs WAIT** → **RUN transmits**

- The slot also frees itself after the **release time** (set on the master, default 40 s; 0 = only RUN frees it).
- The master can switch the lock **off** – then everybody may transmit, no priority.
- `no RUN on 7 MHz – lock off`: there is no RUN on your band, so nobody is locked.
- Only transmissions **N1MM starts** count. Paddle, microphone PTT or footswitch are not seen and not blocked.

## Phone lamp

Options ▾ → **Phone lamp QR code…** → scan it with the phone. The phone shows the same lamp (needs the firewall rule).

## 4 · Messages under the lamp – what to do

| Message | Do |
|---|---|
| `no data from this PC's N1MM on UDP 12062` | N1MM: Config → Configure Ports… → **Broadcast Data** → **Radio** ticked, line `127.0.0.1:12060 127.0.0.1:12062` → OK. |
| `⚠ UDP 12062 also used by …` (red) | Another program takes N1MM's data on this PC – tell the captain. |
| `no PingPong heard – firewall?` | Options ▾ → Network → **Allow PingPong in Windows Firewall…** (asks for administrator rights). |
| `⚠ TWO MASTERS` · different versions | Tell the captain (Overview: **Update all lamps…**). |
| `🔒 … has a password – click here` | Click the line and type the network password (ask the captain) – it is checked at once. |
| Lamp gone / closed | Start `n1mm_lamps.exe` again – only one lamp per PC. The Overview raises an alarm when an operating lamp is silent for 30 s. |



It prevents mistakes – it is not a hardware interlock. N1MM's own interlock still applies.