

1.

What is the output of the following code?

```
#include <stdio.h>
typedef enum
{
    X, Y, Z
} E;
typedef E EnumType;
int main(void)
{
    EnumType e = 5;
    switch(e)
    {
        case X: printf("X\n");
                break;
        case Y: printf("Y\n");
                break;
        case Z: printf("Z\n");
                break;
        default:
                printf("Default\n");
    }
    return 0;
}
```

- A. X
- B. Y
- C. Z
- D. Default

Answer: D

2.

What is the output of the following code?

```
#include <stdio.h>
```

```
enum day
```

```
{
```

```
    MON = 1, TUE, WED = 5, THU, FRI = MON + 4
```

```
};
```

```
int main(void)
```

```
{
```

```
    enum day today = THU;
```

```
    int val = today + FRI - TUE;
```

```
    printf("%d\n", val);
```

```
    return 0;
```

```
}
```

A. 9

B. 10

C. 11

D. 12

Answer: A

3.

What is the output of the following code?

```
#include <stdio.h>
int main(void)
{
    int a = 1;
    switch(a)
    {
        case 1;
            printf("One");
            break;
        default:
            printf("Default");
    }
    return 0;
}
```

- A. One
- B. Default
- C. Compile time error
- D. No output

Answer: C

4.

What is the output of the following code?

```
#include <stdio.h>
typedef enum
{
    SUNDAY, MONDAY, TUESDAY
} Day;
int main(void)
{
    Day today = MONDAY;
    switch(today)
    {
        case SUNDAY:
            printf("Weekend");
            break;
        case MONDAY:
            printf("Start of Week");
            break;
        default:
            printf("Midweek");
            break;
    }
    return 0;
}
```

- A. Weekend
- B. Start of Week
- C. Midweek
- D. Compile Error

Answer: B

5.

```
#include <stdio.h>
typedef enum {RED, GREEN, BLUE} Color;
int main(void)
{
    Color c = 0 + 1 * 0 + 1 % 2;
    if (c == RED)
        printf("Red\n");
    else if (c == GREEN)
        printf("Green\n");
    else
        printf("Blue\n");
    return 0;
}
```

- A. Red
- B. Green
- C. Blue
- D. Compile time error

Answer: B

6.

What is the output of the following code?

```
#include<stdio.h>
typedef enum {MON=1, TUE, WED} Day;
int main(void)
{
    Day d = 2;
    if (d == MON)
        printf("Monday");
    else if (d == --TUE)
        printf("Tuesday");
    else
        printf("Other day");
    return 0;
}
```

- A. Monday
- B. Tuesday
- C. Other day
- D. Compile time error

Answer: D

7.

What is the output of the following code?

```
#include<stdio.h>
int main(void)
{
    int n = 5;
    switch(n % 2)
    {
        case 0:
            if (n == 0) printf("Zero");
            else printf("Even");
            break;
        default:
            printf("Odd");
    }
}
```

- A. Zero
- B. Even
- C. Odd
- D. Compile error

Answer: C