

1.

Find the output of the following

#include<stdio.h>

typedef enum

{

EVEN, ODD

} Type;

int main(void)

{

int i=0;

Begin:

i++;

for (; i < 5; i++)

{

Type t = (i % 2 == 0) ? EVEN : ODD;

if (t == ODD)

{

printf("%d ", i);

break;

goto Begin;

}

}

return 0;

}

A. 1

B. 0 2 4

C. 0 1 2 3 4

D. Compile time error

E. infinite loop

Answer: A

2.

Find the output of the following

```
#include<stdio.h>
typedef enum {ON=1, OFF=0} Power;
int main(void)
{
    Power state = OFF;
    int count = 0;
    do
    {
        if (state == OFF && count == 2)
            state = ON;
        printf("%d ", count);
        count++;
    }while (state == OFF);
    return 0;
}
```

A. 0 1 2

B. 0 1

C. 0 1 2 3

D. Infinite loop

E. 0 2 4

Answer: A

3.

Find the output of the following

#include<stdio.h>

int main(void)

{

int i = 0;

End:

while (i < 3)

{

printf("Loop %d\t", i);

if (i == 1)

goto Start;

i++;

}

printf(" SunBeam ");

Start:

printf(" End ");

return 0;

}

A. Loop 0 Loop 1 SunBeam End

B. Loop 0 Loop 1 End

C. Loop 0 End

D. Compile Error

D. infinte loop

Answer: B

4.

Find the output of the following

```
#include<stdio.h>
typedef enum {START=1, STOP=5} State;
int main(void)
{
    State s;
    for (s = START; s <= STOP; s++) {
        if (s == 3)
            continue;
        printf("%d ", s);
    }
    return 0;
}
```

- A. 1 2 3 4 5
- B. 1 2 4 5
- C. 1 2 3 5
- D. Compile time error

Answer: B

5.

Find the output of the following

```
#include<stdio.h>
int main(void)
{
    for (int i = 0; i < 5; i++) {
        if (i != 2)
            continue;
        printf("%d ", i);
    }
    return 0;
}
```

A. 0 1 2 3 4

B. 0 1 3 4

C. 0 1 2

D. 1 2 3 4

E. 2

Answer: E

SunBeam