

EXP 1

Flashing of Led using AT89C51 Microcontroller using Proteus

Code: -

```
ORG 0000H
```

```
UP: SETB P2.0
```

```
ACALL DELAY
```

```
CLR P2.0
```

```
ACALL DELAY
```

```
SJMP UP
```

```
DELAY: MOV R4,#35
```

```
H1:MOV R3,#255
```

```
H2:DJNZ R3,H2
```

```
DJNZ R4,H1
```

```
RET
```

```
END
```

