# Prompt2Patch Dashboard

Deployment guide for Vercel and the X-Ops website

## 1. How it works

Two pages talk to each other through a small server on Vercel, so they can run on **different laptops**:

| Page | Where to open it | Who uses it |
|---|---|---|
| /prompt2patch/ | Projector laptop, fullscreen (press F) | Shows poster, timer, music, hints, results |
| /prompt2patch/admin/ | Admin laptop (password protected) | Scenes, timer, hint images, scores, reveal |

The projector asks the server for the latest commands every 3 seconds. The admin laptop's commands (change scene, start timer, upload a hint, start the reveal) are stored in a free **Upstash Redis** database and picked up by the projector. Passwords are checked on the server, and scores stay private until the reveal.

**Event flow:** Waiting (poster, timer hidden, soft BGM) → Lamp lighting (traditional music) → Event (light hopping music, timer visible, hint images at equal intervals) → Results (names shuffle, podium, winner).

## 2. Your current site

https://xops-hub-spark.vercel.app looks like a Vite/React site created with Lovable. That works well: files in **public/** are served as-is, and a top-level **api/** folder becomes serverless functions. Two ways to deploy; **Option A** puts it under your existing domain, **Option B** is safest if you do not want to touch the main site before the event.

## 3. Step 1 - Create the free database (needed for both options)

**1.** Sign in at vercel.com and open the **project** you will deploy to (Option A: your X-Ops site project; Option B: the new project from Part 5).

**2.** Open the **Storage** tab → **Create Database** (or **Marketplace**) → choose **Upstash for Redis** → pick a free plan and the nearest region (e.g. Mumbai/Singapore) → **Connect to project**.

**3.** Vercel automatically adds environment variables such as **KV_REST_API_URL** and **KV_REST_API_TOKEN**. The code also accepts UPSTASH_REDIS_REST_URL / UPSTASH_REDIS_REST_TOKEN.

**4.** Open **Settings** → **Environment Variables** and add **ADMIN_PASSWORD** with a long password of your choice (Production, Preview and Development). This is the admin login.

**5.** Redeploy after adding variables (Deployments → latest → **Redeploy**); variables only apply to new deployments.

## 4. Option A - Add it to your existing X-Ops site

**1.** Unzip the package. Get your site's code from its GitHub repository (Lovable projects can be synced to GitHub; clone it, or use the GitHub web editor).

**2.** Copy the folder **public/prompt2patch** from the zip into your repository's **public/** folder, so you end up with **public/prompt2patch/index.html** and **public/prompt2patch/admin/index.html**.

**3.** Copy the **api** folder from the zip into the **root** of the repository (next to package.json). If the repository already has an **api** folder, copy the files into it.

**4.** Do **not** copy the zip's vercel.json over yours. If your repository has no vercel.json, create one containing only the redirect below. If it has one, add this entry to its **redirects** array. If it has a catch-all rewrite for the React router, keep it: real files are served first.

**5.** Commit and push to GitHub. Vercel redeploys automatically. Then do Step 1 (database + password) and redeploy again.

```
{
  "redirects": [
    { "source": "/prompt2patch", "destination": "/prompt2patch/", "permanent": false }
  ]
}
```

Your links will be **https://xops-hub-spark.vercel.app/prompt2patch/** (projector) and **https://xops-hub-spark.vercel.app/prompt2patch/admin/** (admin). Lovable: if you edit the site in Lovable after this, the new folders stay in GitHub; just do not delete them.

**If your site uses Next.js** instead of Vite, the **public/** part is identical, but put the API files in the repository's **api** folder anyway (Vercel supports it next to Next.js) or tell me and I will convert them to route handlers.

## 5. Option B - Separate Vercel project (no risk to the main site)

**1.** Create a new GitHub repository (for example **prompt2patch-dashboard**) and upload everything from the zip: public/, api/, vercel.json, package.json.

**2.** On Vercel: **Add New** → **Project** → import that repository. Framework preset: **Other**. Leave the build command empty. Output directory: **public** (already set in vercel.json). Deploy.

**3.** Do Step 1 (database + ADMIN_PASSWORD) in this new project and redeploy.

**4.** Your links are https://<new-project>.vercel.app/prompt2patch/ and /prompt2patch/admin/. You can add a button on the main site that links to them, or add a custom domain such as hack.yourdomain.com in Settings → Domains.

## 6. Test before the event

**1.** Open /prompt2patch/admin/ on the admin laptop and log in with ADMIN_PASSWORD. The status line should say **Projector connected** once the projector page is open.

**2.** Open /prompt2patch/ on the projector laptop. **Click once anywhere** (browsers block sound until you do) and press **F** for fullscreen. A small green dot at the bottom right means it is connected to the admin.

**3.** Admin: click each scene button and confirm the projector changes within about 3 seconds. Set a 1-minute timer, upload 2 hint images, press Start, and watch the hints appear at 1/3 and 2/3 of the time.

**4.** Enter 5 fake teams in Scores and press **Start the reveal animation**. Then delete the fake teams.

**5.** No internet at the projector? The page still works in local mode with its own on-screen controls (move the mouse to see them), but admin control, hint images and results need internet. Test the venue Wi-Fi, or use a phone hotspot.

## 7. Event-day checklist

• Both laptops: latest Chrome or Edge, charged, on stable internet.
• Projector laptop: open /prompt2patch/, click once, press F, check sound through the venue speakers at ~50% volume, then hide the control panel (H).
• Admin laptop: log in early; keep the page open. Order: Waiting → Lamp lighting → Event → set timer → Start → (hints appear automatically) → enter scores → Teaser → Start reveal.

• Projector shortcuts: F fullscreen, H hide/show panel (or right-click), T timer, Esc close overlays.
• Waiting music from your own MP3s: add files to public/prompt2patch/music/ and list them in public/prompt2patch/playlist.js (only music you are licensed to play). With no files, a soft generated BGM plays instead.

## 8. Troubleshooting

| Problem | Fix |
| --- | --- |
| Login says 'Wrong password' or server error | ADMIN_PASSWORD missing or not redeployed. Add it under Settings → Environment Variab |
| 'Database not connected' error | Upstash database not connected to this project. Redo Step 1 and redeploy. |
| /prompt2patch/ shows the main site's #1 search result page | 404 cannot find public/prompt2patch/ or the new deployment has not finished. Check the repositor |
| /api/... returns 404 | The api folder must be at the repository root (not inside public) and contain .mjs files. |
| Projector has no sound | Click once on the projector page; check the browser tab is not muted and the volume slider is up. |
| Hints do not appear | Timer must be running, scene must be Event, and at least one hint image uploaded. |
| Changes not showing | Hard refresh (Ctrl+Shift+R). Projector updates within 3 seconds. |

## 9. Good to know

• Free tiers are enough for one event (the projector makes about 1,200 requests per hour). Do not leave the projector page open for days.
• Hint images are shrunk to about 1280 px in the browser before upload; use up to 5 images.
• Change the admin password any time in Vercel and redeploy; old logins expire after 12 hours.
• The projector URL is public, but it only shows what the admin sends. Scores are not exposed until the reveal. Keep the admin URL and password private.
• Music is generated in the browser, so there are no copyright issues; the lamp-lighting piece is an original devotional-style ambience, not a recording.