

CF-WA350 -

OpenWrt 24.10 / Linux 6.6



- 1. **phy1radio** phy0radio (ath9k = phy1, ath10k = phy0)
- 2. **\$(Device/uimage-lzma-loader)** generic.mk
- 3. **nvmem-layout** MAC addresses (Linux 6.6 (
- 4. **wifi@0,0** &pcie
- 5. **linux,default-trigger** LAN/WAN LEDs) 01_leds)
- 6. **uhttpd** .config) LuCI)



qca9563_comfast_cf-wa350.dts	Device Tree
01_leds_cf-wa350.patch	LEDs
02_network_cf-wa350.patch	+ MAC
generic_mk_cf-wa350.patch	Makefile
11-ath10k-caldata_cf-wa350.patch	caldata 5GHz
config-additions.txt	.config



1: DTS

```
cp qca9563_comfast_cf-wa350.dts openwrt/target/linux/ath79/dts/
```

2:

```
cd openwrt

# 01_leds
patch -p1 < 01_leds_cf-wa350.patch

# 02_network
patch -p1 < 02_network_cf-wa350.patch

# generic.mk
patch -p1 < generic_mk_cf-wa350.patch

# 11-ath10k-caldata
patch -p1 < 11-ath10k-caldata_cf-wa350.patch
```

3: .config

```
config-additions.txt .config :
```

```
make oldconfig
```

4: uhttpd

```
grep CONFIG_PACKAGE_uhttpd .config  
# CONFIG_PACKAGE_uhttpd=y
```

5:

```
make clean  
make -j$(nproc) V=s
```



1. **Ping** ← (dropbear (
2. **LuCI** ← http://192.168.1.1
3. **WiFi 2.4GHz** ←
4. **LAN/WAN** ← 01_leds



- GPIO (4, 15, 16, 17) .
- 02_network_mac_cf-wa350.patch 02_network_cf-wa350.patch .
- uboot-envtools (-uboot-envtools) CF-E375AC.