Expression API

class **mini.apis.api_expression.RobotExpressionType**(*value*) [source]

Bases: `enum.Enum`

Robot expression type

INNER (built-in): Unmodifiable emoticon files built into the robot

> **INNER**= *0*

class **mini.apis.api_expression.PlayExpression**(*is_serial: bool = True, express_name: Optional[str] = None*) [source]

Bases: `mini.apis.base_api.BaseApi`

Play built-in emoji api

Let the robot eyes show an expression

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **express_name** (*str*) – emoticon name, cannot be empty or None

#PlayExpressionResponse.isSuccess: Is it successful

#PlayExpressionResponse.resultCode: Return code

> *async* **execute**() [source]
>
> Execute the play emoticon command
>
> **Returns:** PlayExpressionResponse

class **mini.apis.api_expression.MouthLampColor**(*value*) [source]

Bases: `enum.Enum`

Mouth light color

RED: red

GREEN: Green

WHITE: white

> **RED**= *1*

GREEN= *2*

WHITE= *4*

---

class **mini.apis.api_expression.MouthLampMode**(*value*) [source]

Bases: `enum.Enum`

Mouth light mode

NORMAL (normal mode): constant light mode

BREATH (breathing mode): Breathing mode

NORMAL= *0*

BREATH= *1*

---

class **mini.apis.api_expression.SetMouthLamp**(*is_serial: bool = True, mode: mini.apis.api_expression.MouthLampMode = MouthLampMode.NORMAL, color: mini.apis.api_expression.MouthLampColor = MouthLampColor.RED, duration: int = 1000, breath_duration: int = 1000*) [source]

Bases: `mini.apis.base_api.BaseApi`

Set mouth light api

Set parameters such as the mode and color of the mouth light

When mode=NORMAL, the duration parameter works, indicating how long it will be on

When mode=BREATH, the breath_duration parameter indicates how often to breathe

After the setting takes effect, the robot will immediately return the setting result (it has nothing to do with the set duration parameter)

Parameters:

- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **mode** (*MouthLampMode*) – Mouth lamp mode, default NORMAL, normal (constant light) mode
- **color** (*MouthLampColor*) – Mouth lamp color, default RED, red
- **duration** (*int*) – duration, in milliseconds, -1 means unlimited time, when the length is set to more than 10s, the result will be returned within 10s
- **breath_duration** (*int*) – the duration of one blink, in milliseconds

#SetMouthLampResponse.isSuccess: Is it successful

#SetMouthLampResponse.resultCode: Return code

async **execute**() [source]

Execute the command to set the mouth light

Returns: SetMouthLampResponse

---

class **mini.apis.api_expression.ControlMouthLamp**(*is_serial: bool = True, is_open: bool = True*) [source]

Bases: `mini.apis.base_api.BaseApi`

Control mouth light switch api

Turn on/off the mouth light

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **is_open** (*bool*) – Whether to turn on the mouth light. Default true, turn on the mouth light

#ControlMouthResponse.isSuccess: Is it successful

#ControlMouthResponse.resultCode: Return code

async **execute**() [source]

Execute the command to control the mouth light

Returns: ControlMouthResponse