Voice API

class **mini.apis.api_sound.TTSControlType**(*value*) [source]

Bases: `enum.Enum`

TTS control type

START: start playing tts

STOP: Stop playing tts

> **START**= *1*

> **STOP**= *0*

class **mini.apis.api_sound.StartPlayTTS**(*is_serial: bool = True, text: Optional[str] = None*) [source]

Bases: `mini.apis.base_api.BaseApi`

Start playing TTS api

The robot plays the synthesized TTS voice

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **text** (*str*) – The text to be played, cannot be empty or None

#ControlTTSResponse.isSuccess: Is it successful, True or False

#ControlTTSResponse.resultCode: Return code

> *async* **execute**() [source]

> Execute the TTS command to start playing

> **Returns:** ControlTTSResponse

class **mini.apis.api_sound.StopPlayTTS**(*is_serial: bool = True*) [source]

Bases: `mini.apis.base_api.BaseApi`

Stop playing TTS api

The robot stops playing TTS voice

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#ControlTTSResponse.isSuccess: Is it successful

#ControlTTSResponse.resultCode: Return code

async **execute**() [source]

Execute the stop playing TTS command

Returns: ControlTTSResponse

---

class **mini.apis.api_sound.AudioStorageType**(*value*) [source]

Bases: `enum.Enum`

Audio storage type

NET_PUBLIC: public network

PRESET_LOCAL: The robot is built locally

CUSTOMIZE_LOCAL: Robot local customization

NET_PUBLIC= *2*

PRESET_LOCAL= *3*

CUSTOMIZE_LOCAL= *4*

---

class **mini.apis.api_sound.PlayAudio**(*is_serial: bool = True, url: Optional[str] = None, storage_type: mini.apis.api_sound.AudioStorageType = AudioStorageType.NET_PUBLIC, volume: float = 1.0*) [source]

Bases: `mini.apis.base_api.BaseApi`

Play audio api

The robot plays the specified audio, supports mp3, wav, amr, etc.

Parameters:

- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **url** (*str*) – audio address, when storage_type is NET_PUBLIC, url is the URL of the audio file; when storage_type is PRESET_LOCAL/CUSTOMIZE_LOCAL, url is the local audio name (the local audio name can be obtained through the FetchAudioList interface)
- **storage_type** (*AudioStorageType*) – Audio storage type, default NET_PUBLIC, public network
- **volume** (*float*) – volume size, range [0.0,1.0], default 1.0

#PlayAudioResponse.isSuccess: Is it successful

#PlayAudioResponse.resultCode: Return code

async **execute**() [source]

Execute the play audio command

Returns: PlayAudioResponse

---

class **mini.apis.api_sound.StopAllAudio**(*is_serial: bool = True*) [source]

Bases: `mini.apis.base_api.BaseApi`

Stop all audio APIs

The robot stops all audio being played

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#StopAudioResponse.isSuccess: Is it successful

#StopAudioResponse.resultCode: Return code

async **execute**() [source]

Execute stop all audio commands

Returns: StopAudioResponse

---

class **mini.apis.api_sound.AudioSearchType**(*value*) [source]

Bases: `enum.Enum`

Audio query type

INNER (built-in): unmodifiable sound effects built into the robot,

CUSTOM (custom): placed in the sdcard/customize/music directory and can be modified by the developer

INNER= *0*

CUSTOM= *1*

---

class **mini.apis.api_sound.FetchAudioList**(*is_serial: bool = True, search_type: mini.apis.api_sound.AudioSearchType = AudioSearchType.INNER*) [source]

Bases: `mini.apis.base_api.BaseApi`

Get the audio list api of the robot

Get the audio list stored in the robot rom or sdcard

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **search_type** (*AudioSearchType*) – search type, default INNER, built-in robot

#GetAudioListResponse.audio ([Audio]): Audio effect list

#Audio.name: Audio effect name

#Audio.suffix: audio suffix

#GetAudioListResponse.isSuccess: Is it successful

#GetAudioListResponse.resultCode: Return code

async **execute**() [source]

Execute get audio list command

Returns: GetAudioListResponse

---

class **mini.apis.api_sound.ChangeRobotVolume**(*is_serial: bool = True, volume: float = 0.5*) [source]

Bases: `mini.apis.base_api.BaseApi`

Set robot volume api

Adjust the robot volume

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **volume** (*float*) – volume, range [0.0,1.0], default 0.5

#ChangeRobotVolumeResponse.isSuccess: Is it successful

#ChangeRobotVolumeResponse.resultCode: Return code

async **execute**() [source]

Send command to set robot volume

Returns: ChangeRobotVolumeResponse

---

class **mini.apis.api_sound.RobotAudioRecordControlType**(*value*) [source]

Bases: `enum.Enum`

Robot recording control type

START_RECORD= *0*

STOP_RECORD= *1*

START_PLAY= *2*

STOP_PLAY= *3*

PAUSE_PLAY= *4*

CONTINUE_PLAY= *5*

RENAME_FILE= *6*

---

class **mini.apis.api_sound.ControlRobotAudioRecord**(*is_serial: bool = True, control_type: mini.apis.api_sound.RobotAudioRecordControlType = RobotAudioRecordControlType.START_RECORD, time_limit: int = 60000, file_name: Optional[str] = None, new_file_name: Optional[str] = None*) [source]

Bases: `mini.apis.base_api.BaseApi`

Control robot recording/playing api

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **control_type** (*RobotAudioRecordControlType*) – control type, default START_RECORD, start recording
- **time_limit** (*int*) – The length of the recording, in ms, the default is 60000ms, which is 60s
- **file_name** (*str*) – Recording file storage name
- **new_file_name** (*str*) – rename the name of the recording file

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

async **execute**() [source]

Send control recording instructions

Returns: ControlRobotRecordResponse

---

class **mini.apis.api_sound.RobotAudioStartRecord**(*is_serial: bool = True, time_limit: int = 60000*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

Robot starts recording api

Control the robot to start recording

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True

- **time_limit** (*int*) – The length of the recording, in ms, the default is 60000ms, which is 60s

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioStopRecord**(*is_serial: bool = True*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

Robot stop recording api

Control the robot to stop recording

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioStartPlay**(*is_serial: bool = True, file_name: Optional[str] = None*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

The robot starts to play the recording api

Control the robot to start playing the recording

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **file_name** (*str*) – recording file name, cannot be empty or None

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioStopPlay**(*is_serial: bool = True*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

The robot stops playing the recording api

Control the robot to stop playing the recording

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioPausePlay**(*is_serial: bool = True*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

The robot pauses the recording api

Control the robot to pause the recording

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioContinuePlay**(*is_serial: bool = True*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

The robot continues to play the recording api

Control the robot to continue playing the recording

Parameters: **is_serial** (*bool*) – Whether to wait for a reply, the default is True

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file

---

class **mini.apis.api_sound.RobotAudioRenameFile**(*is_serial: bool = True, file_name: Optional[str] = None, new_file_name: Optional[str] = None*) [source]

Bases: `mini.apis.api_sound.ControlRobotAudioRecord`

Robot rename recording file api

Control the robot to rename the recording file

Parameters:
- **is_serial** (*bool*) – Whether to wait for a reply, the default is True
- **file_name** (*str*) – recording file name, cannot be empty or None

#ControlRobotRecordResponse.isSuccess: Is it successful

#ControlRobotRecordResponse.resultCode: Return code

#ControlRobotRecordResponse.id: The name of the generated recording file