Memory Management


```
cudaError_t cudaHostGetDevicePointer ( void **       pDevice,
                                       void *        pHost,
                                       unsigned int  flags
                                     )
```

Passes back the device pointer corresponding to the mapped, pinned host buffer allocated by **cudaHostAlloc()**.

cudaHostGetDevicePointer() will fail if the **cudaDeviceMapHost** flag was not specified before deferred context creation occurred, or if called on a device that does not support mapped, pinned memory.

`flags` provides for future releases. For now, it must be set to 0.

Parameters:

pDevice	- Returned device pointer for mapped memory
pHost	- Requested host pointer mapping
flags	- Flags for extensions (must be 0 for now)

Returns:

cudaSuccess, **cudaErrorInvalidValue**, **cudaErrorMemoryAllocation**

Note:

Note that this function may also return error codes from previous, asynchronous launches.

See also:

cudaSetDeviceFlags, **cudaHostAlloc**

Generated by Doxygen for NVIDIA CUDA Library