



Improving the EKF in some cases

- The EKF sometimes struggles to make good state estimates for systems having very nonlinear output equations.
- More refined linearization techniques can be used to reduce the linearization error and improve estimates.
- Some examples include the second-order EKF and Gaussian-sum filters, but we will not discuss those here.
- Instead, we will focus on a simple, common, and frequently helpful iterated-refinement approach.
- The result will be the algorithm known as the “iterated EKF” or “IEKF”.



The EKF's output-equation linearization approach

- The EKF derivation approximated the measurement equation:

$$\begin{aligned} h(x_k, u_k, v_k) &\approx h(\hat{x}_k^-, u_k, \bar{v}_k) + \left. \frac{\partial h}{\partial x} \right|_{\hat{x}_k^-} (x_k - \hat{x}_k^-) + \left. \frac{\partial h}{\partial v} \right|_{\hat{x}_k^-} (v_k - \bar{v}_k) \\ &= h(\hat{x}_k^-, u_k, \bar{v}_k) + \hat{C}_k (x_k - \hat{x}_k^-) + \hat{D}_k (v_k - \bar{v}_k). \end{aligned}$$

- Based on this linearization, we then derived EKF steps 1c–2c to be:

$$\begin{aligned} \hat{z}_k &= h(\hat{x}_k^-, u_k, \bar{v}_k) \\ L_k &= \Sigma_{\bar{x},k} \hat{C}_k^T \left[\hat{C}_k \Sigma_{\bar{x},k} \hat{C}_k^T + \hat{D}_k \Sigma_{\bar{v}} \hat{D}_k^T \right]^{-1} \\ \hat{x}_k^+ &= \hat{x}_k^- + L_k (z_k - \hat{z}_k) \\ \Sigma_{\bar{x},k}^+ &= \left(I - L_k \hat{C}_k \right) \Sigma_{\bar{x},k}^- \end{aligned}$$



Reconsidering the EKF thought process

- The reason that we expanded $h(x_k, u_k, v_k)$ around $\hat{x}_k^-$ in the Taylor series was because that was our best guess of x_k before the measurement at time k is taken into account.
- But, after we compute $\hat{x}_k^+$, we have a better estimate of x_k than $\hat{x}_k^-$.
- So, after we compute $\hat{x}_k^+$, what if we re-linearize $h(\cdot)$ around $\hat{x}_k^+$ and recompute steps 1c–2c to see if we get an even better estimate of x_k ?
- In fact, we could repeat this multiple times until we see some kind of convergence.
- This is the main idea of the IEKF.



Notation and initialization

- We introduce notation $\hat{x}_{k,i}^+$ to refer to the estimate of x_k after i re-linearizations have been performed.
 - We initialize $\hat{x}_{k,0}^+ = \hat{x}_k^-$ to the prediction produced by the standard EKF.
- Similarly, $\Sigma_{\tilde{x},k,i}^+$ is the estimation-error covariance of $\hat{x}_{k,i}^+$ after i re-linearizations.
 - We initialize $\Sigma_{\tilde{x},k,0}^+ = \Sigma_{\tilde{x},k}^-$, which is the prediction-error covariance produced by the standard EKF.
- We will denote the Kalman gain of the i th iteration as $L_{k,i}$, and the partial derivatives of the i th iteration as $\hat{C}_{k,i}$ and $\hat{D}_{k,i}$.



A first method to iterate the EKF

- As just mentioned, to begin the iteration process for every measurement update, we set $\hat{x}_{k,0}^+ = \hat{x}_k^-$ and $\Sigma_{\tilde{x},k,0}^+ = \Sigma_{\tilde{x},k}^-$.
- Then, for $i = 0, 1, \dots, N$ we compute (in principle):

$$\text{Step 1c}_i: \quad \hat{C}_{k,i} = \partial h / \partial x |_{\hat{x}_{k,i}^+} \quad \text{and} \quad \hat{D}_{k,i} = \partial h / \partial v |_{\hat{x}_{k,i}^+}$$

$$\hat{z}_k = h(\hat{x}_k^-, u_k, \bar{v}_k)$$

$$\text{Step 2a}_i: \quad L_{k,i} = \Sigma_{\tilde{x},k}^- \hat{C}_{k,i}^T \left[\hat{C}_{k,i} \Sigma_{\tilde{x},k}^- \hat{C}_{k,i}^T + \hat{D}_{k,i} \Sigma_{\tilde{v}} \hat{D}_{k,i}^T \right]^{-1}$$

$$\text{Step 2b}_i: \quad \hat{x}_{k,i}^+ = \hat{x}_k^- + L_{k,i} (z_k - \hat{z}_k)$$

$$\text{Step 2c}_i: \quad \Sigma_{\tilde{x},k,i}^+ = \left(I - L_{k,i} \hat{C}_{k,i} \right) \Sigma_{\tilde{x},k}^-.$$

- Note that $\Sigma_{\tilde{x},k}^-$ is not changed in this modification to the EKF since it still describes the prediction; neither is $\hat{z}_k$ changed, but should it be?



A better way to iterate Step 1c

- The original EKF derivation used Assumption 1 to approximate:

$$\hat{z}_k = \mathbb{E}[h(x_k, u_k, v_k) | \mathbb{Z}_{k-1}] \approx h(\mathbb{E}[x_k | \mathbb{Z}_{k-1}], u_k, \mathbb{E}[v_k]) = h(\hat{x}_k^-, u_k, \bar{v}_k).$$

- An alternate derivation approach uses only Assumption 2 and not Assumption 1:

$$\begin{aligned} \hat{z}_k &= \mathbb{E}[h(x_k, u_k, v_k) | \mathbb{Z}_{k-1}] \\ &\approx \mathbb{E} \left[h(\hat{x}_k^-, u_k, \bar{v}_k) + \frac{\partial h}{\partial x} \Big|_{\hat{x}_k^-} (x_k - \hat{x}_k^-) + \frac{\partial h}{\partial v} \Big|_{\hat{x}_k^-} (v_k - \bar{v}_k) \mid \mathbb{Z}_{k-1} \right] \\ &= h(\hat{x}_k^-, u_k, \bar{v}_k) + \hat{C}_k (\mathbb{E}[x_k - \hat{x}_k^- | \mathbb{Z}_{k-1}]) \\ &= h(\hat{x}_k^-, u_k, \bar{v}_k) + \hat{C}_k (\hat{x}_k^- - \hat{x}_k^-) = h(\hat{x}_k^-, u_k, \bar{v}_k). \end{aligned}$$

- We will use this alternate approach to recompute $\hat{z}_{k,i}$ around $\hat{x}_{k,i}^+$ every iteration.
 - That is, we will compute $\hat{z}_{k,i} = h(\hat{x}_{k,i}^+, u_k, \bar{v}_k) + \hat{C}_{k,i} (\hat{x}_k^- - \hat{x}_{k,i}^+)$.



Summary of IEKF steps

Step 1a: $\hat{x}_k^- = f(\hat{x}_{k-1}^+, u_{k-1}, \bar{w}_{k-1})$

Step 1b: $\Sigma_{\tilde{x},k}^- = \hat{A}_{k-1} \Sigma_{\tilde{x},k-1}^+ \hat{A}_{k-1}^T + \hat{B}_{k-1} \Sigma_{\tilde{w}} \hat{B}_{k-1}^T$

Initialize iteration: $\hat{x}_{k,0}^+ = \hat{x}_k^-$ and $\Sigma_{\tilde{x},k,0}^+ = \Sigma_{\tilde{x},k}^-$

Iterate for $i = 0, 1, \dots, N$

Step 1c_i: $\hat{C}_{k,i} = \partial h / \partial x|_{\hat{x}_{k,i}^+}$, $\hat{D}_{k,i} = \partial h / \partial v|_{\hat{x}_{k,i}^+}$

$\hat{z}_{k,i} = h(\hat{x}_{k,i}^+, u_k, \bar{v}_k) + \hat{C}_{k,i} (\hat{x}_k^- - \hat{x}_{k,i}^+)$

Step 2a_i: $L_{k,i} = \Sigma_{\tilde{x},k}^- \hat{C}_{k,i}^T [\hat{C}_{k,i} \Sigma_{\tilde{x},k}^- \hat{C}_{k,i}^T + \hat{D}_{k,i} \Sigma_{\tilde{v}} \hat{D}_{k,i}^T]^{-1}$

Step 2b_i: $\hat{x}_{k,i}^+ = \hat{x}_k^- + L_{k,i} (z_k - \hat{z}_{k,i})$

Step 2c_i: $\Sigma_{\tilde{x},k,i}^+ = (I - L_{k,i} \hat{C}_{k,i}) \Sigma_{\tilde{x},k}^-$

end of iteration “for” loop

Output: $\hat{x}_k^+ = \hat{x}_{k,N}^+$ and $\Sigma_{\tilde{x},k}^+ = \Sigma_{\tilde{x},k,N}^+$



Summary

- The EKF sometimes struggles to compute good state estimates if the output equation is “very nonlinear.”
- Examining the EKF algorithm, we notice that the output equation appears in Steps 1c–2c, which rely on $\hat{x}_k^-$ as the best “guess” of x_k found to date.
- But, by iterating Steps 1c–2c when we replace $\hat{x}_k^-$ with our best $\hat{x}_k^+$ found so far, we can improve estimates.
- We could iterate until some metric of convergence is satisfied, but often iterating only a few times (or even once) is helpful.
- In the next lesson, you will learn how to implement the IEKF in Octave, and see some results from a very difficult example.